

Logs Reference

Introduction

This guide describes the logs that may be raised during operation and configuration of the Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000.

A description of the log and an appropriate remedial action is provided along with the severity and source of the log. Each log is listed alphabetically corresponding to the first letter of the log name. You can navigate the alphabetical listings by selecting:

- [All logs](#)
- [Log source](#)
- [Log severity](#)

Use the 'find-in-page' function of the browser to search for a command based on the page you are viewing. Most browsers launch 'find' using CTRL+F.

Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Avaya assumes no liability for any errors. Avaya reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

Documentation disclaimer

Avaya shall not be responsible for any modifications, additions, or deletions to the original published version of this documentation unless such modifications, additions, or deletions were performed by Avaya. End User agree to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End User.

Link disclaimer

Avaya is not responsible for the contents or reliability of any linked Web sites referenced within this site or documentation(s) provided by Avaya. Avaya is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Avaya does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

Warranty

Avaya provides a limited warranty on this product. Refer to your sales agreement to establish the terms of the limited warranty. In addition, Avaya's standard warranty language, as well as information regarding support for this product, while under warranty, is available to Avaya customers and other parties through the Avaya Support Web site: <http://www.avaya.com/support>. Please note that if you acquired the product from an authorized Avaya reseller outside of the United States and Canada, the warranty is provided to you by said Avaya reseller and not by Avaya.

License types

THE SOFTWARE LICENSE TERMS AVAILABLE ON THE AVAYA WEBSITE, [HTTP://SUPPORT.AVAYA.COM/LICENSEINFO](http://support.avaya.com/licenseinfo) ARE APPLICABLE TO ANYONE WHO DOWNLOADS, USES AND/OR INSTALLS AVAYA SOFTWARE, PURCHASED FROM AVAYA INC., ANY AVAYA AFFILIATE, OR AN AUTHORIZED AVAYA RESELLER (AS APPLICABLE) UNDER A COMMERCIAL AGREEMENT WITH AVAYA OR AN AUTHORIZED AVAYA RESELLER. UNLESS OTHERWISE AGREED TO BY AVAYA IN WRITING, AVAYA DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE WAS OBTAINED FROM ANYONE OTHER THAN AVAYA, AN AVAYA AFFILIATE OR AN AVAYA AUTHORIZED RESELLER, AND AVAYA RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU AND ANYONE ELSE USING OR SELLING THE SOFTWARE WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE INSTALLING, DOWNLOADING OR USING THE SOFTWARE (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"),

AGREE TO THESE TERMS AND CONDITIONS AND CREATE A BINDING CONTRACT BETWEEN YOU AND AVAYA INC. OR THE APPLICABLE AVAYA AFFILIATE ("AVAYA").

Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation(s) and Product(s) provided by Avaya. All content on this site, the documentation(s) and the product(s) provided by Avaya including the selection, arrangement and design of the content is owned either by Avaya or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part, including any code and software. Unauthorized reproduction, transmission, dissemination, storage, and or use without the express written consent of Avaya can be a criminal, as well as a civil, offense under the applicable law.

Third-party components

Certain software programs or portions thereof included in the Product may contain software distributed under third party agreements ("Third Party Components"), which may contain terms that expand or limit rights to use certain portions of the Product ("Third Party Terms"). Information regarding distributed Linux OS source code (for those Products that have distributed the Linux OS source code), and identifying the copyright holders of the Third Party Components and the Third Party Terms that apply to them is available on the Avaya Support Web site: support.Avaya.com/copyright.

Trademarks

The trademarks, logos and service marks ("Marks") displayed in this site, the documentation(s) and product(s) provided by Avaya are the registered or unregistered Marks of Avaya, its affiliates, or other third parties. Users are not permitted to use such Marks without prior written consent from Avaya or such third party which may own the Mark. Nothing contained in this site, the documentation(s) and product(s) should be construed as granting, by implication, estoppel, or otherwise, any license or right in and to the Marks without the express written permission of Avaya or the applicable third party.

Avaya is a registered trademark of Avaya Inc.

All other trademarks are the property of their respective owners.

Technical support

Avaya provides a telephone number for you to use to report problems or to ask questions about your product. The support telephone number is 1-800-242-2121 in the United States. For additional support telephone numbers, see the Avaya Web site: support.Avaya.com.

If you purchased a service contract for your Avaya product from a distributor or authorized reseller, contact the technical support staff for that distributor or reseller for assistance.

Documentation support

For the most current versions of documentation, see the Avaya Support Web site: support.Avaya.com.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Alphabetized list of logs

All logs are organized alphabetically by their name. Select the letter to navigate to the list of all logs starting with that letter.

A 73 logs	B 30 logs	C 107 logs	D 109 logs
E 129 logs	F 128 logs	G 2 logs	H 2 logs
I 277 logs	J 1 logs	K	L 46 logs
M 39 logs	N 30 logs	O 34 logs	P 74 logs
Q 24 logs	R 57 logs	S 232 logs	T 158 logs
U 154 logs	V 23 logs	W 22 logs	X
Y		Z	

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Log source listing

Select name of the source to see all logs that are generated by that source. Each source page lists all the applicable logs alphabetically.

Sources sorted by log quantity

[QoS](#) --624 logs

[Fabric Attach](#) --80 logs

[VLAN](#) --58 logs

[port driver](#) --53 logs

[EAP](#) --51 logs

[DHCP Snoop](#) --36 logs

[Stack Manager](#) --35 logs

[Telnet server](#) --30 logs

[Radius](#) --28 logs

[AUR](#) --26 logs

[Console](#) --26 logs

[SLAMon](#) --25 logs

[OSPF](#) --24 logs

[Flash Driver](#) --20 logs

[IGMP](#) --20 logs

[TACACS](#) --20 logs

[Source Based Routing](#) --19 logs

[config](#) --18 logs

[SMLT](#) --18 logs

[Run scripts: IP Office, LLDP, ADAC](#) --16 logs

[Link State Tracking](#) --14 logs

[SSH](#) --14 logs

Sources sorted alphabetically

[_](#) -- 1 log

[802.1AB](#) -- 5 logs

[AAA](#) -- 7 logs

[ACG](#) -- 7 logs

[ADAC](#) -- 11 logs

[AES](#) -- 8 logs

[Audit](#) -- 2 logs

[AUR](#) -- 26 logs

[Bay secure](#) -- 13 logs

[BAYSECURE, DCE](#) -- 2 logs

[CDT](#) -- 11 logs

[CFC](#) -- 1 log

[CFG](#) -- 5 logs

[CFGSO](#) -- 8 logs

[CLI](#) -- 4 logs

[config](#) -- 18 logs

[CONFIG DATA](#) -- 1 log

[Console](#) -- 26 logs

[DAI](#) -- 2 logs

[DCE](#) -- 2 logs

[DHCP](#) -- 2 logs

[DHCP Snoop](#) -- 36 logs

[SSHC \(SFTP and SSH Client\)](#) --14 logs

[WEB](#) --14 logs

[Bay secure](#) --13 logs

[FCoE Redirect](#) --13 logs

[LACP](#) --13 logs

[MLT](#) --13 logs

[ospf\(drpmgr\)](#) --13 logs

[SNMP](#) --13 logs

[HMOD](#) --12 logs

[Quick Install](#) --12 logs

[SSH Client](#) --12 logs

[ADAC](#) --11 logs

[CDT](#) --11 logs

[PIM](#) --11 logs

[Hello Module](#) --10 logs

[PMT](#) --10 logs

[SPB](#) --10 logs

[SPBM](#) --10 logs

[Stack Monitor](#) --10 logs

[VRRP](#) --10 logs

[ipsg](#) --9 logs

[L3Mgr](#) --9 logs

[PoE](#) --9 logs

[AES](#) --8 logs

[CFGSO](#) --8 logs

[AAA](#) --7 logs

[ACG](#) --7 logs

[ISIS](#) --7 logs

[PDT](#) --7 logs

[IPT](#) --6 logs

[IPv6](#) --6 logs

[Run scripts: LLDP, ADAC](#) --6 logs

[Download Task](#) -- 4 logs

[DRIVER](#) -- 2 logs

[EAP](#) -- 51 logs

[EAP-Filter Manager](#) -- 5 logs

[EAP-VLAN \(QDT\)](#) -- 2 logs

[ENTMIB](#) -- 1 log

[Exception](#) -- 1 log

[Fabric Attach](#) -- 80 logs

[FCoE Redirect](#) -- 13 logs

[Flash Driver](#) -- 20 logs

[Hello Module](#) -- 10 logs

[HMOD](#) -- 12 logs

[IFMGR, SNMP](#) -- 2 logs

[IGMP](#) -- 20 logs

[IMC](#) -- 5 logs

[Inband IP address](#) -- 1 log

[IPFIX](#) -- 1 log

[ipmc \(igmp\)](#) -- 3 logs

[ipsg](#) -- 9 logs

[IPT](#) -- 6 logs

[IPv4 Routing](#) -- 1 log

[IPv6](#) -- 6 logs

[ISIS](#) -- 7 logs

[L3, MLT](#) -- 2 logs

[L3Mgr](#) -- 9 logs

[LAC](#) -- 4 logs

[LACP](#) -- 13 logs

[Link State Tracking](#) -- 14 logs

[LST](#) -- 2 logs

[MCFG](#) -- 5 logs

[MCFG \(Second INFO BLOCK\)](#) -- 1 log

[MCMGR, DRPMGR](#) -- 1 log

[SSL](#) --6 logs
[Telnet](#) --6 logs
[VLACP](#) --6 logs
[802.1AB](#) --5 logs
[CFG](#) --5 logs
[EAP-Filter Manager](#) --5 logs
[IMC](#) --5 logs
[MCFG](#) --5 logs
[MDA](#) --5 logs
[NNCLI](#) --5 logs
[NNRST](#) --5 logs
[Run scripts: ADAC](#) --5 logs
[CLI](#) --4 logs
[Download Task](#) --4 logs
[LAC](#) --4 logs
[NUQC](#) --4 logs
[POL](#) --4 logs
[QPAV2](#) --4 logs
[Run scripts: IP Office](#) --4 logs
[SFTP Client](#) --4 logs
[ipmc \(igmp\)](#) --3 logs
[MCMGR/IGMP](#) --3 logs
[MLD](#) --3 logs
[QoS Agent](#) --3 logs
[RADIUS Client](#) --3 logs
[SLPP Guard](#) --3 logs
[Audit](#) --2 logs
[BAYSECURE, DCE](#) --2 logs
[DAI](#) --2 logs
[DCE](#) --2 logs
[DHCPR](#) --2 logs
[MCMGR/IGMP](#) -- 3 logs
[MDA](#) -- 5 logs
[Memory Tool](#) -- 1 log
[MLD](#) -- 3 logs
[MLT](#) -- 13 logs
[Multicast manager](#) -- 1 log
[Multi Config](#) -- 2 logs
[NNCLI](#) -- 5 logs
[NNRST](#) -- 5 logs
[NUQC](#) -- 4 logs
[OSPF](#) -- 24 logs
[ospf\(drpmgr\)](#) -- 13 logs
[Password Security](#) -- 2 logs
[PDT](#) -- 7 logs
[PIM](#) -- 11 logs
[PM](#) -- 1 log
[PMT](#) -- 10 logs
[PoE](#) -- 9 logs
[POL](#) -- 4 logs
[port driver](#) -- 53 logs
[Port Mirroring](#) -- 2 logs
[QoS](#) -- 624 logs
[QoS Agent](#) -- 3 logs
[QPAV2](#) -- 4 logs
[Quick Install](#) -- 12 logs
[Radius](#) -- 28 logs
[RADIUS Client](#) -- 3 logs
[Rear-Port](#) -- 2 logs
[RMON](#) -- 2 logs
[Run scripts: ADAC](#) -- 5 logs
[Run scripts: IP Office](#) -- 4 logs

[DRIVER](#) --2 logs
[EAP-VLAN \(QDT\)](#) --2 logs
[IFMGR, SNMP](#) --2 logs
[L3, MLT](#) --2 logs
[LST](#) --2 logs
[Multi Config](#) --2 logs
[Password Security](#) --2 logs
[Port Mirroring](#) --2 logs
[Rear-Port](#) --2 logs
[RMON](#) --2 logs
[Run scripts: IP Office, LLDP](#) --2 logs
[SFTP](#) --2 logs
[SNTP](#) --2 logs
[SOFTLIC](#) --2 logs
[STP](#) --2 logs
[USB](#) --2 logs
[_](#) -- 1 log
[CFC](#) -- 1 log
[CONFIG DATA](#) -- 1 log
[ENTMIB](#) -- 1 log
[Exception](#) -- 1 log
[Inband IP address](#) -- 1 log
[IPFIX](#) -- 1 log
[IPv4 Routing](#) -- 1 log
[MCFG \(Second INFO BLOCK\)](#) -- 1 log
[MCMGR, DRPMGR](#) -- 1 log
[Memory Tool](#) -- 1 log
[Multicast manager](#) -- 1 log
[PM](#) -- 1 log
[SBR](#) -- 1 log
[Serious](#) -- 1 log
[System Logging](#) -- 1 log

[Run scripts: IP Office, LLDP](#) -- 2 logs
[Run scripts: IP Office, LLDP, ADAC](#) -- 16 logs
[Run scripts: LLDP, ADAC](#) -- 6 logs
[SBR](#) -- 1 log
[Serious](#) -- 1 log
[SFTP](#) -- 2 logs
[SFTP Client](#) -- 4 logs
[SLAMon](#) -- 25 logs
[SLPP Guard](#) -- 3 logs
[SMLT](#) -- 18 logs
[SNMP](#) -- 13 logs
[SNTP](#) -- 2 logs
[SOFTLIC](#) -- 2 logs
[Source Based Routing](#) -- 19 logs
[SPB](#) -- 10 logs
[SPBM](#) -- 10 logs
[SSH](#) -- 14 logs
[SSHC \(SFTP and SSH Client\)](#) -- 14 logs
[SSH Client](#) -- 12 logs
[SSL](#) -- 6 logs
[Stack Manager](#) -- 35 logs
[Stack Monitor](#) -- 10 logs
[STP](#) -- 2 logs
[System Logging](#) -- 1 log
[TACACS](#) -- 20 logs
[Telnet](#) -- 6 logs
[Telnet server](#) -- 30 logs
[TOTAL SYS UPTIME \(TSU\)](#) -- 1 log
[USB](#) -- 2 logs
[VLACP](#) -- 6 logs
[VLAN](#) -- 58 logs
[VRRP](#) -- 10 logs

TOTAL SYS UPTIME (TSU) -- 1 log

WEB -- 14 logs

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Log severity listing

Select name of the source to see all logs that are generated by that source. Each severity page lists all the applicable logs alphabetically.

Severities sorted by log quantity

[Information](#) --988 logs

[Serious](#) --522 logs

[Critical](#) --179 logs

[Minor](#) --31 logs

[Error](#) --13 logs

[Major](#) --8 logs

[Warning](#) --6 logs

[Warning/Information](#) --2 logs

[Console](#) -- 1 log

[Serious/Critical](#) -- 1 log

Severities sorted alphabetically

[Console](#) -- 1 log

[Critical](#) -- 179 logs

[Error](#) -- 13 logs

[Information](#) -- 988 logs

[Major](#) -- 8 logs

[Minor](#) -- 31 logs

[Serious](#) -- 522 logs

[Serious/Critical](#) -- 1 log

[Warning](#) -- 6 logs

[Warning/Information](#) -- 2 logs

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with A

This page lists all logs that have a starting letter of A. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [AAUR-Info AAUR default](#)
- [AAUR-Info AAUR disable](#)
- [AAUR-Info AAUR enable](#)
- [AAUR-Info Agent transfer finished](#)
- [AAUR-Info Receive request for agent image start transfer](#)
- [AAUR-Info Receive request for agent image. Unable to start transfer](#)
- [AAUR-Info Send request for new agent image](#)
- [AAUR-Info Slave refuse transfer](#)
- [AAUR-Info The hardware is not compatible with the image version number version](#)
- [AAUR - Warning Agent image check sum ERROR](#)
- [AAUR-Warning Cannot get FLASH resource](#)
- [AAUR - Warning Slave agent image check sum ERROR](#)
- [Access assignment distribution across stack failed](#)
- [Access assignment modifications not supported](#)
- [Access assignment modification support limited](#)
- [Access assignment name contains unacceptable characters](#)
- [Access assignment name length outside of acceptable limits](#)
- [Access assignment name not acceptable - reserved](#)
- [Access assignment template still in use \(siblings active\)](#)
- [Access element block label contains unacceptable characters](#)
- [Access element block label length outside of acceptable limits](#)
- [Access element cluster count \(cluster count \) exceeds limit \(cluster limit \)](#)
- [Access element cluster is referenced \(addition prohibited\)](#)
- [Access element cluster is referenced \(deletion prohibited\)](#)
- [Access element distribution across stack failed](#)
- [Access element modifications not supported](#)
- [Access element name contains unacceptable characters](#)
- [Access element name length outside of acceptable limits](#)
- [Access element name not acceptable - reserved](#)
- [ADAC: ADAC of Nortel IP Phones not functional](#)
- [ADAC Error applying main VLAN QoS configuration](#)
- [ADAC Error applying VLAN QoS configuration for unit port unit# port#](#)
- [ADAC Error forcing administrative state to disable enable](#)
- [ADAC: Error registering CDT handlers](#)
- [ADAC Error removing main VLAN QoS configuration](#)
- [ADAC Error removing VLAN QoS configuration for unit port unit# port#](#)
- [ADAC Forced administrative state to disable enable](#)
- [ADAC System operationally disable enable](#)
- [AES activated by schedule](#)
- [AES deactivated by schedule](#)
- [AES globally disabled](#)
- [AES globally enabled](#)
- [AES manually activated](#)
- [AES manually deactivated](#)
- [AES not applying schedule because SNTP not synchronized](#)

- [AES time is synchronized applying schedule](#)
- [After agent change message became invalid:](#)
- [Agent configuration distribution across stack failed](#)
- [Allowed connection attempt from user :](#)
- [Allowed connection attempt from user](#)
- [Another BU tried to join the stack. Unit ignored](#)
- [application-name failed DB-exchange stack failed to form](#)
- [application-name failed DB-exchange stack formation delayed](#)
- [application_name failed DB-exchange stack formation delayed](#)
- [ASCII failed](#)
- [ASCII finished successfully](#)
- [ASCII finished successfully at load on boot](#)
- [ASCII transfer failed](#)
- [ASCII transfer failed at load on boot](#)
- [ASCII transfer OK](#)
- [ASCII transfer OK at load on boot](#)
- [Assertion Failure in bcm_l3_hit_check- l3sw ip=%#x.l3hw ip=%#x](#)
- [Attempt to create an element that already exists \(prohibited\)](#)
- [Attempt to delete modify non-existing element \(prohibited\)](#)
- [Attempt to manipulate system-owned interface \(prohibited\)](#)
- [Attempt to manipulate user policy data rejected \(disabled\)](#)
- [Audit data initialized \(bad checksum\)](#)
- [Audit data initialized \(bad magic number\)](#)
- [AUR-Info AUR disable](#)
- [AUR-Info AUR enable](#)
- [AUR-Info AUR Restored to default](#)
- [AUR-Info New unit has different HW config Using cfg from the new unit](#)
- [Authentication Failure Trap](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with B

This page lists all logs that have a starting letter of B. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Backup configuration block # block number in use](#)
- [Backup configuration restored from primary configuration block # block number](#)
- [Backup configuration updated for next active configuration block # block number](#)
- [Backup Configuration Version is updated](#)
- [Base action distribution across stack failed](#)
- [Base action entry referenced by clfr block \(deletion prohibited\)](#)
- [Base action entry referenced by meter \(deletion prohibited\)](#)
- [Base action entry referenced by policy \(deletion prohibited\)](#)
- [Base action extension identifier invalid](#)
- [Base action modification prohibited due to action usage](#)
- [Base action modifications not supported](#)
- [Base unit has loopback port mode %s and the current unit %s. Unit reconfigured and rebooted](#)
- [Base unit has loopback port mode <SPBM reserved port mode> and the current unit <SPBM reserved port mode>. Unit reconfigured and rebooted](#)
- [BaySec Exceeded number MAC addresses on unit# port#](#)
- [BaySec Not enough resource on port port# . Check QOS cfg](#)
- [Bay Secure error line line# # of octets read from NVRAM](#)
- [Bay Secure: Exceeded %d per-trunk MAC addresses on trunk %d](#)
- [Bay Secure Exceeded number per-port MAC addresses on port unit# port#](#)
- [Bay Secure intruder](#)
- [Bay Secure intruder MAC](#)
- [Bay Secure MAC DA filtering not enough resources](#)
- [Bay Secure: MAC DA filtering not enough resources](#)
- [Bay Secure per-port addresses deleted](#)
- [Bay Secure Policy Error error type line line# 0](#)
- [Bay Secure Resource Error error# line line# resource ID](#)
- [BECOME_TEMP_BU event sent unit mask value appl mask value](#)
- [Boot: system boot status 0x%x](#)
- [BPDU received on port with BPDU-Filtering enabled.](#)
- [Buffer configuration inconsistency detected \(local buffer conf stack buffer conf \)](#)
- [BU was unable to send IMC for NBUs VLAN/Port configuration](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with C

This page lists all logs that have a starting letter of C. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [call to cdt api function due to lock timeout \(code= error type total failures= number errno= error code \)](#)
- [cam driver initialization failed \(code= error type argument= line# \)](#)
- [cam driver initialized](#)
- [cam processing aborted \(code= error type argument= line# \)](#)
- [Cannot configure without loopback port available](#)
- [Cannot create CVLAN on vlan: IGMP Snooping enabled and SPBM Mcast disabled](#)
- [Cannot disable IP Source Guard on Unit unit# Port port#](#)
- [Cannot disable SPBM multicast - IGMP Snooping is enabled on C-VLANs](#)
- [Cannot enable SPBM multicast: feature unsupported](#)
- [Cannot enable SPBM multicast while unknown-mcast-no-flood is enabled](#)
- [Cannot enable SPBM while PIM is enabled](#)
- [Capabilities determined by agent \(not-writable\)](#)
- [CDT MAC address mac_address was removed because LAG trunk trunked has disaggregated.](#)
- [CDT MAC address mac_address was removed because port port_no has aggregated in LAG](#)
- [CDT The static FDB entry MAC mac_address VLAN vlan_id trunk trunkId was deleted because LAG has disaggregated](#)
- [CDT The static FDB entry MAC mac_address VLAN vlan_id was deleted because Unit Port unit_port has aggregated](#)
- [CFG - Could not acquire FLASH sem](#)
- [CFG - Could not create ram copy buffer.](#)
- [CFG - NVRAM file system check: errors detected. Please reboot the system!](#)
- [CFG - NVRAM file system check: errors detected. Restored to default.](#)
- [CFGSO - Error: Failed to create watchdog timer](#)
- [CFGSO - Error: Failed to get an imc buffer](#)
- [CFGSO - Error: Failed to save data to NBU](#)
- [CFGSO - Error: Failed to start watchdog timer](#)
- [CFGSO - Error: File not read](#)
- [CFGSO - Error: File not write](#)
- [CFGSO - Warning Invalid Msg Id](#)
- [CFGSO - Warning Watchdog timer expire](#)
- [CFM: ERROR adding port filters for VLAN %d - no resources](#)
- [Change of active config block and or reset failed block-number](#)
- [Classifier block component set ID out-of-range \(clfr comp set ID \)](#)
- [Classifier block distribution across stack failed](#)
- [Classifier block modifications not supported](#)
- [Classifier block number out-of-range \(block# \)](#)
- [Classifier block precedence value not supported](#)
- [Classifier component distribution across stack failed](#)
- [Classifier component modifications not supported](#)
- [Classifier component set ID out-of-range \(clfsr comp set ID \)](#)
- [Classifier conflict \(duplicate clfr data in block\) detected](#)
- [Classifier content incompatible with target interface\(s\)](#)
- [Classifier set block reference out-of-range \(clfr setblock# \)](#)
- [Classifier type unknown](#)
- [Clfr content \(system\) incompatible with target interface\(s\)](#)
- [Cli add vlan vlan_id members port mask](#)
- [Cli create vlan vlan_id type port](#)

- [Cli delete vlan vlan id members port mask](#)
- [Cli delete vlan vlan id type port](#)
- [CLI pswd: Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch](#)
- [CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially \(stack IP addr not set\). Local user/pass used](#)
- [CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially \(switch IP addr not set\). Local user/pass used](#)
- [CLI pswd: Switch authentication parameter is obsolete; changes have not been applied](#)
- [Cli set autopvid disable](#)
- [Cli set autopvid enable](#)
- [Cli set management vlan vlan id](#)
- [Cli set ports port mask tagging disable](#)
- [Cli set ports port mask tagging enable](#)
- [Cli set pvid vlan id ports port mask](#)
- [Cli set vlan vlan id members port mask](#)
- [Cold Start Trap](#)
- [Composite filter set addition failure comp filter set unknown](#)
- [Composite filter set addition failure data consistency issue](#)
- [Composite filter set addition failure data invalid](#)
- [Composite filter set addition failure replication failure](#)
- [Composite filter set addition failure resources unavailable](#)
- [Composite filter set addition failure seed filter set unknown](#)
- [Composite filter set creation failure data invalid](#)
- [Composite filter set creation failure MAC data not allowed](#)
- [Composite filter set creation failure replication failure](#)
- [Composite filter set creation failure seed filter set unknown](#)
- [Composite filter set deletion failure base set target invalid](#)
- [Composite filter set deletion failure comp filter set unknown](#)
- [Composite filter set deletion failure data invalid](#)
- [Composite filter set deletion failure seed filter set unknown](#)
- [Composite filter set destruction failure data invalid](#)
- [Composite filter set membership limits exceeded](#)
- [Configuration block %d is now in use](#)
- [Configuration saved to nv block # block number](#)
- [Conflicting action sources detected](#)
- [Conflicting egress interface and egress trunk data specified](#)
- [Conflicting master block member information detected](#)
- [Conflicting policy role policy interface index data detected](#)
- [Connection closed \(failed login\) IP address](#)
- [Connection closed \(inactivity logout\) IP address](#)
- [Connection closed \(login timeout\) IP address](#)
- [Connection closed \(lost connection\) IP address](#)
- [Connection closed. Maximum number of sessions reached. IP address:](#)
- [Connection closed. Maximum number of sessions reached. IP address:](#)
- [Connection closed \(user logout\) IP address](#)
- [Cons activate vlan vlan id](#)
- [Cons add vlan vlan id port unit port](#)
- [Cons create vlan vlan id type port](#)
- [Cons delete vlan vlan id port unit port](#)
- [Cons delete vlan vlan id type port](#)
- [Cons set autopvid disable](#)
- [Cons set autopvid enable](#)
- [Cons set management vlan vlan id](#)
- [Cons set port unit port pvid vlan id](#)
- [Cons set port unit port tagging disable](#)
- [Cons set port unit port tagging enable](#)
- [COS mapping distribution across stack failed](#)
- [CoS shaping distribution across stack failed](#)
- [CoS shaping modifications not supported](#)
- [CoS shaping not supported with specified interface](#)
- [Count action distribution across stack failed](#)
- [Count action entry referenced by meter \(deletion prohibited\)](#)
- [Count action entry referenced by policy \(deletion prohibited\)](#)
- [Count action modifications not supported](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with D

This page lists all logs that have a starting letter of D. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [DAI: ARP packet with invalid IP/MAC binding dropped on untrusted port %d/%d. ARP packet has MAC source %02x-%02x-%02x-%02x-%02x-%02x.](#)
- [DAI ARP packet with invalid IP MAC binding dropped on untrusted port unit# port#](#)
- [DAPP-detected DoS attack blocked unit unit# \(many ports\)](#)
- [DAPP-detected DoS attack blocked unit unit# port port#](#)
- [DAPP resources not available \(unit unit# \)](#)
- [DAPP support disable failure](#)
- [DAPP support enable failure](#)
- [DAPP with statistics tracking in use \(QoS disable prohibited\)](#)
- [Data distribution class class# across stack failed](#)
- [Data model version attribute value not supported](#)
- [DAUR - Info Diag transfer finished](#)
- [DAUR - Info Receive request for diag image start transfer](#)
- [DAUR - Info Receive request for diag image. Unable to transfer](#)
- [DAUR - Info Send request for new diag image](#)
- [DAUR - Info Slave refuse transfer](#)
- [DAUR - Info Start receive image](#)
- [DAUR - The hardware is not compatible with the image version number version](#)
- [DAUR - Warning: Cannot get FLASH resource](#)
- [DAUR - Warning Diag image check sum ERROR](#)
- [DAUR - Warning Slave diag image check sum ERROR](#)
- [Default ifc assignment failure port# port\(s\) ifc QoS-disabled](#)
- [Destination MAC address and mask values out-of-sync](#)
- [DHCP packet with mismatch MAC address dropped on un-trusted port unit# port# mac\(MAC ADDRESS\)](#)
- [DHCP Snoop DHCP ACK dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop DHCP binding table is full additional DHCP clients will not be added to the binding table](#)
- [DHCP Snoop: DHCP DISCOVER dropped on port %d/%d \(source MAC not matching client MAC\)](#)
- [DHCP Snoop DHCP NAK dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop DHCP OFFER dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table](#)
- [DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table](#)
- [DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# because MAC Addr\(MACaddress \) is associated to port unit# port#](#)
- [DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# \(MAC Addr\(MACaddress \) does not exist in binding table\)](#)
- [DHCP Snoop DHCP REQUEST dropped on un-trusted port unit# port# due to source MAC address\(MAC ADDRESS\) not matching DHCP client](#)
- [DHCP Snoop DHCP snooping binding table restored successfully from TFTP address](#)
- [DHCP Snoop DHCP snooping binding table restored successfully from USB unit unit#](#)
- [DHCP Snoop: DHCP snooping binding table restore from SFTP address](#)
- [DHCP Snoop DHCP snooping binding table restore from TFTP address A.B.C.D IPv6 address failed](#)
- [DHCP Snoop DHCP snooping binding table restore from USB unit unit# failed](#)
- [DHCP Snoop: DHCP snooping binding table saved successfully to SFTP address](#)

- [DHCP Snoop DHCP snooping binding table saved successfully to TFTP address](#)
- [DHCP Snoop DHCP snooping binding table saved successfully to USB unit unit#](#)
- [DHCP Snoop: DHCP snooping binding table save to SFTP address](#)
- [DHCP Snoop DHCP snooping binding table save to TFTP address A.B.C.D IPv6 address failed](#)
- [DHCP Snoop: DHCP snooping binding table save to TFTP address, failed](#)
- [DHCP Snoop DHCP snooping binding table save to USB unit unit# failed](#)
- [DHCP Snoop: DHCP snooping binding table succesfully restored from SFTP address](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to expired lease](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to MAC conflict](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to parsing failure](#)
- [DHCP Snoop DHCP snooping entry with MAC MacAddress not restored on invalid interface unit# port#](#)
- [DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored \(invalid Vlan %d\)](#)
- [DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored on trusted interface %d/%d](#)
- [DHCP Snoop: DHCP snooping entry 0x%08x not restored on trusted interface %d/%d](#)
- [DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored \(invalid Vlan %d\)](#)
- [DHCP Snoop NTP is not synchronized: external save restore of DHCP snooping entries not possible](#)
- [Different classifier component masks keys in block detected](#)
- [Different spanning-tree mode configured than BU. Unit reconfigured and rebooted.](#)
- [Different spanning-tree mode configured than BU. Unit re-configured and rebooted](#)
- [Disallowed connection Access Reject for user](#)
- [Disallowed connection Access Reject for user](#)
- [Disallowed connection attempt from IP address](#)
- [Disallowed connection attempt - too many telnet sessions](#)
- [Disallowed connection Invalid SvcType for user](#)
- [Disallowed connection Invalid SvcType for user](#)
- [DISTRIBUTE DB event sent unit mask value appl mask value](#)
- [DosFs - Error File not closed](#)
- [Down 1 cable inserted or neighbor powered on](#)
- [Down 2 cable inserted or neighbor powered on](#)
- [Down 1 cable removed or neighbor powered off](#)
- [Down 2 cable removed or neighbor powered off](#)
- [Download - DL CKSUM ACK ERROR](#)
- [Download - DL PROGRAM STATUS ACK ERROR](#)
- [Download - DL START PROGRAM FLASH ACK ERROR](#)
- [Download - Error Failed to get the dl resource.](#)
- [Download - Error Watchdog expire No Ack from NBUs download MSG # message ID](#)
- [Download - Failed to get buffer](#)
- [Download - Failed to malloc for buffer](#)
- [Download - Failed to start a watchdog](#)
- [Download - Image Checksum Error](#)
- [Download - image type image_image version programmed successfully](#)
- [Download - Largest mem blk DL SYMEM RESERVED](#)
- [Download - NBU Block Checksum Error](#)
- [Download - NBU DL PROGRAM STATUS ERROR](#)
- [Download - TFTP timeout OR image file not found](#)
- [Download - tftpXfer failed](#)
- [Downstream stack direction is down cable removed or neighbor powered off](#)
- [Downstream stack direction is mis-configured](#)
- [Downstream stack direction is up cable inserted or neighbor powered on](#)
- [DSCP mapping distribution across stack failed](#)
- [DSCP mapping modifications not supported](#)
- [DSCP remarking not supported for IPv6 \(green action\)](#)
- [DSCP remarking not supported for IPv6 \(in-profile action\)](#)
- [DSCP remarking not supported for IPv6 \(match action\)](#)
- [DSCP remarking not supported for IPv6 \(non-match action\)](#)
- [DSCP remarking not supported for IPv6 \(out-of-profile action\)](#)
- [DSCP remarking not supported for IPv6 \(red action\)](#)
- [DSCP remarking not supported for IPv6 \(yellow action\)](#)
- [DSCP value modification prohibited](#)
- [Dst IP addr matching not supported with IP addr type data](#)
- [Dst Layer 4 port min max values invalid \(max must be = to min\)](#)
- [Dst MAC addr matching not supported with address type data](#)
- [Duplicate access asgn name type index detected \(prohibited\)](#)
- [Duplicate address deletion failed ipv6 address](#)

- [Duplicate address detection succeeded ipv6 address](#)
- [Duplicate classifier class values in set detected](#)
- [Duplicate entry detected \(prohibited\)](#)
- [Duplicate FCoE redirection entry detected](#)
- [Duplicate set values in block detected](#)
- [Dynamic ARP could not be learned, maximum dynamic ARP limit is reached.](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with E

This page lists all logs that have a starting letter of E. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [EAP Bad pkt id](#)
- [EAP Bad pkt len](#)
- [EAP: Cannot assign PVID %d, on port %d it is in another STP group](#)
- [EAP: Cannot auto-create VLAN %d, it is mapped to another STP group](#)
- [EAP CDT Error](#)
- [EAP Client blocked \(Block Subsequent MAC Authentication\): Different VID than expected](#)
- [EAP Client blocked \(Block Subsequent MAC Authentication\): Invalid VID](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All bindings have been rejected](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All RAVs or Bindings from RADIUS are invalid](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Autocreate is enabled, but no RAV is present](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Cannot use FA bindings in Legacy or Autoprov networks](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. EAP FA context unknown network](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Only MHSA mode supports multiple RAVs](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Receiving unconfigured VLAN from Radius without Autocreate](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid bindings exceeded the maximum threshold of 16](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid not supported in MHMA and SHSA](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid with Isid not equal to 0 not supported in Standalone Proxy or Autoprov](#)
- [EAP Could not process pkt](#)
- [EAP Error - Default](#)
- [EAP Error - Failed to free mac info memory](#)
- [EAP Error Radius - ifIndex not found](#)
- [EAP Error: Reached maximum number of messages in the queue](#)
- [EAP Error while sending Access Violation Trap](#)
- [EAP Error while sending RAV Error Trap](#)
- [EAP Failed initialize global arrays](#)
- [EAP Failed qpa-RoleAssociation unitPort ifIndex macHi xx-xx macLo xx-xx-xx-xx](#)
- [EAP Failed qpa-RoleAssociation unitPort 0x%x mac %08x%04x](#)
- [EAP Failed to add host, max number of clients reached](#)
- [EAP Failed to add host, memory allocation error](#)
- [EAP Failed to create dyna global arrays](#)
- [EAP GVlan Disabled for unitPort ifIndex - GVlan\(vid \) in different stg\(id \)](#)
- [EAP IMC Failed to send message](#)
- [EAP IMC Memory allocation error](#)
- [EAP Invalid RAV ID](#)
- [EAP Invalid Vlan ID vid configured for port num](#)
- [EAP Mac AuthFail - unitPort <unit-portnum> macHi <xx-xx> macLo <xx-xx-xx-xx>](#)
- [EAP Memory allocation error](#)
- [EAP Message queue error](#)
- [EAP Neap port was not member of any vlan](#)
- [EAP NULL pkt to send on Success](#)
- [EAP NVRAM open error](#)
- [EAP NVRAM read port admin state error](#)
- [EAP NVRAM read system admin state error](#)

- [EAP NVRAM read system ubp state error](#)
- [EAP NVRAM write error](#)
- [EAP Reached Mac Intruder Count](#)
- [EAP: Reached Mac Intruder Count](#)
- [EAP: Receiving unsupported Auto-Create-VLAN VSA in SHSA or MHMA](#)
- [EAP Task spawn error](#)
- [EAP Unable to Reserve EapAdmin Filter Resources rc retCode unitPort ifIndex](#)
- [EAP Unable to Reserve Filter Resources rc retCode unitPort ifIndex Force- Unauthorised](#)
- [EAP Unable to UnReserve EapAdmin Filter Resources rc retCode unitPort ifIndex](#)
- [EAP Unable to UnReserve Filter Resources rc retCode unitPort unit-portnum](#)
- [EAP Vlan Change Aborted](#)
- [ECMP features disabled due to inadequate license](#)
- [Egp Neighbor Loss Trap](#)
- [Egress interface and egress mask are mutually exclusive](#)
- [Egress interface or trunk data is required - data missing](#)
- [Element deletion prohibited \(permanent read-only system entry\)](#)
- [Element enable prohibited. Please delete and re-enter data](#)
- [Element label contains unacceptable characters](#)
- [Element label length outside of acceptable limits \(max 16 chars\)](#)
- [Element label not acceptable - reserved](#)
- [Element may only be modified not created or deleted](#)
- [Element modification prohibited \(read-only or system entry\)](#)
- [Enterprise Specific Trap](#)
- [Error accessing Image File](#)
- [Error Bad Image Checksum](#)
- [Error configuring 802.1AB](#)
- [Error configuring LLDP MED policies](#)
- [Error configuring Management IP Address](#)
- [Error configuring port names](#)
- [Error creating Data VLAN](#)
- [Error creating MLT](#)
- [Error creating Voice VLAN](#)
- [Error deleting previously created cost 1 default route](#)
- [Error deleting previously created Voice and Data VLANs](#)
- [Error disabling global DHCP relay errCode](#)
- [Error enabling ADAC](#)
- [Error enabling ADAC on ports](#)
- [Error enabling global DHCP relay errCode](#)
- [Error enabling IP Routing](#)
- [Error enabling mstp learning on all ports](#)
- [Error enabling rstp learning on all ports](#)
- [Error executing script](#)
- [Error getting VLAN info for Port's pvid](#)
- [Error in XGS3 memory DMA transfer](#)
- [Error loading backup configuration block # block_number](#)
- [Error loading configuration block %d](#)
- [Error loading primary configuration block # block_number](#)
- [Error reading Image File](#)
- [Error reading nvq_ObjDescr from VLAN file](#)
- [Error reading prec from VLAN file](#)
- [Error reading vmrec from VLAN file](#)
- [Error reading vrec from VLAN file](#)
- [Error restoring from VLAN file](#)
- [Error restoring from VLAN file. Wrong nvq.Descr.devVer](#)
- [Error restoring from VLAN file. Wrong nvq.Descr.notBlank](#)
- [Error restoring management vlan to 1 or disabling ip routing](#)
- [Error restoring nvq.Descr from VLAN file](#)
- [Error restoring object from VLAN file - bad file pointer or mode](#)
- [Error restoring object from VLAN NVRAM file](#)
- [Error restoring Port from VLAN NVRAM file](#)
- [Error restoring Ports from VLAN file](#)
- [Error restoring VLANs from VLAN file](#)
- [Error restoring VMACs from VLAN file](#)
- [Error saving configuration](#)
- [Error saving configuration to block # block_number](#)

- [Error seeking object in VLAN file](#)
- [Error seeking Ports in VLAN file](#)
- [Error seeking VLANs in VLAN file](#)
- [Error seeking VMACs in VLAN file](#)
- [Error setting ADAC operating mode](#)
- [Error setting call server ports](#)
- [Error setting Data VLAN Gateway IP address and network mask](#)
- [Error setting default IP Route](#)
- [Error setting IP Office Call-Server IP address](#)
- [Error setting IP Office File-Server IP address](#)
- [Error setting Management VLAN](#)
- [Error setting poe-priority high on ports](#)
- [Error setting QoS](#)
- [Error setting spanning-tree learning to fast on all ports](#)
- [Error setting uplink ports](#)
- [Error setting VLAN attributes](#)
- [Error setting VLAN Gateway IP address and network mask](#)
- [Error setting Voice VLAN Gateway IP address and network mask](#)
- [Evaluation precedence conflict detected \(UBP filter set data\)](#)
- [Evaluation precedence conflict \(Traffic Prof filter set data\)](#)
- [Evaluation precedence value required but not specified](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with F

This page lists all logs that have a starting letter of F. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Fabric Attach: agent settings reset incomplete](#)
- [Fabric Attach: asgn activation failure \(port tagging\)](#)
- [Fabric Attach: asgn activation failure \(VLAN creation\)](#)
- [Fabric Attach: asgn activation failure \(VLAN membership\)](#)
- [Fabric Attach: auto provision setting not supported by platform](#)
- [Fabric Attach: binding acceptance failure \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding accepted \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation failure \(<ISID>/<VID>\)](#)
- [Fabric Attach: binding activation success \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation success \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding deactivation failure \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding deactivation failure \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding deactivation success \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding deactivation success \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding expiration \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: client binding deleted \(<IFINDEX>/<ISID>/<VID>\)](#)
- [Fabric Attach: conflicting uplink data detected](#)
- [Fabric Attach: device deleted \(port <PORT>\)](#)
- [Fabric Attach: device deleted \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Fail - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Fail - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Pass - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Pass - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Not Authenticated - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Not Authenticated - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device expired \(port <PORT>\)](#)
- [Fabric Attach: device expired \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: element type updated](#)
- [Fabric Attach: incompatible device advertisement \(port <PORT>\)](#)
- [Fabric Attach: incompatible device advertisement \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: interface-specific I-SID/VLAN assignments not allowed](#)
- [Fabric Attach: invalid VLAN data \(unknown or incompatible type\)](#)
- [Fabric Attach: I-SID/VLAN assignment creation failure \(unexpected\)](#)
- [Fabric Attach: I-SID/VLAN assignment deletion failure \(unexpected\)](#)
- [Fabric Attach: management VLAN updated \(was <VID>, now <VID>\) by Zero Touch](#)
- [Fabric Attach: message authentication support not available](#)
- [Fabric Attach: multiple FA Servers detected](#)
- [Fabric Attach: non-MLT trunk uplink requires MLT ID/LACP key binding \(missing\)](#)
- [Fabric Attach: operation failure detected](#)
- [Fabric Attach: operation rejected - client-owned entry](#)
- [Fabric Attach: operation rejected - CVLAN already exists](#)
- [Fabric Attach: operation rejected - entry does not exist](#)
- [Fabric Attach: operation rejected - not supported by element type](#)
- [Fabric Attach: operation rejected - service not enabled](#)
- [Fabric Attach: operation rejected - table entry limits reached](#)

- [Fabric Attach: port authentication update - data flushed \(MLT %d\)](#)
- [Fabric Attach: port authentication update - data flushed \(port %d\)](#)
- [Fabric Attach: port authentication update - data flushed \(port %d/%d\)](#)
- [Fabric Attach: primary FA Server lost](#)
- [Fabric Attach: primary FA server selected \(port %d\)](#)
- [Fabric Attach: primary FA server selected \(port %d/%d\)](#)
- [Fabric Attach: primary FA server selected \(trunk %d\)](#)
- [Fabric Attach: proxy not supported by element type](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - application interactions](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - invalid VLAN](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - no FA resources](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - no VLAN resources](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - peer acceptance](#)
- [Fabric Attach: server connection type change](#)
- [Fabric Attach: server connection type change \(different ports\)](#)
- [Fabric Attach: server connection type change \(different trunks\)](#)
- [Fabric Attach: server connection type change \(non-trunk to trunk\)](#)
- [Fabric Attach: server connection type change \(trunk to non-trunk\)](#)
- [Fabric Attach: service disabled](#)
- [Fabric Attach: service enabled](#)
- [Fabric Attach: specified element type not supported](#)
- [Fabric Attach: specified uplink currently a trunk member](#)
- [Fabric Attach: specified uplink currently invalid](#)
- [Fabric Attach: standalone/non-standalone proxy transition \(service reset\)](#)
- [Fabric Attach: static uplink addition failure](#)
- [Fabric Attach: static uplink deletion failure](#)
- [Fabric Attach: temporary I-SID/VLAN binding deletion failure](#)
- [Fabric Attach: trunk link automatically enabled \(MLT %d port %d/%d\)](#)
- [Fabric Attach: uplink operation only supported by FA Proxy](#)
- [Fabric Attach: Zero Touch capabilities disabled](#)
- [Fabric Attach: Zero Touch capabilities enabled](#)
- [Fabric Attach: zero touch operations not completed \(mgmt VLAN <VID>\)](#)
- [Fabric Attach: Zero Touch option processing failure detected](#)
- [Fabric Attach: Zero Touch settings read-only for FA element type](#)
- [Failed ARP add ip addr 0xFFFFFFFF to HW hw error code](#)
- [Failed login from IP address](#)
- [Failed login from serial connection](#)
- [Failed login \(local auth\) from IP address:](#)
- [Failed login \(local auth\) from serial connection](#)
- [Failed login\(radius auth\) from IP add](#)
- [Failed login\(radius auth\) from serial conn](#)
- [Failed MVLAN\(vid \) L3 ip addr ip mask](#)
- [Failed route add <ip addr/ip mask> to HW <hw error code>](#)
- [Failed to Create a Watchdog](#)
- [Failed to create IP intf vid ip addr in HW hw error code](#)
- [Failed to Read Image from Memory](#)
- [FCoE controller ifIndex not set - FCoE redirection enable prohibited](#)
- [FCoE controller VLAN not set - FCoE redirection enable prohibited](#)
- [FCoE redirection default frame filter deletion failure detected](#)
- [FCoE redirection default frame filter installation failure detected](#)
- [FCoE redirection - egress interface issue detected \(ifIndex %d\)](#)
- [FCoE redirection - egress trunk issue detected \(trunk ID %d\)](#)
- [Filter control block resources exhausted](#)
- [Filter creation issue detected - in-profile action component](#)
- [Filter creation issue detected - match action component](#)
- [Filter creation issue detected - metering component](#)
- [Filter creation issue detected - non-match action component](#)
- [Filter creation issue detected - out-of-profile action component](#)
- [Filter limiting mode not supported on 5510-XX unit cannot join stack](#)
- [Filter manager internal error encountered](#)
- [Filter manager memory resources exhausted](#)
- [Filter manager metering or policy rule space exhausted](#)
- [Filter manager metering resources exhausted](#)
- [Filter manager request parameter invalid](#)

- [Filter manager statistics tracking resources exhausted](#)
- [Filter set requirements incompatible with target interface](#)
- [First TrTCM Meter Index must be in range 1-5000](#)
- [Flash Erase Failed Sector %d Address 0x%x](#)
- [Flash Erase Warning Sector %d Address 0x%x Erase time %d ms](#)
- [Flow ID filtering not supported for IPv4](#)
- [Flow ID out-of-range \(Flow ID \)](#)
- [Front-panel UI selected use rear-panel base non-base switch](#)
- [FSH - Error Calling taskLock\(\) returns Error](#)
- [FSH - Error Failed to erase flash sector](#)
- [FSH - Error Failed to lock flash sector](#)
- [FSH - Error Failed to program flash](#)
- [FSH - Error Failed to unlock flash sector](#)
- [FSH - Error Failed to write to flash address](#)
- [FSH - File not closed .:](#)
- [FSH - Some files are not closed. MsgType #%d](#)
- [FSH - Time to Download the Image number seconds](#)
- [FSH - Time to Program the Image to flash number seconds](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with G

This page lists all logs that have a starting letter of G. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Gateway IP changed](#)
- [Got UserPolicy from Radius but UBP disabled - unitPort 0x%x mac %08x%04x](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with H

This page lists all logs that have a starting letter of H. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Hello Module unable to communicate with neighbor\(s\) unit reset](#)
- [Hello Module unable to communicate with neighbor\(s\) unit reset](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with I

This page lists all logs that have a starting letter of I. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Ifc app modification issue \(inconsistent default gateway data\)](#)
- [Ifc app modification issue \(inconsistent DHCP server data\)](#)
- [Ifc app modification issue \(inconsistent ifType data\)](#)
- [Ifc app support not currently available on interface \(ifc# \)](#)
- [Ifc assignment issue - prec conflict \(policy policy# disabled\)](#)
- [IGMP Added reserved multicast address](#)
- [IGMP Error sending database from unit unit#](#)
- [IGMP Error sending group database from unit unit#](#)
- [IGMP Exceeded reserved multicast address range #Addr numResAddrEntries+1 * #VLANs numActiveVLANs maxReservedRange](#)
- [IGMP Initialization failed Error code errCode](#)
- [IGMP: Max hardware Resources reached](#)
- [IGMP Maximum number of igmp enabled interfaces reached](#)
- [IGMP No hardware resource available](#)
- [IGMP Proxy disabled on VLAN vlan#](#)
- [IGMP Proxy enabled on VLAN vlan#](#)
- [IGMP Query Time set to num on VLAN vlan#](#)
- [IGMP Removed reserved multicast address](#)
- [IGMP Robust Value set to num on VLAN vlan#](#)
- [IGMP Snooping disabled on VLAN vlan#](#)
- [IGMP Snooping enabled on VLAN vlan#](#)
- [IGMP SSM Range changed](#)
- [IGMP SSM Range changed](#)
- [IGMP Unable to add reserved multicast address](#)
- [IGMP Unknown Multicast Filter disabled](#)
- [IGMP Unknown Multicast Filter enabled](#)
- [IGMP: Unknown Query received on SPBM Multicast C-VLAN](#)
- [IGMP: V2 report drop on reserved GA](#)
- [IGMP: V3 report group skip on invalid GA](#)
- [IGMP: V3 report group skip on reserved GA](#)
- [IGMP V1 router ports mask](#)
- [IGMP V2 router ports mask](#)
- [IMC buffers of size buffer size have been exhausted buffer pool size pool size](#)
- [IMC buffers of size size have been exhausted buffer pool size size](#)
- [IMC imc_idtPacketDispatch\(\) incorrect rcvMsgType = %s\(%d\)](#)
- [IMC memory allocation error packetLength = %d file %s line %d](#)
- [Inadequate resources available for application policy criteria](#)
- [Incompatible base action extension specified](#)
- [Incompatible classifier reference \(agent-defined clfr\)](#)
- [Incompatible data model version values \(referenced clfr data\)](#)
- [Incompatible data model version values \(referenced meter data\)](#)
- [Incompatible in-profile action \(trusted ifc\)](#)
- [Incompatible in-profile action \(unrestricted ifc\)](#)
- [Incompatible in-profile action \(untrusted ifc\)](#)
- [Incompatible in-profile action \(untrustedv4v6 ifc\)](#)

- [Incompatible match action \(unrestricted ifc\)](#)
- [Incompatible match action \(untrusted ifc\)](#)
- [Incompatible match action \(untrustedv4v6 ifc\)](#)
- [Incompatible non-match action \(trusted ifc\)](#)
- [Incompatible non-match action \(unrestricted ifc\)](#)
- [Incompatible non-match action \(unrestricted ifc\)](#)
- [Incompatible non-match action \(untrusted ifc\)](#)
- [Incompatible out-of-profile action \(trusted ifc\)](#)
- [Incompatible out-of-profile action \(unrestricted ifc\)](#)
- [Incompatible out-of-profile action \(untrusted ifc\)](#)
- [Incompatible out-of-profile action \(untrustedv4v6 ifc\)](#)
- [Incompatible StorageType specified \(re classifier\)](#)
- [Inconsistent action criteria detected across block members](#)
- [Inconsistent classifier component \(clfr comp# \) state detected](#)
- [Inconsistent labels detected for members of same block](#)
- [Inconsistent labels detected for members of same set](#)
- [Inconsistent MAC data detected across filter set members](#)
- [Inconsistent metering criteria detected across block members](#)
- [Index value out-of-range](#)
- [Info: Transceiver inserted on %s](#)
- [Info: Transceiver removed from %s](#)
- [Inner VLAN ID filtering requires double tag](#)
- [Inner VLAN ID min max values invalid \(min VLAN ID ! max VLAN ID \)](#)
- [In-profile action contains conflicting data](#)
- [Insufficient HW resources to support port role association](#)
- [Insufficient policy space available to support access assignment](#)
- [Insufficient resources available to support policy installation](#)
- [Interface action distribution across stack failed](#)
- [Interface action entry referenced by base action](#)
- [Interface action extension identifier invalid](#)
- [Interface action modifications not supported](#)
- [Interface Application data in use \(QoS disable prohibited\)](#)
- [Interface application distribution across stack failed](#)
- [Interface application modifications not supported](#)
- [Interface application Undo failure \(app app# \)](#)
- [Interface assignment distribution across stack failed](#)
- [Interface assignment failure - precedence conflict detected](#)
- [Interface assignment modifications not supported](#)
- [Interface capabilities incompatible with policy data](#)
- [Interface data out-of-sync in Policy and User Policy entries](#)
- [Interface queue modifications not supported](#)
- [Interface resources inadequate to support application enable](#)
- [Interface shaping and CoS shaping conflict \(same ifc specified\)](#)
- [Interface shaping and queue shaping conflict \(same ifc specified\)](#)
- [Interface shaping modifications not supported](#)
- [Interface shaping not supported with specified interface](#)
- [Interfaces QoS-disabled \(port# on unit# \) - restoration issue](#)
- [Invalid access assignment type option specified](#)
- [Invalid access element type option specified](#)
- [Invalid classifier ID specified](#)
- [Invalid classifier reference](#)
- [Invalid classifier reference \(unknown class\)](#)
- [Invalid classifier reference \(unknown incompatible set\)](#)
- [Invalid classifier reference \(unknown instance\)](#)
- [Invalid Configuration Block Number %d](#)
- [Invalid Configuration Magic Number](#)
- [Invalid Configuration Version Number](#)
- [Invalid DAPP state transition detected \(prohibited\)](#)
- [Invalid datapath identifier specified](#)
- [Invalid destination MAC address length specified](#)
- [Invalid destination MAC address mask length specified](#)
- [Invalid drop action option specifiedInvalid drop action option specified](#)
- [Invalid drop precedence value specified \(precedence \)](#)
- [Invalid DSCP value specified \(DSCP value \)](#)
- [Invalid egress interface specified \(ifc# \)](#)

- [Invalid egress interface type specified \(<ifc type>\)](#)
- [Invalid egress mask value specified](#)
- [Invalid entry creation attempted \(index index# \)](#)
- [Invalid EtherType value specified \(Ether Type 0xXXXX \)](#)
- [Invalid expired session data specified](#)
- [Invalid FCoE controller ingress interface specified](#)
- [Invalid FCoE controller VLAN specified](#)
- [Invalid filter set priority value detected](#)
- [Invalid interface found in egress mask \(egress mask bit# \)](#)
- [Invalid interface index data specified \(ifc# \)](#)
- [Invalid interface index data specified \(ifc index \)](#)
- [Invalid interface index data \(system-owned\) specified](#)
- [Invalid IP destination address prefix detected](#)
- [Invalid IP source address prefix detected](#)
- [Invalid master block member value specified](#)
- [Invalid maximum inner VLAN ID value specified \(VLAN ID \)](#)
- [Invalid maximum VLAN ID value specified \(VLAN ID \)](#)
- [Invalid metering data \(bucket size\) specified for interface\(s\)](#)
- [Invalid metering data \(granularity\) specified for interface\(s\)](#)
- [Invalid metering data \(rate\) specified for interface\(s\)](#)
- [Invalid metering data \(srTCM trTCM\) specified for interface\(s\)](#)
- [Invalid minimum inner VLAN ID value specified \(VLAN ID \)](#)
- [Invalid minimum VLAN ID value specified \(VLAN ID \)](#)
- [Invalid mix of IP address data \(Dst IP type\) in set detected](#)
- [Invalid mix of IP and non-IP data in set detected](#)
- [Invalid mix of IP data \(IPv4 IPv6\) in set detected](#)
- [Invalid option specified for BcastFrames attribute](#)
- [Invalid option specified for KnownIpMcast attribute](#)
- [Invalid option specified for KnownMcastFrames attribute](#)
- [Invalid option specified for KnownNonIpMcast attribute](#)
- [Invalid option specified for KnownUcastFrames attribute](#)
- [Invalid option specified for NonIpPkt attribute](#)
- [Invalid option specified for PatternIpVersion attribute](#)
- [Invalid option specified for UnknownMcastFrames attribute](#)
- [Invalid option specified for UnknownNonIpMcast attribute](#)
- [Invalid option specified for UnknownUcastFrames attribute](#)
- [Invalid pattern data length \(untagged format\) specified](#)
- [Invalid pattern data string length specified](#)
- [Invalid pattern format data specified](#)
- [Invalid pattern position string length specified](#)
- [Invalid port detected in specified port mask](#)
- [Invalid 802.1p user priority value specified \(priority value \)](#)
- [Invalid RAV id %d, on port %d, cannot be Switched UNI or B-VLAN](#)
- [Invalid RAV id %d, on port %d, it isn't a CVLAN](#)
- [Invalid resetToDefaults value specified](#)
- [Invalid set drop precedence value specified](#)
- [Invalid shaping data \(bucket size\) specified for interface\(s\)](#)
- [Invalid shaping data \(granularity\) specified for interface\(s\)](#)
- [Invalid shaping data \(minimum rate granularity\) specified](#)
- [Invalid shaping data \(minimum rate maximum rate\) specified](#)
- [Invalid shaping data \(minimum rate\) specified](#)
- [Invalid shaping data \(rate\) specified for interface\(s\)](#)
- [Invalid source MAC address length specified](#)
- [Invalid source MAC address mask length specified](#)
- [Invalid statistics counter identification specified](#)
- [Invalid statistics tracking value](#)
- [Invalid statistics type value](#)
- [Invalid track statistics value specified](#)
- [Invalid unknown access assignment entry state encountered \(entry state \)](#)
- [Invalid unknown access element entry state encountered \(entry state \)](#)
- [Invalid unknown action entry state encountered \(entry state \)](#)
- [Invalid unknown bandwidth type specified](#)
- [Invalid unknown classifier block entry state encountered \(entry state \)](#)
- [Invalid unknown CoS shaping entry state encountered \(entry state \)](#)
- [Invalid unknown DSCP mapping entry state encountered \(entry state \)](#)

- [Invalid unknown entry state \(class class# \) encountered \(entry state \)](#)
- [Invalid/unknown FCoE redirection egress trunk ID specified](#)
- [Invalid unknown interface action entry state encountered \(entry state \)](#)
- [Invalid/unknown interface app entry state encountered \(<entry state>\)](#)
- [Invalid unknown interface assignment entry state encountered \(entry state \)](#)
- [Invalid unknown interface queue entry state encountered \(entry state \)](#)
- [Invalid unknown interface shaping entry state encountered \(entry# \)](#)
- [Invalid unknown IP filter entry state encountered \(entry state \)](#)
- [Invalid unknown Layer 2 filter entry state encountered \(entry state \)](#)
- [Invalid unknown meter entry state encountered \(entry state \)](#)
- [Invalid unknown policy entry state encountered \(entry state \)](#)
- [Invalid unknown 802.1p user priority mapping entry state \(entry state \)](#)
- [Invalid unknown queue set assignment entry state encountered \(entry state \)](#)
- [Invalid unknown queue shaping entry state encountered \(entry state \)](#)
- [Invalid unknown queuing discipline enum specified \(queuing discipline \)](#)
- [Invalid unknown role combination entry state encountered \(entry state \)](#)
- [Invalid unknown System filter entry state encountered \(entry state \)](#)
- [Invalid unknown token bucket entry state encountered \(entry state \)](#)
- [Invalid unknown user policy entry state encountered \(entry state \)](#)
- [Invalid unsupported buffering capabilities value specified](#)
- [Invalid unsupported copy-to-cpu option specified](#)
- [Invalid unsupported DAPP enable value specified](#)
- [Invalid unsupported DAPP maximum IPv4 ICMP length specified](#)
- [Invalid unsupported DAPP maximum IPv6 ICMP length specified](#)
- [Invalid unsupported DAPP minimum TCP header length specified](#)
- [Invalid unsupported default gateway address length specified](#)
- [Invalid unsupported default gateway address specified](#)
- [Invalid unsupported destination IP address length specified](#)
- [Invalid unsupported DHCP server address length specified](#)
- [Invalid unsupported DHCP server address specified](#)
- [Invalid unsupported interface type specified](#)
- [Invalid unsupported mirror frame option specified](#)
- [Invalid unsupported NT application mode value specified](#)
- [Invalid unsupported packet type value specified](#)
- [Invalid unsupported OoS system operational mode value specified](#)
- [Invalid unsupported queue configuration value specified](#)
- [Invalid unsupported role assoc compatibility specified](#)
- [Invalid unsupported source IP address length specified](#)
- [Invalid unsupported Trusted processing mode value specified](#)
- [Invalid unsupported UBP support level value specified](#)
- [Invalid unsupported VLAN tag value specified \(VLAN tag \)](#)
- [Invalid update DSCP value specified \(DSCP value \)](#)
- [Invalid update DSCP value specified \(not currently supported\)](#)
- [Invalid update priority value specified](#)
- [Invalid update VLAN Id specified \(VLAN Id \)](#)
- [Invalid user priority match selection specified \(priority value \)](#)
- [IP blocking now 1 2 \(1=ON 2=OFF\)](#)
- [IP classifier distribution across stack failed](#)
- [IP classifier entry still referenced \(deletion prohibited\)](#)
- [IP classifier modifications not supported](#)
- [IP destination address and mask values out-of-sync](#)
- [IP destination Layer 4 port maximum value out-of-range \(dest port#](#)
- [IP destination Layer 4 port minimum value out-of-range \(dest port# \)](#)
- [IPFIX enable failure](#)
- [IpFwdNhop Err Filter Install mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Filter Modify mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Filter UnInstall mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Save DB to NVRAM General File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop Err Save DB to NVRAM Instance File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop Err Save DB to NVRAM Policy File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop: Feature enable temporarily blocked - resources unavailable](#)
- [IpFwdNhop: Filter installation issue - resources unavailable](#)
- [IpFwdNhop: Issue detected during data restore \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during enable retry \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during feature enable \(interface entry %d\)](#)

- [IpFwdNhop: Issue detected during interface creation \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during VLAN %d routing status update](#)
- [IpFwdNhop: Issue detected during VLAN membership addition \(VID %d\)](#)
- [IpFwdNhop: Issue detected during VLAN membership deletion \(VID %d\)](#)
- [IpFwdNhop: Issue detected during VLAN policy association \(entry %d\)](#)
- [IpFwdNhop: Requested precedence and/or filter resources unavailable](#)
- [IpFwdNhop: Requested range checking resources unavailable](#)
- [IpFwdNhop: VLAN membership update \(VID %d\) issue - resources unavailable](#)
- [IP protocol value out-of-range \(IP protocol# \)](#)
- [IP protocol value TCP or UDP needed with Layer 4 port filtering](#)
- [IPSG Insufficient resources available to enable IPSG on port unit# port#](#)
- [IPSG Maximum IP entries on port unit# port# has been reached](#)
- [IPSG nvRam file error param1 param2 param3](#)
- [IPSG Reached Max. IP entries supported on this port port#](#)
- [IPSG Reached Max. IP entries supported on this port unit# port#](#)
- [IPSG Resource allocated for Ports unit# port#](#)
- [IP source address and mask values out-of-sync](#)
- [IP Source Guard disabled on Unit unit# Port port#](#)
- [IP Source Guard enabled on Unit unit# Port port#](#)
- [IP source Layer 4 port minimum value out-of-range \(src port# \)](#)
- [IP source Layer 4 port minimum value out-of-range \(src port# \)](#)
- [IPT BootP Disabled \(response not received from server\)](#)
- [IPT IP Address changed by BOOTP Server](#)
- [IPT: IP Address not in use \(duplicate detected\)](#)
- [IPv6 enabled with hardware support and FMGR filters](#)
- [IPv6 enabled with hardware support only](#)
- [IPv6 Forwarding disabled due to inadequate license](#)
- [IPv6 malloc failure](#)
- [IPv4-only filter criteria mixed with IPv6 criteria](#)
- [Issue detected during OoS stack synchronization](#)
- [Issue detected enabling/disabling DSCP Mapping Table usage \(port %d\)](#)
- [Issue detected enabling/disabling DSCP table usage \(port#\)](#)
- [Issue detected restoring QPA data from NV \(class class# \)](#)
- [Issue detected setting native DSCP Mapping Table values](#)
- [Issue detected setting native DSCP table values](#)
- [Issues detected with OoS operational mode disable \(ifcs# ifcs\)](#)
- [Issues detected with OoS operational mode enable \(ifcs# ifcs\)](#)
- [Issue with classifier component mask detected](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with J

This page lists all logs that have a starting letter of J. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [JOIN event sent unit mask value appl mask value](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with L

This page lists all logs that have a starting letter of L. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [LAC MLT error on far end. 0 - 0 - 0](#)
- [LAC: MLT error, partner aggregation bit not set](#)
- [LAC: MLT error, partner expired bit set.](#)
- [LAC: MLT error, partner synchronization bit not set.](#)
- [LAC No more trunk group available for LAC. 0 - 0 - 0](#)
- [LAC with admin key %d failed configuration verification. Bad ARP INSPECTION configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad DHCP-SNOOPING configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad IGMP configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad MAC Security configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad qos status.](#)
- [LAC with admin key %d failed configuration verification. Bad rate-limiting configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad VLAN configuration.](#)
- [LAC with admin key %d failed configuration verification. Error #: %d-%d](#)
- [LAC with admin key %d failed configuration verification. Ports have different qos config.](#)
- [LAC with admin key %d failed configuration verification. Ports have different SPBM configurations.](#)
- [Last MLT trunk was allocated by LAC. No more free trunk groups.](#)
- [Last MLT trunk was allocated by MLT. No more free trunk groups.](#)
- [Layer 2 classifier modifications not supported](#)
- [Layer 2 classifier still referenced \(deletion prohibited\)](#)
- [Layer 2 filter distribution across stack failed](#)
- [Layer 4 port filtering with IPv6 requires UDP TCP Next Header](#)
- [Layer 4 port range could not be reduced sufficiently](#)
- [LEAVE event sent unit mask value appl mask value](#)
- [Link Down Trap](#)
- [LinkStateTracking: First interface %d/d went up in link state group %d, enabling downstream ports](#)
- [LinkStateTracking: First interface mlt %d went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: Interface %d/d went down in link state group %d](#)
- [LinkStateTracking: Interface %d/d went up in link state group %d](#)
- [LinkStateTracking: Interface mlt %d went down in link state group %d](#)
- [LinkStateTracking: Interface mlt %d went up in link state group %d](#)
- [LinkStateTracking: Interface %s went down in link state group %d](#)
- [LinkStateTracking: Interface %s went up in link state group %d](#)
- [LinkStateTracking: Last interface %d/d went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface mlt %d went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces](#)
- [Link Up Trap](#)
- [Loading configuration block # block_number](#)
- [Local authentication disabled on serial](#)
- [Local authentication disabled on telnet](#)
- [Local authentication enabled on serial](#)
- [Local authentication enabled on telnet](#)
- [Login timeout serial connection](#)

- [Lossless and Lossless-PFC modes are only supported in queue set 2](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with M

This page lists all logs that have a starting letter of M. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [MAC security table full](#)
- [MAC %02x:%02x:%02x:%02x:%02x:%02x not authenticated: only one client is allowed in MHSA mode](#)
- [Management IP: excess traffic received on Management port%s](#)
- [Management IP: OOB port%s](#)
- [Management IP: OOB port%s](#)
- [Maximum number of dynamic routes reached](#)
- [MCM group node corrupted:](#)
- [Memory Allocation Error](#)
- [Memory on unit %d is under %d MBytes.](#)
- [Meter distribution across stack failed](#)
- [Meter entry referenced by clfr block \(deletion prohibited\)](#)
- [Meter entry referenced by meter \(deletion prohibited\)](#)
- [Meter entry referenced by policy \(deletion prohibited\)](#)
- [Meter \(from clfr block\) usage in multiple policies prohibited](#)
- [Meter \(from policy\) usage in multiple policies prohibited](#)
- [Meter identifier out-of-range \(meter id \)](#)
- [Metering not supported with DS L2 access control lists](#)
- [Meter modifications not supported](#)
- [Mirroring \(requested via action\) not configured correctly](#)
- [MLD: Maximum number of mld enabled interfaces reached](#)
- [MLD: The maximum number of available hardware MLD entries has been reached](#)
- [MLD: The maximum number of available hardware MLD entries has been reached](#)
- [MLT %d failed configuration verification. Bad ARP INSPECTION configuration.](#)
- [MLT %d failed configuration verification. Bad DHCP-SNOOPING configuration.](#)
- [MLT %d failed configuration verification. Bad IGMP configuration.](#)
- [MLT %d failed configuration verification. Bad IPSG CLASS configuration.](#)
- [MLT %d failed configuration verification. Bad MAC learning configuration.](#)
- [MLT %d failed configuration verification. Bad rate-limiting configuration.](#)
- [MLT %d failed configuration verification. Bad SPBM configuration.](#)
- [MLT %d failed configuration verification. Bad VLACP configuration](#)
- [MLT %d failed configuration verification. Bad VLAN configuration.](#)
- [MLT ID# failed configuration verification. Error # error num](#)
- [MLT NV File error](#)
- [Modification of action \(non-match usage\) prohibited](#)
- [Modify the pattern data or use the correct data format](#)
- [MODULE_INACTIVE event sent unit mask value appl mask value](#)
- [More than value units discovered](#)
- [Multiple base units detected](#)
- [Multiple Waverunner units detected when base is a Flagship](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with N

This page lists all logs that have a starting letter of N. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [NEAP Accounting - Memory allocation failure](#)
- [Network access settings for FCoE Redirect must be modified locally](#)
- [Non-EAP Client blocked \(Block Subsequent MAC Authentication\): Different VID than expected](#)
- [Non-EAP Client blocked \(Block Subsequent MAC Authentication\): EAP Use Rav Not enabled](#)
- [Non-match action contains conflicting data](#)
- [Non-match action not available for use with filter sets](#)
- [Non-match action support not available on certain interfaces](#)
- [Non-QoS interfaces may not be assigned to a role combination](#)
- [Non-supported action option \(green action\) specified](#)
- [Non-supported action option \(in-profile action\) specified](#)
- [Non-supported action option \(match action\) specified](#)
- [Non-supported action option \(out-of-profile action\) specified](#)
- [Non-supported action option \(policy non-match action\) specified](#)
- [Non-supported action option \(red action\) specified](#)
- [Non-supported action option \(yellow action\) specified](#)
- [Non-unique element label detected \(prohibited\)](#)
- [Non-unique precedence order value detected \(prohibited\)](#)
- [Non-volatile OoS data discarded during restoration](#)
- [Non-volatile storage commit delay too large](#)
- [No resources available for classifier port range checking](#)
- [No Response from RADIUS Server](#)
- [Not Enough Memory](#)
- [Notice: DAC Cable on %s is below HW rev "H" and may cause link issues with a small number of PHYs](#)
- [NT application mode enable failure - inadequate resources](#)
- [Number of VLANs does not match BU number of VLANs. VLAN config defaulted](#)
- [Number of VLANs does not match BU number of VLANs. VLAN config defaulted](#)
- [NUOC - Disabled](#)
- [NUOC - Enabled](#)
- [NUOC - Execution of the cli template failed](#)
- [NUOC - Execution of the cli template succeeded](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with O

This page lists all logs that have a starting letter of O. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Only one frame type supported per classifier](#)
- [Ospf Area Mismatch RxArea ra.rb.rc.rd IntfArea ia.ib.ic.id](#)
- [Ospf Auth Failed IpAddr ia.ib.ic.id](#)
- [Ospf Auth Type Mismatch in Hello](#)
- [Ospf Auto Virt Link Failed area a1.a2.a3.a4 rtid r1.r2.r3.r4](#)
- [Ospf Bad Version](#)
- [OSPF Callback function of timer is NULL](#)
- [Ospf Cost Exceeds Limit Skip route Lsid l1.l2.l3.l4 Adv-rtr a1.a2.a3.a4](#)
- [OspfDbg Done Filter Init](#)
- [OspfDbg Done Global Init](#)
- [OspfDbg Done NV-Restore](#)
- [OspfDbg Done ReDist Init](#)
- [OspfDbg Init Instance vrfId=%d nodeP=0x%0x](#)
- [OspfDbg PostInit Done vrfId=%d nodeP=0x%0x](#)
- [OspfDbg PostInit EnableOspf vrfId=%d nodeP=0x%0x](#)
- [OspfDbg Started ospfTxHelloTimerTask](#)
- [Ospf Dead Int Mismatch in Hello](#)
- [Ospf Enable Failed as Resource Unavailable](#)
- [Ospf Hello Int Mismatch in Hello](#)
- [Ospf Hello: RId Same as Neighbor: rtid <r1.r2.r3.r4>, IpAddr <i1.i2.i3.i4>](#)
- [Ospf HW Mode Change:](#)
- [Ospf Invalid packet received: Pkt type <ospfPacketType>](#)
- [Ospf License Is Missing. Disable OSPF](#)
- [Ospf Nbr State Change: rtid <ra.rb.rc.rd> ipa <ia.ib.ic.id> state <neighborState>](#)
- [Ospf Netmask Mismatch in Hello IpAddr ia.ib.ic.id](#)
- [Ospf Option Mismatch in Hello IpAddr ia.ib.ic.id RxOption optionVal IntfOption optionVal](#)
- [OSPF Timer Link Error](#)
- [OSPF Timer List is corrupted](#)
- [OSPF Timer Unlink Error](#)
- [Ospf Virt Nbr State Change: rtid <r1.r2.r3.r4>, virtAreaId <v1.v2.v3.v4>, state <neighborState>](#)
- [Out-of-profile action contains conflicting data](#)
- [Out-of-range CoS index value \(COS index value \)](#)
- [Out-of-range queue index value \(queue index \) for in-use queue set](#)
- [Out-of-range queue index value \(queue index \) for pending queue set](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with P

This page lists all logs that have a starting letter of P. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Packet redirection support limited by target interfaces](#)
- [Pattern matching data in excess of bytes# bytes specified](#)
- [Pattern matching \(Dst IP\) not supported with IP addr type data](#)
- [Pattern matching \(Dst MAC\) not supported with address type data](#)
- [Pattern matching \(IP\) not supported with non-IP addr type data](#)
- [Pattern matching not supported with other classification data](#)
- [Pattern modifier data specified without actual pattern data](#)
- [Pattern position and data strings must be same length](#)
- [Pim E-BSR change](#)
- [Pim Invalid packet received](#)
- [Pim License Is Missing Disable PIM](#)
- [Pim Mode Change](#)
- [Pim Nbr State Change Up](#)
- [PIM Neighbor status change Down](#)
- [PIM Neighbor status change Up](#)
- [Pim RP type state](#)
- [Pim Unicast route change](#)
- [Pim Virt Nbr State Change Down](#)
- [Pim Virt Nbr State Change Up](#)
- [PM in port mirroring the old data were modified - feature Allow Traffic in mirror port was added.](#)
- [PM in port mirroring the old data were modified - feature Many to Many was added.](#)
- [PM in port mirroring the old data were modified - feature Many to One was added.](#)
- [PM in port mirroring the old data were modified - feature Many to One with 128bits was added.](#)
- [PM: in port mirroring the old data were modified - feature RSPAN was added](#)
- [PM in port mirroring the old data were modified - mode type was out of range.](#)
- [PM in port mirroring the old data were modified - monitored portA was out of range.](#)
- [PM in port mirroring the old data were modified - monitored portB was out of range.](#)
- [PM in port mirroring the old data were modified - NVRAM file structure was changed.](#)
- [PM in port mirroring the old data were modified - probe port was out of range.](#)
- [PM: instance %d has been deleted because of insufficient HW resource](#)
- [PM some port mirroring messages were stored to be displayd with delay.](#)
- [PM unable to create mirror for instance instance number due to lack of available filter resources](#)
- [PoE Main Power Usage Off](#)
- [PoE Main Power Usage On](#)
- [PoE Module Reset](#)
- [PoE Port Detection Status port# Status powerStatus](#)
- [PoE The PoE power limit for port unit port has been changed to x Watts based on IP phone discovery settings](#)
- [PoE The PoE power limit for port unit port has been restored to previous value x Watts](#)
- [PoE The PoE priority for port unit port has been changed to x based on IP phone discovery settings](#)
- [PoE The PoE priority for port unit port has been restored to previous value x](#)
- [Policies with session data must be port-based](#)
- [Policy action out-of-range \(action# \)](#)
- [Policy content incompatible with target interface\(s\)](#)
- [Policy distribution across stack failed](#)
- [Policy mask availability issue \(space exhausted\)](#)

- [Policy modifications not supported](#)
- [Policy modification support limited](#)
- [Policy non-match action out-of-range \(non-match action# \)](#)
- [Policy precedence conflict detected with non-QoS application](#)
- [Policy precedence value out-of-range for target interface\(s\)](#)
- [Policy requirements exceed available resources \(slot slot# \)](#)
- [Policy statistics index out-of-range \(stats index \)](#)
- [Policy with this filtering values is already installed on this precedence](#)
- [Port %d blocked by VLACP due to end-partner down state](#)
- [Port %d blocked by VLACP until end-partner connection reestablished](#)
- [Port %d/%d blocked by VLACP due to end-partner down state](#)
- [Port %d reenabled by VLACP](#)
- [Port unit# port# blocked by VLACP until end-partner connection reestablished](#)
- [Port unit# port# reenabled by VLACP](#)
- [Post-join ACL installation issue detected \(ifc ifc# \)](#)
- [Post-join filter set installation issue detected \(ifc ifc# \)](#)
- [Post-join policy installation issue detected \(ifc ifc# \)](#)
- [Post-join traffic-profile installation issue detected \(ifc ifc# \)](#)
- [Potential inconsistent access asgn state \(Undo fail\) detected](#)
- [Potential inconsistent access elem state \(Undo fail\) detected](#)
- [Potential inconsistent block state \(Undo fail\) detected](#)
- [Potential inconsistent ifc assignment state \(Undo fail\) detected](#)
- [Potential inconsistent policy state \(Undo fail\) detected](#)
- [Precedence value out-of-range](#)
- [Primary Configuration files are corrupted. Restored to default](#)
- [Primary Configuration Version is updated](#)
- [Provided metering information incomplete](#)
- [802.1p user priority mapping modifications not supported](#)
- [802.1p user priority value modification prohibited](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with Q

This page lists all logs that have a starting letter of Q. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [QoS filter-limiting mode modified and unit reset](#)
- [QoS inter-module communication issue detected](#)
- [QoS policies may not be applied to uplink or daisy chain ports \(port# \)](#)
- [Queue configuration inconsistency detected \(local queue conf stack queue conf.\)](#)
- [Queue data distribution across stack failed](#)
- [Queue set assignment distribution across stack failed](#)
- [Queue set assignment modifications not supported](#)
- [Queue set unacceptable - pending range excludes in-use queues](#)
- [Queue set value modification prohibited](#)
- [Queue set value modification prohibited](#)
- [Queue shaping distribution across stack failed](#)
- [Queue shaping modifications not supported](#)
- [QuickInstall console configuration error.](#)
- [QuickInstall:console configuration success.](#)
- [QuickInstall: Error! Unable to locate agent software file](#)
- [QuickInstall: Error! Unable to locate ASCII configuration file](#)
- [QuickInstall: Error! Unable to locate diagnostics software file.](#)
- [QuickInstall: Processing of USB config file has commenced.](#)
- [QuickInstall: Processing of USB config file is complete](#)
- [QuickInstall USB config file not found.](#)
- [QuickInstall USB file config error at line line#](#)
- [QuickInstall USB file config error - file exceed 4096 bytes](#)
- [QuickInstall USB file config error - file exceed 200 lines.](#)
- [QuickInstall:USB file config success.](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with R

This page lists all logs that have a starting letter of R. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [RADIUS authentication on stack serial disabled](#)
- [RADIUS authentication on stack serial enabled](#)
- [RADIUS authentication on stack telnet disabled](#)
- [RADIUS authentication on stack telnet enabled](#)
- [RADIUS authentication on switch serial disabled](#)
- [RADIUS authentication on switch serial enabled](#)
- [RADIUS authentication on switch telnet disabled](#)
- [RADIUS authentication on switch telnet enabled](#)
- [RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't create RADIUS semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS AcctClient\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS client\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start radius_recv\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS ServerCheck\(\) task, errno %d](#)
- [RADIUS MS-CHAPv2: Failed to change password](#)
- [RADIUS MS-CHAPv2: No response from RADIUS server](#)
- [RADIUS MS-CHAPv2: Password changed succesfully](#)
- [RADIUS MS-CHAPv2: RADIUS server not properly configured](#)
- [RADIUS MS-CHAPv2: Server does not speak RADIUS](#)
- [RADIUS MS-CHAPv2: Unable to change password at RADIUS server](#)
- [Radius: Server with index %d is down](#)
- [Radius: Server with index %d is up](#)
- [Radius use-mgmt-ip must be disabled first](#)
- [Rate granularity limited to increments of 1 Mbps or 64 Kbps](#)
- [Rate \(min\) granularity limited \(increments of 1 Mbps or 64 Kbps\)](#)
- [Referenced block \(by policy\) deletion prohibited](#)
- [Referenced set \(by block\) modifications prohibited](#)
- [Referenced set \(by policy\) modifications prohibited](#)
- [Remote QoS-disable request failure \(port# on unit unit# \)](#)
- [REMOVE_DATA event sent unit mask value appl mask value](#)
- [Replaced "Wrong QoS Agent buffer setting, expected %u, actual %u, unit cannot join stack" with "Wrong QoS Agent buffer setting, expected %s, actual %s, unit cannot join stack"](#)
- [Requested attribute usage is currently not supported](#)
- [Requested filter manager support unavailable](#)
- [Requested reserve data invalid](#)
- [Request invalid - QoS interface apps enabled on interface\(s\)](#)
- [Request invalid - specified interface currently QoS-disabled](#)
- [Request temporarily denied - QoS support is currently disabled](#)
- [Required bandwidth information not specified](#)
- [Reset - Error Failed to get the Reset sem](#)
- [Reset initiated by console](#)
- [Reset initiated through SSH by IP address](#)
- [Reset initiated through telnet by IP address](#)
- [Reset to default initiated by console](#)

- [Reset to default initiated through telnet by IP address](#)
- [Resource alloc event timeout \(tgt all apps except OoS Agent rcv event \)](#)
- [Resources exhausted \(maximum class entries reached\)](#)
- [Resources exhausted \(out-of-memory\)](#)
- [Restore Backup Configuration to Manufacture Default](#)
- [Restore Primary Configuration to Manufacture Default](#)
- [Role combination associated with interface \(deletion prohibited\)](#)
- [Role combination contains unacceptable characters](#)
- [Role combination distribution across stack failed](#)
- [Role combination length outside of acceptable limits](#)
- [Role combination modifications not supported](#)
- [Role combination referenced by policy \(deletion prohibited\)](#)
- [Role \(interface\) capabilities incompatible with policy data](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with S

This page lists all logs that have a starting letter of S. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [%s card inserted \(in unit %s\)](#)
- [%s card removed \(from unit %s\)](#)
- [Script was successfully executed](#)
- [Session closed \(inactivity logout\) IP address](#)
- [Session closed \(inactivity logout\) IP address](#)
- [Session closed \(lost connection\) IP address](#)
- [Session closed \(user logout\) IP address](#)
- [Session closed \(user logout\) serial connection](#)
- [Session opened from IP address](#)
- [Session opened from serial connection](#)
- [Session opened \(local auth\) from IP address:](#)
- [Session opened \(local auth\) from serial connection](#)
- [Session opened\(radius auth\) from IP add](#)
- [Session opened\(radius auth\) from serial conn](#)
- [Set port to default](#)
- [SFP internal supply voltage is at high alarm level on s](#)
- [SFP internal supply voltage is at high warning level on %s](#)
- [SFP internal supply voltage is at low alarm level on %s](#)
- [SFP internal supply voltage is at low warning level on %s](#)
- [SFP internal supply voltage is no longer at the high alarm level](#)
- [SFP internal supply voltage is no longer at the high warning level](#)
- [SFP internal supply voltage is no longer at the low alarm level](#)
- [SFP internal supply voltage is no longer at the low warning level](#)
- [SFP internal temperature is at high alarm level on %s](#)
- [SFP internal temperature is at high warning level on %s](#)
- [SFP internal temperature is at low alarm level on %s](#)
- [SFP internal temperature is at low warning level on %s](#)
- [SFP internal temperature is no longer at the high alarm level](#)
- [SFP internal temperature is no longer at the high warning level](#)
- [SFP internal temperature is no longer at the low alarm level](#)
- [SFP internal temperature is no longer at the low warning level](#)
- [SFP Received power is at high alarm level on %s](#)
- [SFP Received power is at high warning level on %s](#)
- [SFP Received power is at low alarm level on %s](#)
- [SFP Received power is at low warning level on %s](#)
- [SFP Received power is no longer at the high alarm level](#)
- [SFP Received power is no longer at the high warning level](#)
- [SFP Received power is no longer at the low alarm level](#)
- [SFP Received power is no longer at the low warning level](#)
- [SFP TX Bias current is at high alarm level on %s](#)
- [SFP TX Bias current is at high warning level on %s](#)
- [SFP TX Bias current is at low alarm level on %s](#)
- [SFP TX Bias current is at low warning level on %s](#)
- [SFP TX Bias is no longer at the high alarm level](#)
- [SFP TX Bias is no longer at the high warning level](#)

- [SFP TX Bias is no longer at the low alarm level](#)
- [SFP TX Bias is no longer at the low warning level](#)
- [SFP TX output power is at high alarm level on %s](#)
- [SFP TX output power is at high warning level on %s](#)
- [SFP TX output power is at low alarm level on %s](#)
- [SFP TX output power is at low warning level on %s](#)
- [SFP TX output power is no longer at the high alarm level](#)
- [SFP TX output power is no longer at the high warning level](#)
- [SFP TX output power is no longer at the low alarm level](#)
- [SFP TX output power is no longer at the low warning level](#)
- [Simultaneous operations involving access asgn ifcs prohibited](#)
- [Simultaneous operations involving policies and blocks prohibited](#)
- [Simultaneous operations involving policies and ifcs prohibited](#)
- [Simultaneous operations involving policy blocks ifcs prohibited](#)
- [SLAMon Agent: agent IP address reset to default value](#)
- [SLAMon Agent CLI support not available](#)
- [SLAMon Agent CLI timeout value out of range](#)
- [SLAMon Agent disabled](#)
- [SLAMon Agent enabled](#)
- [SLAMon Agent: inconsistent IP address data specified](#)
- [SLAMon Agent inconsistent UDP port data specified](#)
- [SLAMon Agent info: %d %d %d](#)
- [SLAMon Agent invalid agent-to-agent port \(must be even value\)](#)
- [SLAMon Agent: message channel creation failure](#)
- [SLAMon Agent message channel creation failure](#)
- [SLAMon Agent operation is restricted CLI-only](#)
- [SLAMon Agent platform CLI command interface initialization issue](#)
- [SLAMon Agent platform timer initialization issue](#)
- [SLAMon Agent: terminated](#)
- [SLAMon Agent terminated](#)
- [SLAMon Agent: terminated - command/frame processing issue detected](#)
- [SLAMon Agent terminated — command/frame processing issue detected](#)
- [SLAMon Agent: terminated - NTR test exception detected](#)
- [SLAMon Agent terminated NTR test exception detected](#)
- [SLAMon Agent: terminated - resources unavailable](#)
- [SLAMon Agent terminated - resources unavailable](#)
- [SLAMon Agent: terminated - RTP test exception detected](#)
- [SLAMon Agent terminated - RTP test exception detected](#)
- [SLPP-guard: hold-down timer has expired on port with SLPP-guard enabled. Port %s has been re-enabled](#)
- [SLPP-guard: SLPP-guard has not been enabled on port %s as no filters or filter precedences are available to setup an Ethertype filter](#)
- [SLPP-guard: SLPP packet received on port with SLPP-guard enabled. Port %s has been disabled](#)
- [SLPP Warning - PDU was received on Vlan VlanId Unit UnitNo Port PortNo .](#)
- [SMLT IMC invalid cmd 1- StkCmd](#)
- [SMLT IMC tx error](#)
- [SMLT input parameter error mlt port vlan](#)
- [SMLT Stack db ex event num -0 -0*22221111](#)
- [SMLT stackEventNotify Invalid Msg Cmd - 0 - 0](#)
- [SMLT Stack inactive event 0-0- modMask](#)
- [SMLT Stack joined event num - 0 - 0*33331111](#)
- [SMLT Stack leaved event 0 - 0 - modMask](#)
- [SMLT STP enabled on IST trunk trkNo stp group grp](#)
- [SMLT Warning - LAC SMLT with more than 8 links - key - count](#)
- [SMLT Warning - smltEnable Software License Error- 0 - 0](#)
- [SMLT Warning - SMLT mismatched Lac Sys ID error shutdown all SMLT lac po](#)
- [SNMP-access is disabled](#)
- [SNMP-access is enabled](#)
- [SNTP Could not sync to NTP servers.](#)
- [SNTP: First synchronization successful.](#)
- [Source MAC address and mask values out-of-sync](#)
- [SPBM adjacency with neighbor](#)
- [SPB-MC Dynamic i-sid range conflicts with existing i-sid](#)
- [SPBM detect adj](#)
- [SPBM: ERROR adding C-VLAN UNI for i-sid %d, vlan %d - no resources](#)
- [SPBM: ERROR adding i-sid %x to i-sid table - table full](#)

- [SPBM: ERROR adding i-sid %x to i-sid table - table full](#)
- [SPBM: ERROR adding NNI on port %d vlan %d - no resources](#)
- [SPBM: ERROR adding peer %04x.%04x.%04x - no resources](#)
- [SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources](#)
- [SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources](#)
- [SPBM: ERROR adding Transparent UNI for i-sid %d, port %d - no resources](#)
- [SPBM: ERROR enabling SPBM due to Software License error](#)
- [SPBM: ERROR updating UNI for port %d/%d - no resources](#)
- [SPBM ISIS](#)
- [SPBM ISIS detect duplicate nick-name](#)
- [SPBM ISIS node](#)
- [Specified Destination Layer 4 min max range not supported](#)
- [Specified filter criteria is invalid inconsistent](#)
- [Specified filter information not found](#)
- [Specified filter manager resource invalid](#)
- [Specified filter manager resource uninitialized](#)
- [Specified inner VLAN ID min max range not supported](#)
- [Specified metering operation not supported](#)
- [Specified metering statistics entry already in-use \(by policy\)](#)
- [Specified policy components \(classifiers\) conflicting](#)
- [Specified policy components \(classifiers\) conflicting](#)
- [Specified policy identifier \(cookie\) invalid](#)
- [Specified policy statistics entry already in-use \(by meter\)](#)
- [Specified queue set information invalid](#)
- [Specified Source Layer 4 min max range not supported](#)
- [Specified token bucket criteria out of range](#)
- [Specified token bucket refresh interval not supported](#)
- [Specified token bucket size \(burst size\) not supported](#)
- [Specified user policy interface currently OoS-disabled](#)
- [Specified VLAN ID min max range not supported](#)
- [Src Layer 4 port min max values invalid \(max must be = to min\)](#)
- [srTCM meter issue - CIR must be the same in both meters](#)
- [srTCM meter issue - EBS must be greater than CBS](#)
- [srTCM trTCM meter issue - diff algorithms in associated meters](#)
- [srTCM trTCM meter issue - referenced meter incompatible unknown](#)
- [srTCM trTCM meter issue - too many cascaded meters](#)
- [SSHC: ASCII CFG download SFTP failure](#)
- [SSHC ASCII CFG download SFTP failure](#)
- [SSHC: ASCII CFG upload SFTP failure](#)
- [SSHC ASCII CFG upload SFTP failure](#)
- [SSHC: CFG download SFTP failure](#)
- [SSHC CFG download SFTP failure](#)
- [SSHC: CFG upload SFTP failure](#)
- [SSHC CFG upload SFTP failure](#)
- [SSHC DSA Authentication failure](#)
- [SSHC DSA key generation failure](#)
- [SSHC DSA key save failure](#)
- [SSHC DSA key upload TFTP failure](#)
- [SSHC DSA key upload USB failure](#)
- [SSH CLIENT Key couldnt be saved for host ip address](#)
- [SSH CLIENT SSH Connection to IP ip address was closed because parent console session console session ID was closed](#)
- [SSH CLIENT SSH Connection to %s was disconnected](#)
- [SSH CLIENT: SSH Connection to %s was disconnected by host. Connection time: %s](#)
- [SSH CLIENT: SSH Connection to %s was disconnected by user. Connection time: %s.](#)
- [SSH CLIENT Successful SSH Connection to %s using %s authentication](#)
- [SSHC Password Authentication failure](#)
- [SSHC: Password Authentication failure](#)
- [SSHC RSA Authentication failure](#)
- [SSHC: RSA Authentication failure](#)
- [SSHC RSA key generation failure](#)
- [SSHC RSA key save failure](#)
- [SSHC RSA key upload TFTP failure](#)
- [SSHC RSA key upload TFTP failure](#)
- [SSHC RSA key upload USB failure](#)
- [SSHC RSA key upload USB failure](#)

- [SSHC server connection failure](#)
- [SSH disabled](#)
- [SSH DSA key deleted](#)
- [SSH DSA KEY generation completed](#)
- [SSH enabled in non-secure mode](#)
- [SSH enabled in secure mode](#)
- [SSH Maximum number of ssh sessions has been reached](#)
- [SSH RSA KEY generation completed](#)
- [SSH RSA key overwritten](#)
- [SSH session closed by ip address remote host. Connection time h hours m minutes](#)
- [SSH session login using port](#)
- [SSH System is generating DSA KEY wait ...](#)
- [SSH TFTP DSA key download complete](#)
- [SSH TFTP RSA key download complete](#)
- [SSH USB DSA key download complete](#)
- [SSH USB RSA key download complete](#)
- [SSL certificate creation completed](#)
- [SSL certificate creation failed](#)
- [SSL certificate deleted](#)
- [SSL disabled](#)
- [SSL enabled](#)
- [SSL server reset](#)
- [Stack cable Down 1 is misconfigured](#)
- [Stack cable Down 2 is misconfigured](#)
- [Stack cable "Down 1" is misconfigured](#)
- [Stack cable "Down 2" is misconfigured](#)
- [Stack cable Up 1 is misconfigured](#)
- [Stack cable Up 2 is misconfigured](#)
- [Stack cable "Up 1" is misconfigured](#)
- [Stack cable "Up 2" is misconfigured](#)
- [Stack IP changed](#)
- [Stack must have a configured base unit!](#)
- [Stack operation mode modified to Hybrid and unit reset](#)
- [Stack operation mode modified to Pure and unit reset](#)
- [Stack RO password changed from IP add](#)
- [Stack RO password changed from serial conn](#)
- [Stack RW password changed from IP add](#)
- [Stack RW password changed from serial conn](#)
- [Stack sync failed stack failed to form](#)
- [Stack synchronization failed Exp value Act value Missing value](#)
- [Stack synchronization failed stack formation delayed](#)
- [Successful connection from IP address](#)
- [Successfully loaded backup configuration files](#)
- [Successfully loaded backup configuration files](#)
- [Successfully loaded configuration files from block %d](#)
- [Successfully loaded configuration files from block %d](#)
- [Successful SSH connection to ip address](#)
- [Sw Exception](#)
- [Switch IP changed](#)
- [Switch RO password changed from IP add](#)
- [Switch RO password changed from serial conn](#)
- [Switch RW password changed from IP add](#)
- [Switch RW password changed from serial conn](#)
- [System classifier modifications not supported](#)
- [System classifier still referenced \(deletion prohibited\)](#)
- [System filter distribution across stack failed](#)
- [System: Rear-Port Mode has been set to disable \(reboot required to take effect\)](#)
- [System: Rear-Port Mode has been set to enable \(reboot required to take effect\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with T

This page lists all logs that have a starting letter of T. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [TACACS+ accounting disabled](#)
- [TACACS+ accounting enabled](#)
- [TACACS+ authenticated serial connection closed](#)
- [TACACS+ authenticated telnet session closed](#)
- [TACACS+ authenticated telnet session max retries exceeded](#)
- [TACACS+ authentication on switch serial port disabled](#)
- [TACACS+ authentication on switch serial port enabled](#)
- [TACACS+ authentication on switch telnet disabled](#)
- [TACACS+ authentication on switch telnet disabled](#)
- [TACACS+ authentication on switch telnet enabled](#)
- [TACACS+ authentication on switch telnet enabled](#)
- [TACACS+ authorization disabled](#)
- [TACACS+ authorization enabled](#)
- [TACACS+ successful authentication](#)
- [TACACS+ unsuccessful authentication](#)
- [TACACS authenticated SSH session closed](#)
- [TACACS authentication on stack serial disabled](#)
- [TACACS authentication on stack serial enabled](#)
- [TACACS authentication on stack telnet disabled](#)
- [TACACS authentication on stack telnet enabled](#)
- [Task task-name is suspended](#)
- [Task task name is suspended](#)
- [Task whose index is Index1 Index2 is suspended](#)
- [Task whose index is taskID taskID is suspended](#)
- [TCP Control Flag filter criteria requires TCP protocol](#)
- [Telnet-access is disabled](#)
- [Telnet-access is disabled](#)
- [Telnet-access is enabled](#)
- [Telnet-access is enabled](#)
- [TFTP Failed](#)
- [The base \(unit# number \) has left the stack. Unit# number is now the base](#)
- [The BU switch is enabled. Cannot join existing stack](#)
- [The IP phone PoE limit has been changed to x Watts due to the stack modules configuration](#)
- [The number of stack units is number instead of expected number](#)
- [The password for user <%s> has expired.](#)
- [The password for user <%s> was changed](#)
- [The user <%s> was locked](#)
- [The user <%s> was locked.](#)
- [The user <%s> was unlocked](#)
- [This unit has wrong F W version expected version actual version](#)
- [This unit has wrong S W version expected version actual version](#)
- [Toggle the Agent Primary Image](#)
- [Token bucket algorithm identifier invalid](#)
- [Token bucket algorithm identifier unknown unsupported](#)
- [Token bucket data distribution across stack failed](#)

- [Token bucket entry referenced by meter \(deletion prohibited\)](#)
- [Token bucket entry referenced by shaper \(deletion prohibited\)](#)
- [Token bucket minimum rate outside limits \(64 - 10230000 Kbps\)](#)
- [Token bucket modifications not supported](#)
- [Token bucket rate outside limits \(64 - 10230000 Kbps\)](#)
- [Token bucket size not compatible with committed fill rate](#)
- [Traffic Prof filter set delete operation failed](#)
- [Traffic Prof filter set elem count exceeds available resources](#)
- [Traffic Prof filter set install operation failed](#)
- [Traffic Prof filter set policy count \(policy count \) exceeds limit \(policy limit \)](#)
- [Traffic Prof filter set rule count \(rule count \) exceeds limit \(rule limit \)](#)
- [Traffic Prof filter set update operation failed](#)
- [Trap bsAdacPortConfigNotification](#)
- [Trap bsAdacPortOperDisabledNotification](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncFailure](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess](#)
- [Trap: bsLstGroupOperStateChanged](#)
- [Trap: bsLstInterfaceStatusChanged](#)
- [Trap: bsnAaaAlreadyConnected](#)
- [Trap: bsnAaaIncorrectLogOnThresholdExceeded](#)
- [Trap: bsnAaaMaxNoOfSessionsExceeded](#)
- [Trap: bsnAaaUserAccountNotUsed](#)
- [Trap: bsnAaaUserPasswordExpired](#)
- [Trap bsnConfigurationSavedToNvram](#)
- [Trap bsnEapAccessViolation](#)
- [Trap bsnEapUbpFailure](#)
- [Trap bsnLacPortDisabledDueToLossOfVLACPDU](#)
- [Trap bsnLacPortEnabledDueToReceiptOfVLACPDU](#)
- [Trap: bsnRopPasswordExpired: Read-only password expired](#)
- [Trap: bsnRwPasswordExpired: Read-write password expired](#)
- [Trap: bsnSFPIinsertion on port](#)
- [Trap: bsnSFPRemoval on port](#)
- [Trap bsnStackConfigurationError](#)
- [Trap bsnStackManagerReconfiguration](#)
- [Trap: bsnSystemUp365Days sent from unit %d](#)
- [Trap bsnTrialLicenseExpiration Trial license license# has expired. Disable licensed features to avoid network interruption](#)
- [Trap bsnTrialLicenseExpiration Trial license license# will expire in # days day\(s\).](#)
- [Trap: bsnUSBInsertion on unit](#)
- [Trap: bsnUSBRemoval on unit](#)
- [Trap bspePethPsePortCurrentStatusNotification](#)
- [Trap bsUnicastStormControlAboveHighWatermark](#)
- [Trap bsUnicastStormControlBelowLowWatermark](#)
- [Trap bsveVrrpTrapStateTransition](#)
- [Trap DAPP - DoS Attack Detected](#)
- [Trap Device has entered Forced Stack Mode \(MAC Address \)](#)
- [Trap entConfigChange](#)
- [Trap fallingAlarm](#)
- [Trap: FCoE - Egress Issue Detected](#)
- [Trap lldpRemTableChange Ageouts = count](#)
- [Trap lldpRemTableChange Deletes = count](#)
- [Trap lldpRemTableChange Drops = count](#)
- [Trap lldpRemTableChange Inserts = count](#)
- [Trap lldpXMedTopologyChangeDetected Subtype = subtype Class = class](#)
- [Trap newRoot](#)
- [Trap ntnQosPolicyEvolLocalUbpSessionFailure](#)
- [Trap ospfIfAuthFailure](#)
- [Trap ospfIfConfigError](#)
- [Trap ospfIfStateChange](#)
- [Trap ospfNbrStateChange](#)
- [Trap ospfVirtIfAuthFailure](#)
- [Trap ospfVirtIfConfigError](#)
- [Trap ospfVirtIfStateChange](#)

- [Trap ospfVirtNbrStateChange](#)
- [Trap_pethMainPowerUsageOffNotification](#)
- [Trap_pethMainPowerUsageOnNotification](#)
- [Trap_pethPsePortOnOffNotification](#)
- [Trap: rcIIsPlsbBvidMismatchTrap](#)
- [Trap: rcIIsPlsbLsdbUpdateTrap](#)
- [Trap: rcIIsPlsbSmltPeerBmacMismatchTrap](#)
- [Trap: rcIIsPlsbSmltSplitBebMismatchTrap](#)
- [Trap: rcIIsPlsbSmltVirtBmacMismatchTrap](#)
- [Trap risingAlarm](#)
- [Trap RSTP Error Event](#)
- [Trap RSTP General Event](#)
- [Trap RSTP New Root](#)
- [Trap RSTP Protocol Migration](#)
- [Trap RSTP Topology Change](#)
- [Trap: Run %s %s](#)
- [Trap: s5CtrFanDirectionError](#)
- [Trap: s5CtrHighTemperatureError](#)
- [Trap s5CtrHotSwap](#)
- [Trap s5CtrUnitDown](#)
- [Trap s5CtrUnitDown](#)
- [Trap: s5EtrMacAddressTablesThresholdReached](#)
- [Trap s5EtrSbsMacAccessViolation](#)
- [Trap s5EtrSbsMacAccessViolation](#)
- [Trap s5EtrSbsMacRemoved](#)
- [Trap s5EtrSbsMacTableCleared](#)
- [Trap s5EtrSbsMacTableClearedForPort](#)
- [Trap: SFP Transceiver's Bias is no longer at warning/alarm level](#)
- [Trap: \\$/160: SFP Transceiver's Bias is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Temperature is no longer at warning/alarm level](#)
- [Trap: \\$/160: SFP Transceiver's Temperature is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap: \\$/160: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap: \\$/160: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap: slaMonitorAgentExceptionDetected](#)
- [Trap SLPP Port Down Event](#)
- [Trap Smlt Ist Link Down](#)
- [Trap Smlt Ist Link Up](#)
- [Trap Smlt Link Down](#)
- [Trap Smlt Link Up](#)
- [Trap topologyChange](#)
- [Trap ubpEAPSessionEnd](#)
- [Trap ubpEAPSessionStart](#)
- [Trap vrrpTrapNewMaster](#)
- [trTCM meter issue - PBS must be greater than CBS](#)
- [trTCM meter issue - PIR must be greater than CIR](#)
- [Trusted processing mode change rejected - inadequate resources](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with U

This page lists all logs that have a starting letter of U. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Unable to add block member \(block elem# component set id \) to existing policy](#)
- [Unable to apply existing policy data to interface \(unit# port# \)](#)
- [Unable to apply existing user-based policy data to new user](#)
- [Unable to apply filter set to ports \(unsupported capabilities\)](#)
- [Unable to apply newly-defined UBP filter set to existing user](#)
- [Unable to apply pre-defined UBP filter set to new user](#)
- [Unable to apply pre-defined UBP filter set to new user \(port %d/%d\)](#)
- [Unable to complete requested access asgn system operation \(oper type \)](#)
- [Unable to complete requested policy system operation \(operation type \)](#)
- [Unable to compress classification criteria in set adequately](#)
- [Unable to compress specified policy criteria](#)
- [Unable to create action for access element](#)
- [Unable to create classifier block entry for access element](#)
- [Unable to create classifier component entry for access element](#)
- [Unable to create count action \(meter\) for access assignment](#)
- [Unable to create count action \(policy\) for access assignment](#)
- [Unable to create count action \(secondary meter\) for access asgn](#)
- [Unable to create DS MF classifier for access element](#)
- [Unable to create L2 MF classifier for access element](#)
- [Unable to create metering data for access assignment](#)
- [Unable to create non-match components for ACL](#)
- [Unable to create out-of-profile action for access assignment](#)
- [Unable to create policy data for access assignment](#)
- [Unable to create secondary metering data for access assignment](#)
- [Unable to create secondary token bucket data for access asgn](#)
- [Unable to create token bucket data for access assignment](#)
- [Unable to create yellow action for access assignment](#)
- [Unable to deactivate policy associated with interface](#)
- [Unable to delete block member \(block element# component set id \) from existing policy](#)
- [Unable to delete UBP filter set on interface ifc#](#)
- [Unable to derive suitable filter set element eval precedence](#)
- [Unable to determine clfr interface\(s\) compatibility](#)
- [Unable to disable ARP Spoofing support on interface \(ifc# \)](#)
- [Unable to disable BPDUBlkr support on interface \(ifc# \)](#)
- [Unable to disable DHCP Snooping support on interface \(ifc# \)](#)
- [Unable to disable DHCP Spoofing support on interface \(ifc# \)](#)
- [Unable to disable DNSPort support on interface \(ifc# \)](#)
- [Unable to disable existing policy data on interface \(unit# port# \)](#)
- [Unable to disable FTPPort support on interface \(ifc# \)](#)
- [Unable to disable Nachia support on interface \(ifc# \)](#)
- [Unable to disable policy data for access assignment](#)
- [Unable to disable SQLSlam support on interface \(ifc# \)](#)
- [Unable to disable SynFinScan support on interface \(ifc# \)](#)
- [Unable to disable Xmas support on interface \(ifc# \)](#)
- [Unable to enable ARP Spoofing support on interface \(ifc# \)](#)

- [Unable to enable BPDUBIkr support on interface \(ifc# \)](#)
- [Unable to enable DHCP Snooping support on interface \(ifc# \)](#)
- [Unable to enable DHCP Spoofing support on interface \(ifc# \)](#)
- [Unable to enable DNSPort support on interface \(ifc# \)](#)
- [Unable to enable FTPPort support on interface \(ifc# \)](#)
- [Unable to enable Nachia support on interface \(ifc# \)](#)
- [Unable to enable policy data for access assignment](#)
- [Unable to enable SQLSlam support on interface \(ifc# \)](#)
- [Unable to enable SynFinScan support on interface \(ifc# \)](#)
- [Unable to enable Xmas support on interface \(ifc# \)](#)
- [Unable to inform SPB of ifc assignment change \(%d/%d\)](#)
- [Unable to inform SPB of ifc assignment change \(%d/%d\)](#)
- [Unable to install access assignment - component creation issue](#)
- [Unable to install access element - component creation issue](#)
- [Unable to locate corresponding DS L2 access elements](#)
- [Unable to manipulate DAPP support \(no applicable interfaces\)](#)
- [Unable to modify access assignment - component modify issue](#)
- [Unicast block unit port unit port level level watermark watermark](#)
- [Unicast \(Interface# \) and Non-Unicast \(interface# \) interfaces in conflict](#)
- [Unicast unblock unit port unit port level level watermark watermark](#)
- [Unknown access assignment entry specified \(entry# \)](#)
- [Unknown access element entry specified \(entry# \)](#)
- [Unknown action entry specified \(entry# \)](#)
- [Unknown classifier block entry specified \(entry# \)](#)
- [Unknown classifier component entry specified \(entry# \)](#)
- [Unknown CoS shaping entry specified \(entry# CoS \)](#)
- [Unknown count action entry specified \(entry# \)](#)
- [Unknown DSCP mapping entry specified \(entry# \)](#)
- [Unknown entry \(class class# \) specified \(entry# \)](#)
- [Unknown incompatible access element specified](#)
- [Unknown incompatible action component specified](#)
- [Unknown incompatible classifier block specified](#)
- [Unknown incompatible classifier set specified](#)
- [Unknown incompatible in-profile action specified](#)
- [Unknown incompatible in-profile \(green\) action specified](#)
- [Unknown incompatible match action specified](#)
- [Unknown incompatible metering component specified](#)
- [Unknown incompatible metering statistics entry specified](#)
- [Unknown incompatible out-of-profile action specified](#)
- [Unknown incompatible out-of-profile \(red\) action specified](#)
- [Unknown incompatible out-of-profile \(yellow\) action specified](#)
- [Unknown incompatible policy non-match action specified](#)
- [Unknown incompatible policy statistics entry specified](#)
- [Unknown incompatible queue set specified](#)
- [Unknown incompatible role combination specified](#)
- [Unknown incompatible token bucket reference specified](#)
- [Unknown incompatible token bucket reference specified](#)
- [Unknown interface application entry specified \(entry# \)](#)
- [Unknown interface assignment entry specified \(entry# \)](#)
- [Unknown interface queue entry specified \(ifc queue id \)](#)
- [Unknown interface shaping entry specified \(entry# \)](#)
- [Unknown IP classifier entry specified \(entry# \)](#)
- [Unknown Layer 2 classifier entry specified \(entry# \)](#)
- [Unknown meter entry specified \(entry# \)](#)
- [Unknown out-of-range interface index value \(ifc# \)](#)
- [Unknown out-of-range interface index value \(ifc index \)](#)
- [Unknown policy entry specified \(entry# \)](#)
- [Unknown 802.1p user priority mapping entry specified \(entry# \)](#)
- [Unknown queue set assignment entry specified \(entry# \)](#)
- [Unknown queue set queue reference detected](#)
- [Unknown queue shaping entry specified \(entry# queue \)](#)
- [Unknown role combination entry specified \(role comb id \)](#)
- [Unknown System classifier entry specified \(entry# \)](#)
- [Unknown token bucket entry specified \(entry# \)](#)
- [Unknown unsupported attribute specified \(attribute \)](#)

- [Unknown unsupported interface application type specified](#)
- [Unknown unsupported interface class specified \(ifc class \)](#)
- [Unknown unsupported IP Flag specified](#)
- [Unknown unsupported RowStatus specified](#)
- [Unknown unsupported StorageType specified](#)
- [Unknown unsupported TCP Control Flag specified](#)
- [Unknown user policy entry specified \(entry# \)](#)
- [Unsupported IP address type specified](#)
- [Unsupported IPv4 Options value specified](#)
- [Unsupported pattern offset data specified](#)
- [Unsupported unknown QoS agent configuration attribute \(attribute# \)](#)
- [Up 1 cable inserted or neighbor powered on](#)
- [Up 2 cable inserted or neighbor powered on](#)
- [Up 1 cable removed or neighbor powered off](#)
- [Up 2 cable removed or neighbor powered off](#)
- [Update priority value and update DSCP value out-of-sync](#)
- [Update priority value per ingress DSCP currently not supported](#)
- [Upstream stack direction is down cable removed or neighbor powered off](#)
- [Upstream stack direction is mis-configured](#)
- [USB device inserted](#)
- [USB device removed](#)
- [USC Install SET fail unit port unit_port status = status](#)
- [USC Install TEST fail unit port unit_port status = status](#)
- [USC UnInst SET failed for port port status = status](#)
- [User allowed \(radius authentication pass\) to log in from Web from Src IP](#)
- [User disallowed \(radius authentication fail\) to log in from Web from Src IP](#)
- [User disallowed \(radius authentication fail\) to log in from Web from Src IP](#)
- [User Policy data referencing interface \(operation prohibited\)](#)
- [User policy distribution across stack failed](#)
- [User policy filter set count \(<set count>\) exceeds limit \(<set limit>\)](#)
- [User policy filter set delete operation failed](#)
- [User policy filter set element count exceeds available resources](#)
- [User policy filter set install operation failed](#)
- [User policy filter set update operation failed](#)
- [User policy group contains invalid unacceptable characters](#)
- [User policy group length outside of acceptable limits](#)
- [User policy modifications not supported](#)
- [User policy name contains invalid unacceptable characters](#)
- [User policy name length outside of acceptable limits](#)
- [User Policy \(UBP\) filter set in use \(QoS disable prohibited\)](#)
- [User Policy \(UBP\) filter set in use \(QoS reset prohibited\)](#)
- [User priority specified with untagged frames \(invalid\)](#)
- [User with %s privilege has been created](#)
- [User with %s privilege has been deleted](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with V

This page lists all logs that have a starting letter of V. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Vlan Change Aborted, it is in another STP Group](#)
- [Vlan Change Aborted on brouter](#)
- [VLAN configuration does not match BU VLAN configuration. VLAN config defaulted](#)
- [VLAN configuration does not match BU VLAN configuration. VLAN config defaulted](#)
- [VLAN ID min max values invalid \(min VLAN ID ! max VLAN ID \)](#)
- [VLAN IMC callback failed](#)
- [VLAN IMC was not sent](#)
- [VLAN NVRAM read error](#)
- [VLAN NVRAM read error](#)
- [VLAN queue messages discarded](#)
- [VLAN queue messages discarded](#)
- [VLAN range could not be reduced sufficiently](#)
- [VLAN set error from IMC](#)
- [VLAN set error from RPC](#)
- [Voice VLAN ID and Data VLAN ID cannot have the same value](#)
- [VRRP Feature globally disabled due to missing license](#)
- [VRRP: vrrpAdvQueue is FULL. RX advertisement dropped in vlan %d!](#)
- [VRRP: vrrpQueue is FULL. Message dropped.](#)
- [VRRP VR VR Id VLAN Id Received mismatching advertisement interval \(advertisement interval\)](#)
- [VRRP VR VR Id VLAN Id Received mismatching advertisement type \(advertisement type \)](#)
- [VRRP VR VR Id VLAN Id Received mismatching fast advertisement interval \(fast advertisement interval\)](#)
- [VRRP VR VR Id VLAN Id Received mismatching virtual IP address \(received virtual ip address \)](#)
- [VRRP VR VR Id VLAN Id Received unknown VRRP packet type \(vrrp packet type \)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Logs starting with W

This page lists all logs that have a starting letter of W. Select the log you wish to view or navigate to a different starting letter.

Using your browser's 'find' function on this page may help you locate a specific log name faster.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Warning failed to connect to %s card \(in unit %s\)](#)
- [Warning: non-supported gsfp inserted on %s. Port will be disabled.](#)
- [Warning:non-supported transceiver on %s has been detected.](#)
- [Warning %s card unsafely removed \(from unit %s\)](#)
- [WEB-access is disabled](#)
- [WEB-access is enabled](#)
- [Web authentication fail from IP address](#)
- [Web authentication from IP address](#)
- [Web authentication \(RADIUS auth\) from IP address](#)
- [Web authentication \(RADIUS auth\) from IP address](#)
- [Web connection from IP address](#)
- [Web disconnect from IP address](#)
- [Web server attempting to open socket for port HTTP port](#)
- [Web server starts service on port HTTP port](#)
- [Web timeout from IP address](#)
- [Wrong OoS Agent buffer setting, expected %s, actual %s, unit re-configured and reboot](#)
- [Wrong OOS Agent buffer setting expected value actual value unit cannot join stack.](#)
- [Wrong OoS Agent queue setting, expected %u, actual %u, unit reconfigured and reboot](#)
- [Wrong OoS Agent queue setting, expected %u, actual %u, unit re-configured and reboot](#)
- [Wrong VLANs nvq RecDescr actRecs](#)
- [Wrong VMACs nvq RecDescr actRecs](#)
- [Wrong vrec field](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs

There are 624 logs for this source. To simplify navigation, all logs are organized alphabetically by their name. Select the letter to navigate to the list of all logs starting with that letter for this source.

A 22 logs	B 8 logs	C 41 logs	D 29 logs
E 12 logs	F 16 logs	G 1 logs	H
I 199 logs	J	K	L 6 logs
M 12 logs	N 17 logs	O 5 logs	P 34 logs
Q 11 logs	R 23 logs	S 33 logs	T 19 logs
U 134 logs	V 2 logs	W	X
Y		Z	

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

logs

The following logs are generated for this source:

- [DosFs - Error File not closed](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach logs

There are 80 logs for this source. To simplify navigation, all logs are organized alphabetically by their name. Select the letter to navigate to the list of all logs starting with that letter for this source.

A	B	C	D
E	F 80 logs	G	H
I	J	K	L
M	N	O	P
Q	R	S	T
U	V	W	X
Y		Z	

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

802.1AB logs

The following logs are generated for this source:

- [Trap IldpRemTableChange Ageouts = count](#)
- [Trap IldpRemTableChange Deletes = count](#)
- [Trap IldpRemTableChange Drops = count](#)
- [Trap IldpRemTableChange Inserts = count](#)
- [Trap IldpXMedTopologyChangeDetected Subtype = subtype Class = class](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN logs

The following logs are generated for this source:

- [BU was unable to send IMC for NBUs VLAN/Port configuration](#)
- [Cli add vlan vlan id members port mask](#)
- [Cli create vlan vlan id type port](#)
- [Cli delete vlan vlan id members port mask](#)
- [Cli delete vlan vlan id type port](#)
- [Cli set autopvid disable](#)
- [Cli set autopvid enable](#)
- [Cli set management vlan vlan id](#)
- [Cli set ports port mask tagging disable](#)
- [Cli set ports port mask tagging enable](#)
- [Cli set pvid vlan id ports port mask](#)
- [Cli set vlan vlan id members port mask](#)
- [Cons activate vlan vlan id](#)
- [Cons add vlan vlan id port unit port](#)
- [Cons create vlan vlan id type port](#)
- [Cons delete vlan vlan id port unit port](#)
- [Cons delete vlan vlan id type port](#)
- [Cons set autopvid disable](#)
- [Cons set autopvid enable](#)
- [Cons set management vlan vlan id](#)
- [Cons set port unit port pvid vlan id](#)
- [Cons set port unit port tagging disable](#)
- [Cons set port unit port tagging enable](#)
- [Error getting VLAN info for Port's pvid](#)
- [Error reading nvq_ObjDescr from VLAN file](#)
- [Error reading prec from VLAN file](#)
- [Error reading vmrec from VLAN file](#)
- [Error reading vrec from VLAN file](#)
- [Error restoring from VLAN file](#)
- [Error restoring from VLAN file. Wrong nvq_Descr.devVer](#)
- [Error restoring from VLAN file. Wrong nvq_Descr.notBlank](#)
- [Error restoring nvq_Descr from VLAN file](#)
- [Error restoring object from VLAN file - bad file pointer or mode](#)
- [Error restoring object from VLAN NVRAM file](#)
- [Error restoring Port from VLAN NVRAM file](#)
- [Error restoring Ports from VLAN file](#)
- [Error restoring VLANs from VLAN file](#)
- [Error restoring VMACs from VLAN file](#)
- [Error seeking object in VLAN file](#)
- [Error seeking Ports in VLAN file](#)
- [Error seeking VLANs in VLAN file](#)
- [Error seeking VMACs in VLAN file](#)
- [Number of VLANs does not match BU number of VLANs. VLAN config defaulted](#)
- [Number of VLANs does not match BU number of VLANs. VLAN config defaulted](#)
- [Set port to default](#)
- [VLAN configuration does not match BU VLAN configuration. VLAN config defaulted](#)
- [VLAN configuration does not match BU VLAN configuration. VLAN config defaulted](#)
- [VLAN IMC callback failed](#)
- [VLAN IMC was not sent](#)

- [VLAN NVRAM read error](#)
- [VLAN NVRAM read error](#)
- [VLAN queue messages discarded](#)
- [VLAN queue messages discarded](#)
- [VLAN set error from IMC](#)
- [VLAN set error from RPC](#)
- [Wrong VLANs nvq_RecDescr_actRecs](#)
- [Wrong VMACs nvq_RecDescr_actRecs](#)
- [Wrong vrec field](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAA logs

The following logs are generated for this source:

- [The password for user <%s> has expired.](#)
- [The password for user <%s> was changed](#)
- [The user <%s> was locked](#)
- [The user <%s> was unlocked](#)
- [Trap: bsnAaaUserPasswordExpired](#)
- [User with %s privilege has been created](#)
- [User with %s privilege has been deleted](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

port driver logs

The following logs are generated for this source:

- [SFP internal supply voltage is at high alarm level on s](#)
- [SFP internal supply voltage is at high warning level on %s](#)
- [SFP internal supply voltage is at low alarm level on %s](#)
- [SFP internal supply voltage is at low warning level on %s](#)
- [SFP internal supply voltage is no longer at the high alarm level](#)
- [SFP internal supply voltage is no longer at the high warning level](#)
- [SFP internal supply voltage is no longer at the low alarm level](#)
- [SFP internal supply voltage is no longer at the low warning level](#)
- [SFP internal temperature is at high alarm level on %s](#)
- [SFP internal temperature is at high warning level on %s](#)
- [SFP internal temperature is at low alarm level on %s](#)
- [SFP internal temperature is at low warning level on %s](#)
- [SFP internal temperature is no longer at the high alarm level](#)
- [SFP internal temperature is no longer at the high warning level](#)
- [SFP internal temperature is no longer at the low alarm level](#)
- [SFP internal temperature is no longer at the low warning level](#)
- [SFP Received power is at high alarm level on %s](#)
- [SFP Received power is at high warning level on %s](#)
- [SFP Received power is at low alarm level on %s](#)
- [SFP Received power is at low warning level on %s](#)
- [SFP Received power is no longer at the high alarm level](#)
- [SFP Received power is no longer at the high warning level](#)
- [SFP Received power is no longer at the low alarm level](#)
- [SFP Received power is no longer at the low warning level](#)
- [SFP TX Bias current is at high alarm level on %s](#)
- [SFP TX Bias current is at high warning level on %s](#)
- [SFP TX Bias current is at low alarm level on %s](#)
- [SFP TX Bias current is at low warning level on %s](#)
- [SFP TX Bias is no longer at the high alarm level](#)
- [SFP TX Bias is no longer at the high warning level](#)
- [SFP TX Bias is no longer at the low alarm level](#)
- [SFP TX Bias is no longer at the low warning level](#)
- [SFP TX output power is at high alarm level on %s](#)
- [SFP TX output power is at high warning level on %s](#)
- [SFP TX output power is at low alarm level on %s](#)
- [SFP TX output power is at low warning level on %s](#)
- [SFP TX output power is no longer at the high alarm level](#)
- [SFP TX output power is no longer at the high warning level](#)
- [SFP TX output power is no longer at the low alarm level](#)
- [SFP TX output power is no longer at the low warning level](#)
- [Trap: SFP Transceiver's Bias is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Bias is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Temperature is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Temperature is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Unicast block unit port unit port level level watermark watermark](#)

- [Unicast unblock unit port unit port level level watermark watermark](#)
- [USC Install SET fail unit port unit port status = status](#)
- [USC Install TEST fail unit port unit port status = status](#)
- [USC UnInst SET failed for port port status = status](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ACG logs

The following logs are generated for this source:

- [ASCII failed](#)
- [ASCII finished successfully](#)
- [ASCII finished successfully at load on boot](#)
- [ASCII transfer failed](#)
- [ASCII transfer failed at load on boot](#)
- [ASCII transfer OK](#)
- [ASCII transfer OK at load on boot](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP logs

The following logs are generated for this source:

- [EAP Bad pkt id](#)
- [EAP Bad pkt len](#)
- [EAP: Cannot assign PVID %d, on port %d it is in another STP group](#)
- [EAP: Cannot auto-create VLAN %d, it is mapped to another STP group](#)
- [EAP Client blocked \(Block Subsequent MAC Authentication\): Different VID than expected](#)
- [EAP Client blocked \(Block Subsequent MAC Authentication\): Invalid VID](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All bindings have been rejected](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All RAVs or Bindings from RADIUS are invalid](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Autocreate is enabled, but no RAV is present](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Cannot use FA bindings in Legacy or Autoprovision networks](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. EAP FA context unknown network](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Only MHSA mode supports multiple RAVs](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Receiving unconfigured VLAN from Radius without Autocreate](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Vid bindings exceeded the maximum threshold of 16](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Vid not supported in MHMA and SHSA](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Vid with Vid not equal to 0 not supported in Standalone Proxy or Autoprovision](#)
- [EAP Could not process pkt](#)
- [EAP Error - Default](#)
- [EAP Error - Failed to free mac info memory](#)
- [EAP Error: Reached maximum number of messages in the queue](#)
- [EAP Error while sending Access Violation Trap](#)
- [EAP Error while sending RAV Error Trap](#)
- [EAP Failed initialize global arrays](#)
- [EAP Failed to add host, max number of clients reached](#)
- [EAP Failed to add host, memory allocation error](#)
- [EAP Failed to create dyna global arrays](#)
- [EAP Invalid Vlan ID vid configured for port num](#)
- [EAP Mac AuthFail - unitPort <unit-portnum> macHi <xx-xx> macLo <xx-xx-xx-xx>](#)
- [EAP Memory allocation error](#)
- [EAP Message queue error](#)
- [EAP Neap port was not member of any vlan](#)
- [EAP NULL pkt to send on Success](#)
- [EAP NVRAM open error](#)
- [EAP NVRAM read port admin state error](#)
- [EAP NVRAM read system admin state error](#)
- [EAP NVRAM read system ubp state error](#)
- [EAP NVRAM write error](#)
- [EAP Reached Mac Intruder Count](#)
- [EAP: Reached Mac Intruder Count](#)
- [EAP: Receiving unsupported Auto-Create-VLAN VSA in SHSA or MHMA](#)
- [EAP Task spawn error](#)
- [Invalid RAV id %d, on port %d, cannot be Switched UNI or B-VLAN](#)
- [Invalid RAV id %d, on port %d, it isn't a CVLAN](#)
- [MAC %02x:%02x:%02x:%02x:%02x:%02x not authenticated: only one client is allowed in MHSA mode](#)
- [NEAP Accounting - Memory allocation failure](#)
- [Non-EAP Client blocked \(Block Subsequent MAC Authentication\): Different VID than expected](#)
- [Non-EAP Client blocked \(Block Subsequent MAC Authentication\): EAP Use Rav Not enabled](#)

- [Trap_bsnEapAccessViolation](#)
- [Trap_bsnEapUbpFailure](#)
- [Vlan_Change_Aborted, it is in another STP Group](#)
- [Vlan_Change_Aborted on brouter](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC logs

The following logs are generated for this source:

- [ADAC: ADAC of Nortel IP Phones not functional](#)
- [ADAC Error applying main VLAN QoS configuration](#)
- [ADAC Error applying VLAN QoS configuration for unit port unit# port#](#)
- [ADAC Error forcing administrative state to disable enable](#)
- [ADAC: Error registering CDT handlers](#)
- [ADAC Error removing main VLAN QoS configuration](#)
- [ADAC Error removing VLAN QoS configuration for unit port unit# port#](#)
- [ADAC Forced administrative state to disable enable](#)
- [ADAC System operationally disable enable](#)
- [Trap bsAdacPortConfigNotification](#)
- [Trap bsAdacPortOperDisabledNotification](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop logs

The following logs are generated for this source:

- [Bay Secure: Exceeded %d per-trunk MAC addresses on trunk %d](#)
- [DHCP packet with mismatch MAC address dropped on un-trusted port unit# port# mac\(MAC ADDRESS\)](#)
- [DHCP Snoop DHCP ACK dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop DHCP binding table is full additional DHCP clients will not be added to the binding table](#)
- [DHCP Snoop: DHCP DISCOVER dropped on port %d/%d \(source MAC not matching client MAC\)](#)
- [DHCP Snoop DHCP NAK dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop DHCP OFFER dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x in binding table](#)
- [DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# because MAC Addr\(MACaddress \) is associated to port unit# port#](#)
- [DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# \(MAC Addr\(MACaddress \) does not exist in binding table\)](#)
- [DHCP Snoop DHCP REQUEST dropped on un-trusted port unit# port# due to source MAC address\(MAC ADDRESS\) not matching DHCP client](#)
- [DHCP Snoop DHCP snooping binding table restored successfully from TFTP address](#)
- [DHCP Snoop DHCP snooping binding table restored successfully from USB unit unit#](#)
- [DHCP Snoop: DHCP snooping binding table restore from SFTP address](#)
- [DHCP Snoop DHCP snooping binding table restore from TFTP address A.B.C.D IPv6 address failed](#)
- [DHCP Snoop DHCP snooping binding table restore from USB unit unit# failed](#)
- [DHCP Snoop: DHCP snooping binding table saved successfully to SFTP address](#)
- [DHCP Snoop DHCP snooping binding table saved successfully to TFTP address](#)
- [DHCP Snoop DHCP snooping binding table saved successfully to USB unit unit#](#)
- [DHCP Snoop: DHCP snooping binding table save to SFTP address](#)
- [DHCP Snoop DHCP snooping binding table save to TFTP address A.B.C.D IPv6 address failed](#)
- [DHCP Snoop: DHCP snooping binding table save to TFTP address, failed](#)
- [DHCP Snoop DHCP snooping binding table save to USB unit unit# failed](#)
- [DHCP Snoop: DHCP snooping binding table succesfully restored from SFTP address](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to expired lease](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to MAC conflict](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to parsing failure](#)
- [DHCP Snoop DHCP snooping entry with MAC MacAddress not restored on invalid interface unit# port#](#)
- [DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored \(invalid Vlan %d\)](#)
- [DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored on trusted interface %d/%d](#)
- [DHCP Snoop: DHCP snooping entry 0x%08x not restored on trusted interface %d/%d](#)
- [DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored \(invalid Vlan %d\)](#)
- [DHCP Snoop NTP is not synchronized: external save restore of DHCP snooping entries not possible](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncFailure](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES logs

The following logs are generated for this source:

- [AES activated by schedule](#)
- [AES deactivated by schedule](#)
- [AES globally disabled](#)
- [AES globally enabled](#)
- [AES manually activated](#)
- [AES manually deactivated](#)
- [AES not applying schedule because SNTP not synchronized](#)
- [AES time is synchronized applying schedule](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack Manager logs

The following logs are generated for this source:

- [Another BU tried to join the stack. Unit ignored](#)
- [application-name failed DB-exchange stack failed to form](#)
- [application-name failed DB-exchange stack formation delayed](#)
- [Base unit has loopback port mode %s and the current unit %s. Unit reconfigured and rebooted](#)
- [Base unit has loopback port mode <SPBM reserved port mode> and the current unit <SPBM reserved port mode>. Unit reconfigured and rebooted](#)
- [BECOME_TEMP BU event sent unit mask value appl mask value](#)
- [Change of active config block and or reset failed block-number](#)
- [Different spanning-tree mode configured than BU. Unit reconfigured and rebooted.](#)
- [Different spanning-tree mode configured than BU. Unit re-configured and rebooted](#)
- [DISTRIBUTE_DB event sent unit mask value appl mask value](#)
- [Filter limiting mode not supported on 5510-XX unit cannot join stack](#)
- [Front-panel UI selected use rear-panel base non-base switch](#)
- [JOIN event sent unit mask value appl mask value](#)
- [LEAVE event sent unit mask value appl mask value](#)
- [MODULE_INACTIVE event sent unit mask value appl mask value](#)
- [More than value units discovered](#)
- [Multiple base units detected](#)
- [Multiple Waverunner units detected when base is a Flagship](#)
- [QoS filter-limiting mode modified and unit reset](#)
- [REMOVE_DATA event sent unit mask value appl mask value](#)
- [Replaced "Wrong OoS Agent buffer setting, expected %u, actual %u, unit cannot join stack" with "Wrong OoS Agent buffer setting, expected %s, actual %s, unit cannot join stack"](#)
- [Stack must have a configured base unit!](#)
- [Stack operation mode modified to Hybrid and unit reset](#)
- [Stack operation mode modified to Pure and unit reset](#)
- [Stack sync failed stack failed to form](#)
- [Stack synchronization failed Exp value Act value Missing value](#)
- [The base \(unit# number \) has left the stack. Unit# number is now the base](#)
- [The BU switch is enabled. Cannot join existing stack](#)
- [This unit has wrong F W version expected version actual version](#)
- [This unit has wrong S W version expected version actual version](#)
- [Trap bsnStackManagerReconfiguration](#)
- [Wrong OoS Agent buffer setting, expected %s, actual %s, unit re-configured and reboot](#)
- [Wrong OoS Agent buffer setting expected value actual value unit cannot join stack.](#)
- [Wrong OoS Agent queue setting, expected %u, actual %u, unit reconfigured and reboot](#)
- [Wrong OoS Agent queue setting, expected %u, actual %u, unit re-configured and reboot](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Audit logs

The following logs are generated for this source:

- [Audit data initialized \(bad checksum\)](#)
- [Audit data initialized \(bad magic number\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Telnet server logs

The following logs are generated for this source:

- [Connection closed \(failed login\) IP address](#)
- [Connection closed \(inactivity logout\) IP address](#)
- [Connection closed \(login timeout\) IP address](#)
- [Connection closed \(lost connection\) IP address](#)
- [Connection closed. Maximum number of sessions reached. IP address:](#)
- [Connection closed. Maximum number of sessions reached. IP address:](#)
- [Connection closed \(user logout\) IP address](#)
- [Disallowed connection attempt from IP address](#)
- [Disallowed connection attempt - too many telnet sessions](#)
- [Failed login from IP address](#)
- [Failed login \(local auth\) from IP address:](#)
- [Failed login\(radius auth\) from IP add](#)
- [Failed login\(radius auth\) from serial conn](#)
- [Reset initiated through SSH by IP address](#)
- [Reset initiated through telnet by IP address](#)
- [Reset to default initiated through telnet by IP address](#)
- [Session closed \(inactivity logout\) IP address](#)
- [Session closed \(inactivity logout\) IP address](#)
- [Session closed \(lost connection\) IP address](#)
- [Session closed \(user logout\) IP address](#)
- [Session opened from IP address](#)
- [Session opened \(local auth\) from IP address:](#)
- [Session opened\(radius auth\) from IP add](#)
- [Stack RO password changed from IP add](#)
- [Stack RW password changed from IP add](#)
- [Successful connection from IP address](#)
- [Switch RO password changed from IP add](#)
- [Switch RW password changed from IP add](#)
- [Telnet-access is disabled](#)
- [Telnet-access is enabled](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AUR logs

The following logs are generated for this source:

- [AAUR-Info AAUR default](#)
- [AAUR-Info AAUR disable](#)
- [AAUR-Info AAUR enable](#)
- [AAUR-Info Agent transfer finished](#)
- [AAUR-Info Receive request for agent image start transfer](#)
- [AAUR-Info Receive request for agent image. Unable to start transfer](#)
- [AAUR-Info Send request for new agent image](#)
- [AAUR-Info Slave refuse transfer](#)
- [AAUR-Info The hardware is not compatible with the image version number version](#)
- [AAUR - Warning Agent image check sum ERROR](#)
- [AAUR-Warning Cannot get FLASH resource](#)
- [AAUR - Warning Slave agent image check sum ERROR](#)
- [AUR-Info AUR disable](#)
- [AUR-Info AUR enable](#)
- [AUR-Info AUR Restored to default](#)
- [AUR-Info New unit has different HW config Using cfg from the new unit](#)
- [DAUR - Info Diag transfer finished](#)
- [DAUR - Info Receive request for diag image start transfer](#)
- [DAUR - Info Receive request for diag image. Unable to transfer](#)
- [DAUR - Info Send request for new diag image](#)
- [DAUR - Info Slave refuse transfer](#)
- [DAUR - Info Start receive image](#)
- [DAUR - The hardware is not compatible with the image version number version](#)
- [DAUR - Warning: Cannot get FLASH resource](#)
- [DAUR - Warning Diag image check sum ERROR](#)
- [DAUR - Warning Slave diag image check sum ERROR](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Radius logs

The following logs are generated for this source:

- [Allowed connection attempt from user :](#)
- [Disallowed connection Access Reject for user](#)
- [Disallowed connection Invalid SvcType for user](#)
- [EAP Error Radius - ifIndex not found](#)
- [No Response from RADIUS Server](#)
- [RADIUS authentication on stack serial disabled](#)
- [RADIUS authentication on stack serial enabled](#)
- [RADIUS authentication on stack telnet disabled](#)
- [RADIUS authentication on stack telnet enabled](#)
- [RADIUS authentication on switch serial disabled](#)
- [RADIUS authentication on switch serial enabled](#)
- [RADIUS authentication on switch telnet disabled](#)
- [RADIUS authentication on switch telnet enabled](#)
- [RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't create RADIUS semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS AcctClient\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS client\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start radius recv\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS ServerCheck\(\) task, errno %d](#)
- [RADIUS MS-CHAPv2: Failed to change password](#)
- [RADIUS MS-CHAPv2: No response from RADIUS server](#)
- [RADIUS MS-CHAPv2: Password changed succesfully](#)
- [RADIUS MS-CHAPv2: RADIUS server not properly configured](#)
- [RADIUS MS-CHAPv2: Server does not speak RADIUS](#)
- [RADIUS MS-CHAPv2: Unable to change password at RADIUS server](#)
- [Radius: Server with index %d is down](#)
- [Radius: Server with index %d is up](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay secure logs

The following logs are generated for this source:

- [BaySec Exceeded number MAC addresses on unit# port#](#)
- [BaySec Not enough resource on port port# . Check QOS cfg](#)
- [Bay Secure error line line# # of octets read from NVRAM](#)
- [Bay Secure Exceeded number per-port MAC addresses on port unit# port#](#)
- [Bay Secure intruder](#)
- [Bay Secure intruder MAC](#)
- [Bay Secure MAC DA filtering not enough resources](#)
- [Bay Secure: MAC DA filtering not enough resources](#)
- [Bay Secure per-port addresses deleted](#)
- [Bay Secure Policy Error error type line line# 0](#)
- [Bay Secure Resource Error error# line line# resource ID](#)
- [MAC security table full](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

BAYSECURE, DCE logs

The following logs are generated for this source:

- [Trap_s5EtrSbsMacAccessViolation](#)
- [Trap_s5EtrSbsMacAccessViolation](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Console logs

The following logs are generated for this source:

- [Error accessing Image File](#)
- [Error Bad Image Checksum](#)
- [Error reading Image File](#)
- [Failed login from serial connection](#)
- [Failed login \(local auth\) from serial connection](#)
- [Failed to Create a Watchdog](#)
- [Failed to Read Image from Memory](#)
- [Login timeout serial connection](#)
- [Memory Allocation Error](#)
- [Not Enough Memory](#)
- [Reset initiated by console](#)
- [Reset to default initiated by console](#)
- [Session closed \(user logout\) serial connection](#)
- [Session opened from serial connection](#)
- [Session opened \(local auth\) from serial connection](#)
- [Session opened\(radius_auth\) from serial conn](#)
- [Stack RO password changed from serial conn](#)
- [Stack RW password changed from serial conn](#)
- [Switch RO password changed from serial conn](#)
- [Switch RW password changed from serial conn](#)
- [TFTP Failed](#)
- [The user <%s> was locked.](#)
- [Trap: bsnAaaAlreadyConnected](#)
- [Trap: bsnAaaIncorrectLogOnThresholdExceeded](#)
- [Trap: bsnAaaMaxNoOfSessionsExceeded](#)
- [Trap: bsnAaaUserAccountNotUsed](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CDT logs

The following logs are generated for this source:

- [call to cdt api function due to lock timeout \(code= error type total failures= number errno= error code \)](#)
- [cam driver initialization failed \(code= error type argument= line# \)](#)
- [cam driver initialized](#)
- [cam processing aborted \(code= error type argument= line# \)](#)
- [CDT MAC address mac_address was removed because LAG trunk trunked has disaggregated.](#)
- [CDT MAC address mac_address was removed because port port_no has aggregated in LAG](#)
- [CDT The static FDB entry MAC mac_address VLAN vlan_id trunk trunkId was deleted because LAG has disaggregated](#)
- [CDT The static FDB entry MAC mac_address VLAN vlan_id was deleted because Unit Port unit_port has aggregated](#)
- [EAP CDT Error](#)
- [Error in XGS3 memory DMA transfer](#)
- [Trap: s5EtrMacAddressTablesThresholdReached](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon logs

The following logs are generated for this source:

- [SLAMon Agent: agent IP address reset to default value](#)
- [SLAMon Agent CLI support not available](#)
- [SLAMon Agent CLI timeout value out of range](#)
- [SLAMon Agent disabled](#)
- [SLAMon Agent enabled](#)
- [SLAMon Agent: inconsistent IP address data specified](#)
- [SLAMon Agent inconsistent UDP port data specified](#)
- [SLAMon Agent info: %d %d %d](#)
- [SLAMon Agent invalid agent-to-agent port \(must be even value\)](#)
- [SLAMon Agent: message channel creation failure](#)
- [SLAMon Agent message channel creation failure](#)
- [SLAMon Agent operation is restricted CLI-only](#)
- [SLAMon Agent platform CLI command interface initialization issue](#)
- [SLAMon Agent platform timer initialization issue](#)
- [SLAMon Agent: terminated](#)
- [SLAMon Agent terminated](#)
- [SLAMon Agent: terminated - command/frame processing issue detected](#)
- [SLAMon Agent terminated — command/frame processing issue detected](#)
- [SLAMon Agent: terminated - NTR test exception detected](#)
- [SLAMon Agent terminated NTR test exception detected](#)
- [SLAMon Agent: terminated - resources unavailable](#)
- [SLAMon Agent terminated - resources unavailable](#)
- [SLAMon Agent: terminated - RTP test exception detected](#)
- [SLAMon Agent terminated - RTP test exception detected](#)
- [Trap: slaMonitorAgentExceptionDetected](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFC logs

The following logs are generated for this source:

- [FSH - Some files are not closed. MsgType #%d](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OSPF logs

The following logs are generated for this source:

- [Ospf Auth Type Mismatch in Hello](#)
- [Ospf Bad Version](#)
- [OSPF Callback function of timer is NULL](#)
- [OspfDbg Done Filter Init](#)
- [OspfDbg Done Global Init](#)
- [OspfDbg Done NV-Restore](#)
- [OspfDbg Done ReDist Init](#)
- [OspfDbg Init Instance vrfId=%d nodeP=0x%0x](#)
- [OspfDbg PostInit Done vrfId=%d nodeP=0x%0x](#)
- [OspfDbg PostInit EnableOspf vrfId=%d nodeP=0x%0x](#)
- [OspfDbg Started ospfTxHelloTimerTask](#)
- [Ospf Dead Int Mismatch in Hello](#)
- [Ospf Hello Int Mismatch in Hello](#)
- [OSPF Timer Link Error](#)
- [OSPF Timer List is corrupted](#)
- [OSPF Timer Unlink Error](#)
- [Trap ospfIfAuthFailure](#)
- [Trap ospfIfConfigError](#)
- [Trap ospfIfStateChange](#)
- [Trap ospfNbrStateChange](#)
- [Trap ospfVirtIfAuthFailure](#)
- [Trap ospfVirtIfConfigError](#)
- [Trap ospfVirtIfStateChange](#)
- [Trap ospfVirtNbrStateChange](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFG logs

The following logs are generated for this source:

- [CFG - Could not acquire FLASH sem](#)
- [CFG - Could not create ram copy buffer.](#)
- [CFG - NVRAM file system check: errors detected. Please reboot the system!](#)
- [CFG - NVRAM file system check: errors detected. Restored to default.](#)
- [FSH - File not closed .:](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Flash Driver logs

The following logs are generated for this source:

- [Download - DL_CKSUM_ACK_ERROR](#)
- [Download - DL_PROGRAM_STATUS_ACK_ERROR](#)
- [Download - DL_START_PROGRAM_FLASH_ACK_ERROR](#)
- [Download - Error Failed to get the dl resource.](#)
- [Download - Error Watchdog expire No Ack from NBUs download MSG # message ID](#)
- [Download - Failed to get buffer](#)
- [Download - Failed to malloc for buffer](#)
- [Download - Failed to start a watchdog](#)
- [Download - Image Checksum Error](#)
- [Download - Largest mem blk DL_SYSMEM_RESERVED](#)
- [Download - NBU Block Checksum Error](#)
- [Download - NBU_DL_PROGRAM_STATUS_ERROR](#)
- [Download - tftpXfer failed](#)
- [FSH - Error Calling taskLock\(\) returns Error](#)
- [FSH - Error Failed to erase flash sector](#)
- [FSH - Error Failed to lock flash sector](#)
- [FSH - Error Failed to program flash](#)
- [FSH - Error Failed to unlock flash sector](#)
- [FSH - Error Failed to write to flash address](#)
- [Reset - Error Failed to get the Reset sem](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO logs

The following logs are generated for this source:

- [CFGSO - Error: Failed to create watchdog timer](#)
- [CFGSO - Error: Failed to get an imc buffer](#)
- [CFGSO - Error: Failed to save data to NBU](#)
- [CFGSO - Error: Failed to start watchdog timer](#)
- [CFGSO - Error: File not read](#)
- [CFGSO - Error: File not write](#)
- [CFGSO - Warning Invalid Msg Id](#)
- [CFGSO - Warning Watchdog timer expire](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP logs

The following logs are generated for this source:

- [IGMP Added reserved multicast address](#)
- [IGMP Error sending database from unit unit#](#)
- [IGMP Error sending group database from unit unit#](#)
- [IGMP Exceeded reserved multicast address range #Addr numResAddrEntries+1 * #VLANs numActiveVLANs maxReservedRange](#)
- [IGMP Initialization failed Error code errCode](#)
- [IGMP: Max hardware Resources reached](#)
- [IGMP Proxy disabled on VLAN vlan#](#)
- [IGMP Proxy enabled on VLAN vlan#](#)
- [IGMP Query Time set to num on VLAN vlan#](#)
- [IGMP Removed reserved multicast address](#)
- [IGMP Robust Value set to num on VLAN vlan#](#)
- [IGMP Snooping disabled on VLAN vlan#](#)
- [IGMP Snooping enabled on VLAN vlan#](#)
- [IGMP SSM Range changed](#)
- [IGMP Unable to add reserved multicast address](#)
- [IGMP Unknown Multicast Filter disabled](#)
- [IGMP Unknown Multicast Filter enabled](#)
- [IGMP: Unknown Query received on SPBM Multicast C-VLAN](#)
- [IGMP V1 router ports mask](#)
- [IGMP V2 router ports mask](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CLI logs

The following logs are generated for this source:

- [Local authentication disabled on serial](#)
- [Local authentication disabled on telnet](#)
- [Local authentication enabled on serial](#)
- [Local authentication enabled on telnet](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS logs

The following logs are generated for this source:

- [TACACS+ accounting disabled](#)
- [TACACS+ accounting enabled](#)
- [TACACS+ authenticated serial connection closed](#)
- [TACACS+ authenticated telnet session closed](#)
- [TACACS+ authenticated telnet session max retries exceeded](#)
- [TACACS+ authentication on switch serial port disabled](#)
- [TACACS+ authentication on switch serial port enabled](#)
- [TACACS+ authentication on switch telnet disabled](#)
- [TACACS+ authentication on switch telnet disabled](#)
- [TACACS+ authentication on switch telnet enabled](#)
- [TACACS+ authentication on switch telnet enabled](#)
- [TACACS+ authorization disabled](#)
- [TACACS+ authorization enabled](#)
- [TACACS+ successful authentication](#)
- [TACACS+ unsuccessful authentication](#)
- [TACACS authenticated SSH session closed](#)
- [TACACS authentication on stack serial disabled](#)
- [TACACS authentication on stack serial enabled](#)
- [TACACS authentication on stack telnet disabled](#)
- [TACACS authentication on stack telnet enabled](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

config logs

The following logs are generated for this source:

- [Backup configuration block # block_number in use](#)
- [Backup configuration restored from primary configuration block # block_number](#)
- [Backup configuration updated for next active configuration block # block_number](#)
- [Backup Configuration Version is updated](#)
- [Configuration saved to nv block # block_number](#)
- [Error loading backup configuration block # block_number](#)
- [Error loading configuration block %d](#)
- [Error loading primary configuration block # block_number](#)
- [Error saving configuration to block # block_number](#)
- [Invalid Configuration Block Number %d](#)
- [Invalid Configuration Magic Number](#)
- [Invalid Configuration Version Number](#)
- [Loading configuration block # block_number](#)
- [Primary Configuration files are corrupted. Restored to default](#)
- [Primary Configuration Version is updated](#)
- [Restore Backup Configuration to Manufacture Default](#)
- [Restore Primary Configuration to Manufacture Default](#)
- [Toggle the Agent Primary Image](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Source Based Routing logs

The following logs are generated for this source:

- [IpFwdNhop Err Filter Install mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Filter Modify mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Filter UnInstall mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Save DB to NVRAM General File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop Err Save DB to NVRAM Instance File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop Err Save DB to NVRAM Policy File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop: Feature enable temporarily blocked - resources unavailable](#)
- [IpFwdNhop: Filter installation issue - resources unavailable](#)
- [IpFwdNhop: Issue detected during data restore \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during enable retry \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during feature enable \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during interface creation \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during VLAN %d routing status update](#)
- [IpFwdNhop: Issue detected during VLAN membership addition \(VID %d\)](#)
- [IpFwdNhop: Issue detected during VLAN membership deletion \(VID %d\)](#)
- [IpFwdNhop: Issue detected during VLAN policy association \(entry %d\)](#)
- [IpFwdNhop: Requested precedence and/or filter resources unavailable](#)
- [IpFwdNhop: Requested range checking resources unavailable](#)
- [IpFwdNhop: VLAN membership update \(VID %d\) issue - resources unavailable](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CONFIG DATA logs

The following logs are generated for this source:

- [Trap_bsnConfigurationSavedToNvram](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT logs

The following logs are generated for this source:

- [SLPP Warning - PDU was received on Vlan VlanId Unit UnitNo Port PortNo .](#)
- [SMLT IMC invalid cmd 1- StkCmd](#)
- [SMLT IMC tx error](#)
- [SMLT input parameter error mlt port vlan](#)
- [SMLT Stack db ex event num -0 -0*22221111](#)
- [SMLT stackEventNotify Invalid Msg Cmd - 0 - 0](#)
- [SMLT Stack inactive event 0-0- modMask](#)
- [SMLT Stack joined event num - 0 - 0*33331111](#)
- [SMLT Stack leaved event 0 - 0 - modMask](#)
- [SMLT STP enabled on IST trunk trkNo stp group grp](#)
- [SMLT Warning - LAC SMLT with more than 8 links - key - count](#)
- [SMLT Warning - smltEnable Software License Error- 0 - 0](#)
- [SMLT Warning - SMLT mismatched Lac Sys ID error shutdown all SMLT lac po](#)
- [Trap SLPP Port Down Event](#)
- [Trap Smlt Ist Link Down](#)
- [Trap Smlt Ist Link Up](#)
- [Trap Smlt Link Down](#)
- [Trap Smlt Link Up](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAI logs

The following logs are generated for this source:

- [DAI: ARP packet with invalid IP/MAC binding dropped on untrusted port %d/%d. ARP packet has MAC source %02x-%02x-%02x-%02x-%02x-%02x.](#)
- [DAI ARP packet with invalid IP MAC binding dropped on untrusted port unit# port#](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Run scripts: IP Office, LLDP, ADAC logs

The following logs are generated for this source:

- [Error creating Data VLAN](#)
- [Error creating Voice VLAN](#)
- [Error deleting previously created cost 1 default route](#)
- [Error deleting previously created Voice and Data VLANs](#)
- [Error executing script](#)
- [Error restoring management vlan to 1 or disabling ip routing](#)
- [Error saving configuration](#)
- [Error setting Data VLAN Gateway IP address and network mask](#)
- [Error setting default IP Route](#)
- [Error setting IP Office Call-Server IP address](#)
- [Error setting IP Office File-Server IP address](#)
- [Error setting spanning-tree learning to fast on all ports](#)
- [Error setting VLAN attributes](#)
- [Error setting Voice VLAN Gateway IP address and network mask](#)
- [Script was successfully executed](#)
- [Voice VLAN ID and Data VLAN ID cannot have the same value](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DCE logs

The following logs are generated for this source:

- [Trap: s5CtrFanDirectionError](#)
- [Trap: s5CtrHighTemperatureError](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Link State Tracking logs

The following logs are generated for this source:

- [LinkStateTracking: First interface %d/d went up in link state group %d, enabling downstream ports](#)
- [LinkStateTracking: First interface mlt %d went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: Interface %d/d went down in link state group %d](#)
- [LinkStateTracking: Interface %d/d went up in link state group %d](#)
- [LinkStateTracking: Interface mlt %d went down in link state group %d](#)
- [LinkStateTracking: Interface mlt %d went up in link state group %d](#)
- [LinkStateTracking: Interface %s went down in link state group %d](#)
- [LinkStateTracking: Interface %s went up in link state group %d](#)
- [LinkStateTracking: Last interface %d/d went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface mlt %d went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCPR logs

The following logs are generated for this source:

- [Error disabling global DHCP relay errCode](#)
- [Error enabling global DHCP relay errCode](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH logs

The following logs are generated for this source:

- [SSH disabled](#)
- [SSH DSA key deleted](#)
- [SSH DSA KEY generation completed](#)
- [SSH enabled in non-secure mode](#)
- [SSH enabled in secure mode](#)
- [SSH Maximum number of ssh sessions has been reached](#)
- [SSH RSA KEY generation completed](#)
- [SSH RSA key overwritten](#)
- [SSH session login using port](#)
- [SSH System is generating DSA KEY wait ...](#)
- [SSH TFTP DSA key download complete](#)
- [SSH TFTP RSA key download complete](#)
- [SSH USB DSA key download complete](#)
- [SSH USB RSA key download complete](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC (SFTP and SSH Client) logs

The following logs are generated for this source:

- [SSHC ASCII CFG download SFTP failure](#)
- [SSHC ASCII CFG upload SFTP failure](#)
- [SSHC CFG download SFTP failure](#)
- [SSHC CFG upload SFTP failure](#)
- [SSHC DSA key generation failure](#)
- [SSHC DSA key save failure](#)
- [SSHC DSA key upload TFTP failure](#)
- [SSHC DSA key upload USB failure](#)
- [SSHC RSA key generation failure](#)
- [SSHC RSA key save failure](#)
- [SSHC RSA key upload TFTP failure](#)
- [SSHC RSA key upload TFTP failure](#)
- [SSHC RSA key upload USB failure](#)
- [SSHC RSA key upload USB failure](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download Task logs

The following logs are generated for this source:

- [Download - image type image image version programmed successfully](#)
- [Download - TFTP timeout OR image file not found](#)
- [FSH - Time to Download the Image number seconds](#)
- [FSH - Time to Program the Image to flash number seconds](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

WEB logs

The following logs are generated for this source:

- [User allowed \(radius authentication pass\) to log in from Web from Src IP](#)
- [User disallowed \(radius authentication fail\) to log in from Web from Src IP](#)
- [User disallowed \(radius authentication fail\) to log in from Web from Src IP](#)
- [WEB-access is disabled](#)
- [WEB-access is enabled](#)
- [Web authentication fail from IP address](#)
- [Web authentication from IP address](#)
- [Web authentication \(RADIUS auth\) from IP address](#)
- [Web authentication \(RADIUS auth\) from IP address](#)
- [Web connection from IP address](#)
- [Web disconnect from IP address](#)
- [Web server attempting to open socket for port HTTP port](#)
- [Web server starts service on port HTTP port](#)
- [Web timeout from IP address](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DRIVER logs

The following logs are generated for this source:

- [Trap_bsUnicastStormControlAboveHighWatermark](#)
- [Trap_bsUnicastStormControlBelowLowWatermark](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE Redirect logs

The following logs are generated for this source:

- [Conflicting egress interface and egress trunk data specified](#)
- [Egress interface or trunk data is required - data missing](#)
- [FCoE controller ifIndex not set - FCoE redirection enable prohibited](#)
- [FCoE controller VLAN not set - FCoE redirection enable prohibited](#)
- [FCoE redirection default frame filter deletion failure detected](#)
- [FCoE redirection default frame filter installation failure detected](#)
- [FCoE redirection - egress interface issue detected \(ifIndex %d\)](#)
- [FCoE redirection - egress trunk issue detected \(trunk ID %d\)](#)
- [Invalid FCoE controller ingress interface specified](#)
- [Invalid FCoE controller VLAN specified](#)
- [Invalid/unknown FCoE redirection egress trunk ID specified](#)
- [Network access settings for FCoE Redirect must be modified locally](#)
- [Trap: FCoE - Egress Issue Detected](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP-Filter Manager logs

The following logs are generated for this source:

- [EAP Failed gpa-RoleAssociation unitPort ifIndex macHi xx-xx macLo xx-xx-xx-xx](#)
- [EAP Unable to Reserve EapAdmin Filter Resources rc retCode unitPort ifIndex](#)
- [EAP Unable to Reserve Filter Resources rc retCode unitPort ifIndex Force- Unauthorised](#)
- [EAP Unable to UnReserve EapAdmin Filter Resources rc retCode unitPort ifIndex](#)
- [EAP Unable to UnReserve Filter Resources rc retCode unitPort unit-portnum](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LACP logs

The following logs are generated for this source:

- [LAC: MLT error, partner aggregation bit not set](#)
- [LAC: MLT error, partner expired bit set.](#)
- [LAC: MLT error, partner synchronization bit not set.](#)
- [LAC with admin key %d failed configuration verification. Bad ARP INSPECTION configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad DHCP-SNOOPING configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad IGMP configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad MAC Security configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad qos status.](#)
- [LAC with admin key %d failed configuration verification. Bad rate-limiting configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad VLAN configuration.](#)
- [LAC with admin key %d failed configuration verification. Error #: %d-%d](#)
- [LAC with admin key %d failed configuration verification. Ports have different qos config.](#)
- [LAC with admin key %d failed configuration verification. Ports have different SPBM configurations.](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP-VLAN (QDT) logs

The following logs are generated for this source:

- [EAP GVlan Disabled for unitPort ifIndex - GVlan\(vid \) in different stg\(id \)](#)
- [EAP Invalid RAV ID](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT logs

The following logs are generated for this source:

- [Last MLT trunk was allocated by LAC. No more free trunk groups.](#)
- [Last MLT trunk was allocated by MLT. No more free trunk groups.](#)
- [MLT %d failed configuration verification. Bad ARP INSPECTION configuration.](#)
- [MLT %d failed configuration verification. Bad DHCP-SNOOPING configuration.](#)
- [MLT %d failed configuration verification. Bad IGMP configuration.](#)
- [MLT %d failed configuration verification. Bad IPSG CLASS configuration.](#)
- [MLT %d failed configuration verification. Bad MAC learning configuration.](#)
- [MLT %d failed configuration verification. Bad rate-limiting configuration.](#)
- [MLT %d failed configuration verification. Bad SPBM configuration.](#)
- [MLT %d failed configuration verification. Bad VLACP configuration.](#)
- [MLT %d failed configuration verification. Bad VLAN configuration.](#)
- [MLT ID# failed configuration verification. Error # error num](#)
- [MLT NV File error](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ENTMIB logs

The following logs are generated for this source:

- [Trap_entConfigChange](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ospf(drpmgr) logs

The following logs are generated for this source:

- [Ospf Area Mismatch RxArea ra.rb.rc.rd IntfArea ia.ib.ic.id](#)
- [Ospf Auth Failed IpAddr ia.ib.ic.id](#)
- [Ospf Auto Virt Link Failed area a1.a2.a3.a4 rtid r1.r2.r3.r4](#)
- [Ospf Cost Exceeds Limit Skip route Lsid l1.l2.l3.l4 Adv-rtr a1.a2.a3.a4](#)
- [Ospf Enable Failed as Resource Unavailable](#)
- [Ospf Hello: RId Same as Neighbor: rtid <r1.r2.r3.r4>, IpAddr <i1.i2.i3.i4>](#)
- [Ospf HW Mode Change:](#)
- [Ospf Invalid packet received: Pkt type <ospfPacketType>](#)
- [Ospf License Is Missing. Disable OSPF](#)
- [Ospf Nbr State Change: rtid <ra.rb.rc.rd> ipa <ia.ib.ic.id> state <neighborState>](#)
- [Ospf Netmask Mismatch in Hello IpAddr ia.ib.ic.id](#)
- [Ospf Option Mismatch in Hello IpAddr ia.ib.ic.id RxOption optionVal IntfOption optionVal](#)
- [Ospf Virt Nbr State Change: rtid <r1.r2.r3.r4>, virtAreald <v1.v2.v3.v4>, state <neighborState>](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Exception logs

The following logs are generated for this source:

- [Sw Exception](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SNMP logs

The following logs are generated for this source:

- [Authentication Failure Trap](#)
- [Cold Start Trap](#)
- [DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table](#)
- [Egp Neighbor Loss Trap](#)
- [Enterprise Specific Trap](#)
- [SNMP-access is disabled](#)
- [SNMP-access is enabled](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess](#)
- [Trap: bsnSFPIinsertion on port](#)
- [Trap: bsnSFPRemoval on port](#)
- [Trap: bsnUSBInsertion on unit](#)
- [Trap: bsnUSBRemoval on unit](#)
- [Trap: Run %s %s](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

HMOD logs

The following logs are generated for this source:

- [Down 1 cable inserted or neighbor powered on](#)
- [Down 2 cable inserted or neighbor powered on](#)
- [Down 1 cable removed or neighbor powered off](#)
- [Down 2 cable removed or neighbor powered off](#)
- [Stack cable "Down 1" is misconfigured](#)
- [Stack cable "Down 2" is misconfigured](#)
- [Stack cable "Up 1" is misconfigured](#)
- [Stack cable "Up 2" is misconfigured](#)
- [Up 1 cable inserted or neighbor powered on](#)
- [Up 2 cable inserted or neighbor powered on](#)
- [Up 1 cable removed or neighbor powered off](#)
- [Up 2 cable removed or neighbor powered off](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Quick Install logs

The following logs are generated for this source:

- [QuickInstall console configuration error.](#)
- [QuickInstall:console configuration success.](#)
- [QuickInstall: Error! Unable to locate agent software file](#)
- [QuickInstall: Error! Unable to locate ASCII configuration file](#)
- [QuickInstall: Error! Unable to locate diagnostics software file.](#)
- [QuickInstall: Processing of USB config file has commenced.](#)
- [QuickInstall: Processing of USB config file is complete](#)
- [QuickInstall USB config file not found.](#)
- [QuickInstall USB file config error at line line#](#)
- [QuickInstall USB file config error - file exceed 4096 bytes](#)
- [QuickInstall USB file config error - file exceed 200 lines.](#)
- [QuickInstall:USB file config success.](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH Client logs

The following logs are generated for this source:

- [SSHC: CFG download SFTP failure](#)
- [SSHC: CFG upload SFTP failure](#)
- [SSH_CLIENT Key couldnt be saved for host ip address](#)
- [SSH CLIENT SSH Connection to IP ip address was closed because parent console session console session ID was closed](#)
- [SSH_CLIENT SSH Connection to %s was disconnected](#)
- [SSH CLIENT: SSH Connection to %s was disconnected by host. Connection time: %s](#)
- [SSH CLIENT: SSH Connection to %s was disconnected by user. Connection time: %s.](#)
- [SSH_CLIENT Successful SSH Connection to %s using %s authentication](#)
- [SSHC: Password Authentication failure](#)
- [SSHC: RSA Authentication failure](#)
- [SSH session closed by ip address remote host. Connection time h hours m minutes](#)
- [Successful SSH connection to ip address](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Hello Module logs

The following logs are generated for this source:

- [Downstream stack direction is down cable removed or neighbor powered off](#)
- [Downstream stack direction is mis-configured](#)
- [Downstream stack direction is up cable inserted or neighbor powered on](#)
- [Hello Module unable to communicate with neighbor\(s\) unit reset](#)
- [Stack cable Down 1 is misconfigured](#)
- [Stack cable Down 2 is misconfigured](#)
- [Stack cable Up 1 is misconfigured](#)
- [Stack cable Up 2 is misconfigured](#)
- [Upstream stack direction is down cable removed or neighbor powered off](#)
- [Upstream stack direction is mis-configured](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IFMGR, SNMP logs

The following logs are generated for this source:

- [Link Down Trap](#)
- [Link Up Trap](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PIM logs

The following logs are generated for this source:

- [Pim E-BSR change](#)
- [Pim Invalid packet received](#)
- [Pim License Is Missing Disable PIM](#)
- [Pim Mode Change](#)
- [Pim Nbr State Change Up](#)
- [PIM Neighbor status change Down](#)
- [PIM Neighbor status change Up](#)
- [Pim RP type state](#)
- [Pim Unicast route change](#)
- [Pim Virt Nbr State Change Down](#)
- [Pim Virt Nbr State Change Up](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IMC logs

The following logs are generated for this source:

- [EAP IMC Failed to send message](#)
- [EAP IMC Memory allocation error](#)
- [IMC buffers of size buffer size have been exhausted buffer pool size pool size](#)
- [IMC imc_idtPacketDispatch\(\) incorrect rcvMsgType = %s\(%d\)](#)
- [IMC memory allocation error packetLength = %d file %s line %d](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PMT logs

The following logs are generated for this source:

- [PM in port mirroring the old data were modified - feature Allow Traffic in mirror port was added.](#)
- [PM in port mirroring the old data were modified - feature Many to Many was added.](#)
- [PM in port mirroring the old data were modified - feature Many to One was added.](#)
- [PM in port mirroring the old data were modified - feature Many to One with 128bits was added.](#)
- [PM in port mirroring the old data were modified - mode type was out of range.](#)
- [PM in port mirroring the old data were modified - monitored portA was out of range.](#)
- [PM in port mirroring the old data were modified - monitored portB was out of range.](#)
- [PM in port mirroring the old data were modified - NVRAM file structure was changed.](#)
- [PM in port mirroring the old data were modified - probe port was out of range.](#)
- [PM some port mirroring messages were stored to be displayd with delay.](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inband IP address logs

The following logs are generated for this source:

- [IPT: IP Address not in use \(duplicate detected\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPB logs

The following logs are generated for this source:

- [Cannot configure without loopback port available](#)
- [Cannot create CVLAN on vlan: IGMP Snooping enabled and SPBM Mcast disabled](#)
- [Cannot disable SPBM multicast - IGMP Snooping is enabled on C-VLANs](#)
- [Cannot enable SPBM multicast: feature unsupported](#)
- [Cannot enable SPBM multicast while unknown-mcast-no-flood is enabled](#)
- [Cannot enable SPBM while PIM is enabled](#)
- [CFM: ERROR adding port filters for VLAN %d - no resources](#)
- [SPB-MC Dynamic i-sid range conflicts with existing i-sid](#)
- [Trap: rclsisPlsbSmltPeerBmacMismatchTrap](#)
- [Trap: rclsisPlsbSmltVirtBmacMismatchTrap](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPFIX logs

The following logs are generated for this source:

- [IPFIX enable failure](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM logs

The following logs are generated for this source:

- [SPBM: ERROR adding C-VLAN UNI for i-sid %d, vlan %d - no resources](#)
- [SPBM: ERROR adding i-sid %x to i-sid table - table full](#)
- [SPBM: ERROR adding i-sid %x to i-sid table - table full](#)
- [SPBM: ERROR adding NNI on port %d vlan %d - no resources](#)
- [SPBM: ERROR adding peer %04x.%04x.%04x - no resources](#)
- [SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources](#)
- [SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources](#)
- [SPBM: ERROR adding Transparent UNI for i-sid %d, port %d - no resources](#)
- [SPBM: ERROR enabling SPBM due to Software License error](#)
- [SPBM: ERROR updating UNI for port %d/%d - no resources](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ipmc (igmp) logs

The following logs are generated for this source:

- [IGMP Maximum number of igmp enabled interfaces reached](#)
- [IGMP No hardware resource available](#)
- [IGMP SSM Range changed](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack Monitor logs

The following logs are generated for this source:

- [application_name failed DB-exchange stack formation delayed](#)
- [Hello Module unable to communicate with neighbor\(s\) unit reset](#)
- [IMC buffers of size size have been exhausted buffer pool size size](#)
- [Stack synchronization failed stack formation delayed](#)
- [Task task-name is suspended](#)
- [Task task_name is suspended](#)
- [Task whose index is Index1 Index2 is suspended](#)
- [Task whose index is taskID taskID is suspended](#)
- [The number of stack units is number instead of expected number](#)
- [Trap bsnStackConfigurationError](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ipsg logs

The following logs are generated for this source:

- [Cannot disable IP Source Guard on Unit unit# Port port#](#)
- [IPSG Insufficient resources available to enable IPSG on port unit# port#](#)
- [IPSG Maximum IP entries on port unit# port# has been reached](#)
- [IPSG nvRam file error param1 param2 param3](#)
- [IPSG Reached Max. IP entries supported on this port port#](#)
- [IPSG Reached Max. IP entries supported on this port unit# port#](#)
- [IPSG Resource allocated for Ports unit# port#](#)
- [IP Source Guard disabled on Unit unit# Port port#](#)
- [IP Source Guard enabled on Unit unit# Port port#](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP logs

The following logs are generated for this source:

- [Trap bsveVrrpTrapStateTransition](#)
- [Trap vrrpTrapNewMaster](#)
- [VRRP Feature globally disabled due to missing license](#)
- [VRRP: vrrpAdvtQueue is FULL. RX advertisement dropped in vlan %d!](#)
- [VRRP: vrrpQueue is FULL. Message dropped.](#)
- [VRRP VR VR Id VLAN Id Received mismatching advertisement interval \(advertisement interval\)](#)
- [VRRP VR VR Id VLAN Id Received mismatching advertisement type \(advertisement type \)](#)
- [VRRP VR VR Id VLAN Id Received mismatching fast advertisement interval \(fast advertisement interval\)](#)
- [VRRP VR VR Id VLAN Id Received mismatching virtual IP address \(received virtual ip address \)](#)
- [VRRP VR VR Id VLAN Id Received unknown VRRP packet type \(vrrp packet type \)](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPT logs

The following logs are generated for this source:

- [Gateway IP changed](#)
- [IPT BootP Disabled \(response not received from server\)](#)
- [IPT IP Address changed by BOOTP Server](#)
- [Stack IP changed](#)
- [Switch IP changed](#)
- [Trap Device has entered Forced Stack Mode \(MAC Address \)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv4 Routing logs

The following logs are generated for this source:

- [Assertion Failure in bcm_l3_hit_check- l3sw ip=%#x,l3hw ip=%#x](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

L3Mgr logs

The following logs are generated for this source:

- [Dynamic ARP could not be learned, maximum dynamic ARP limit is reached.](#)
- [ECMP features disabled due to inadequate license](#)
- [Failed ARP add ip addr 0xFFFFFFFF to HW hw error code](#)
- [Failed MVLAN\(vid \) L3 ip addr ip mask](#)
- [Failed route add <ip addr/ip mask> to HW <hw error code>](#)
- [Failed to create IP intf vid ip addr in HW hw error code](#)
- [IP blocking now 1 2 \(1=ON 2=OFF\)](#)
- [Maximum number of dynamic routes reached](#)
- [Radius use-mgmt-ip must be disabled first](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv6 logs

The following logs are generated for this source:

- [Duplicate address deletion failed ipv6_address](#)
- [Duplicate address detection succeeded ipv6_address](#)
- [IPv6 enabled with hardware support and FMGR filters](#)
- [IPv6 enabled with hardware support only](#)
- [IPv6 Forwarding disabled due to inadequate license](#)
- [IPv6 malloc failure](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE logs

The following logs are generated for this source:

- [PoE Main Power Usage Off](#)
- [PoE Main Power Usage On](#)
- [PoE Module Reset](#)
- [PoE Port Detection Status port# Status powerStatus](#)
- [PoE The PoE power limit for port unit port has been changed to x Watts based on IP phone discovery settings](#)
- [PoE The PoE power limit for port unit port has been restored to previous value x Watts](#)
- [PoE The PoE priority for port unit port has been changed to x based on IP phone discovery settings](#)
- [PoE The PoE priority for port unit port has been restored to previous value x](#)
- [The IP phone PoE limit has been changed to x Watts due to the stack modules configuration](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ISIS logs

The following logs are generated for this source:

- [SPBM adjacency with neighbor](#)
- [SPBM detect adj](#)
- [SPBM ISIS](#)
- [SPBM ISIS detect duplicate nick-name](#)
- [SPBM ISIS node](#)
- [Trap: rcIsisPlsbBvidMismatchTrap](#)
- [Trap: rcIsisPlsblsdbUpdateTrap](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

L3, MLT logs

The following logs are generated for this source:

- [Trap_s5CtrUnitDown](#)
- [Trap_s5CtrUnitDown](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC logs

The following logs are generated for this source:

- [LAC MLT error on far end. 0 - 0 - 0](#)
- [LAC No more trunk group available for LAC. 0 - 0 - 0](#)
- [Trap_bsnLacPortDisabledDueToLossOfVLACPDU](#)
- [Trap_bsnLacPortEnabledDueToReceiptOfVLACPDU](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PDT logs

The following logs are generated for this source:

- [Info: Transceiver inserted on %s](#)
- [Info: Transceiver removed from %s](#)
- [Management IP: excess traffic received on Management port%s](#)
- [Management IP: OOB port%s](#)
- [Management IP: OOB port%s](#)
- [Notice: DAC Cable on %s is below HW rev "H" and may cause link issues with a small number of PHYs](#)
- [Warning:non-supported transceiver on %s has been detected.](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LST logs

The following logs are generated for this source:

- [Trap: bsLstGroupOperStateChanged](#)
- [Trap: bsLstInterfaceStatusChanged](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MCFG logs

The following logs are generated for this source:

- [Configuration block %d is now in use](#)
- [Flash Erase Failed Sector %d Address 0x%x](#)
- [Flash Erase Warning Sector %d Address 0x%x Erase time %d ms](#)
- [Successfully loaded backup configuration files](#)
- [Successfully loaded configuration files from block %d](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MCFG (Second INFO BLOCK) logs

The following logs are generated for this source:

- [Boot: system boot status 0x%x](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Run scripts: LLDP, ADAC logs

The following logs are generated for this source:

- [Error configuring LLDP MED policies](#)
- [Error configuring Management IP Address](#)
- [Error enabling IP Routing](#)
- [Error setting Management VLAN](#)
- [Error setting uplink ports](#)
- [Error setting VLAN Gateway IP address and network mask](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MCMGR, DRPMGR logs

The following logs are generated for this source:

- [Trap_s5CtrHotSwap](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL logs

The following logs are generated for this source:

- [SSL certificate creation completed](#)
- [SSL certificate creation failed](#)
- [SSL certificate deleted](#)
- [SSL disabled](#)
- [SSL enabled](#)
- [SSL server reset](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MCMGR/IGMP logs

The following logs are generated for this source:

- [IGMP: V2 report drop on reserved GA](#)
- [IGMP: V3 report group skip on invalid GA](#)
- [IGMP: V3 report group skip on reserved GA](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Telnet logs

The following logs are generated for this source:

- [CLI pswd: Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch](#)
- [CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially \(stack IP addr not set\). Local user/pass used](#)
- [CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially \(switch IP addr not set\). Local user/pass used](#)
- [CLI pswd: Switch authentication parameter is obsolete; changes have not been applied](#)
- [Telnet-access is disabled](#)
- [Telnet-access is enabled](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MDA logs

The following logs are generated for this source:

- [%s card inserted \(in unit %s\)](#)
- [%s card removed \(from unit %s\)](#)
- [Warning failed to connect to %s card \(in unit %s\)](#)
- [Warning: non-supported qsfm inserted on %s. Port will be disabled.](#)
- [Warning %s card unsafely removed \(from unit %s\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLACP logs

The following logs are generated for this source:

- [Port %d blocked by VLACP due to end-partner down state](#)
- [Port %d blocked by VLACP until end-partner connection reestablished](#)
- [Port %d/%d blocked by VLACP due to end-partner down state](#)
- [Port %d reenabled by VLACP](#)
- [Port unit# port# blocked by VLACP until end-partner connection reestablished](#)
- [Port unit# port# reenabled by VLACP](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Memory Tool logs

The following logs are generated for this source:

- [Memory on unit %d is under %d MBytes.](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLD logs

The following logs are generated for this source:

- [MLD: Maximum number of mld enabled interfaces reached](#)
- [MLD: The maximum number of available hardware MLD entries has been reached](#)
- [MLD: The maximum number of available hardware MLD entries has been reached](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Multicast manager logs

The following logs are generated for this source:

- [MCM group node corrupted:](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Multi Config logs

The following logs are generated for this source:

- [Successfully loaded backup configuration files](#)
- [Successfully loaded configuration files from block %d](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NNCLI logs

The following logs are generated for this source:

- [Trap_newRoot](#)
- [Trap_s5EtrSbsMacRemoved](#)
- [Trap_s5EtrSbsMacTableCleared](#)
- [Trap_s5EtrSbsMacTableClearedForPort](#)
- [Trap_topologyChange](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NNRST logs

The following logs are generated for this source:

- [Trap RSTP Error Event](#)
- [Trap RSTP General Event](#)
- [Trap RSTP New Root](#)
- [Trap RSTP Protocol Migration](#)
- [Trap RSTP Topology Change](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NUQC logs

The following logs are generated for this source:

- [NUQC - Disabled](#)
- [NUQC - Enabled](#)
- [NUQC - Execution of the cli template failed](#)
- [NUQC - Execution of the cli template succeeded](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Run scripts: ADAC logs

The following logs are generated for this source:

- [Error creating MLT](#)
- [Error enabling ADAC](#)
- [Error enabling ADAC on ports](#)
- [Error setting ADAC operating mode](#)
- [Error setting call server ports](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Password Security logs

The following logs are generated for this source:

- [Trap: bsnROPasswordExpired: Read-only password expired](#)
- [Trap: bsnRWPasswordExpired: Read-write password expired](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM logs

The following logs are generated for this source:

- [PM unable to create mirror for instance instance number due to lack of available filter resources](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

POL logs

The following logs are generated for this source:

- [Trap_bspePethPsePortCurrentStatusNotification](#)
- [Trap_pethMainPowerUsageOffNotification](#)
- [Trap_pethMainPowerUsageOnNotification](#)
- [Trap_pethPsePortOnOffNotification](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QPAV2 logs

The following logs are generated for this source:

- [Trap_DAPP - DoS Attack Detected](#)
- [Trap_ntnQosPolicyEvoLocalUbpSessionFailure](#)
- [Trap_ubpEAPSessionEnd](#)
- [Trap_ubpEAPSessionStart](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Run scripts: IP Office logs

The following logs are generated for this source:

- [Error configuring port names](#)
- [Error enabling mstp learning on all ports](#)
- [Error enabling rstp learning on all ports](#)
- [Error setting poe-priority high on ports](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFTP Client logs

The following logs are generated for this source:

- [SSHC DSA Authentication failure](#)
- [SSHC Password Authentication failure](#)
- [SSHC RSA Authentication failure](#)
- [SSHC server connection failure](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port Mirroring logs

The following logs are generated for this source:

- [PM: in port mirroring the old data were modified - feature RSPAN was added](#)
- [PM: instance %d has been deleted because of insufficient HW resource](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS Agent logs

The following logs are generated for this source:

- [Issue detected enabling/disabling DSCP Mapping Table usage \(port %d\)](#)
- [Issue detected setting native DSCP Mapping Table values](#)
- [Unable to inform SPB of ifc assignment change \(%d/%d\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS Client logs

The following logs are generated for this source:

- [Allowed connection attempt from user](#)
- [Disallowed connection Access Reject for user](#)
- [Disallowed connection Invalid SvcType for user](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLPP Guard logs

The following logs are generated for this source:

- [SLPP-guard: hold-down timer has expired on port with SLPP-guard enabled. Port %s has been re-enabled](#)
- [SLPP-guard: SLPP-guard has not been enabled on port %s as no filters or filter precedences are available to setup an Ethertype filter](#)
- [SLPP-guard: SLPP packet received on port with SLPP-guard enabled. Port %s has been disabled](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Rear-Port logs

The following logs are generated for this source:

- [System: Rear-Port Mode has been set to disable \(reboot required to take effect\)](#)
- [System: Rear-Port Mode has been set to enable \(reboot required to take effect\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RMON logs

The following logs are generated for this source:

- [Trap fallingAlarm](#)
- [Trap risingAlarm](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Run scripts: IP Office, LLDP logs

The following logs are generated for this source:

- [Error configuring 802.1AB](#)
- [Error setting QoS](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SBR logs

The following logs are generated for this source:

- [Trap: rclsisPlsbSmltSplitBebMismatchTrap](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs

The following logs are generated for this source:

- [Unable to apply pre-defined UBP filter set to new user \(port %d/%d\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFTP logs

The following logs are generated for this source:

- [SSHC: ASCII CFG download SFTP failure](#)
- [SSHC: ASCII CFG upload SFTP failure](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SNTP logs

The following logs are generated for this source:

- [SNTP Could not sync to NTP servers.](#)
- [SNTP: First synchronization successful.](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SOFTLIC logs

The following logs are generated for this source:

- [Trap bsnTrialLicenseExpiration Trial license license# has expired. Disable licensed features to avoid network interruption](#)
- [Trap bsnTrialLicenseExpiration Trial license license# will expire in # days day\(s\)](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

STP logs

The following logs are generated for this source:

- [BPDU received on port with BPDU-Filtering enabled.](#)
- [EAP Vlan Change Aborted](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

USB logs

The following logs are generated for this source:

- [USB device inserted](#)
- [USB device removed](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

System Logging logs

The following logs are generated for this source:

- [After agent change message became invalid:](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TOTAL SYS UPTIME (TSU) logs

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TOTAL SYS UPTIME (TSU) logs

The following logs are generated for this source:

- [Trap: bsnSystemUp365Days sent from unit %d](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs

There are 988 logs for this severity. To simplify navigation, all logs are organized alphabetically by their name. Select the letter to navigate to the list of all logs starting with that letter for this severity.

A 44 logs	B 15 logs	C 64 logs	D 68 logs
E 107 logs	F 53 logs	G 2 logs	H 1 logs
I 81 logs	J 1 logs	K	L 42 logs
M 24 logs	N 12 logs	O 29 logs	P 42 logs
Q 15 logs	R 30 logs	S 162 logs	T 133 logs
U 23 logs	V 21 logs	W 19 logs	X
Y		Z	

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Console logs

The following logs are generated for this severity:

- [Failed login\(radius_auth\) from serial conn](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs

There are 522 logs for this severity. To simplify navigation, all logs are organized alphabetically by their name. Select the letter to navigate to the list of all logs starting with that letter for this severity.

A 25 logs	B 12 logs	C 29 logs	D 25 logs
E 22 logs	F 22 logs	G	H
I 141 logs	J	K	L 3 logs
M 11 logs	N 18 logs	O 5 logs	P 27 logs
Q 6 logs	R 24 logs	S 36 logs	T 19 logs
U 92 logs	V 2 logs	W 3 logs	X
Y		Z	

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs

There are 179 logs for this severity. To simplify navigation, all logs are organized alphabetically by their name. Select the letter to navigate to the list of all logs starting with that letter for this severity.

A 3 logs	B 2 logs	C 12 logs	D 16 logs
E	F 10 logs	G	H 1 logs
I 53 logs	J	K	L 1 logs
M 4 logs	N	O	P 5 logs
Q 2 logs	R 3 logs	S 24 logs	T 4 logs
U 39 logs	V	W	X
Y		Z	

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error logs

The following logs are generated for this severity:

- [CFGSO - Warning Watchdog timer expire](#)
- [Fabric Attach: non-MLT trunk uplink requires MLT ID/LACP key binding \(missing\)](#)
- [Fabric Attach: specified uplink currently a trunk member](#)
- [SPBM: ERROR adding C-VLAN UNI for i-sid %d, vlan %d - no resources](#)
- [SPBM: ERROR adding NNI on port %d vlan %d - no resources](#)
- [SPBM: ERROR adding peer %04x.%04x.%04x - no resources](#)
- [SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources](#)
- [SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources](#)
- [SPBM: ERROR updating UNI for port %d/%d - no resources](#)
- [Stack cable Down 1 is misconfigured](#)
- [Stack cable Down 2 is misconfigured](#)
- [Stack cable Up 1 is misconfigured](#)
- [Stack cable Up 2 is misconfigured](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Minor logs

The following logs are generated for this severity:

- [Fabric Attach: auto provision setting not supported by platform](#)
- [Fabric Attach: binding acceptance failure \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation failure \(<ISID>/<VID>\)](#)
- [Fabric Attach: conflicting uplink data detected](#)
- [Fabric Attach: device discovered \(Authentication Fail - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Fail - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: incompatible device advertisement \(port <PORT>\)](#)
- [Fabric Attach: incompatible device advertisement \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: interface-specific I-SID/VLAN assignments not allowed](#)
- [Fabric Attach: invalid VLAN data \(unknown or incompatible type\)](#)
- [Fabric Attach: message authentication support not available](#)
- [Fabric Attach: operation failure detected](#)
- [Fabric Attach: operation rejected - client-owned entry](#)
- [Fabric Attach: operation rejected - CVLAN already exists](#)
- [Fabric Attach: operation rejected - entry does not exist](#)
- [Fabric Attach: operation rejected - not supported by element type](#)
- [Fabric Attach: operation rejected - service not enabled](#)
- [Fabric Attach: operation rejected - table entry limits reached](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - application interactions](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - invalid VLAN](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - no FA resources](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - no VLAN resources](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - peer acceptance](#)
- [Fabric Attach: specified uplink currently invalid](#)
- [Fabric Attach: static uplink addition failure](#)
- [Fabric Attach: static uplink deletion failure](#)
- [Fabric Attach: temporary I-SID/VLAN binding deletion failure](#)
- [Fabric Attach: uplink operation only supported by FA Proxy](#)
- [Fabric Attach: zero touch operations not completed \(mgmt VLAN <VID>\)](#)
- [Fabric Attach: Zero Touch settings read-only for FA element type](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Major logs

The following logs are generated for this severity:

- [Fabric Attach: agent settings reset incomplete](#)
- [Fabric Attach: asgn activation failure \(port tagging\)](#)
- [Fabric Attach: asgn activation failure \(VLAN creation\)](#)
- [Fabric Attach: asgn activation failure \(VLAN membership\)](#)
- [Fabric Attach: binding deactivation failure \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: I-SID/VLAN assignment creation failure \(unexpected\)](#)
- [Fabric Attach: I-SID/VLAN assignment deletion failure \(unexpected\)](#)
- [Fabric Attach: Zero Touch option processing failure detected](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Warning logs

The following logs are generated for this severity:

- [Composite filter set addition failure seed filter set unknown](#)
- [Failed route add <ip addr/ip mask> to HW <hw error code>](#)
- [IMC imc_idtPacketDispatch\(\) incorrect rcvMsgType = %s\(%d\)](#)
- [IMC memory allocation error packetLength = %d file %s line %d](#)
- [Queue set value modification prohibited](#)
- [Trap s5CtrUnitDown](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Warning/Information logs

The following logs are generated for this severity:

- [Bay Secure: Exceeded %d per-trunk MAC addresses on trunk %d](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious/Critical logs

The following logs are generated for this severity:

- [After agent change message became invalid:](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info AAUR default log

AAUR-Info AAUR default

AAUR default.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info AAUR disable log

AAUR-Info AAUR disable

The AAUR is disabled.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info AAUR enable log

AAUR-Info AAUR enable

The AAUR is enabled.

Source	Severity
AUR	Information

Remedial action

No action required.



AAUR-Info Agent transfer finished

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info Agent transfer finished log

AAUR-Info Agent transfer finished

The agent transfer is completed.

Source	Severity
AUR	Information

Remedial action

No action required.



AAUR-Info Receive request for agent image start transfer

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info Receive request for agent image start transfer log

AAUR-Info Receive request for agent image start transfer

The system received request for an agent image and the transfer is started.

Source	Severity
AUR	Information

Remedial action

No action required.



AAUR-Info Receive request for agent image. Unable to start transfer

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info Receive request for agent image. Unable to start transfer log

AAUR-Info Receive request for agent image. Unable to start transfer

The system received request for an agent image. Unable to start transfer.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info Send request for new agent image log

AAUR-Info Send request for new agent image

The system is sending request for a new agent image.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info Slave refuse transfer log

AAUR-Info Slave refuse transfer

Slave refuse transfer.

Source	Severity
AUR	Information

Remedial action

No action required.



AAUR-Info The hardware is not compatible with the image_version_number version

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Info The hardware is not compatible with the image_version_number version log

AAUR-Info The hardware is not compatible with the image_version_number version

The hardware is not compatible.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR - Warning Agent image check sum ERROR log

AAUR - Warning Agent image check sum ERROR

Agent image check sum error.

Source	Severity
AUR	Serious

Remedial action

No action required.



AAUR-Warning Cannot get FLASH resource

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR-Warning Cannot get FLASH resource log

AAUR-Warning Cannot get FLASH resource

The system cannot get the flash resource.

Source	Severity
AUR	Information

Remedial action

No action required.



AAUR - Warning Slave agent image check sum ERROR

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AAUR - Warning Slave agent image check sum ERROR log

AAUR - Warning Slave agent image check sum ERROR

Slave agent image check sum error.

Source	Severity
AUR	Serious

Remedial action

No action required.



Access assignment distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment distribution across stack failed log

Access assignment distribution across stack failed

Unable to carry out the access assignment distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Access assignment modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment modifications not supported log

Access assignment modifications not supported

The system detected an internal error; The Specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment modification support limited log

Access assignment modification support limited

Access assignment entries under system control may be deleted but not modified. The same goes for templates.

Source	Severity
QoS	Serious

Remedial action

Create a different access assignment entry with the wanted parameters.



Access assignment name contains unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment name contains unacceptable characters log

Access assignment name contains unacceptable characters

Only printable characters are allowed.

Source	Severity
QoS	Serious

Remedial action

Enter valid characters for the access element block label.



Access assignment name length outside of acceptable limits

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment name length outside of acceptable limits log

Access assignment name length outside of acceptable limits

The maximum length for the access assignment name is 16.

Source	Severity
QoS	Serious

Remedial action

Enter an access assignment label within the limit.



Access assignment name not acceptable - reserved

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment name not acceptable - reserved log

Access assignment name not acceptable - reserved

The label is reserved in the system.

Source	Severity
QoS	Serious

Remedial action

Enter a different label.



Access assignment template still in use (siblings active)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access assignment template still in use (siblings active) log

Access assignment template still in use (siblings active)

Cannot delete an access assignment entry if it has one or more active siblings in use.

Source	Severity
QoS	Serious

Remedial action

Remove the sibling(s) first.



Access element block label contains unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element block label contains unacceptable characters log

Access element block label contains unacceptable characters

Only printable characters are allowed.

Source	Severity
QoS	Serious

Remedial action

Enter valid characters for the access element block label.



Access element block label length outside of acceptable limits

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element block label length outside of acceptable limits log

Access element block label length outside of acceptable limits

The maximum length for the access element block name is 16.

Source	Severity
QoS	Serious

Remedial action

Enter a smaller access element block label.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element cluster count (cluster count) exceeds limit (cluster limit) log

Access element cluster count (cluster count) exceeds limit (cluster limit)

The cluster limit of the access element depends on the target hardware platform.

Source	Severity
QoS	Serious

Remedial action

Check the documentation for the maximum number of access elements allowed.



Access element cluster is referenced (addition prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element cluster is referenced (addition prohibited) log

Access element cluster is referenced (addition prohibited)

The access-list can not be modified if it is currently referenced (assigned).

Source	Severity
QoS	Serious

Remedial action

Remove the referee before requesting any modifications.



Access element cluster is referenced (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element cluster is referenced (deletion prohibited) log

Access element cluster is referenced (deletion prohibited)

Access element can not be removed if it is currently referenced.

Source	Severity
QoS	Serious

Remedial action

Remove the conflicting element first.



Access element distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element distribution across stack failed log

Access element distribution across stack failed

Unable to access the element distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Access element modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element modifications not supported log

Access element modifications not supported

The system detected an Internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Access element name contains unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element name contains unacceptable characters log

Access element name contains unacceptable characters

Only printable characters are allowed.

Source	Severity
QoS	Serious

Remedial action

Enter valid characters for the access element's label.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element name length outside of acceptable limits log

Access element name length outside of acceptable limits

The maximum length for the access element name is 16.

Source	Severity
QoS	Serious

Remedial action

Enter a smaller access element label.



Access element name not acceptable - reserved

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Access element name not acceptable - reserved log

Access element name not acceptable - reserved

The label is reserved in the system.

Source	Severity
QoS	Serious

Remedial action

Enter a different label.



ADAC: ADAC of Nortel IP Phones not functional

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC: ADAC of Nortel IP Phones not functional log

ADAC: ADAC of Nortel IP Phones not functional

ADAC is not working.

Source	Severity
ADAC	Serious

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC Error applying main VLAN QoS configuration log

ADAC Error applying main VLAN QoS configuration

The system detected an error while applying QoS or VLAN global configuration.

Source	Severity
ADAC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC Error applying VLAN QoS configuration for unit port unit# port# log

ADAC Error applying VLAN QoS configuration for unit port unit# port#

The system detected an error while applying QoS or VLAN configuration from unit or port.

Source	Severity
ADAC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC Error forcing administrative state to disable enable log

ADAC Error forcing administrative state to disable enable

The system detected an error when forcing the administrative state to disable/enable.

Source	Severity
ADAC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC: Error registering CDT handlers log

ADAC: Error registering CDT handlers

The system detected an error when registering the CDT handlers.

Source	Severity
ADAC	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC Error removing main VLAN QoS configuration log

ADAC Error removing main VLAN QoS configuration

The system detected an error while removing QoS or VLAN global configuration.

Source	Severity
ADAC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC Error removing VLAN QoS configuration for unit port unit# port# log

ADAC Error removing VLAN QoS configuration for unit port unit# port#

The system detected an error while removing QoS or VLAN configuration to unit or port.

Source	Severity
ADAC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC Forced administrative state to disable enable log

ADAC Forced administrative state to disable enable

The administrative state of ADAC feature is forced to disable/enable.

Source	Severity
ADAC	Information

Remedial action

No action required.



ADAC System operationally disable enable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ADAC System operationally disable enable log

ADAC System operationally disable enable

The system is operating with ADAC as disabled/enabled.

Source	Severity
ADAC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES activated by schedule log

AES activated by schedule

The Avaya Engery Saver is activated by the AES schedule.

Source	Severity
AES	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES deactivated by schedule log

AES deactivated by schedule

The Avaya Energy Saver is deactivated by the AES schedule.

Source	Severity
AES	Information

Remedial action

No action required.



AES globally disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES globally disabled log

AES globally disabled

The Avaya Energy Saver is disabled.

Source	Severity
AES	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



AES globally enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES globally enabled log

AES globally enabled

The Avaya Engery Saver is enabled.

Source	Severity
AES	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



AES manually activated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES manually activated log

AES manually activated

The Avaya Energy Saver is manually activated.

Source	Severity
AES	Information

Remedial action

No action required.



AES manually deactivated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES manually deactivated log

AES manually deactivated

The Avaya Engery Saver is manually deactivated.

Source	Severity
AES	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



AES not applying schedule because SNTP not synchronized

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES not applying schedule because SNTP not synchronized log

AES not applying schedule because SNTP not synchronized

The Avaya Energy Saver cannot be activated, as the internal clock is not synchronized with SNTP Server

Source	Severity
AES	Information

Remedial action

Check the availability of the SNTP server, and wait for the clock to be synchronized with SNTP Server.



AES time is synchronized applying schedule

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AES time is synchronized applying schedule log

AES time is synchronized applying schedule

The Avaya Energy Saver schedule is applied, as the clock is synchronized with the SNTP.

Source	Severity
AES	Information

Remedial action

No action required.



After agent change message became invalid:

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

After agent change message became invalid: log

After agent change message became invalid:

After upgrade/intermediary downgrade, if the Application id or message id are out of range, the message is replaced in order to avoid DAE.

Source	Severity
--------	----------

System Logging	Serious/Critical
----------------	------------------

Remedial action

No action required.



Agent configuration distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Agent configuration distribution across stack failed log

Agent configuration distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Unable to commit changes across the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Allowed connection attempt from user :

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Allowed connection attempt from user : log

Allowed connection attempt from user :

Radius - allowed connection attempt for user starting with the given name.

Source	Severity
RADIUS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Allowed connection attempt from user log

Allowed connection attempt from user

RADIUS: allowed connection attempt for the user starting with the given name.

Source	Severity
RADIUS Client	Information

Remedial action

No action required.



Another BU tried to join the stack. Unit ignored

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Another BU tried to join the stack. Unit ignored log

Another BU tried to join the stack. Unit ignored

A switch having BU switch selected was added to an existing stack.

Source	Severity
Stack Manager	Information

Remedial action

Unset BU switch from the new added unit.



application-name failed DB-exchange stack failed to form

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

application-name failed DB-exchange stack failed to form log

application-name failed DB-exchange stack failed to form

The stack did not form, as the application <application-name> did not exchange its database successfully.

Source	Severity
Stack Manager	Critical

Remedial action

Reboot the stack.



application-name failed DB-exchange stack formation delayed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

application-name failed DB-exchange stack formation delayed log

application-name failed DB-exchange stack formation delayed

The application <application-name> failed to exchange its database.

Source	Severity
Stack Manager	Serious

Remedial action

Reboot the unit if it is unsuccessful in joining the stack.



application_name failed DB-exchange stack formation delayed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

application_name failed DB-exchange stack formation delayed log

application_name failed DB-exchange stack formation delayed

The application name in the Stack Monitor failed the DB exchange for three times simultaneously.

Source	Severity
--------	----------

Stack Monitor	Information
---------------	-------------

Remedial action

No action required. The Stack Manager will wait for 3 minutes after a DB-exchange failure and then restart the stack formation process. The logs are saved to NVRAM for future reference.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII failed log

ASCII failed

The ASCII configuration file contains syntax errors or inconsistent/incorrect configuration data.

Source	Severity
ACG	Information

Remedial action

Attempt to load the ASCII configuration file manually from a console and look for error messages.



ASCII finished successfully

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII finished successfully log

ASCII finished successfully

The ASCII configuration file is successfully loaded and processed during manual configuration.

Source	Severity
ACG	Information

Remedial action

No action required.



ASCII finished successfully at load on boot

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII finished successfully at load on boot log

ASCII finished successfully at load on boot

The ASCII configuration file is successfully loaded and processed at boot time.

Source	Severity
ACG	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII transfer failed log

ASCII transfer failed

The ASCII configuration file could not be transferred from the TFTP server (or USB port on the switch) during manual configuration.

Source	Severity
ACG	Information

Remedial action

Check if the TFTP server is accessible.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII transfer failed at load on boot log

ASCII transfer failed at load on boot

The ASCII configuration file could not be transferred from the TFTP server (or USB port on the switch) at boot time.

Source	Severity
ACG	Information

Remedial action

Check if the TFTP server is accessible.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII transfer OK log

ASCII transfer OK

The ASCII configuration file was successfully transferred from the TFTP server (or USB port on the switch) during manual configuration.

Source	Severity
ACG	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ASCII transfer OK at load on boot log

ASCII transfer OK at load on boot

ASCII config file was transferred successfully from TFTP server (or USB port on ERS45xx and ERS5xxx) at boot time.

Source	Severity
ACG	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Assertion Failure in bcm_I3_hit_check- I3sw ip=%#x,I3hw ip=%#x log

Assertion Failure in bcm_I3_hit_check- I3sw ip=%#x,I3hw ip=%#x

Inconsistency between software and hardware IP values at some index. The software IP address and hardware IP address are displayed in the log.

Source	Severity
IPv4 Routing	Serious

Remedial action

Do not connect a host for which you have a host route configured directly to the switch.



Attempt to create an element that already exists (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Attempt to create an element that already exists (prohibited) log

Attempt to create an element that already exists (prohibited)

An entry with the same characteristics already exists in the system.

Source	Severity
QoS	Serious

Remedial action

Remove the existing entry if necessary.



Attempt to delete modify non-existing element (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Attempt to delete modify non-existing element (prohibited) log

Attempt to delete modify non-existing element (prohibited)

You cannot remove or modify an inexistent element.

Source	Severity
QoS	Serious

Remedial action

If this is a modification attempt create a new element.



Attempt to manipulate system-owned interface (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Attempt to manipulate system-owned interface (prohibited) log

Attempt to manipulate system-owned interface (prohibited)

Modification of the system-owned interfaces is prohibited.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface index.



Attempt to manipulate user policy data rejected (disabled)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Attempt to manipulate user policy data rejected (disabled) log

Attempt to manipulate user policy data rejected (disabled)

All user based policy data modifications are prohibited when the UBP support is disabled.

Source	Severity
QoS	Serious

Remedial action

Enable the UPB support.



Audit data initialized (bad checksum)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Audit data initialized (bad checksum) log

Audit data initialized (bad checksum)

The audit data is corrupt.

Source	Severity
Audit	Serious

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Audit data initialized (bad magic number)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Audit data initialized (bad magic number) log

Audit data initialized (bad magic number)

The audit data is corrupt.

Source	Severity
Audit	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AUR-Info AUR disable log

AUR-Info AUR disable

AUR is disabled.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AUR-Info AUR enable log

AUR-Info AUR enable

AUR is enabled.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AUR-Info AUR Restored to default log

AUR-Info AUR Restored to default

AUR is restored to default.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

AUR-Info New unit has different HW config Using cfg from the new unit log

AUR-Info New unit has different HW config Using cfg from the new unit

The new unit has a different HW configuration.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Authentication Failure Trap log

Authentication Failure Trap

Authentication Failure.

Source	Severity
SNMP	Information

Remedial action

No action required.



Backup configuration block # block_number in use

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Backup configuration block # block_number in use log

Backup configuration block # block_number in use

The back up configuration is in use.

Source	Severity
config	Information

Remedial action

No action required.



Backup configuration restored from
primary configuration block #
block_number

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Backup configuration restored from primary configuration block # block_number log

Backup configuration restored from primary configuration block # block_number

Copy the back up primary configuration to the backup configuration.

Source	Severity
config	Information

Remedial action

No action required.



Backup configuration updated for next
active configuration block #
block_number

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Backup configuration updated for next active configuration block # block_number log

Backup configuration updated for next active configuration block # block_number

The back up configuration will be used for the next active configuration.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Backup Configuration Version is updated log

Backup Configuration Version is updated

The back up configuration version is updated.

Source	Severity
config	Information

Remedial action

No action required.



Base action distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action distribution across stack failed log

Base action distribution across stack failed

Unable to commit base action distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Base action entry referenced by clfr block (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action entry referenced by clfr block (deletion prohibited) log

Base action entry referenced by clfr block (deletion prohibited)

Cannot delete a base action if it's referenced by a classifier block.

Source	Severity
QoS	Serious

Remedial action

Remove the classifier block first.



Base action entry referenced by meter (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action entry referenced by meter (deletion prohibited) log

Base action entry referenced by meter (deletion prohibited)

Cannot delete a base action if it's referenced in a meter.

Source	Severity
QoS	Serious

Remedial action

Remove the meter first.



Base action entry referenced by policy (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action entry referenced by policy (deletion prohibited) log

Base action entry referenced by policy (deletion prohibited)

Cannot delete a base action if it's referenced by a policy.

Source	Severity
QoS	Serious

Remedial action

Remove the policy first.



Base action extension identifier invalid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action extension identifier invalid log

Base action extension identifier invalid

The specified base action extension identifier is invalid

Source	Severity
QoS	Serious

Remedial action

Enter a valid base action extension identifier.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Base action modification prohibited due to action usage

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action modification prohibited due to action usage log

Base action modification prohibited due to action usage

Cannot modify a base action if it's in use.

Source	Severity
QoS	Serious

Remedial action

Remove the QoS entries that are using the base action first.



Base action modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base action modifications not supported log

Base action modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Base unit has loopback port mode %s and the current unit %s. Unit reconfigured and rebooted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base unit has loopback port mode %s and the current unit %s. Unit reconfigured and rebooted log

Base unit has loopback port mode %s and the current unit %s. Unit reconfigured and rebooted

The loopback port mode of the current unit is different than the BU's. Current unit will reconfigure and will be rebooted. Loopback port modes are: stack, rear, MDA, none.

Source	Severity
Stack Manager	Serious

Remedial action

No action required.



Base unit has loopback port mode <SPBM reserved port mode> and the current unit <SPBM reserved port mode>. Unit reconfigured and rebooted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Base unit has loopback port mode <SPBM reserved port mode> and the current unit <SPBM reserved port mode>. Unit reconfigured and rebooted log

Base unit has loopback port mode <SPBM reserved port mode> and the current unit <SPBM reserved port mode>. Unit reconfigured and rebooted

Current unit has different SPBM reserved port setting than the one used by BU. Unit will be reconfigured and rebooted.

Source	Severity
--------	----------

Stack Manager	Serious
---------------	---------

Remedial action

No action required.



BaySec Exceeded number MAC addresses on unit# port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

BaySec Exceeded number MAC addresses on unit# port# log

BaySec Exceeded number MAC addresses on unit# port#

This message appears when the system is trying to set too many security roles on a port.

Source	Severity
Bay Secure	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



BaySec Not enough resource on port port# . Check QOS cfg

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

BaySec Not enough resource on port port# . Check QOS cfg log

BaySec Not enough resource on port port# . Check QOS cfg

The system detected an error when reserving the policy on port. (This is generated by an error in creating the Filter Manager database information for a policy and installing that policy to the hardware)

Source	Severity
--------	----------

Bay Secure	Serious
------------	---------

Remedial action

No action required.



Bay Secure error line line# # of octets read from NVRAM

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure error line line# # of octets read from NVRAM log

Bay Secure error line line# # of octets read from NVRAM

The system is facing problem in reading the data saved in the NVRAM.

Source	Severity
Bay Secure	Serious

Remedial action

Activate the default configuration.



Bay Secure: Exceeded %d per-trunk MAC addresses on trunk %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure: Exceeded %d per-trunk MAC addresses on trunk %d log

Bay Secure: Exceeded %d per-trunk MAC addresses on trunk %d

This notification is generated after successfully saving the DHCP snooping binding table to a SFTP server external file.

Source

Severity

DHCP Snoop

Warning/Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Bay Secure Exceeded number per-port MAC addresses on port unit# port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure Exceeded number per-port MAC addresses on port unit# port# log

Bay Secure Exceeded number per-port MAC addresses on port unit# port#

The maximum number of MAC addresses that can be learned on a port is reached.

Source	Severity
Bay Secure	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure intruder log

Bay Secure intruder

The system detected an intruder.

Source	Severity
Bay Secure	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure intruder MAC log

Bay Secure intruder MAC

The system detected an intruder.

Source	Severity
Bay Secure	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure MAC DA filtering not enough resources log

Bay Secure MAC DA filtering not enough resources

The system detected an error when trying to add a MAC DA filtering address. (This is generated by an error in creating the Filter Manager database information for a policy and installing that policy to the hardware)

Source	Severity
--------	----------

Bay Secure	Serious
------------	---------

Remedial action

No action required.



Bay Secure: MAC DA filtering not enough resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure: MAC DA filtering not enough resources log

Bay Secure: MAC DA filtering not enough resources

Source	Severity
--------	----------

Bay Secure	Information
------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure per-port addresses deleted log

Bay Secure per-port addresses deleted

An auto-learned address is deleted (This warning appears only on the BU or stand-alone switch).

Source	Severity
Bay Secure	Information

Remedial action

No action required.



Bay Secure Policy Error error type line line# 0

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure Policy Error error type line line# 0 log

Bay Secure Policy Error error type line line# 0

The system detected an error in getting or setting a policy.

Source	Severity
Bay Secure	Serious

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Bay Secure Resource Error error# line line# resource ID

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Bay Secure Resource Error error# line line# resource ID log

Bay Secure Resource Error error# line line# resource ID

The system detected an error when operating with the task resource.

Source	Severity
--------	----------

Bay Secure	Critical
------------	----------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

BECOME_TEMP_BU event sent unit mask value appl mask value log

BECOME_TEMP_BU event sent unit mask value appl mask value

The unit on which this message is logged has become the temporary base unit.

Source	Severity
--------	----------

Stack Manager	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Boot: system boot status 0x%x log

Boot: system boot status 0x%x

Presents the state of all configs; ex: which config is active. The boot status is displayed in the log.

Source	Severity
MCFG (Second INFO BLOCK)	Information

Remedial action

No action required.



BPDU received on port with BPDU-Filtering enabled.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

BPDU received on port with BPDU-Filtering enabled. log

BPDU received on port with BPDU-Filtering enabled.

BPDU received on port with BPDU-Filtering enabled.

Source	Severity
STP	Information

Remedial action

No action required.



Buffer configuration inconsistency detected (local buffer conf stack buffer conf)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Buffer configuration inconsistency detected (local buffer conf stack buffer conf) log

Buffer configuration inconsistency detected (local buffer conf stack buffer conf)

The buffering configuration is not the same on all units in stack.

Source	Severity
QoS	Serious

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



BU was unable to send IMC for NBUs VLAN/Port configuration

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

BU was unable to send IMC for NBUs VLAN/Port configuration log

BU was unable to send IMC for NBUs VLAN/Port configuration

There was an error when sending VLAN configuration to stack.

Source	Severity
VLAN	Information

Remedial action

No action required.



call to cdt api function due to lock
timeout (code= error type total
failures= number errno= error code)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

call to cdt api function due to lock timeout (code= error type total failures= number errno= error code) log

call to cdt api function due to lock timeout (code= error type total failures= number errno= error code)

The system detected an error caused by failure in the mutual exclusion lock mechanisms.

Source	Severity
CDT	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

cam driver initialization failed (code= error type argument= line#) log

cam driver initialization failed (code= error type argument= line#)

The CAM driver initialization critically failed, as the system resources were unavailable.

Source	Severity
CDT	Critical

Remedial action

Restart the system.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

cam driver initialized log

cam driver initialized

The system initialized the CAM driver.

Source	Severity
CDT	Information

Remedial action

No action required.



cam processing aborted (code= error type argument= line#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

cam processing aborted (code= error type argument= line#) log

cam processing aborted (code= error type argument= line#)

The system could not process the MAC address, due to repeated internal failures.

Source	Severity
CDT	Critical

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot configure without loopback port available log

Cannot configure without loopback port available

SPBM multicast cannot function without reserved loopback port for multi-pass processing

Source	Severity
SPB	Information

Remedial action

Configure spbm reserved-loopback-port before attempting to enable SPBM multicast.



Cannot create CVLAN on vlan: IGMP Snooping enabled and SPBM Mcast disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot create CVLAN on vlan: IGMP Snooping enabled and SPBM Mcast disabled log

Cannot create CVLAN on vlan: IGMP Snooping enabled and SPBM Mcast disabled

C-VLANs with IGMP snooping are supported only when SPBM multicast is enabled (router isis multicast setting)

Source	Severity
SPB	Information

Remedial action

Enable SPBM multicast OR disable IGMP snooping on VLAN before mapping VLAN to I-SID.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot disable IP Source Guard on Unit unit# Port port# log

Cannot disable IP Source Guard on Unit unit# Port port#

The IPSG cannot be disabled on the specified unit/port.

Source	Severity
ipsg	Information

Remedial action

Disable the MLT (if it enabled) and try again. If it fails, then reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot disable SPBM multicast - IGMP Snooping is enabled on C-VLANs log

Cannot disable SPBM multicast - IGMP Snooping is enabled on C-VLANs

C-VLANs with IGMP snooping are supported only when SPBM multicast is enabled (router isis multicast setting)

Source	Severity
SPB	Information

Remedial action

Disable IGMP snooping on all C-VLANs before disabling SPBM multicast.



Cannot enable SPBM multicast: feature unsupported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot enable SPBM multicast: feature unsupported log

Cannot enable SPBM multicast: feature unsupported

Source	Severity
SPB	Information

Remedial action

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot enable SPBM multicast while unknown-mcast-no-flood is enabled log

Cannot enable SPBM multicast while unknown-mcast-no-flood is enabled

SPBM and unknown-mcast-no-flood are mutually exclusive

Source	Severity
SPB	Information

Remedial action

Disable unknown-mcast-no-flood before enabling SPBM.



Cannot enable SPBM while PIM is enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cannot enable SPBM while PIM is enabled log

Cannot enable SPBM while PIM is enabled

SPBM and PIM are mutually exclusive

Source	Severity
SPB	Information

Remedial action

Disable PIM before enabling SPBM.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Capabilities determined by agent (not-writable) log

Capabilities determined by agent (not-writable)

The interface type capabilities cannot be modified.

Source	Severity
QoS	Information

Remedial action

Eliminate option.



CDT MAC address mac_address was removed because LAG trunk trunked has disaggregated.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CDT MAC address mac_address was removed because LAG trunk trunked has disaggregated. log

CDT MAC address mac_address was removed because LAG trunk trunked has disaggregated.

The static MAC address for a LAG trunk was deleted because the specific LAG trunk is disaggregated.

Source	Severity
CDT	Information

Remedial action

No action required.



CDT MAC address mac_address was removed because port port_no has aggregated in LAG

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CDT MAC address mac_address was removed because port port_no has aggregated in LAG log

CDT MAC address mac_address was removed because port port_no has aggregated in LAG

The static MAC address for a port is deleted, because the specific port is aggregated in a LAG

Source	Severity
CDT	Information

Remedial action

No action required.



CDT The static FDB entry MAC mac_address VLAN vlan Id trunk trunkId was deleted because LAG has disaggregated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CDT The static FDB entry MAC mac_address VLAN vlan Id trunk trunkId was deleted because LAG has disaggregated log

CDT The static FDB entry MAC mac_address VLAN vlan Id trunk trunkId was deleted because LAG has disaggregated

The static MAC address for a LAG trunk was deleted because the specific LAG trunk has disaggregated.

Source	Severity
CDT	Information

Remedial action

No action required.



CDT The static FDB entry MAC mac_address VLAN vlan id was deleted because Unit Port unit port has aggregated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CDT The static FDB entry MAC mac_address VLAN vlan id was deleted because Unit Port unit port has aggregated log

CDT The static FDB entry MAC mac_address VLAN vlan id was deleted because Unit Port unit port has aggregated

The static MAC address for a port was deleted as the specific port has aggregated in a LAG.

Source	Severity
CDT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFG - Could not acquire FLASH sem log

CFG - Could not acquire FLASH sem

An extreme concurrency faced when you copy or auto-synchronize the configuration.

Source	Severity
CFG	Information

Remedial action

Retry the last command.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFG - Could not create ram copy buffer. log

CFG - Could not create ram copy buffer.

Can be logged at system boot-up if no RAM memory can be allocated for the FLASH file system copy.

Source	Severity
CFG	Serious

Remedial action

Reboot the system.



CFG - NVRAM file system check: errors detected. Please reboot the system!

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFG - NVRAM file system check: errors detected. Please reboot the system! log

CFG - NVRAM file system check: errors detected. Please reboot the system!

Can be logged at runtime if checkdisk operation fails when the configuration is saved to flash. This can be triggered by corrupt files or incorrect file references used.

Source	Severity
CFG	Serious

Remedial action

Reboot the system.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFG - NVRAM file system check: errors detected. Restored to default. log

CFG - NVRAM file system check: errors detected. Restored to default.

Can be logged at system boot-up if FLASH config checkdisk operation fails, which will default the config.

Source	Severity
CFG	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Error: Failed to create watchdog timer log

CFGSO - Error: Failed to create watchdog timer

The system failed to create a watchdog timer.

Source	Severity
CFGSO	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Error: Failed to get an imc buffer log

CFGSO - Error: Failed to get an imc buffer

The system failed to get an IMC buffer.

Source	Severity
CFGSO	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Error: Failed to save data to NBU log

CFGSO - Error: Failed to save data to NBU

The system failed to save data to NBU.

Source	Severity
CFGSO	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Error: Failed to start watchdog timer log

CFGSO - Error: Failed to start watchdog timer

The system failed to start the watchdog timer.

Source	Severity
CFGSO	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Error: File not read log

CFGSO - Error: File not read

The system could not read the file.

Source	Severity
CFGSO	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Error: File not write log

CFGSO - Error: File not write

The system could not write the file.

Source	Severity
CFGSO	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Warning Invalid Msg Id log

CFGSO - Warning Invalid Msg Id

The system detected an invalid message Id.

Source	Severity
CFGSO	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFGSO - Warning Watchdog timer expire log

CFGSO - Warning Watchdog timer expire

The watchdog timer expired.

Source	Severity
CFGSO	Error

Remedial action

No action required.



CFM: ERROR adding port filters for VLAN %d - no resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CFM: ERROR adding port filters for VLAN %d - no resources log

CFM: ERROR adding port filters for VLAN %d - no resources

Error adding port filters.

Source	Severity
SPB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Change of active config block and or reset failed block-number log

Change of active config block and or reset failed block-number

Active configuration block was changed and the unit was restarted.

Source	Severity
--------	----------

Stack Manager	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier block component set ID out-of-range (clfr comp set ID) log

Classifier block component set ID out-of-range (clfr comp set ID)

Set ID must be between 1 and 55000.

Source	Severity
QoS	Serious

Remedial action

Enter a valid classifier block component setID.



Classifier block distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier block distribution across stack failed log

Classifier block distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Classifier block modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier block modifications not supported log

Classifier block modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier block number out-of-range (block#) log

Classifier block number out-of-range (block#)

Classifier block number must be between 1 and 55000.

Source	Severity
QoS	Serious

Remedial action

Enter a valid classifier block number.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier block precedence value not supported log

Classifier block precedence value not supported

Classifier block precedence range depends on the platform.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid classifier block precedence or ignore option.



Classifier component distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier component distribution across stack failed log

Classifier component distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Classifier component modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier component modifications not supported log

Classifier component modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Classifier component set ID out-of-range (clfsr comp set ID)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier component set ID out-of-range (clfsr comp set ID) log

Classifier component set ID out-of-range (clfsr comp set ID)

Set ID must be between 1 and 55000.

Source	Severity
QoS	Serious

Remedial action

Specify a valid set ID.



Classifier conflict (duplicate clfr data in block) detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier conflict (duplicate clfr data in block) detected log

Classifier conflict (duplicate clfr data in block) detected

A classifier with the same characteristics already exists in the specified block.

Source	Severity
QoS	Serious

Remedial action

Remove the existing classifier or use a different block.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier content incompatible with target interface(s) log

Classifier content incompatible with target interface(s)

The classifier element options not supported by the specified interface(s).

Source	Severity
QoS	Serious

Remedial action

Change the classifier content and try again or change the interface(s).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier set block reference out-of-range (clfr setblock#) log

Classifier set block reference out-of-range (clfr setblock#)

Classifier set/block id must be between 1 and 55000.

Source	Severity
QoS	Serious

Remedial action

Enter a valid classifier set/block id.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Classifier type unknown log

Classifier type unknown

The valid classifier types are individual and block.

Source	Severity
QoS	Serious

Remedial action

Specify a valid classifier type.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Clfr content (system) incompatible with target interface(s) log

Clfr content (system) incompatible with target interface(s)

The system classifier element options not supported by the specified interface(s).

Source	Severity
QoS	Serious

Remedial action

Change the system classifier content and try again or change the interface(s).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli add vlan vlan id members port mask log

Cli add vlan vlan id members port mask

Add new members indicated in port list to VLAN.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli create vlan vlan id type port log

Cli create vlan vlan id type port

A new VLAN type port is created.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli delete vlan vlan id members port mask log

Cli delete vlan vlan id members port mask

Remove members indicated in port list from VLAN.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli delete vlan vlan id type port log

Cli delete vlan vlan id type port

The existing VLAN type port is deleted.

Source	Severity
VLAN	Information

Remedial action

No action required.



CLI pswd: Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CLI pswd: Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch log

CLI pswd: Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch

Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch.

Source	Severity
Telnet	Information

Remedial action

No action required.



CLI pswd: Stack auth type
RADIUS/TACACS+ won't apply partially
(stack IP addr not set). Local user/pass
used

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially (stack IP addr not set). Local user/pass used log

CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially (stack IP addr not set). Local user/pass used

Stack IP address is not set

Source	Severity
Telnet	Information

Remedial action

No action required.



CLI pswd: Stack auth type
RADIUS/TACACS+ won't apply partially
(switch IP addr not set). Local
user/pass used

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially (switch IP addr not set). Local user/pass used log

CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially (switch IP addr not set). Local user/pass used

Switch IP address is not set

Source	Severity
Telnet	Information

Remedial action

No action required.



CLI pswd: Switch authentication parameter is obsolete; changes have not been applied

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CLI pswd: Switch authentication parameter is obsolete; changes have not been applied log

CLI pswd: Switch authentication parameter is obsolete; changes have not been applied

Switch authentication parameter is obsolete; changes have not been applied.

Source	Severity
Telnet	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set autopvid disable log

Cli set autopvid disable

Disable the auto PVID.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set autopvid enable log

Cli set autopvid enable

Enable auto PVID.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set management vlan vlan id log

Cli set management vlan vlan id

Set the management VLAN.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set ports port mask tagging disable log

Cli set ports port mask tagging disable

Port tagging is disabled.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set ports port mask tagging enable log

Cli set ports port mask tagging enable

Port tagging is enabled.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set pvid vlan id ports port mask log

Cli set pvid vlan id ports port mask

Port PVID is set.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cli set vlan vlan id members port mask log

Cli set vlan vlan id members port mask

VLAN ports are set.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cold Start Trap log

Cold Start Trap

Cold Start

Source	Severity
SNMP	Information

Remedial action

No action required.



Composite filter set addition failure comp filter set unknown

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set addition failure comp filter set unknown log

Composite filter set addition failure comp filter set unknown

One of the components in the specified composite filter set does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set addition failure data consistency issue log

Composite filter set addition failure data consistency issue

The system detected inconsistent data; Following are the possible reasons: Filter set duplication, Conflicting MAC data (the same filter set cannot be added with or without MAC data).

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check the parameters, and resolve if any possible invalid values.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set addition failure data invalid log

Composite filter set addition failure data invalid

The system detected invalid data; Following are the possible reasons: Source MAC address and mask length with different values, Seed name must be specified, and within the limited length, Clone name must be specified, and within the limited length (0-16).

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check the parameters and resolve if any possible invalid values.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set addition failure replication failure log

Composite filter set addition failure replication failure

The system failed to clone the composite filter member.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Composite filter set addition failure resources unavailable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set addition failure resources unavailable log

Composite filter set addition failure resources unavailable

Unable to add any more members to the specified filter set as the resources are unavailable.

Source	Severity
QoS	Serious

Remedial action

Check for and remove the resources that are not needed.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Composite filter set addition failure seed filter set unknown

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set addition failure seed filter set unknown log

Composite filter set addition failure seed filter set unknown

The seed filter for the specified composite filter set does not exist.

Source	Severity
QoS	Warning

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set creation failure data invalid log

Composite filter set creation failure data invalid

The system detected invalid data; Following are the possible reasons: Source MAC address and mask length with different values, Seed name must be specified; and within the limited length, Clone name must be specified, and within the limited length.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check the parameters, and resolve if any possible invalid values.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set creation failure MAC data not allowed log

Composite filter set creation failure MAC data not allowed

MAC data is not allowed in the base composite filter set.

Source	Severity
QoS	Serious

Remedial action

Remove the MAC data filter or classifier.



Composite filter set creation failure replication failure

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set creation failure replication failure log

Composite filter set creation failure replication failure

The system failed to clone the filter set.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Composite filter set creation failure seed filter set unknown

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set creation failure seed filter set unknown log

Composite filter set creation failure seed filter set unknown

The seed filter for the specified composite filter set does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set deletion failure base set target invalid log

Composite filter set deletion failure base set target invalid

The base composite filter set is on target. The base composite filter set can not be deleted without destroying the entire composite filter set.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Remove the filter set dependencies if any before deleting the base filter set.



Composite filter set deletion failure comp filter set unknown

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set deletion failure comp filter set unknown log

Composite filter set deletion failure comp filter set unknown

One of the components in the specified composite filter set does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Composite filter set deletion failure data invalid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set deletion failure data invalid log

Composite filter set deletion failure data invalid

The system detected invalid data; Following are the possible reasons: Source MAC address and mask length with different values, Seed name must be specified and within the limited length, Clone name must be specified and within the limited length (0-16).

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check the parameters and resolve, if any possible invalid values.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set deletion failure seed filter set unknown log

Composite filter set deletion failure seed filter set unknown

The seed filter for the specified composite filter set does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set destruction failure data invalid log

Composite filter set destruction failure data invalid

The system detected invalid data detected; Following is the possible reason: The Clone name must be specified and within the limited length (0-16).

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check the parameters and resolve, if any possible invalid values.



Composite filter set membership limits exceeded

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Composite filter set membership limits exceeded log

Composite filter set membership limits exceeded

The maximum number of composite members in a filter set is 16.

Source	Severity
QoS	Serious

Remedial action

Enter at the most 16 composite members in a filter set.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Configuration block %d is now in use log

Configuration block %d is now in use

Logs the configuration block currently used.

Source	Severity
MCFG	Information

Remedial action

No action required.



Configuration saved to nv block # block_number

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Configuration saved to nv block # block_number log

Configuration saved to nv block # block_number

This message appears when the configuration is saved to block n.

Source	Severity
config	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Conflicting action sources detected log

Conflicting action sources detected

Multiple actions specified from different sources (via policy match action, policy meter or classifier block) A combination of sources if prohibited.

Source	Severity
QoS	Serious

Remedial action

Remove conflicts by using a single action source.



Conflicting egress interface and egress trunk data specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Conflicting egress interface and egress trunk data specified log

Conflicting egress interface and egress trunk data specified

FCoE Redirect profile element data is not correct.

Source	Severity
--------	----------

FCoE Redirect	Information
---------------	-------------

Remedial action

Specify all required profile data.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Conflicting master block member information detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Conflicting master block member information detected log

Conflicting master block member information detected

Multiple master blocks detected.

Source	Severity
QoS	Serious

Remedial action

Enter a single master block.



Conflicting policy role policy interface index data detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Conflicting policy role policy interface index data detected log

Conflicting policy role policy interface index data detected

Both role and interface index were specified.

Source	Severity
QoS	Serious

Remedial action

Enter either a role or an interface index.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Connection closed (failed login) IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed (failed login) IP address log

Connection closed (failed login) IP address

The connection was disconnected after three login attempts failed.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

Enter a valid username and password.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed (inactivity logout) IP address log

Connection closed (inactivity logout) IP address

Client was disconnected by the server after 15 minutes of terminal inactivity.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.



Connection closed (login timeout) IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed (login timeout) IP address log

Connection closed (login timeout) IP address

The Telnet Login prompt message is available for the user input for one minute with maximum of three attempts. If you do not provide a valid username and password the connection will be disconnected.

Source	Severity
Telnet Server	Information

Remedial action

Enter the correct username and password within one minute.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed (lost connection) IP address log

Connection closed (lost connection) IP address

Client aborted the connection (RST message is sent).

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.



Connection closed. Maximum number of sessions reached. IP address:

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed. Maximum number of sessions reached. IP address: log

Connection closed. Maximum number of sessions reached. IP address:

The maximum number of active telnet connections has been reached.

Source	Severity
Telnet server	Information

Remedial action

Close other active sessions in order to free Telnet server slots.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Connection closed. Maximum number of sessions reached. IP address:

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed. Maximum number of sessions reached. IP address: log

Connection closed. Maximum number of sessions reached. IP address:

Telnet server has reached its maximum connections. No new connections currently allowed for the IP Address displayed in the log message.

Source	Severity
Telnet Server	Information

Remedial action

Disconnect at least one telnet connection.



Connection closed (user logout) IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Connection closed (user logout) IP address log

Connection closed (user logout) IP address

User ends telnet session. The connection is lost.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons activate vlan vlan id log

Cons activate vlan vlan id

VLAN is activated.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons add vlan vlan id port unit port log

Cons add vlan vlan id port unit port

Port is added to VLAN.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons create vlan vlan id type port log

Cons create vlan vlan id type port

New VLAN type port is created.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons delete vlan vlan id port unit port log

Cons delete vlan vlan id port unit port

Port is removed from VLAN.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons delete vlan vlan id type port log

Cons delete vlan vlan id type port

Existing VLAN type port is deleted.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons set autopvid disable log

Cons set autopvid disable

Disable auto PVID.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons set autopvid enable log

Cons set autopvid enable

Enable auto PVID.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons set management vlan vlan id log

Cons set management vlan vlan id

Management VLAN is set.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons set port unit port pvid vlan id log

Cons set port unit port pvid vlan id

Port PVID is set.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons set port unit port tagging disable log

Cons set port unit port tagging disable

Port tagging is disabled.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Cons set port unit port tagging enable log

Cons set port unit port tagging enable

Port tagging enabled.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

COS mapping distribution across stack failed log

COS mapping distribution across stack failed

Unable to commit COS mapping distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CoS shaping distribution across stack failed log

CoS shaping distribution across stack failed

Unable to make CoS shaping distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.



CoS shaping modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CoS shaping modifications not supported log

CoS shaping modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

CoS shaping not supported with specified interface log

CoS shaping not supported with specified interface

The specified interface is unable to support the CoS shaping.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface.



Count action distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Count action distribution across stack failed log

Count action distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Count action entry referenced by meter (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Count action entry referenced by meter (deletion prohibited) log

Count action entry referenced by meter (deletion prohibited)

Cannot delete a count action entry if it's referenced by a meter.

Source	Severity
QoS	Serious

Remedial action

Remove the meter first.



Count action entry referenced by policy (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Count action entry referenced by policy (deletion prohibited) log

Count action entry referenced by policy (deletion prohibited)

Cannot delete a count action if it's referenced by a policy.

Source	Severity
QoS	Serious

Remedial action

Remove the policy first.



Count action modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Count action modifications not supported log

Count action modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DAI: ARP packet with invalid IP/MAC binding dropped on untrusted port %d/%d. ARP packet has MAC source %02x-%02x-%02x-%02x-%02x-%02x.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAI: ARP packet with invalid IP/MAC binding dropped on untrusted port %d/%d. ARP packet has MAC source %02x-%02x-%02x-%02x-%02x-%02x. log

DAI: ARP packet with invalid IP/MAC binding dropped on untrusted port %d/%d. ARP packet has MAC source %02x-%02x-%02x-%02x-%02x-%02x.

ARP packet is ingressed on a DAI untrusted port with a MAC address and IP address that does not match any entries in the binding table. This causes the packet to be dropped.

Source	Severity
DAI	Information

Remedial action

Potential intruder. Isolate the offender.



DAI ARP packet with invalid IP MAC binding dropped on untrusted port unit# port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAI ARP packet with invalid IP MAC binding dropped on untrusted port unit# port# log

DAI ARP packet with invalid IP MAC binding dropped on untrusted port unit# port#

ARP packet ingress on a DAI untrusted port with a hardware MAC address and IP address does not match any entries in the DHCP binding table. This violates the DAI integrity check and the packet is dropped.

Source	Severity
DAI	Information

Remedial action

Isolate the offender.



DAPP-detected DoS attack blocked unit unit# (many ports)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAPP-detected DoS attack blocked unit unit# (many ports) log

DAPP-detected DoS attack blocked unit unit# (many ports)

A Denial of Service attack was blocked on the specified unit and on multiple ports.

Source	Severity
QoS	Information

Remedial action

No action required.



DAPP-detected DoS attack blocked unit unit# port port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAPP-detected DoS attack blocked unit unit# port port# log

DAPP-detected DoS attack blocked unit unit# port port#

A Denial of Service attack was blocked on the specified unit and port.

Source	Severity
QoS	Information

Remedial action

No action required.



DAPP resources not available (unit unit#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAPP resources not available (unit unit#) log

DAPP resources not available (unit unit#)

Some of the resources required are not available on all the interfaces.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded resources.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAPP support disable failure log

DAPP support disable failure

Unable to commit changes (disable DAAP) across the stack.

Source	Severity
QoS	Information

Remedial action

Try again later, reset the QoS agent, reset the unit or check stack health.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAPP support enable failure log

DAPP support enable failure

Unable to commit changes (enable DAAP) across the stack.

Source	Severity
QoS	Information

Remedial action

Try again later, reset the QoS agent, reset the unit or check stack health.



DAPP with statistics tracking in use (QoS disable prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAPP with statistics tracking in use (QoS disable prohibited) log

DAPP with statistics tracking in use (QoS disable prohibited)

Cannot disable the QoS system if DAAP with tracking statistics is enable.

Source	Severity
QoS	Serious

Remedial action

Disable DAAP or change it's enabled state before disabling QoS.



Data distribution class class# across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Data distribution class class# across stack failed log

Data distribution class class# across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Data model version attribute value not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Data model version attribute value not supported log

Data model version attribute value not supported

Data versions 1 and 2 are currently supported in the system.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Info Diag transfer finished log

DAUR - Info Diag transfer finished

Diag transfer finished.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Info Receive request for diag image start transfer log

DAUR - Info Receive request for diag image start transfer

The system received request for the diag image and started transferring.

Source	Severity
AUR	Information

Remedial action

No action required.



DAUR - Info Receive request for diag image. Unable to transfer

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Info Receive request for diag image. Unable to transfer log

DAUR - Info Receive request for diag image. Unable to transfer

Received request for diag image, unable to start transfer.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Info Send request for new diag image log

DAUR - Info Send request for new diag image

The system is sending request for new diag image.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Info Slave refuse transfer log

DAUR - Info Slave refuse transfer

Slave refuse transfer.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Info Start receive image log

DAUR - Info Start receive image

The image is being received.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - The hardware is not compatible with the image_version_number version log

DAUR - The hardware is not compatible with the image_version_number version

The hardware is not compatible.

Source	Severity
AUR	Information

Remedial action

No action required.



DAUR - Warning: Cannot get FLASH resource

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Warning: Cannot get FLASH resource log

DAUR - Warning: Cannot get FLASH resource

The system cannot get the flash resource.

Source	Severity
AUR	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Warning Diag image check sum ERROR log

DAUR - Warning Diag image check sum ERROR

Diag image check sum error.

Source	Severity
AUR	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DAUR - Warning Slave diag image check sum ERROR log

DAUR - Warning Slave diag image check sum ERROR

Slave diag image check sum error.

Source	Severity
AUR	Serious

Remedial action

No action required.



Default ifc assignment failure port# port(s) ifc QoS-disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Default ifc assignment failure port# port(s) ifc QoS-disabled log

Default ifc assignment failure port# port(s) ifc QoS-disabled

Unable to set the specified port to it's default state.

Source	Severity
QoS	Serious

Remedial action

Reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Destination MAC address and mask values out-of-sync

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Destination MAC address and mask values out-of-sync log

Destination MAC address and mask values out-of-sync

The destination MAC address and mask do not correspond (at least one address bit not included in mask is set).

Source	Severity
QoS	Serious

Remedial action

Modify the destination MAC address or mask.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DHCP packet with mismatch MAC address dropped on un-trusted port unit# port# mac(MAC ADDRESS)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP packet with mismatch MAC address dropped on un-trusted port unit# port# mac(MAC ADDRESS) log

DHCP packet with mismatch MAC address dropped on un-trusted port unit# port# mac(MAC ADDRESS)

DHCP packet with the ethernet source MAC address not matching with the DHCP client hardware MAC address ingressed on an DHCP Snoop untrusted port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Isolate the offender.



DHCP Snoop DHCP ACK dropped on untrusted port unit# port# (not allowed on untrusted port)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP ACK dropped on untrusted port unit# port# (not allowed on untrusted port) log

DHCP Snoop DHCP ACK dropped on untrusted port unit# port# (not allowed on untrusted port)

DHCP ACK reply packet ingressed on an untrusted DHCP Snoop port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Isolate the offender.



DHCP Snoop DHCP binding table is full
additional DHCP clients will not be
added to the binding table

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP binding table is full additional DHCP clients will not be added to the binding table log

DHCP Snoop DHCP binding table is full additional DHCP clients will not be added to the binding table

The maximum number of DHCP binding entries (1024) reached. Any additional DHCP client entries will not be added to the binding table.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Scale down the number of DHCP clients.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DHCP Snoop: DHCP DISCOVER dropped on port %d/%d (source MAC not matching client MAC)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP DISCOVER dropped on port %d/%d (source MAC not matching client MAC) log

DHCP Snoop: DHCP DISCOVER dropped on port %d/%d (source MAC not matching client MAC)

A DHCP Discover packet was received on port %d/%d but the source MAC Address displayed in the log message did not match the client MAC address.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Check the sending client. It may be an intrusion.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DHCP Snoop DHCP NAK dropped on untrusted port unit# port# (not allowed on untrusted port)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP NAK dropped on untrusted port unit# port# (not allowed on untrusted port) log

DHCP Snoop DHCP NAK dropped on untrusted port unit# port# (not allowed on untrusted port)

DHCP NAK reply packet ingressed on an DHCP Snoop untrusted port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Isolate the offender.



DHCP Snoop DHCP OFFER dropped on untrusted port unit# port# (not allowed on untrusted port)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP OFFER dropped on untrusted port unit# port# (not allowed on untrusted port) log

DHCP Snoop DHCP OFFER dropped on untrusted port unit# port# (not allowed on untrusted port)

DHCP OFFER reply packet ingressed on an DHCP Snoop untrusted port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Isolate the offender.



DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table log

DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table

DHCP packet ingress on the specified port is dropped as a static entry with the same MAC address as the DHCP client MAC address is found in the binding table. This violates the DHCP Snoop integrity check and the packet is dropped.

Source

Severity

DHCP Snoop

Information

Remedial action

No action required.



DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table log

DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table

Drop static entry.

Source	Severity
SNMP	Information

Remedial action

No action required.



DHCP Snoop DHCP RELEASE DECLINE
dropped on untrusted port unit# port#
because MAC Addr(MACaddress) is
associated to port unit# port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# because MAC Addr(MACaddress) is associated to port unit# port# log

DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# because MAC Addr(MACaddress) is associated to port unit# port#

DHCP RELEASE or DECLINE packet with the DHCP client hardware MAC address and client port from the binding table ingress on a different DHCP Snoop untrusted port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source

DHCP Snoop

Severity

Information

Remedial action

Isolate the offender.



DHCP Snoop DHCP RELEASE DECLINE
dropped on untrusted port unit# port#
(MAC Addr(MACaddress) does not exist
in binding table)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# (MAC Addr(MACaddress) does not exist in binding table) log

DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# (MAC Addr(MACaddress) does not exist in binding table)

DHCP RELEASE or DECLINE packet with the DHCP client hardware MAC address is not found in the binding table ingressed on a DHCP Snoop untrusted port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source

DHCP Snoop

Severity

Information

Remedial action

Isolate the offender.



DHCP Snoop DHCP REQUEST dropped on un-trusted port unit# port# due to source MAC address(MAC ADDRESS) not matching DHCP client

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP REQUEST dropped on un-trusted port unit# port# due to source MAC address(MAC ADDRESS) not matching DHCP client log

DHCP Snoop DHCP REQUEST dropped on un-trusted port unit# port# due to source MAC address(MAC ADDRESS) not matching DHCP client

DHCP packet with the ethernet source MAC address not matching with the DHCP client hardware MAC address ingressed on an DHCP Snoop untrusted port. This violates the DHCP Snoop integrity check and the packet is dropped.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Isolate the offender.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table restored successfully from TFTP address log

DHCP Snoop DHCP snooping binding table restored successfully from TFTP address

External-save/restore was unsuccessful.

Source	Severity
DHCP Snoop	Information

Remedial action

Check TFTP connection or the USB target for availability.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table restored successfully from USB unit unit# log

DHCP Snoop DHCP snooping binding table restored successfully from USB unit unit#

External-save/restore was unsuccessful on the mentioned target.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Check TFTP connection or the USB target for availability.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping binding table restore from SFTP address log

DHCP Snoop: DHCP snooping binding table restore from SFTP address

The message is logged with the SNMP Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure / * 1.3.6.1.4.1.45.5.17.0.21 * / This notification is generated when a DHCP snooping binding entry is not restored from an external file with SFTP.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.



DHCP Snoop DHCP snooping binding table restore from TFTP address A.B.C.D IPv6_address failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table restore from TFTP address A.B.C.D IPv6_address failed log

DHCP Snoop DHCP snooping binding table restore from TFTP address A.B.C.D IPv6_address failed

External-save/restore was unsuccessful on the mentioned target.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Check TFTP connection or the USB target for availability.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table restore from USB unit unit# failed log

DHCP Snoop DHCP snooping binding table restore from USB unit unit# failed

External-save/restore was unsuccessful.

Source	Severity
DHCP Snoop	Information

Remedial action

Check TFTP connection or the USB target for availability.



DHCP Snoop: DHCP snooping binding table saved successfully to SFTP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping binding table saved successfully to SFTP address log

DHCP Snoop: DHCP snooping binding table saved successfully to SFTP address

The message is logged with the SNMP Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess. /* 1.3.6.1.4.1.45.5.17.0.18 */ This notification is generated when a DHCP snooping binding entry is successfully saved to external file with SFTP.

Source

Severity

DHCP Snoop

Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table saved successfully to TFTP address log

DHCP Snoop DHCP snooping binding table saved successfully to TFTP address

External-save/restore was unsuccessful on the mentioned target.

Source	Severity
DHCP Snoop	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table saved successfully to USB unit unit# log

DHCP Snoop DHCP snooping binding table saved successfully to USB unit unit#

External-save/restore was unsuccessful on the mentioned target.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping binding table save to SFTP address log

DHCP Snoop: DHCP snooping binding table save to SFTP address

Error while saving the DHCP binding table to SFTP server.

Source	Severity
DHCP Snoop	Information

Remedial action

Check connection and configuration.



DHCP Snoop DHCP snooping binding
table save to TFTP address A.B.C.D
IPv6_address failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table save to TFTP address A.B.C.D IPv6_address failed log

DHCP Snoop DHCP snooping binding table save to TFTP address A.B.C.D IPv6_address failed

External-save/restore was unsuccessful on the mentioned target.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping binding table save to TFTP address, failed log

DHCP Snoop: DHCP snooping binding table save to TFTP address, failed

External-save/restore occurred successfully on the mentioned target.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping binding table save to USB unit unit# failed log

DHCP Snoop DHCP snooping binding table save to USB unit unit# failed

External-save/restore was unsuccessful on the mentioned target.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping binding table successfully restored from SFTP address log

DHCP Snoop: DHCP snooping binding table successfully restored from SFTP address

The message is logged with the SNMP Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess /* 1.3.6.1.4.1.45.5.17.0.20 */ This notification is generated when a DHCP snooping binding entry is restored successfully from an external file with SFTP.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping entry entry number not restored due to expired lease log

DHCP Snoop DHCP snooping entry entry number not restored due to expired lease

Binding entry could not be restored as the lease expired.

Source	Severity
DHCP Snoop	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping entry entry number not restored due to MAC conflict log

DHCP Snoop DHCP snooping entry entry number not restored due to MAC conflict

Binding entry could not be restored due to MAC conflict.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping entry entry number not restored due to parsing failure log

DHCP Snoop DHCP snooping entry entry number not restored due to parsing failure

Binding entry could not be restored due to various parsing failures.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Check and modify the external-save file for unexpected modifications in entry syntax.



DHCP Snoop DHCP snooping entry with MAC MacAddress not restored on invalid interface unit# port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop DHCP snooping entry with MAC MacAddress not restored on invalid interface unit# port# log

DHCP Snoop DHCP snooping entry with MAC MacAddress not restored on invalid interface unit# port#

Binding entry could not be restored due to an invalid interface (unit/ port combination read from external file is no longer available or invalid altogether).

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Check the unit/port combinations in the external-save file with your actual topology, and modify the external-save file if necessary.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored (invalid Vlan %d) log

DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored (invalid Vlan %d)

External-save entry could not be restored due to an invalid VLAN.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Compare external entry VLAN against currently configured VLANs and change configuration if necessary.



DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored on trusted interface %d/%d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored on trusted interface %d/%d log

DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored on trusted interface %d/%d

The message is logged with the SNMP trap bsDhcpSnoopingExtSaveEntryIfTrustedConflict. This notification is generated when a DHCP snooping binding entry fails to restore from an external file on a trusted interface.

Source

DHCP Snoop

Severity

Information

Remedial action

No action required.



DHCP Snoop: DHCP snooping entry
0x%08x not restored on trusted
interface %d/%d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop: DHCP snooping entry 0x%08x not restored on trusted interface %d/%d log

DHCP Snoop: DHCP snooping entry 0x%08x not restored on trusted interface %d/%d

Binding entry could not be restored because the interface of the externally saved entry is currently configured as DHCPSPN trusted

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Check configuration.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x not restored (invalid Vlan %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored (invalid Vlan %d) log

DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored (invalid Vlan %d)

The message is logged with the SNMP trap bsDhcpSnoopingExtSaveEntryInvalidVlan. /* b45.5.17.0.17 */ This notification is generated when a DHCP snooping binding entry is not restored from an external file on a invalid VLAN.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DHCP Snoop NTP is not synchronized; external save restore of DHCP snooping entries not possible log

DHCP Snoop NTP is not synchronized; external save restore of DHCP snooping entries not possible

The external actions (Restore or Save) not possible, as the Unit (S)NTP server is not synchronized.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

Make sure time source is properly set to (S)NTP and the server is synchronized.



Different classifier component masks keys in block detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Different classifier component masks keys in block detected log

Different classifier component masks keys in block detected

Examines classifier criteria to determine whether the specified data is supported in the context of the target interface(s).

Source	Severity
QoS	Serious

Remedial action

Use a compatible interface or change the conflicting filter criteria.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Different spanning-tree mode configured than BU. Unit reconfigured and rebooted.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Different spanning-tree mode configured than BU. Unit reconfigured and rebooted. log

Different spanning-tree mode configured than BU. Unit reconfigured and rebooted.

Current unit has different spanning-tree mode than the one used by BU. Unit will be reconfigured and rebooted.

Source	Severity
Stack Manager	Serious

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Different spanning-tree mode configured than BU. Unit re-configured and rebooted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Different spanning-tree mode configured than BU. Unit re-configured and rebooted log

Different spanning-tree mode configured than BU. Unit re-configured and rebooted

Spanning tree mode is different than BU's.

Source	Severity
Stack Manager	Serious

Remedial action

Wait for re-configuration and reboot cycle.



Disallowed connection Access Reject for user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Disallowed connection Access Reject for user log

Disallowed connection Access Reject for user

Radius - disallowed connection attempt for user starting with given name due to invalid user credentials.

Source	Severity
RADIUS	Information

Remedial action

Correct the user-configuration at the radius server when needed; also make sure the username and password entered are correct.



Disallowed connection Access Reject for user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Disallowed connection Access Reject for user log

Disallowed connection Access Reject for user

RADIUS - disallowed connection attempt for the user starting with the given name due to invalid user credentials.

Source	Severity
RADIUS Client	Information

Remedial action

Correct the user-configuration at the radius server; and retry entering valid user credentials.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Disallowed connection attempt from IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Disallowed connection attempt from IP address log

Disallowed connection attempt from IP address

Telnet-access is disabled or the client IP address does not pass the telnet-access/IP manager rules. Hence, the client connection is dropped.

Source	Severity
Telnet Server	Information

Remedial action

Check the telnet-access/IP manager configuration and modify the settings accordingly.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Disallowed connection attempt - too many telnet sessions

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Disallowed connection attempt - too many telnet sessions log

Disallowed connection attempt - too many telnet sessions

The attempt to telnet session connection is disallowed, as the maximum number of telnet sessions is reached.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.



Disallowed connection Invalid SvcType for user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Disallowed connection Invalid SvcType for user log

Disallowed connection Invalid SvcType for user

Radius - disallowed connection attempt for user starting with given name due to invalid service type.

Source	Severity
RADIUS	Information

Remedial action

Send correct svc-type from radius-server when needed.



Disallowed connection Invalid SvcType for user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Disallowed connection Invalid SvcType for user log

Disallowed connection Invalid SvcType for user

RADIUS - disallowed connection attempt for the user starting with the given name due to invalid service type

Source	Severity
RADIUS Client	Information

Remedial action

Send the correct svc-type from the radius server when needed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DISTRIBUTE_DB event sent unit mask value appl mask value log

DISTRIBUTE_DB event sent unit mask value appl mask value

The DISTRIBUTE_DB event is sent during the stack formation process.

Source	Severity
--------	----------

Stack Manager	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DosFs - Error File not closed log

DosFs - Error File not closed

The system detected an error in closing the file.

Source	Severity
	Information

Remedial action

Retry the operation.



Down 1 cable inserted or neighbor powered on

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Down 1 cable inserted or neighbor powered on log

Down 1 cable inserted or neighbor powered on

Cable inserted, link up.

Source	Severity
HMOD	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Down 2 cable inserted or neighbor powered on log

Down 2 cable inserted or neighbor powered on

Cable inserted, link up.

Source	Severity
HMOD	Information

Remedial action

No action required.



Down 1 cable removed or neighbor powered off

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Down 1 cable removed or neighbor powered off log

Down 1 cable removed or neighbor powered off

Link down: cable removed or neighbor powered off.

Source	Severity
HMOD	Serious

Remedial action

Do not remove cable, power off neighbor.



Down 2 cable removed or neighbor powered off

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Down 2 cable removed or neighbor powered off log

Down 2 cable removed or neighbor powered off

Link down: cable removed or neighbor powered off.

Source	Severity
HMOD	Serious

Remedial action

Do not remove cable, power off neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - DL_CKSUM_ACK_ERROR log

Download - DL_CKSUM_ACK_ERROR

This message appears when the image on NBU fails checksum validation.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or download another image.



Download - DL_PROGRAM_STATUS_ACK_ERROR

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - DL_PROGRAM_STATUS_ACK_ERROR log

Download - DL_PROGRAM_STATUS_ACK_ERROR

This message appears when all NBUs succeed in programming the image.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Download - DL_START_PROGRAM_FLASH_ACK_ERROR

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - DL_START_PROGRAM_FLASH_ACK_ERROR log

Download - DL_START_PROGRAM_FLASH_ACK_ERROR

This message appears when not all NBUs succeed in programming image.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Download - Error Failed to get the dl resource.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Error Failed to get the dl resource. log

Download - Error Failed to get the dl resource.

The system failed to access flash for the image download.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry or reboot the switch



Download - Error Watchdog expire No Ack from NBUs download MSG # message ID

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Error Watchdog expire No Ack from NBUs download MSG # message ID log

Download - Error Watchdog expire No Ack from NBUs download MSG # message ID

The watchdog timer expired waiting for acknowledgements from the NBUs during the image programming.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry or reboot the switch

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Failed to get buffer log

Download - Failed to get buffer

The system failed to obtain the data buffer for downloading the image.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Failed to malloc for buffer log

Download - Failed to malloc for buffer

The system does not have enough memory to download the image in to it.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Failed to start a watchdog log

Download - Failed to start a watchdog

The system failed to start the watchdog timer for image programming process.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Image Checksum Error log

Download - Image Checksum Error

This message appears when the Checksum in the image is not the same as the computed one.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or download another image.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - image type image image version programmed successfully log

Download - image type image image version programmed successfully

This is an informational message.

Source	Severity
--------	----------

Download Task	Serious
---------------	---------

Remedial action

No action required.



Download - Largest mem blk DL_SYSMEM_RESERVED

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - Largest mem blk DL_SYSMEM_RESERVED log

Download - Largest mem blk DL_SYSMEM_RESERVED

The system does not have enough memory to download the image into it.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - NBU Block Checksum Error log

Download - NBU Block Checksum Error

The image on NBU failed the Checksum validation.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or download another image.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - NBU DL_PROGRAM_STATUS ERROR log

Download - NBU DL_PROGRAM_STATUS ERROR

This message appears when not all NBUs succeed in programming the image.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry, download another image, or reboot the stack.



Download - TFTP timeout OR image file not found

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - TFTP timeout OR image file not found log

Download - TFTP timeout OR image file not found

The system detected an error: TFTP timeout

Source	Severity
Download Task	Critical

Remedial action

Retry or reboot the switch

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Download - tftpXfer failed log

Download - tftpXfer failed

The system detected an error in fetching the download resource.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Downstream stack direction is down cable removed or neighbor powered off log

Downstream stack direction is down cable removed or neighbor powered off

The Downstream stack direction is down, cable removed or neighbor powered off.

Source	Severity
--------	----------

Hello Module	Information
--------------	-------------

Remedial action

Connect the downstream port to the upstream port of the neighbor. Also check if the neighbor is powered on.



Downstream stack direction is mis-configured

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Downstream stack direction is mis-configured log

Downstream stack direction is mis-configured

This message appears when a downstream port is mis-configured.

Source	Severity
Hello Module	Information

Remedial action

Connect the downstream port to the upstream port of the neighbor.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Downstream stack direction is up cable inserted or neighbor powered on log

Downstream stack direction is up cable inserted or neighbor powered on

The Downstream stack direction is up, cable inserted and neighbor powered on. Physical link is up now.

Source	Severity
--------	----------

Hello Module	Information
--------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP mapping distribution across stack failed log

DSCP mapping distribution across stack failed

Unable to commit DSCP mapping distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.



DSCP mapping modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP mapping modifications not supported log

DSCP mapping modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (green action) log

DSCP remarking not supported for IPv6 (green action)

Match action (green) containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different match action or a different classifier.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (in-profile action) log

DSCP remarking not supported for IPv6 (in-profile action)

In-profile action containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different in-profile action or a different classifier.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (match action) log

DSCP remarking not supported for IPv6 (match action)

Match action containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different match action or a different classifier.



DSCP remarking not supported for IPv6 (non-match action)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (non-match action) log

DSCP remarking not supported for IPv6 (non-match action)

Non-match action containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different non-match action or a different classifier.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DSCP remarking not supported for IPv6 (out-of-profile action)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (out-of-profile action) log

DSCP remarking not supported for IPv6 (out-of-profile action)

Out-of-profile action containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different out-of-profile action or a different classifier.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



DSCP remarking not supported for IPv6 (red action)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (red action) log

DSCP remarking not supported for IPv6 (red action)

Match action (red) containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different match action or a different classifier.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP remarking not supported for IPv6 (yellow action) log

DSCP remarking not supported for IPv6 (yellow action)

Match action (yellow) containing DSCP remarking cannot be used on a filter with Ipv6 fields.

Source	Severity
QoS	Serious

Remedial action

Enter a different match action or a different classifier.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

DSCP value modification prohibited log

DSCP value modification prohibited

Since the qset/dscp-to-queue assignment association is created when the qset (queue set) is defined including the creation of an element per DSCP value, the DSCP may not be modified. Also, only IPv4/IPv6 packets can have the DSCP value updated.

Source	Severity
QoS	Information

Remedial action

Verify that the DSCP being specified is indeed the original DSCP or eliminate option if not an Ipv4/IPv6 packet.



Dst IP addr matching not supported with IP addr type data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Dst IP addr matching not supported with IP addr type data log

Dst IP addr matching not supported with IP addr type data

Filters with pattern matching (Dst IP) cannot be used with data of the IP address type .

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple filters.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Dst Layer 4 port min max values invalid (max must be = to min) log

Dst Layer 4 port min max values invalid (max must be = to min)

The maximum destination port must be bigger than the minimum destination port.

Source	Severity
QoS	Serious

Remedial action

Correct destination port range limits.



Dst MAC addr matching not supported with address type data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Dst MAC addr matching not supported with address type data log

Dst MAC addr matching not supported with address type data

Destination MAC address matching and the address type matching is prohibited in the same classifier element.

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple filters.



Duplicate access asgn name type index detected (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate access asgn name type index detected (prohibited) log

Duplicate access asgn name type index detected (prohibited)

Multiple entries with the same name, type, or index are prohibited.

Source	Severity
QoS	Serious

Remedial action

Enter a different name, type, index compared to the ones already installed in the system.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Duplicate address deletion failed ipv6_address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate address deletion failed ipv6_address log

Duplicate address deletion failed ipv6_address

The Duplicate Address Detection procedure found a duplicate for the IPv6_address on the link.

Source	Severity
IPV6	Information

Remedial action

Change the link-local ID for the IPV6 interface if the ipv6_address is in link-local scope. Remove and assign a different ipv6_address if the ipv6_address is in global scope.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Duplicate address detection succeeded ipv6_address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate address detection succeeded ipv6_address log

Duplicate address detection succeeded ipv6_address

The Duplicate Address Detection procedure is successfully completed for the ipv6_address, and no duplicate is found on the link.

Source	Severity
IPV6	Information

Remedial action

No action required.



Duplicate classifier class values in set detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate classifier class values in set detected log

Duplicate classifier class values in set detected

A classifier with the same class already exists in the specified set-id.

Source	Severity
QoS	Serious

Remedial action

Remove the existing classifier or use a different set-id.



Duplicate entry detected (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate entry detected (prohibited) log

Duplicate entry detected (prohibited)

The QoS entry already exists.

Source	Severity
QoS	Information

Remedial action

Use the existing entry if possible.



Duplicate FCoE redirection entry detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate FCoE redirection entry detected log

Duplicate FCoE redirection entry detected

Duplicate FCoE redirection entry detected.

Source	Severity
QOS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Duplicate set values in block detected log

Duplicate set values in block detected

The specified set value already exists in classifier block.

Source	Severity
QoS	Serious

Remedial action

Enter a different set value or remove the existing one.



Dynamic ARP could not be learned, maximum dynamic ARP limit is reached.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Dynamic ARP could not be learned, maximum dynamic ARP limit is reached. log

Dynamic ARP could not be learned, maximum dynamic ARP limit is reached.

The maximum number of allowed ARP entries has been reached

Source	Severity
L3Mgr	Information

Remedial action

If new ARPs need to be learned, try flushing the ARP table to remove any unused ARP entries in order to free up space.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Bad pkt id log

EAP Bad pkt id

EAP received a packet with another ID than expected.

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Bad pkt len log

EAP Bad pkt len

EAP received an EAPoL packet greater than 1500 bytes.

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP: Cannot assign PVID %d, on port %d it is in another STP group log

EAP: Cannot assign PVID %d, on port %d it is in another STP group

Cannot assign a PVID in another STP group

Source	Severity
EAP	Information

Remedial action

Ensure the PVID used in RADIUS is in the same STP group as the port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP: Cannot auto-create VLAN %d, it is mapped to another STP group log

EAP: Cannot auto-create VLAN %d, it is mapped to another STP group

The vlan cannot be created if it is a MSTI with another STP group

Source	Severity
EAP	Information

Remedial action

Ensure the RAVs used in RADIUS are in the same STP group as the port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP CDT Error log

EAP CDT Error

EAP will not correctly receive events about MACs from CDT.

Source	Severity
CDT	Information

Remedial action

No Action Required



EAP Client blocked (Block Subsequent MAC Authentication): Different VID than expected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked (Block Subsequent MAC Authentication): Different VID than expected log

EAP Client blocked (Block Subsequent MAC Authentication): Different VID than expected

An EAP client was blocked because it had a different Radius Assigned VLAN than the previous one.

Source	Severity
EAP	Information

Remedial action

Check the Attributes sent by RADIUS Server.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked (Block Subsequent MAC Authentication): Invalid VID log

EAP Client blocked (Block Subsequent MAC Authentication): Invalid VID

An EAP client was blocked because it had an invalid Radius Assigned VLAN.

Source	Severity
EAP	Information

Remedial action

Check the Attributes sent by RADIUS Server.



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
All bindings have been rejected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All bindings have been rejected log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All bindings have been rejected

All FA Bindings creation has failed in the FA feature

Source	Severity
EAP	Information

Remedial action

Check the switch topology and verify if it supports FA bindings creation.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
All RAVs or Bindings from RADIUS are
invalid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All RAVs or Bindings from RADIUS are invalid log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All RAVs or Bindings from RADIUS are invalid

All received RAVs or bindings are invalid

Source	Severity
EAP	Information

Remedial action

In the RADIUS user entry, correct the RAV/FA binding attributes.



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
Autocreate is enabled, but no RAV is
present

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Autocreate is enabled, but no RAV is present log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Autocreate is enabled, but no RAV is present

Cannot use Auto-Create-VLAN VSA without having a VLAN from radius to create on switch

Source	Severity
EAP	Information

Remedial action

Remove Auto-Create-VLAN attribute from RADIUS user configuration or add RAV attribute.



EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Cannot use FA bindings in Legacy or Autoprov networks

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Cannot use FA bindings in Legacy or Autoprov networks log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Cannot use FA bindings in Legacy or Autoprov networks

FA bindings(Vlan:Isid) are not supported in Legacy or Autoprov topologies

Source	Severity
EAP	Information

Remedial action

Re-configure the RADIUS user entry (Delete FA bindings, use only RAV).



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
EAP FA context unknown network

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. EAP FA context unknown network log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. EAP FA context unknown network

FA doesn't recognize the network topology it is in and can't transmit it to the EAP feature

Source	Severity
EAP	Information

Remedial action

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Only MHTSA mode supports multiple RAVs

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Only MHTSA mode supports multiple RAVs log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Only MHTSA mode supports multiple RAVs

Only the MHTSA mode has support for multiple RAVs/FA bindings

Source	Severity
EAP	Information

Remedial action

Remove excess RAVs/FA bindings from the RADIUS user entry.



EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Receiving unconfigured VLAN from Radius without Autocreate

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Receiving unconfigured VLAN from Radius without Autocreate log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Receiving unconfigured VLAN from Radius without Autocreate
A VLAN without the AutoCreate attribute is received from RADIUS which does not exist on switch

Source	Severity
EAP	Information

Remedial action

In the RADIUS user entry, add the autocreate attribute or create the vlan manually on switch.



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
Vlan:Isid bindings exceeded the
maximum threshold of 16

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid bindings exceeded the maximum threshold of 16 log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid bindings exceeded the maximum threshold of 16

The number of FA bindings exceeds the maximum limit

Source	Severity
EAP	Information

Remedial action

In the RADIUS user entry, reduce the number of FA bindings to be less equal than the maximum limit of 16.



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
Vlan:Isid not supported in MHMA and
SHSA

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid not supported in MHMA and SHSA log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid not supported in MHMA and SHSA

FA bindings (Vlan:Isid pairs) are not supported in SHSA/MHMA EAP modes

Source	Severity
EAP	Information

Remedial action

Remove FA bindings from the RADIUS user entry.



EAP Client blocked - MAC
%02x:%02x:%02x:%02x:%02x:%02x.
Vlan:Isid with Isid not equal to 0 not
supported in Standalone Proxy or
Autoprov

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid with Isid not equal to 0 not supported in Standalone Proxy or Autoprov log

EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid with Isid not equal to 0 not supported in Standalone Proxy or Autoprov

FA bindings (Vlan:Isid) with Isid not equal to 0 are not supported in Standalone Proxy or Autoprov Topologies

Source	Severity
EAP	Information

Remedial action

For all FA bindings in the RADIUS user entry, replace all ISID values with 0.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Could not process pkt log

EAP Could not process pkt

EAP received a packet with length smaller than the header size or greater than the maximum limit.

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Error - Default log

EAP Error - Default

Wrong EAP parameter.

Source	Severity
EAP	Information

Remedial action

No Action Required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Error - Failed to free mac info memory log

EAP Error - Failed to free mac info memory

A NEAP client could not be deleted from the list.

Source	Severity
EAP	Information

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Error Radius - ifIndex not found log

EAP Error Radius - ifIndex not found

Radius received a wrong port number for which to send a response

Source	Severity
Radius	Information

Remedial action

No action required.



EAP Error: Reached maximum number of messages in the queue

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Error: Reached maximum number of messages in the queue log

EAP Error: Reached maximum number of messages in the queue

EAP received too many messages from other applications.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



EAP Error while sending Access Violation Trap

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Error while sending Access Violation Trap log

EAP Error while sending Access Violation Trap

EAP cannot send an Access Violation Trap

Source	Severity
EAP	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Error while sending RAV Error Trap log

EAP Error while sending RAV Error Trap

EAP cannot send a Radius Assigned VLAN Error Trap.

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Failed initialize global arrays log

EAP Failed initialize global arrays

EAP could not initialize data about global or ports admin state

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Failed qpa-RoleAssociation unitPort ifIndex macHi xx-xx macLo xx-xx-xx-xx log

EAP Failed qpa-RoleAssociation unitPort ifIndex macHi xx-xx macLo xx-xx-xx-xx

The EAP User Based Policy Role Association failed at the given unit port (ifIndex) for given MAC address

Source	Severity
EAP-Filter Manager	Information

Remedial action

Show QoS agent; make sure the UBP is enabled; or enable as needed; Show QoS diag and check if filters are available.



EAP Failed qpa-RoleAssociation unitPort 0x%x mac %08x%04x

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Failed qpa-RoleAssociation unitPort 0x%x mac %08x%04x log

EAP Failed qpa-RoleAssociation unitPort 0x%x mac %08x%04x

A UBP filter could not be installed because of a QoS specific error.

Source	Severity
QoS	Information

Remedial action

Check QoS resources on port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Failed to add host, max number of clients reached log

EAP Failed to add host, max number of clients reached

EAP already reached the maximum number of clients limit on a port.

Source	Severity
EAP	Information

Remedial action

Increase the number of eap-mac-max clients.



EAP Failed to add host, memory allocation error

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Failed to add host, memory allocation error log

EAP Failed to add host, memory allocation error

EAP could not allocate memory for a new EAP client.

Source	Severity
EAP	Information

Remedial action

Reboot the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Failed to create dyna global arrays log

EAP Failed to create dyna global arrays

EAP could not initialize some of the data regarding global or port-specific info detailed in the "Could not create global arrays" log.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP GVlan Disabled for unitPort ifIndex - GVlan(vid) in different stg(id) log

EAP GVlan Disabled for unitPort ifIndex - GVlan(vid) in different stg(id)

The EAP failed to apply Guest VLAN since new Guest VLAN ID is in a different spanning tree group than the current port VLAN; GVLAN disabled for that port.

Source	Severity
EAP-VLAN (QDT)	Information

Remedial action

Show VLAN; show interfaces; show spanning-tree commands ; reconfigure VLANs in spanning tree groups as needed, and re-enable EAP on the port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP IMC Failed to send message log

EAP IMC Failed to send message

EAP could not send an Inter Module Communication message.

Source	Severity
IMC	Information

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP IMC Memory allocation error log

EAP IMC Memory allocation error

EAP could not allocate memory for an Inter Module Communication message

Source	Severity
IMC	Information

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Invalid RAV ID log

EAP Invalid RAV ID

The EAP failed to apply Radius Assigned VLAN since it is not an active VLAN at the switch.

Source	Severity
EAP-VLAN (QDT)	Information

Remedial action

show VLAN VID; show interfaces; show spanning tree commands; And make sure the VLAN is active.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Invalid Vlan ID vid configured for port num log

EAP Invalid Vlan ID vid configured for port num

The EAP VLAN ID received is not active for that port.

Source	Severity
EAP	Information

Remedial action

Show VLAN VID; show interfaces; show spanning-tree commands ; make sure that the VLAN is active; then re-authenticate at the port.



EAP Mac AuthFail - unitPort <unit-portnum> macHi <xx-xx> macLo <xx-xx-xx-xx>

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Mac AuthFail - unitPort <unit-portnum> macHi <xx-xx> macLo <xx-xx-xx-xx> log

EAP Mac AuthFail - unitPort <unit-portnum> macHi <xx-xx> macLo <xx-xx-xx-xx>

EAP Debug only - Eng Menu - EAP removed MAC on given port for given mac address on aborting PAE state machine - Not Used

Source	Severity
EAP	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Memory allocation error log

EAP Memory allocation error

EAP could not allocate memory to receive or send a packet.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Message queue error log

EAP Message queue error

EAP could not initialize the EAP message queue.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.



EAP Neap port was not member of any vlan

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Neap port was not member of any vlan log

EAP Neap port was not member of any vlan

A Non-EAP port was added to either GuestVLAN or VLAN 1, because it was not a member of any VLAN.

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP NULL pkt to send on Success log

EAP NULL pkt to send on Success

An error appeared when creating the message to be sent for supplicant

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP NVRAM open error log

EAP NVRAM open error

EAP could not open the NVRAM file to write settings.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP NVRAM read port admin state error log

EAP NVRAM read port admin state error

EAP could not read the port EAP admin setting from NVRAM

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP NVRAM read system admin state error log

EAP NVRAM read system admin state error

EAP could not read the global EAP setting from NVRAM

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP NVRAM read system ubp state error log

EAP NVRAM read system ubp state error

EAP could not read the global UBP setting from NVRAM

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP NVRAM write error log

EAP NVRAM write error

EAP could not write settings in the NVRAM file.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Reached Mac Intruder Count log

EAP Reached Mac Intruder Count

EAP reached the maximum number of intruders on a port.

Source	Severity
EAP	Information

Remedial action

Check the number of intruders per port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP: Reached Mac Intruder Count log

EAP: Reached Mac Intruder Count

The number of MAC addresses has reached the limit set on port. New MACs will be ignored

Source	Severity
EAP	Information

Remedial action

Admin should detect the cause of the big number of intruders for that particular port and after that manually enable EAP again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP: Receiving unsupported Auto-Create-VLAN VSA in SHSA or MHMA log

EAP: Receiving unsupported Auto-Create-VLAN VSA in SHSA or MHMA

Auto-Create-VLAN VSA is not supported in SHSA/MHMA EAP modes

Source	Severity
EAP	Information

Remedial action

Remove Auto-Create-VLAN attribute from RADIUS user configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Task spawn error log

EAP Task spawn error

The EAP application task could not be started.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Unable to Reserve EapAdmin Filter Resources rc retCode unitPort ifIndex log

EAP Unable to Reserve EapAdmin Filter Resources rc retCode unitPort ifIndex

The EAP Filter Reservation Failed (5520 and 5530) with the given filter manager return code for the given unit port (ifIndex) upon admin change from authorised to unauthorised or auto

Source	Severity
EAP-Filter Manager	Information

Remedial action

Show QoS diag and check if filters are available; adjust the resource usage if required.



EAP Unable to Reserve Filter Resources rc retCode unitPort ifIndex Force- Unauthorised

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Unable to Reserve Filter Resources rc retCode unitPort ifIndex Force- Unauthorised log

EAP Unable to Reserve Filter Resources rc retCode unitPort ifIndex Force- Unauthorised

The EAP Filter Reservation Failure (5520 and 5530) with given filter manager return code for given unit-port (ifIndex); port is now set to force unauthorised and is blocking.

Source

Severity

EAP-Filter Manager

Information

Remedial action

Show QoS diag and check if filters are available; adjust the resource usage if required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Unable to UnReserve EapAdmin Filter Resources rc retCode unitPort ifIndex log

EAP Unable to UnReserve EapAdmin Filter Resources rc retCode unitPort ifIndex

The EAP Filter Release Failure with the given filter manager return code for given unit port (ifIndex) upon admin change to force authorised.

Source	Severity
--------	----------

EAP-Filter Manager	Information
--------------------	-------------

Remedial action

Show QoS diag and check if filters are available; try filter allocations again and disable or enable EAP.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Unable to UnReserve Filter Resources rc retCode unitPort unit-portnum log

EAP Unable to UnReserve Filter Resources rc retCode unitPort unit-portnum

The EAP is unable to release filters with given filter manager return code for given unit port (ifIndex).

Source	Severity
--------	----------

EAP-Filter Manager	Information
--------------------	-------------

Remedial action

Show QoS diag and check if filters are available; adjust the resource usage if required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

EAP Vlan Change Aborted log

EAP Vlan Change Aborted

EAP could not add a port to a VLAN that is in a different STG than the STG where the port is.

Source	Severity
STP	Information

Remedial action

Change the STG of the VLAN.



ECMP features disabled due to inadequate license

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

ECMP features disabled due to inadequate license log

ECMP features disabled due to inadequate license

This message appears if the ECMP is enabled and the license is not available.

Source	Severity
L3Mgr	Information

Remedial action

Acquire License for ECMP to enable this feature.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Egp Neighbor Loss Trap log

Egp Neighbor Loss Trap

Egp Neighbor Loss.

Source	Severity
SNMP	Information

Remedial action

No action required.



Egress interface and egress mask are mutually exclusive

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Egress interface and egress mask are mutually exclusive log

Egress interface and egress mask are mutually exclusive

Invalid egress mask.

Source	Severity
QoS	Serious

Remedial action

Enter both options (egress unicast and egress non-unicast) with the same port.



Egress interface or trunk data is required - data missing

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Egress interface or trunk data is required - data missing log

Egress interface or trunk data is required - data missing

FCoE Redirect profile element data is not complete.

Source	Severity
--------	----------

FCoE Redirect	Information
---------------	-------------

Remedial action

Specify all required profile data.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element deletion prohibited (permanent read-only system entry) log

Element deletion prohibited (permanent read-only system entry)

" System-owned policies cannot be deleted via the normal commands. Some of them may be removed through certain "disable" commands. "

Source	Severity
QoS	Information

Remedial action

Check the documentation if necessary and use the appropriate disable command(s) where possible.



Element enable prohibited. Please delete and re-enter data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element enable prohibited. Please delete and re-enter data log

Element enable prohibited. Please delete and re-enter data

Request rejected as no underlying policies are configured.

Source	Severity
QoS	Serious

Remedial action

Delete and re-enter valid data.



Element label contains unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element label contains unacceptable characters log

Element label contains unacceptable characters

Only printable characters are allowed

Source	Severity
QoS	Serious

Remedial action

Enter valid characters for the access element's label.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element label length outside of acceptable limits (max 16 chars) log

Element label length outside of acceptable limits (max 16 chars)

The maximum length for QoS labels is 16 characters.

Source	Severity
QoS	Serious

Remedial action

Enter a smaller label in order for it to be accepted by the system.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element label not acceptable - reserved log

Element label not acceptable - reserved

The label is reserved in the system.

Source	Severity
QoS	Information

Remedial action

Enter a different label.



Element may only be modified not created or deleted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element may only be modified not created or deleted log

Element may only be modified not created or deleted

The specified element can only be modified. Possible entries: COS-to-DSCP assignment default values created at initialization; default DSCP-to-queue assignments and default CoS-to-queue assignments created when a new queue set is defined.

Source	Severity
QoS	Information

Remedial action

Modify the existing entry if necessary.



Element modification prohibited (read-only or system entry)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Element modification prohibited (read-only or system entry) log

Element modification prohibited (read-only or system entry)

You cannot modify or remove a read-only or system entry.

Source	Severity
QoS	Information

Remedial action

Create a similar entry with the proper modifications if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Enterprise Specific Trap log

Enterprise Specific Trap

Enterprise Specific Trap.

Source	Severity
SNMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error accessing Image File log

Error accessing Image File

The system could not find the image file.

Source	Severity
Console	Serious

Remedial action

Enter a valid image file name

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error Bad Image Checksum log

Error Bad Image Checksum

The system indicated a Bad Image Checksum.

Source	Severity
Console	Serious

Remedial action

Enter a different image.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error configuring 802.1AB log

Error configuring 802.1AB

Cannot configure LLDP med-network-policies or dot1q-framing tagging

Source	Severity
Run scripts: IP Office, LLDP	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error configuring LLDP MED policies log

Error configuring LLDP MED policies

Cannot configure LLDP med-network-policies parameters.

Source	Severity
Run scripts: LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error configuring Management IP Address log

Error configuring Management IP Address

IP address conflict

Source	Severity
Run scripts: LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error configuring port names log

Error configuring port names

Cannot set port names.

Source	Severity
Run scripts: IP Office	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error creating Data VLAN log

Error creating Data VLAN

Cannot create new Data VLAN.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error creating MLT log

Error creating MLT

Cannot create new trunk for uplink ports.

Source	Severity
Run scripts: ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error creating Voice VLAN log

Error creating Voice VLAN

Cannot create new Voice VLAN. (Maximum number of Voice Vlan reached)

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error deleting previously created cost 1 default route log

Error deleting previously created cost 1 default route

Error delting default ip route.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error deleting previously created Voice and Data VLANs log

Error deleting previously created Voice and Data VLANs

Error deleting existing VLAN.

Source	Severity
--------	----------

Run scripts: IP Office, LLDP, ADAC	Information
------------------------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error disabling global DHCP relay errCode log

Error disabling global DHCP relay errCode

The DHCP relay cannot be globally disabled as the appropriate filter could not be uninstalled (other DHCP application is using it).

Source	Severity
DHCPR	Information

Remedial action

Redo the QoS filter allocations, and retry to disable the DHCPR.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error enabling ADAC log

Error enabling ADAC

Cannot enable ADAC.

Source	Severity
Run scripts: ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error enabling ADAC on ports log

Error enabling ADAC on ports

Cannot configure telephony ports.

Source	Severity
--------	----------

Run scripts: ADAC	Information
-------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error enabling global DHCP relay errCode log

Error enabling global DHCP relay errCode

The DHCP relay cannot be enabled globally as the appropriate filter cannot be installed (other DHCP application has already installed it).

Source	Severity
DHCPR	Information

Remedial action

Redo the QoS filter allocations, and retry to enable the DHCPR.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error enabling IP Routing log

Error enabling IP Routing

Cannot enable IP routing.

Source	Severity
Run scripts: LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error enabling mstp learning on all ports log

Error enabling mstp learning on all ports

Cannot configure MSTP on ports.

Source	Severity
Run scripts: IP Office	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error enabling rstp learning on all ports log

Error enabling rstp learning on all ports

Cannot configure RSTP on ports.

Source	Severity
Run scripts: IP Office	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error executing script log

Error executing script

Cannot continue with the script execution.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error getting VLAN info for Port's pvid log

Error getting VLAN info for Port's pvid

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error in XGS3 memory DMA transfer log

Error in XGS3 memory DMA transfer

Logs an error for XGS3 switches in case of DMA error.

Source	Severity
CDT	Serious

Remedial action

Reboot device

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error loading backup configuration block # block_number log

Error loading backup configuration block # block_number

The system failed to load the backup configuration.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error loading configuration block %d log

Error loading configuration block %d

The system failed to load configuration from block n.

Source	Severity
config	Information

Remedial action

No action required.



Error loading primary configuration block # block_number

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error loading primary configuration block # block_number log

Error loading primary configuration block # block_number

The system failed to load the primary configuration.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error reading Image File log

Error reading Image File

The system could not read the image file.

Source	Severity
Console	Serious

Remedial action

Enter a valid image.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error reading nvq_ObjDescr from VLAN file log

Error reading nvq_ObjDescr from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error reading prec from VLAN file log

Error reading prec from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error reading vmrec from VLAN file log

Error reading vmrec from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error reading vrec from VLAN file log

Error reading vrec from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring from VLAN file log

Error restoring from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.



Error restoring from VLAN file. Wrong nvq.Descr.devVer

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring from VLAN file. Wrong nvq.Descr.devVer log

Error restoring from VLAN file. Wrong nvq.Descr.devVer

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.



Error restoring from VLAN file. Wrong nvq.Descr.notBlank

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring from VLAN file. Wrong nvq.Descr.notBlank log

Error restoring from VLAN file. Wrong nvq.Descr.notBlank

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring management vlan to 1 or disabling ip routing log

Error restoring management vlan to 1 or disabling ip routing

Previously configured settings (by user or another execution of the script) must be deleted at the beginning of the script to allow other settings to be made. In this case, IP routing cannot be disabled or the management vlan restored to VID 1.

Source	Severity
--------	----------

Run scripts: IP Office, LLDP, ADAC	Information
------------------------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring nvq.Descr from VLAN file log

Error restoring nvq.Descr from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring object from VLAN file - bad file pointer or mode log

Error restoring object from VLAN file - bad file pointer or mode

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring object from VLAN NVRAM file log

Error restoring object from VLAN NVRAM file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring Port from VLAN NVRAM file log

Error restoring Port from VLAN NVRAM file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring Ports from VLAN file log

Error restoring Ports from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring VLANs from VLAN file log

Error restoring VLANs from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error restoring VMACs from VLAN file log

Error restoring VMACs from VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error saving configuration log

Error saving configuration

Cannot save current configuration.

Source	Severity
--------	----------

Run scripts: IP Office, LLDP, ADAC	Information
------------------------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error saving configuration to block # block_number log

Error saving configuration to block # block_number

The system failed to save the configuration to block n.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error seeking object in VLAN file log

Error seeking object in VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error seeking Ports in VLAN file log

Error seeking Ports in VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error seeking VLANs in VLAN file log

Error seeking VLANs in VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error seeking VMACs in VLAN file log

Error seeking VMACs in VLAN file

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting ADAC operating mode log

Error setting ADAC operating mode

Cannot set ADAC tagged frames operating mode.

Source	Severity
--------	----------

Run scripts: ADAC	Information
-------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting call server ports log

Error setting call server ports

Cannot configure ports as Call-Server ports..

Source	Severity
Run scripts: ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting Data VLAN Gateway IP address and network mask log

Error setting Data VLAN Gateway IP address and network mask

IP address conflict.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting default IP Route log

Error setting default IP Route

IP address conflict.

Source	Severity
--------	----------

Run scripts: IP Office, LLDP, ADAC	Information
------------------------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting IP Office Call-Server IP address log

Error setting IP Office Call-Server IP address

Cannot configure Call-Server IP Address.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting IP Office File-Server IP address log

Error setting IP Office File-Server IP address

Cannot configure File-Server IP Address.

Source	Severity
--------	----------

Run scripts: IP Office, LLDP, ADAC	Information
------------------------------------	-------------

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting Management VLAN log

Error setting Management VLAN

Cannot set Data V:AM as Management VLAN.

Source	Severity
Run scripts: LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting poe-priority high on ports log

Error setting poe-priority high on ports

Cannot configure poe priority

Source	Severity
Run scripts: IP Office	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting QoS log

Error setting QoS

Cannot add new QoS interface group of trusted.

Source	Severity
Run scripts: IP Office, LLDP	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting spanning-tree learning to fast on all ports log

Error setting spanning-tree learning to fast on all ports

Cannot configure STP on ports.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting uplink ports log

Error setting uplink ports

Cannot configure ports as Uplinks.

Source	Severity
Run scripts: LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting VLAN attributes log

Error setting VLAN attributes

Error setting port vlan membership and tagging or (only for Ip Office script) setting the Data VLAN as management VLAN.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting VLAN Gateway IP address and network mask log

Error setting VLAN Gateway IP address and network mask

IP address conflict.

Source	Severity
Run scripts: LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Error setting Voice VLAN Gateway IP address and network mask log

Error setting Voice VLAN Gateway IP address and network mask

IP address conflict.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.



Evaluation precedence conflict detected (UBP filter set data)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Evaluation precedence conflict detected (UBP filter set data) log

Evaluation precedence conflict detected (UBP filter set data)

Unable to make the required changes.

Source	Severity
QoS	Serious

Remedial action

Check the availability of resources on the specified port or use a different interface index.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Evaluation precedence conflict (Traffic Prof filter set data) log

Evaluation precedence conflict (Traffic Prof filter set data)

The system detected a Precedence conflict - multiple entries cannot occupy the same precedence on the same port.

Source	Severity
QoS	Serious

Remedial action

Check for the available precedence, and remove the resources that are not needed if any.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Evaluation precedence value required but not specified log

Evaluation precedence value required but not specified

A precedence must be assigned to the access classifier (similar to the policy), else it cannot be installed on the interface.

Source	Severity
QoS	Serious

Remedial action

Enter a specific or the next available precedence.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: agent settings reset incomplete log

Fabric Attach: agent settings reset incomplete

Previously established settings were not completely cleaned-up as expected.

Source	Severity
Fabric Attach	Major

Remedial action

Check VLAN and/or SPBM settings restored after a reset and delete settings that are no longer needed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: asgn activation failure (port tagging) log

Fabric Attach: asgn activation failure (port tagging)

An accepted binding could not be successfully activated due to a VLAN-interaction issue.

Source	Severity
--------	----------

Fabric Attach	Major
---------------	-------

Remedial action

Reset the device and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: asgn activation failure (VLAN creation) log

Fabric Attach: asgn activation failure (VLAN creation)

An accepted binding could not be successfully activated due to a VLAN-interaction issue.

Source	Severity
--------	----------

Fabric Attach	Major
---------------	-------

Remedial action

Reset the device and retry.



Fabric Attach: asgn activation failure (VLAN membership)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: asgn activation failure (VLAN membership) log

Fabric Attach: asgn activation failure (VLAN membership)

An accepted binding could not be successfully activated due to a VLAN-interaction issue.

Source	Severity
--------	----------

Fabric Attach	Major
---------------	-------

Remedial action

Reset the device and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: auto provision setting not supported by platform log

Fabric Attach: auto provision setting not supported by platform

Request to change FA Auto Provision setting failed.

Source	Severity
Fabric Attach	Minor

Remedial action

Supported Auto Provision settings differ based on platform capabilities (e.g., FA Server, FA Proxy/Server, FA Proxy). An appropriate AP setting should be specified for the platform.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding acceptance failure (ifc <IFINDEX> <ISID>/<VID>) log

Fabric Attach: binding acceptance failure (ifc <IFINDEX> <ISID>/<VID>)

The I-SID/VLAN binding was rejected by the proxy (FA Client request) or the server because of data validity, resource or application interaction issues.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the request data is correct and can be supported by the target device. Confirm resource availability. Retry.



Fabric Attach: binding accepted (ifc <IFINDEX> <ISID>/<VID>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding accepted (ifc <IFINDEX> <ISID>/<VID>) log

Fabric Attach: binding accepted (ifc <IFINDEX> <ISID>/<VID>)

The FA Server has accepted a received I-SID/VLAN binding request.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding activation failure (<ISID>/<VID>) log

Fabric Attach: binding activation failure (<ISID>/<VID>)

The I-SID/VLAN binding was accepted but could not be activated by the proxy because of application interaction issues.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the request data is correct and can be supported by the target device. Confirm resource availability. Retry.



Fabric Attach: binding activation success (ifc <IFINDEX> <ISID>/<VID>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding activation success (ifc <IFINDEX> <ISID>/<VID>) log

Fabric Attach: binding activation success (ifc <IFINDEX> <ISID>/<VID>)

An I-SID/VLAN binding has been successfully activated on a FA Proxy.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: binding activation success (trunk %d %d/%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding activation success (trunk %d %d/%d) log

Fabric Attach: binding activation success (trunk %d %d/%d)

An I-SID/VLAN binding was activated and the related settings updates applied to the trunk

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding deactivation failure (ifc <IFINDEX> <ISID>/<VID>) log

Fabric Attach: binding deactivation failure (ifc <IFINDEX> <ISID>/<VID>)

An active proxy binding could not be successfully deactivated due to an application interaction issue.

Source	Severity
Fabric Attach	Major

Remedial action

Reset the device and retry.



Fabric Attach: binding deactivation failure (trunk %d %d/%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding deactivation failure (trunk %d %d/%d) log

Fabric Attach: binding deactivation failure (trunk %d %d/%d)

An I-SID/VLAN binding was deactivated but some of the related settings updates could not be completed for the trunk

Source	Severity
Fabric Attach	Serious

Remedial action

Check FA-related settings that are currently applied to the trunk to ensure that the configuration is consistent

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding deactivation success (ifc <IFINDEX> <ISID>/<VID>) log

Fabric Attach: binding deactivation success (ifc <IFINDEX> <ISID>/<VID>)

An I-SID/VLAN binding has been successfully deactivated on a FA Proxy.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: binding deactivation success (trunk %d %d/%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding deactivation success (trunk %d %d/%d) log

Fabric Attach: binding deactivation success (trunk %d %d/%d)

An I-SID/VLAN binding was deactivated and the related settings updates cleared for the trunk

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: binding expiration (ifc <IFINDEX> <ISID>/<VID>) log

Fabric Attach: binding expiration (ifc <IFINDEX> <ISID>/<VID>)

A FA Server binding or an external FA Client binding (FA Proxy) has expired.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: client binding deleted (<IFINDEX>/<ISID>/<VID>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: client binding deleted (<IFINDEX>/<ISID>/<VID>) log

Fabric Attach: client binding deleted (<IFINDEX>/<ISID>/<VID>)

A FA Client binding has been deleted (non-expiration deletion).

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: conflicting uplink data detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: conflicting uplink data detected log

Fabric Attach: conflicting uplink data detected

Both port-based and truck-based uplink data is present.

Source	Severity
Fabric Attach	Minor

Remedial action

Clear current uplink data and retry.



Fabric Attach: device deleted (port <PORT>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device deleted (port <PORT>) log

Fabric Attach: device deleted (port <PORT>)

A FA element has been deleted (port-related action). Standalone.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: device deleted (port <UNIT>/<PORT>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device deleted (port <UNIT>/<PORT>) log

Fabric Attach: device deleted (port <UNIT>/<PORT>)

A FA element has been deleted (port-related action). Stack.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device discovered (Authentication Fail - port <PORT>) log

Fabric Attach: device discovered (Authentication Fail - port <PORT>)

A Fabric Attach element was discovered (Authentication Fail). Standalone.

Source	Severity
Fabric Attach	Minor

Remedial action

If authentication pass expected, check configured key on devices.



Fabric Attach: device discovered (Authentication Fail - port <UNIT>/<PORT>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device discovered (Authentication Fail - port <UNIT>/<PORT>) log

Fabric Attach: device discovered (Authentication Fail - port <UNIT>/<PORT>)

A Fabric Attach element was discovered (Authentication Fail). Stack.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

If authentication pass expected, check configured key on devices.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device discovered (Authentication Pass - port <PORT>) log

Fabric Attach: device discovered (Authentication Pass - port <PORT>)

A Fabric Attach element was discovered (Authentication Pass). Standalone.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: device discovered (Authentication Pass - port <UNIT>/<PORT>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device discovered (Authentication Pass - port <UNIT>/<PORT>) log

Fabric Attach: device discovered (Authentication Pass - port <UNIT>/<PORT>)

A Fabric Attach element was discovered (Authentication Pass). Stack.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device discovered (Not Authenticated - port <PORT>) log

Fabric Attach: device discovered (Not Authenticated - port <PORT>)

A Fabric Attach element was discovered (Not Authenticated). Standalone.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device discovered (Not Authenticated - port <UNIT>/<PORT>) log

Fabric Attach: device discovered (Not Authenticated - port <UNIT>/<PORT>)

A Fabric Attach element was discovered (Not Authenticated). Stack.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device expired (port <PORT>) log

Fabric Attach: device expired (port <PORT>)

A Fabric Attach element was deleted (element expiration). Standalone.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: device expired (port <UNIT>/<PORT>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: device expired (port <UNIT>/<PORT>) log

Fabric Attach: device expired (port <UNIT>/<PORT>)

A Fabric Attach element was deleted (element expiration). Stack.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: element type updated log

Fabric Attach: element type updated

The Fabric Attach element type has been updated

Source	Severity
Fabric Attach	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: incompatible device advertisement (port <PORT>) log

Fabric Attach: incompatible device advertisement (port <PORT>)

A Fabric Attach element was discovered (Authentication Fail). Stack.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Verify trunk connectivity between FA devices.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: incompatible device advertisement (port <UNIT>/<PORT>) log

Fabric Attach: incompatible device advertisement (port <UNIT>/<PORT>)

Incompatible device characteristics advertised on different ports of the same trunk. Standalone.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Verify trunk connectivity between FA devices.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: interface-specific I-SID/VLAN assignments not allowed log

Fabric Attach: interface-specific I-SID/VLAN assignments not allowed

Attempt to create a port-specific I-SID/VLAN assignment on a FA Proxy was rejected.

Source	Severity
Fabric Attach	Minor

Remedial action

Specify non-port specific I-SID/VLAN assignments during creation on FA Proxy.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: invalid VLAN data (unknown or incompatible type) log

Fabric Attach: invalid VLAN data (unknown or incompatible type)

An unknown/incompatible VLAN was specified in a I-SID/VLAN assignment.

Source	Severity
Fabric Attach	Minor

Remedial action

Ensure appropriate VLAN data is specified in requests.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: I-SID/VLAN assignment creation failure (unexpected) log

Fabric Attach: I-SID/VLAN assignment creation failure (unexpected)

A valid I-SID/VLAN assignment creation request was rejected.

Source	Severity
Fabric Attach	Major

Remedial action

Reset the device and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: I-SID/VLAN assignment deletion failure (unexpected) log

Fabric Attach: I-SID/VLAN assignment deletion failure (unexpected)

A valid I-SID/VLAN assignment deletion request was rejected.

Source	Severity
Fabric Attach	Major

Remedial action

Reset the device and retry.



Fabric Attach: management VLAN updated (was <VID>, now <VID>) by Zero Touch

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: management VLAN updated (was <VID>, now <VID>) by Zero Touch log

Fabric Attach: management VLAN updated (was <VID>, now <VID>) by Zero Touch

Zero Touch functionality updated the management VLAN on a FA Proxy.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: message authentication support not available

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: message authentication support not available log

Fabric Attach: message authentication support not available

Request to enable message authentication failed.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Use a secure (SSH) image for the FA device or allow FA exchanges to proceed without being authenticated.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: multiple FA Servers detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: multiple FA Servers detected log

Fabric Attach: multiple FA Servers detected

Multiple devices advertising FA Server capabilities were found.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: non-MLT trunk uplink requires MLT ID/LACP key binding (missing)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: non-MLT trunk uplink requires MLT ID/LACP key binding (missing) log

Fabric Attach: non-MLT trunk uplink requires MLT ID/LACP key binding (missing)

A request to set the static uplink trunk was rejected because the trunk is LACP-based and a MLT ID/LACP key binding has not been configured

Source	Severity
--------	----------

Fabric Attach	Error
---------------	-------

Remedial action

Configure a MLT ID/LACP key bindings for the trunk and repeat request

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation failure detected log

Fabric Attach: operation failure detected

The requested operation was rejected in a non-specific manner.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the request data is correct and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation rejected - client-owned entry log

Fabric Attach: operation rejected - client-owned entry

An attempt was made to delete a client-specified I-SID/VLAN binding.

Source	Severity
Fabric Attach	Minor

Remedial action

Deletion of client-owned I-SID/VLAN bindings must be done through the client.



Fabric Attach: operation rejected - CVLAN already exists

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation rejected - CVLAN already exists log

Fabric Attach: operation rejected - CVLAN already exists

Attempt was made to create an I-SID/VLAN assignment with duplicate VLAN data.

Source	Severity
Fabric Attach	Minor

Remedial action

Specify unique data when creating I-SID/VLAN assignments.



Fabric Attach: operation rejected - entry does not exist

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation rejected - entry does not exist log

Fabric Attach: operation rejected - entry does not exist

An attempt was made to delete an unknown I-SID/VLAN assignment.

Source	Severity
Fabric Attach	Minor

Remedial action

Specify valid data when deleting I-SID/VLAN assignments.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation rejected - not supported by element type log

Fabric Attach: operation rejected - not supported by element type

An unsupported operation (based on the FA element type) was attempted.

Source	Severity
Fabric Attach	Minor

Remedial action

Only initiate operations that are supported by the FA element.



Fabric Attach: operation rejected - service not enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation rejected - service not enabled log

Fabric Attach: operation rejected - service not enabled

The requested operation was rejected because the FA service was disabled.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Enable the FA service and retry.



Fabric Attach: operation rejected - table entry limits reached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: operation rejected - table entry limits reached log

Fabric Attach: operation rejected - table entry limits reached

Table limits have been reached.

Source	Severity
Fabric Attach	Minor

Remedial action

Delete non-necessary data and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: port authentication update - data flushed (MLT %d) log

Fabric Attach: port authentication update - data flushed (MLT %d)

Due to an administrator request to update FA port authentication data, FA element data associated with the port has been flushed

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: port authentication update - data flushed (port %d) log

Fabric Attach: port authentication update - data flushed (port %d)

Due to an administrator request to update FA port authentication data, FA element data associated with the port has been flushed

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: port authentication update - data flushed (port %d/%d) log

Fabric Attach: port authentication update - data flushed (port %d/%d)

Due to an administrator request to update FA port authentication data, FA element data associated with the port has been flushed

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: primary FA Server lost log

Fabric Attach: primary FA Server lost

The connection to the primary server has timed-out. Data has been reset and a new primary server will be selected if one is available.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: primary FA server selected (port %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: primary FA server selected (port %d) log

Fabric Attach: primary FA server selected (port %d)

A primary FA Server was selected through the FA discovery process

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required



Fabric Attach: primary FA server selected (port %d/%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: primary FA server selected (port %d/%d) log

Fabric Attach: primary FA server selected (port %d/%d)

A primary FA Server was selected through the FA discovery process

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required



Fabric Attach: primary FA server selected (trunk %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: primary FA server selected (trunk %d) log

Fabric Attach: primary FA server selected (trunk %d)

A primary FA Server was selected through the FA discovery process

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required



Fabric Attach: proxy not supported by element type

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: proxy not supported by element type log

Fabric Attach: proxy not supported by element type

External client proxy settings can only be manipulated on a FA Proxy.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server asgn (<ISID>/<VID>) rejection log

Fabric Attach: server asgn (<ISID>/<VID>) rejection

The I-SID/VLAN binding request was rejected by the server in a non-specific manner.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the request data is correct and can be supported by the server. Retry.



Fabric Attach: server asgn (<ISID>/<VID>) rejection - application interactions

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server asgn (<ISID>/<VID>) rejection - application interactions log

Fabric Attach: server asgn (<ISID>/<VID>) rejection - application interactions

The I-SID/VLAN assignment request was rejected by the server because VLAN application and/or SPBM application issues were reported.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Verify that the request data is correct and can be supported by the server. Retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: server asgn (<ISID>/<VID>) rejection - invalid VLAN

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server asgn (<ISID>/<VID>) rejection - invalid VLAN log

Fabric Attach: server asgn (<ISID>/<VID>) rejection - invalid VLAN

The I-SID/VLAN assignment request was rejected by the server due to an issue with the specified VLAN (already defined but wrong type).

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Verify that the request data is correct and can be supported by the server. Retry.



Fabric Attach: server asgn (<ISID>/<VID>) rejection - no FA resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server asgn (<ISID>/<VID>) rejection - no FA resources log

Fabric Attach: server asgn (<ISID>/<VID>) rejection - no FA resources

The I-SID/VLAN assignment request was rejected by the server due to a lack of available FA resources.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the request data is correct and can be supported by the server. Retry.



Fabric Attach: server asgn (<ISID>/<VID>) rejection - no VLAN resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server asgn (<ISID>/<VID>) rejection - no VLAN resources log

Fabric Attach: server asgn (<ISID>/<VID>) rejection - no VLAN resources

The I-SID/VLAN assignment request was rejected by the server because a new VLAN could not be created.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the request data is correct and can be supported by the server. Retry.



Fabric Attach: server asgn (<ISID>/<VID>) rejection - peer acceptance

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server asgn (<ISID>/<VID>) rejection - peer acceptance log

Fabric Attach: server asgn (<ISID>/<VID>) rejection - peer acceptance

The I-SID/VLAN assignment request was rejected by the server because peer synchronization issues were encountered.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify FA configuration settings on SMLT peers and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server connection type change log

Fabric Attach: server connection type change

The connection to the primary FA Server has changed (e.g., single link to trunk transition or vice versa).

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.



Fabric Attach: server connection type change (different ports)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server connection type change (different ports) log

Fabric Attach: server connection type change (different ports)

FA Server-related data reset because a change to the type of FA Proxy/FA Server connection was detected

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: server connection type change (different trunks)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server connection type change (different trunks) log

Fabric Attach: server connection type change (different trunks)

FA Server-related data reset because a change to the type of FA Proxy/FA Server connection was detected

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: server connection type change (non-trunk to trunk)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server connection type change (non-trunk to trunk) log

Fabric Attach: server connection type change (non-trunk to trunk)

FA Server-related data reset because a change to the type of FA Proxy/FA Server connection was detected

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: server connection type change (trunk to non-trunk) log

Fabric Attach: server connection type change (trunk to non-trunk)

FA Server-related data reset because a change to the type of FA Proxy/FA Server connection was detected

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required



Fabric Attach: service disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: service disabled log

Fabric Attach: service disabled

The Fabric Attach service was disabled.

Source	Severity
Fabric Attach	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: service enabled log

Fabric Attach: service enabled

The Fabric Attach service was enabled.

Source	Severity
Fabric Attach	Information

Remedial action

No action required.



Fabric Attach: specified element type not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: specified element type not supported log

Fabric Attach: specified element type not supported

The specified Fabric Attach element type is not supported by the platform.

Source	Severity
Fabric Attach	Information

Remedial action

No action required.



Fabric Attach: specified uplink currently a trunk member

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: specified uplink currently a trunk member log

Fabric Attach: specified uplink currently a trunk member

A request to set the static uplink port was rejected because the port is already a member of a trunk

Source	Severity
Fabric Attach	Error

Remedial action

Select a static uplink port that is not a trunk member



Fabric Attach: specified uplink currently invalid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: specified uplink currently invalid log

Fabric Attach: specified uplink currently invalid

Uplink data does not identify a currently valid port or trunk.

Source	Severity
Fabric Attach	Minor

Remedial action

Ensure uplink data is currently valid and retry.



Fabric Attach: standalone/non-standalone proxy transition (service reset)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: standalone/non-standalone proxy transition (service reset) log

Fabric Attach: standalone/non-standalone proxy transition (service reset)

FA agent operation has transitioned between FA Proxy and FA Standalone Proxy due to an administrator update

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: static uplink addition failure log

Fabric Attach: static uplink addition failure

Request to set static uplink port/trunk value failed.

Source	Severity
Fabric Attach	Minor

Remedial action

Ensure uplink data is valid and that no uplink data is currently defined. Delete existing uplink data if present and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: static uplink deletion failure log

Fabric Attach: static uplink deletion failure

Request to clear static uplink data failed.

Source	Severity
Fabric Attach	Minor

Remedial action

Ensure uplink data is defined and retry.



Fabric Attach: temporary I-SID/VLAN binding deletion failure

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: temporary I-SID/VLAN binding deletion failure log

Fabric Attach: temporary I-SID/VLAN binding deletion failure

An active I-SID/VLAN binding can't currently be deleted due to associated interface-related components that are in transition.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Verify the system is stable and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: trunk link automatically enabled (MLT %d port %d/%d) log

Fabric Attach: trunk link automatically enabled (MLT %d port %d/%d)

A trunk link that was disabled during stack join because of VLAN inconsistencies was automatically enabled by FA after updating the VLAN data

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required



Fabric Attach: uplink operation only supported by FA Proxy

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: uplink operation only supported by FA Proxy log

Fabric Attach: uplink operation only supported by FA Proxy

Request to define static uplink data failed.

Source	Severity
--------	----------

Fabric Attach	Minor
---------------	-------

Remedial action

Uplink data can only be defined on a proxy. Verify FA device type and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: Zero Touch capabilities disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: Zero Touch capabilities disabled log

Fabric Attach: Zero Touch capabilities disabled

The Fabric Attach Zero Touch service was disabled.

Source	Severity
--------	----------

Fabric Attach	Information
---------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Fabric Attach: Zero Touch capabilities enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: Zero Touch capabilities enabled log

Fabric Attach: Zero Touch capabilities enabled

The Fabric Attach Zero Touch service was enabled.

Source

Severity

Fabric Attach

Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: zero touch operations not completed (mgmt VLAN <VID>) log

Fabric Attach: zero touch operations not completed (mgmt VLAN <VID>)

Zero Touch processing failed.

Source	Severity
Fabric Attach	Minor

Remedial action

Verify that the data provided by the FA Server does not cause any conflicts on the device. Resolve conflicts and retry.



Fabric Attach: Zero Touch option processing failure detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: Zero Touch option processing failure detected log

Fabric Attach: Zero Touch option processing failure detected

An unexpected issue was detected during Zero Touch option processing.

Source	Severity
--------	----------

Fabric Attach	Major
---------------	-------

Remedial action

Reset the device and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach: Zero Touch settings read-only for FA element type log

Fabric Attach: Zero Touch settings read-only for FA element type

Request to change FA Zero Touch option setting failed.

Source	Severity
Fabric Attach	Minor

Remedial action

Supported Zero Touch configuration capabilities differ based on platform (e.g., FA Server, FA Proxy/Server, FA Proxy). Zero Touch option/data modification is not supported on the platform.



Failed ARP add ip addr 0xFFFFFFFF to HW hw error code

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed ARP add ip addr 0xFFFFFFFF to HW hw error code log

Failed ARP add ip addr 0xFFFFFFFF to HW hw error code

The configuration of L3 ARP(1) into hardware failed.

Source	Severity
L3Mgr	Information

Remedial action

Try deleting the ARP from the software and check if the hardware configuration is successful after re-learning the ARP.



Failed login from IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed login from IP address log

Failed login from IP address

You have entered an incorrect username or password.

Source	Severity
Telnet Server	Information

Remedial action

Enter a valid username and password.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Failed login from serial connection

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed login from serial connection log

Failed login from serial connection

You have entered an incorrect username or password on the serial interface.

Source	Severity
Console	Information

Remedial action

Enter a valid username and password.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Failed login (local auth) from IP address:

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed login (local auth) from IP address: log

Failed login (local auth) from IP address:

Failed authentication with local credentials over telnet session.

Source	Severity
--------	----------

Telnet server	Information
---------------	-------------

Remedial action

Enter correct local username and password.



Failed login (local auth) from serial connection

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed login (local auth) from serial connection log

Failed login (local auth) from serial connection

Failed authentication with local credentials on serial port.

Source	Severity
Console	Information

Remedial action

Enter correct local username and password.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed login(radius auth) from IP add log

Failed login(radius auth) from IP add

You have failed to login as the Radius Server authentication is required for the telnet connections.

Source	Severity
Telnet Server	Information

Remedial action

Enter a valid username and password.



Failed login(radius auth) from serial conn

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed login(radius auth) from serial conn log

Failed login(radius auth) from serial conn

You failed to login as the Radius Server authentication is required for serial connections.

Source	Severity
Telnet Server	Console

Remedial action

Enter a valid username and password.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed MVLAN(vid) L3 ip addr ip mask log

Failed MVLAN(vid) L3 ip addr ip mask

The system failed to configure or restore the primary or secondary management VLAN from the NVRAM. It indicates parameter (IP address or Mask) with an incorrect or conflicting value if appeared during provisioning the message on screen.

Source	Severity
L3Mgr	Information

Remedial action

Re-configure with correct values if the message appears during provisioning the message on the screen. Re-configure the management VLAN IP/Mask if the message appears during ERS device startup.



Failed route add <ip addr/ip mask> to HW <hw error code>

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed route add <ip addr/ip mask> to HW <hw error code> log

Failed route add <ip addr/ip mask> to HW <hw error code>

The configuration of L3 interface(0) into hardware failed.

Source	Severity
L3Mgr	Warning

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed to Create a Watchdog log

Failed to Create a Watchdog

The system failed to create a watchdog.

Source	Severity
Console	Serious

Remedial action

Report the error.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed to create IP intf vid ip addr in HW hw error code log

Failed to create IP intf vid ip addr in HW hw error code

The interface and the L3 interface(0) configuration failed.

Source	Severity
L3Mgr	Information

Remedial action

Check by toggling routing on the VLAN to which the interface belongs, if it still fails then use global routing toggling.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Failed to Read Image from Memory log

Failed to Read Image from Memory

The system failed to read image from memory.

Source	Severity
Console	Serious

Remedial action

Retry the process again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE controller ifIndex not set - FCoE redirection enable prohibited log

FCoE controller ifIndex not set - FCoE redirection enable prohibited

Required FCoE controller data not defined.

Source	Severity
FCoE Redirect	Information

Remedial action

Specify FCoE controller data.



FCoE controller VLAN not set - FCoE redirection enable prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE controller VLAN not set - FCoE redirection enable prohibited log

FCoE controller VLAN not set - FCoE redirection enable prohibited

Required FCoE controller data not defined.

Source	Severity
FCoE Redirect	Information

Remedial action

Specify FCoE controller data.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



FCoE redirection default frame filter deletion failure detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE redirection default frame filter deletion failure detected log

FCoE redirection default frame filter deletion failure detected

Unable to delete installed FCoE Redirect policy data.

Source	Severity
--------	----------

FCoE Redirect	Serious
---------------	---------

Remedial action

Toggle feature enable and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com



FCoE redirection default frame filter installation failure detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE redirection default frame filter installation failure detected log

FCoE redirection default frame filter installation failure detected

Unable to install required FCoE Redirect policy data.

Source	Severity
--------	----------

FCoE Redirect	Serious
---------------	---------

Remedial action

Toggle feature enable and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



FCoE redirection - egress interface issue detected (ifIndex %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE redirection - egress interface issue detected (ifIndex %d) log

FCoE redirection - egress interface issue detected (ifIndex %d)

Issue detected with interface used with FCoE Redirect.

Source	Severity
--------	----------

FCoE Redirect	Serious
---------------	---------

Remedial action

Check status of identified interface.



FCoE redirection - egress trunk issue detected (trunk ID %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FCoE redirection - egress trunk issue detected (trunk ID %d) log

FCoE redirection - egress trunk issue detected (trunk ID %d)

Issue detected with trunk used with FCoE Redirect. The trunk ID is displayed in the log message.

Source	Severity
--------	----------

FCoE Redirect	Serious
---------------	---------

Remedial action

Check status of identified trunk.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter control block resources exhausted log

Filter control block resources exhausted

Not enough resources to create the specified filter control block.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded resources.



Filter creation issue detected - in-profile action component

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter creation issue detected - in-profile action component log

Filter creation issue detected - in-profile action component

Unable to create filter because of a conflicting in-profile action component.

Source	Severity
QoS	Serious

Remedial action

Identify and remove the conflicting component(s).



Filter creation issue detected - match action component

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter creation issue detected - match action component log

Filter creation issue detected - match action component

Unable to create filter because of a conflicting match action component.

Source	Severity
QoS	Serious

Remedial action

Identify and remove the conflicting component(s).



Filter creation issue detected - metering component

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter creation issue detected - metering component log

Filter creation issue detected - metering component

Unable to create filter because of a conflicting meter component.

Source	Severity
QoS	Serious

Remedial action

Identify and remove the conflicting component(s).



Filter creation issue detected - non-match action component

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter creation issue detected - non-match action component log

Filter creation issue detected - non-match action component

Unable to create filter because of a conflicting non-match action component.

Source	Severity
QoS	Serious

Remedial action

Identify and remove the conflicting component(s).



Filter creation issue detected - out-of-profile action component

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter creation issue detected - out-of-profile action component log

Filter creation issue detected - out-of-profile action component

Unable to create filter because of a conflicting out-of-profile action component.

Source	Severity
QoS	Serious

Remedial action

Identify and remove the conflicting component(s).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter limiting mode not supported on 5510-XX unit cannot join stack log

Filter limiting mode not supported on 5510-XX unit cannot join stack

Filter limiting mode is different than the base unit's mode. Some modes are not supported in the ERS 55XX..

Source	Severity
Stack Manager	Information

Remedial action

Modify the Filter Limiting mode on the base unit or remove the ERS 55XX.



Filter manager internal error encountered

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter manager internal error encountered log

Filter manager internal error encountered

Internal filter manager error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Filter manager memory resources exhausted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter manager memory resources exhausted log

Filter manager memory resources exhausted

Not enough resources or inconsistent memory.

Source	Severity
QoS	Serious

Remedial action

Check for and remove the unneeded resources.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter manager metering or policy rule space exhausted log

Filter manager metering or policy rule space exhausted

There is no more space available for rule allocation.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded resources.



Filter manager metering resources exhausted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter manager metering resources exhausted log

Filter manager metering resources exhausted

The filter manager meter support reached it's limit.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded meters.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter manager request parameter invalid log

Filter manager request parameter invalid

Invalid parameter detected during processing on the filter manager level.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Filter manager statistics tracking resources exhausted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter manager statistics tracking resources exhausted log

Filter manager statistics tracking resources exhausted

The statistics tracking/counter table is full.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded statistics related entries.



Filter set requirements incompatible with target interface

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Filter set requirements incompatible with target interface log

Filter set requirements incompatible with target interface

The requirements are not compatible with the target interface.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface or a compatible set of requirements.



First TrTCM Meter Index must be in range 1-5000

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

First TrTCM Meter Index must be in range 1-5000 log

First TrTCM Meter Index must be in range 1-5000

The maximum valid index for the first TrTCM meter is 5000

Source	Severity
QoS	Serious

Remedial action

Specify a valid index.



Flash Erase Failed Sector %d Address 0x%x

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Flash Erase Failed Sector %d Address 0x%x log

Flash Erase Failed Sector %d Address 0x%x

Logs a failed flash sector erase.

Source	Severity
MCFG	Information

Remedial action

Call Avaya.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Flash Erase Warning Sector %d Address 0x%x Erase time %d ms log

Flash Erase Warning Sector %d Address 0x%x Erase time %d ms

Logs a slow and successful flash sector erase.

Source	Severity
MCFG	Information

Remedial action

Message indicates that the flash sector is nearing its end of life. No immediate action is required, but that sector may soon become unprogrammable.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Flow ID filtering not supported for IPv4 log

Flow ID filtering not supported for IPv4

Flow ID is supported only for IPV6.

Source	Severity
QoS	Serious

Remedial action

Enter a Ipv6 address or specify the address type (must be Ipv6).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Flow ID out-of-range (Flow ID) log

Flow ID out-of-range (Flow ID)

Invalid flow ID specified.

Source	Severity
QoS	Serious

Remedial action

Enter a flow ID between 0x00-0xfffff (1048575).



Front-panel UI selected use rear-panel base non-base switch

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Front-panel UI selected use rear-panel base non-base switch log

Front-panel UI selected use rear-panel base non-base switch

The stack has been reset using the front-panel push-button.

Source	Severity
Stack Manager	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Error Calling taskLock() returns Error log

FSH - Error Calling taskLock() returns Error

This message appears when the task is unable to disable the context switching for the flash access.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Error Failed to erase flash sector log

FSH - Error Failed to erase flash sector

The system is unable to erase the flash sector to program the agent image.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Error Failed to lock flash sector log

FSH - Error Failed to lock flash sector

The system is unable to lock the flash sector in order to prevent programming or erasing.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Error Failed to program flash log

FSH - Error Failed to program flash

The system is unable to write the image on flash.

Source	Severity
Flash Driver	Critical

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Error Failed to unlock flash sector log

FSH - Error Failed to unlock flash sector

The system failed to unlock the flash sector in order to allow programming or erasing.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry or reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Error Failed to write to flash address log

FSH - Error Failed to write to flash address

The system could not program the flash memory.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - File not closed : log

FSH - File not closed :

This notification is generated while trying to load/save the configuration, indicating the files which are opened.

Source	Severity
CFG	Information

Remedial action

No action required.



FSH - Some files are not closed. MsgType # %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Some files are not closed. MsgType # %d log

FSH - Some files are not closed. MsgType # %d

This notification is generated while trying to load/save the configuration, if some files remain open. The configuration cannot be saved if the files remain open.

Source	Severity
CFC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Time to Download the Image number seconds log

FSH - Time to Download the Image number seconds

This message indicates the time needed to download the image.

Source	Severity
---------------	-----------------

Download Task	Critical
---------------	----------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

FSH - Time to Program the Image to flash number seconds log

FSH - Time to Program the Image to flash number seconds

This message indicates the time needed to program the image.

Source	Severity
--------	----------

Download Task	Critical
---------------	----------

Remedial action

No action required.



Gateway IP changed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Gateway IP changed log

Gateway IP changed

This message indicates that the Gateway IP has changed.

Source	Severity
IPT	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Got UserPolicy from Radius but UBP disabled - unitPort 0x%x mac %08x%04x

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Got UserPolicy from Radius but UBP disabled - unitPort 0x%x mac %08x%04x log

Got UserPolicy from Radius but UBP disabled - unitPort 0x%x mac %08x%04x

A UBP filter could not be installed because UBP is not enabled from EAP.

Source	Severity
QoS	Information

Remedial action

Enable UBP.



Hello Module unable to communicate with neighbor(s) unit reset

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Hello Module unable to communicate with neighbor(s) unit reset log

Hello Module unable to communicate with neighbor(s) unit reset

This message appears under the following instances: When both stack port directions are physically up but unable to communicate with the neighboring unit(s); When one stack port direction is unable to communicate with its neighbor and the other stack port direction is not connected. The message is stored in a non-volatile memory; the presence of the message means the unit was reset.

Source	Severity
--------	----------

Hello Module	Critical
--------------	----------

Remedial action

No action required.



Hello Module unable to communicate with neighbor(s) unit reset

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Hello Module unable to communicate with neighbor(s) unit reset log

Hello Module unable to communicate with neighbor(s) unit reset

The Hello module is unable to communicate with the neighbor(s), as the stack port direction(s) are logically down for more than 5 minutes.

Source	Severity
--------	----------

Stack Monitor	Information
---------------	-------------

Remedial action

No action required. The switch/stack reboots itself. The logs are saved to NVRAM for future reference.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ifc app modification issue (inconsistent default gateway data) log

Ifc app modification issue (inconsistent default gateway data)

Modification is prohibited as an inconsistent default gateway data is detected.

Source	Severity
QoS	Serious

Remedial action

Remove the entry and add a new one with the modified default gateway value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ifc app modification issue (inconsistent DHCP server data) log

Ifc app modification issue (inconsistent DHCP server data)

Modification is not allowed as the system detected inconsistent DHCP server data.

Source	Severity
QoS	Serious

Remedial action

Remove the entry and add a new one to the modified DHCP server.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ifc app modification issue (inconsistent ifType data) log

Ifc app modification issue (inconsistent ifType data)

Modification is not allowed as an inconsistent interface type data is detected.

Source	Severity
QoS	Serious

Remedial action

Remove the entry and add a new one with the modified interface type data.



Ifc app support not currently available on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ifc app support not currently available on interface (ifc#) log

Ifc app support not currently available on interface (ifc#)

Interface application support is not available on the specified interface as it is incompatible or disabled.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface index.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Ifc assignment issue - prec conflict (policy policy# disabled)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ifc assignment issue - prec conflict (policy policy# disabled) log

Ifc assignment issue - prec conflict (policy policy# disabled)

The interface assignment change needs to install a policy on a precedence that is already occupied by a different one, as a result the conflicting policy was disabled.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Analyze the conflict and choose an appropriate solution (the interface assignment or the policy).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Added reserved multicast address log

IGMP Added reserved multicast address

This message appears when the unknown multicast allowed address is successfully registered on the switch.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Error sending database from unit unit# log

IGMP Error sending database from unit unit#

The IGMP database cannot be sent to a unit in the stack.

Source	Severity
IGMP	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Error sending group database from unit unit# log

IGMP Error sending group database from unit unit#

The IGMP Group database cannot be transmitted from one unit to the other in the stack.

Source	Severity
IGMP	Serious

Remedial action

No action required.



IGMP Exceeded reserved multicast
address range #Addr
numResAddrEntries+1 * #VLANs
numActiveVLANs maxReservedRange

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Exceeded reserved multicast address range #Addr numResAddrEntries+1 * #VLANs numActiveVLANs maxReservedRange log

IGMP Exceeded reserved multicast address range #Addr numResAddrEntries+1 * #VLANs numActiveVLANs maxReservedRange

The maximum number of registered unknown allowed multicast addresses are reached.

Source	Severity
IGMP	Information

Remedial action

No action required.



IGMP Initialization failed Error code errCode

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Initialization failed Error code errCode log

IGMP Initialization failed Error code errCode

The IGMP initialization failed due to unavailable system resources.

Source	Severity
IGMP	Critical

Remedial action

Restart the system.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP: Max hardware Resources reached log

IGMP: Max hardware Resources reached

Maximum hardware resources allocated for forwarding Multicast S,G's ingress locally, has been reached, when running IGMP Snooping over SPBM C-VLAN.

Source	Severity
IGMP	Information

Remedial action

Wait until no longer needed Multicast S,G's already learned on box expire. Force expiration of no longer wanted streams by bouncing the ingress source_port, to make room for new S,G's.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Maximum number of igmp enabled interfaces reached log

IGMP Maximum number of igmp enabled interfaces reached

The IGMP-enabled interfaces reached the maximum limit of 256.

Source	Severity
ipmc (igmp)	Serious

Remedial action

Disable the IGMP on interfaces that no longer need to be IGMP-enabled.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP No hardware resource available log

IGMP No hardware resource available

The IGMP Hardware Resource Allocation Failed.

Source	Severity
ipmc (igmp)	Information

Remedial action

Redo the QoS filter allocations.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Proxy disabled on VLAN vlan# log

IGMP Proxy disabled on VLAN vlan#

The IGMP proxy is disabled for a VLAN.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Proxy enabled on VLAN vlan# log

IGMP Proxy enabled on VLAN vlan#

The IGMP proxy is enabled for a VLAN.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Query Time set to num on VLAN vlan# log

IGMP Query Time set to num on VLAN vlan#

The "Query Time" parameter is modified for a VLAN.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Removed reserved multicast address log

IGMP Removed reserved multicast address

The unknown allowed multicast address is unregistered on the switch.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Robust Value set to num on VLAN vlan# log

IGMP Robust Value set to num on VLAN vlan#

The "Robust Value" parameter is modified for a VLAN.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Snooping disabled on VLAN vlan# log

IGMP Snooping disabled on VLAN vlan#

The IGMP snooping is disabled for a VLAN.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Snooping enabled on VLAN vlan# log

IGMP Snooping enabled on VLAN vlan#

The IGMP snooping is enabled for a VLAN.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP SSM Range changed log

IGMP SSM Range changed

The group range for IP IGMP SSM has changed.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP SSM Range changed log

IGMP SSM Range changed

The IGMP global allowable SSM range is changed.

Source	Severity
ipmc (igmp)	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Unable to add reserved multicast address log

IGMP Unable to add reserved multicast address

This message appears when an unknown multicast address registration fails.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Unknown Multicast Filter disabled log

IGMP Unknown Multicast Filter disabled

The "Unknown Multicast No Flood" feature is disabled from the user interface.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP Unknown Multicast Filter enabled log

IGMP Unknown Multicast Filter enabled

This message appears when the “Unknown Multicast No Flood” feature is enabled from the user interface.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP: Unknown Query received on SPBM Multicast C-VLAN log

IGMP: Unknown Query received on SPBM Multicast C-VLAN

When running IGMP Snooping over SPBM C-VLAN, the respective BEB interface MUST be the designated Querier on it's LAN segment. Stray queries incoming towards this interface are discarded, and the respective port will NOT have an igmp mrouter functionality.

Source	Severity
IGMP	Information

Remedial action

It is recommended to verify multicast setup connected through the respective Snooping C-VLAN and try to prevent other IGMP Queriers to be present in the respective LAN segment. Reconfigure multicast setup keeping in mind that BEB Snooping C-VLAN must be the only querier on the network. If actions presented are not possible, and multicast traffic gets forwarded as desired, message can be ignored.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP: V2 report drop on reserved GA log

IGMP: V2 report drop on reserved GA

IGMP V2 report for reserved group IP was dropped.

Source	Severity
MCMGR/IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP: V3 report group skip on invalid GA log

IGMP: V3 report group skip on invalid GA

A group record in an IGMP V3 report was skipped, as the group address is not multicast.

Source	Severity
--------	----------

MCMGR/IGMP	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP: V3 report group skip on reserved GA log

IGMP: V3 report group skip on reserved GA

A group record in an IGMP V3 report was skipped, as the group address is reserved.

Source	Severity
--------	----------

MCMGR/IGMP	Information
------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP V1 router ports mask log

IGMP V1 router ports mask

This message appears when the list of IGMP version 1 router ports are modified.

Source	Severity
IGMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IGMP V2 router ports mask log

IGMP V2 router ports mask

This message appears when the list of IGMP version 2 router ports are modified.

Source	Severity
IGMP	Information

Remedial action

No action required.



IMC buffers of size buffer size have been exhausted buffer pool size pool size

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IMC buffers of size buffer size have been exhausted buffer pool size pool size log

IMC buffers of size buffer size have been exhausted buffer pool size pool size

This message appears when memory buffers used for communication between units in a stack are exhausted. The <buffer size> > varies and is measured in bytes. The <pool size> can vary for different buffer sizes and different models (ERS 25XX / 45XX /55XX / 56XX).

Source	Severity
IMC	Critical

Remedial action

Restart the system.



IMC buffers of size size have been exhausted buffer pool size size

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IMC buffers of size size have been exhausted buffer pool size size log

IMC buffers of size size have been exhausted buffer pool size size

Stack Monitor detected a depleted IMC (Inter-Module Communication) buffer pool.

Source	Severity
Stack Monitor	Information

Remedial action

No action required. The switch/stack reboots itself. The logs are saved to NVRAM for future reference.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IMC imc_idtPacketDispatch() incorrect rcvMsgType = %s(%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IMC imc_idtPacketDispatch() incorrect rcvMsgType = %s(%d) log

IMC imc_idtPacketDispatch() incorrect rcvMsgType = %s(%d)

An incorrect message type was received.

Source	Severity
IMC	Warning

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IMC memory allocation error packetLength = %d file %s line %d log

IMC memory allocation error packetLength = %d file %s line %d

An error occurred on IMC packet allocation.

Source	Severity
IMC	Warning

Remedial action

No action required.



Inadequate resources available for application policy criteria

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inadequate resources available for application policy criteria log

Inadequate resources available for application policy criteria

The resources potentially consumed by a legacy filter set are not available on the specified interface (on the base or the non-base unit).

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check log for the possible related details on the issue. Check the available resources.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible base action extension specified log

Incompatible base action extension specified

The storage types are not compatible. For example only system-level entries can reference other system-level entries.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and use compatible entries.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible classifier reference (agent-defined clfr) log

Incompatible classifier reference (agent-defined clfr)

It's forbidden to reference an system/agent defined classifier element.

Source	Severity
QoS	Serious

Remedial action

Create a similar user defined classifier element.



Incompatible data model version values (referenced clfr data)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible data model version values (referenced clfr data) log

Incompatible data model version values (referenced clfr data)

The data model version of the classifier is unknown.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible data model version values (referenced meter data) log

Incompatible data model version values (referenced meter data)

The data model version of the meter is unknown

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible in-profile action (trusted ifc) log

Incompatible in-profile action (trusted ifc)

The specified in-profile action is not supported on the associated interface type (trusted).

Source	Severity
QoS	Serious

Remedial action

Enter a different in-profile action or change interface group assignment.



Incompatible in-profile action (unrestricted ifc)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible in-profile action (unrestricted ifc) log

Incompatible in-profile action (unrestricted ifc)

The specified in-profile action is not supported on the associated interface type (unrestricted).

Source	Severity
QoS	Serious

Remedial action

Enter a different in-profile action or change interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible in-profile action (untrusted ifc) log

Incompatible in-profile action (untrusted ifc)

The specified in-profile action is not supported on the associated interface type (untrusted).

Source	Severity
QoS	Serious

Remedial action

Enter a different in-profile action or change interface group assignment.



Incompatible in-profile action (untrustedv4v6 ifc)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible in-profile action (untrustedv4v6 ifc) log

Incompatible in-profile action (untrustedv4v6 ifc)

The specified in-profile action is not compatible with the associated interface type (untrustedv4v6).

Source	Severity
QoS	Serious

Remedial action

Enter a different in-profile action or change the interface group assignment.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible match action (unrestricted ifc) log

Incompatible match action (unrestricted ifc)

The specified action is not supported on the associated interface type (unrestricted).

Source	Severity
QoS	Serious

Remedial action

Enter a different action or change interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible match action (untrusted ifc) log

Incompatible match action (untrusted ifc)

The specified action is not supported on the associated interface type (untrusted).

Source	Severity
QoS	Serious

Remedial action

Enter a different action or change interface group assignment.



Incompatible match action (untrustedv4v6 ifc)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible match action (untrustedv4v6 ifc) log

Incompatible match action (untrustedv4v6 ifc)

The specified action is not compatible with the associated interface type (untrustedv4v6).

Source	Severity
QoS	Serious

Remedial action

Enter a different action or change the interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible non-match action (trusted ifc) log

Incompatible non-match action (trusted ifc)

The specified non-match action is not supported on the associated interface type (trusted)

Source	Severity
QoS	Serious

Remedial action

Enter a different non-match action or change interface group assignment.



Incompatible non-match action (unrestricted ifc)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible non-match action (unrestricted ifc) log

Incompatible non-match action (unrestricted ifc)

The specified non-match action is not supported on the associated interface type (unrestricted).

Source	Severity
QoS	Serious

Remedial action

Enter a different non-match action or change interface group assignment.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Incompatible non-match action (unrestricted ifc)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible non-match action (unrestricted ifc) log

Incompatible non-match action (unrestricted ifc)

The specified non-match action is not supported on the associated interface type (unrestricted).

Source	Severity
QoS	Serious

Remedial action

Enter a different non-match action or change interface group assignment.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible non-match action (untrusted ifc) log

Incompatible non-match action (untrusted ifc)

The specified non-match action is not supported on the associated interface type (untrusted).

Source	Severity
QoS	Serious

Remedial action

Enter a different non-match action or change interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible out-of-profile action (trusted ifc) log

Incompatible out-of-profile action (trusted ifc)

The specified out-of-profile action is not supported on the associated interface type (trusted).

Source	Severity
QoS	Serious

Remedial action

Enter a different out-of-profile action or change interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible out-of-profile action (unrestricted ifc) log

Incompatible out-of-profile action (unrestricted ifc)

The specified out-of-profile action is not supported on the associated interface type (unrestricted).

Source	Severity
QoS	Serious

Remedial action

Enter a different out-of-profile action or change interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible out-of-profile action (untrusted ifc) log

Incompatible out-of-profile action (untrusted ifc)

The specified out-of-profile action is not supported on the associated interface type (untrusted).

Source	Severity
QoS	Serious

Remedial action

Enter a different out-of-profile action or change interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible out-of-profile action (untrustedv4v6 ifc) log

Incompatible out-of-profile action (untrustedv4v6 ifc)

The specified out-of-profile action is not compatible with the associated interface type (untrustedv4v6).

Source	Severity
QoS	Serious

Remedial action

Enter a different out-of-profile action or change the interface group assignment.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Incompatible StorageType specified (re classifier) log

Incompatible StorageType specified (re classifier)

The policy and classifier have incompatible storage types. As a general rule only system-level entries can reference other system-level entries.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Enter a compatible classifier or create a new one.



Inconsistent action criteria detected across block members

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inconsistent action criteria detected across block members log

Inconsistent action criteria detected across block members

The action options within a block entry must be consistent. For instance you cannot specify an action and a meter for a block in the same time.

Source	Severity
---------------	-----------------

QoS	Serious
-----	---------

Remedial action

Enter only an action or a meter across block.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Inconsistent classifier component (clfr comp#) state detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inconsistent classifier component (clfr comp#) state detected log

Inconsistent classifier component (clfr comp#) state detected

Unable to commit changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Inconsistent labels detected for members of same block

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inconsistent labels detected for members of same block log

Inconsistent labels detected for members of same block

The members of the same classifier-block must have the same label.

Source	Severity
QoS	Serious

Remedial action

Enter the same label for all members.



Inconsistent labels detected for members of same set

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inconsistent labels detected for members of same set log

Inconsistent labels detected for members of same set

Entries of the same set must have the same labels.

Source	Severity
QoS	Serious

Remedial action

Enter the same labels for all members in the set or separate the conflicting components into multiple sets.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Inconsistent MAC data detected across filter set members

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inconsistent MAC data detected across filter set members log

Inconsistent MAC data detected across filter set members

Inconsistent MAC data detected across the filter sets; Following are the possible reasons: Different users are on the same interface with different MAC data length, Different users on the same interface with the same MAC data source.

Source	Severity
---------------	-----------------

QoS	Serious
-----	---------

Remedial action

Check for and remove the possible MAC data conflicts.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Inconsistent metering criteria detected across block members

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inconsistent metering criteria detected across block members log

Inconsistent metering criteria detected across block members

Invalid metering option specified. QPA internal error.

Source	Severity
QoS	Serious

Remedial action

Enter a valid meter or ignore option.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Index value out-of-range log

Index value out-of-range

Invalid QoS entry index value. Either system index for a non-system entry, or index out of the supported range.

Source	Severity
QoS	Information

Remedial action

Enter a different entry index.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Info: Transceiver inserted on %s log

Info: Transceiver inserted on %s

The transceiver has been inserted on a certain unit/port, having a specific vendor and type.

Source	Severity
PDT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Info: Transceiver removed from %s log

Info: Transceiver removed from %s

The transceiver has been removed from a certain unit/port.

Source	Severity
PDT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inner VLAN ID filtering requires double tag log

Inner VLAN ID filtering requires double tag

Inner VLAN ID is used in double tagged packets.

Source	Severity
QoS	Serious

Remedial action

Remove inner VLAN ID option or specify double tagged mode.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Inner VLAN ID min max values invalid (min VLAN ID ! max VLAN ID) log

Inner VLAN ID min max values invalid (min VLAN ID ! max VLAN ID)

Max inner VLAN ID value must be bigger that min value.

Source	Severity
QoS	Serious

Remedial action

Correct inner VLAN ID range limits.



In-profile action contains conflicting data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

In-profile action contains conflicting data log

In-profile action contains conflicting data

Unable to install the specified in-profile action, conflicting data detected.

Source	Severity
QoS	Serious

Remedial action

Identify conflicts and separate them into different in-profile actions.



Insufficient HW resources to support port role association

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Insufficient HW resources to support port role association log

Insufficient HW resources to support port role association

Not all the resources required for the interface assignment change are available.

Source	Severity
QoS	Serious

Remedial action

Check for conflicts and remove the un-needed resources if any.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Insufficient policy space available to support access assignment log

Insufficient policy space available to support access assignment

Not enough resources to support the policy installation on base or non-base unit.

Source	Severity
QoS	Serious

Remedial action

Check the policy resource availability and try to remove any resources that are not needed.



Insufficient resources available to support policy installation

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Insufficient resources available to support policy installation log

Insufficient resources available to support policy installation

Not all the resources required for the policy are available on the base or non-base unit(s).

Source	Severity
QoS	Serious

Remedial action

Modify either the interfaces or the demanding resources.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Interface action distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface action distribution across stack failed log

Interface action distribution across stack failed

Unable to perform action distribution changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface action entry referenced by base action log

Interface action entry referenced by base action

Cannot modify or delete an interface action if it is referenced by a base action.

Source	Severity
QoS	Serious

Remedial action

Remove the base action first.



Interface action extension identifier invalid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface action extension identifier invalid log

Interface action extension identifier invalid

The interface action extension identifier is invalid.

Source	Severity
QoS	Critical

Remedial action

Enter a valid interface action extension.



Interface action modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface action modifications not supported log

Interface action modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface Application data in use (QoS disable prohibited) log

Interface Application data in use (QoS disable prohibited)

Cannot disable the QoS system if there are Interface Applications in use.

Source	Severity
QoS	Serious

Remedial action

Disable all the Interface Applications before disabling QoS.



Interface application distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface application distribution across stack failed log

Interface application distribution across stack failed

Unable to carry out the interface application distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Interface application modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface application modifications not supported log

Interface application modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface application Undo failure (app app#) log

Interface application Undo failure (app app#)

Unable to perform the "Undo" action due to the the specified interface application.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Interface assignment distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface assignment distribution across stack failed log

Interface assignment distribution across stack failed

Unable to commit changes (interface assignment) across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Interface assignment failure - precedence conflict detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface assignment failure - precedence conflict detected log

Interface assignment failure - precedence conflict detected

The interface assignment change needs to install a policy on a precedence already occupied by a different one.

Source	Severity
QoS	Serious

Remedial action

Remove or disable if possible the conflicting policy.



Interface assignment modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface assignment modifications not supported log

Interface assignment modifications not supported

The system detected an internal error; The specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface capabilities incompatible with policy data log

Interface capabilities incompatible with policy data

The policy and the specified interface have different version capabilities.

Source	Severity
QoS	Serious

Remedial action

Enter either a compatible interface or adapt the policy to match the required interface.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface data out-of-sync in Policy and User Policy entries log

Interface data out-of-sync in Policy and User Policy entries

The interface data associated with the policy and the session must be the same.

Source	Severity
QoS	Serious

Remedial action

Specify the same interface data.



Interface queue modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface queue modifications not supported log

Interface queue modifications not supported

The system detected an internal error; the specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Interface resources inadequate to support application enable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface resources inadequate to support application enable log

Interface resources inadequate to support application enable

The resources required for interface application support are not available on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue, or use a different interface.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface shaping and CoS shaping conflict (same ifc specified) log

Interface shaping and CoS shaping conflict (same ifc specified)

Interface shaping and CoS shaping can not be applied to the same interface at the same time.

Source	Severity
QoS	Serious

Remedial action

Enter different interfaces for the two shaping types.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface shaping and queue shaping conflict (same ifc specified) log

Interface shaping and queue shaping conflict (same ifc specified)

Both Interface and queue shaping can not be applied to the one interface at the same time.

Source	Severity
QoS	Serious

Remedial action

Enter different interfaces for the two shaping types.



Interface shaping modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface shaping modifications not supported log

Interface shaping modifications not supported

The system detected an Internal error; specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Interface shaping not supported with specified interface

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interface shaping not supported with specified interface log

Interface shaping not supported with specified interface

The specified interface is unable to support the shaping.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Interfaces QoS-disabled (port# on unit#) - restoration issue

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Interfaces QoS-disabled (port# on unit#) - restoration issue log

Interfaces QoS-disabled (port# on unit#) - restoration issue

Failed to disable the Policy/Interface.

Source	Severity
QoS	Serious

Remedial action

Check for the conflicting entries, try again later, reset the QoS agent or reset the unit.



Invalid access assignment type option specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid access assignment type option specified log

Invalid access assignment type option specified

The access assignment type option specified is invalid.

Source	Severity
QoS	Serious

Remedial action

Check the documentation and use a supported access assignment type.



Invalid access element type option specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid access element type option specified log

Invalid access element type option specified

There are 4 supported access element types: ACL, APP, MMC, and UDC; Check through the documentation for further clarifications on the issue.

Source	Severity
QoS	Serious

Remedial action

Remove the classifier block first.



Invalid classifier ID specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid classifier ID specified log

Invalid classifier ID specified

Unable to find the specified classifier ID in the Filter Manager database.

Source	Severity
QoS	Critical

Remedial action

Enter a valid classifier ID or if you are sure it exists try resetting the QoS agent or the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid classifier reference log

Invalid classifier reference

The only valid classifiers type are: ip, l2 and system.

Source	Severity
QoS	Serious

Remedial action

Specify a valid classifier type.



Invalid classifier reference (unknown class)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid classifier reference (unknown class) log

Invalid classifier reference (unknown class)

There are 30 supported classes, check documentation for a full support class description.

Source	Severity
QoS	Critical

Remedial action

Specify a valid classifier class.



Invalid classifier reference (unknown incompatible set)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid classifier reference (unknown incompatible set) log

Invalid classifier reference (unknown incompatible set)

The referenced classifier set must exist prior to being used.

Source	Severity
QoS	Serious

Remedial action

Enter an existing classifier set or create a new one.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid classifier reference (unknown instance) log

Invalid classifier reference (unknown instance)

The referenced classifier element (ip, l2 or system) must exist prior to being used.

Source	Severity
QoS	Serious

Remedial action

Enter an existing classifier element or create a new one.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid Configuration Block Number %d log

Invalid Configuration Block Number %d

Invalid configuration block number entered.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid Configuration Magic Number log

Invalid Configuration Magic Number

The number that identifies the block number is incorrect and is not as expected.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid Configuration Version Number log

Invalid Configuration Version Number

The block version number is not recognized.

Source	Severity
config	Information

Remedial action

No action required.



Invalid DAPP state transition detected (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid DAPP state transition detected (prohibited) log

Invalid DAPP state transition detected (prohibited)

Can only move between disabled and enabled, not between different enable modes.

Source	Severity
QoS	Serious

Remedial action

Disable DAPP before changing the enabled state.



Invalid datapath identifier specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid datapath identifier specified log

Invalid datapath identifier specified

Invalid/Unknown datapath identifier detected. Internal Filter Manager error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid destination MAC address length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid destination MAC address length specified log

Invalid destination MAC address length specified

Destination MAC address length is bigger than 6.

Source	Severity
QoS	Serious

Remedial action

Specify a valid MAC address.



Invalid destination MAC address mask length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid destination MAC address mask length specified log

Invalid destination MAC address mask length specified

Destination MAC address mask length is bigger than 6.

Source	Severity
QoS	Serious

Remedial action

Specify a valid MAC address mask.



Invalid drop action option specified
Invalid drop action option specified
specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid drop action option specified Invalid drop action option specified log

Invalid drop action option specified
Invalid drop action option specified

The valid/supported drop options are drop, don't drop and deferred. Take into account that for certain action types the deferred option is not valid.

Source	Severity
QoS	Information

Remedial action

Check the documentation if necessary and use a compatible/valid drop action option.



Invalid drop precedence value specified (precedence)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid drop precedence value specified (precedence) log

Invalid drop precedence value specified (precedence)

Valid drop precedence values are low and high.

Source	Severity
QoS	Serious

Remedial action

Specify a valid drop precedence value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid DSCP value specified (DSCP value) log

Invalid DSCP value specified (DSCP value)

The valid DSCP values are between 0 and 63.

Source	Severity
QoS	Serious

Remedial action

Enter a valid DSCP value in the range specified.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid egress interface specified (ifc#) log

Invalid egress interface specified (ifc#)

The interface index does not exist.

Source	Severity
QoS	Serious

Remedial action

Check the platform's/stack's port range and use a valid interface index.



Invalid egress interface type specified (<ifc type>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid egress interface type specified (<ifc type>) log

Invalid egress interface type specified (<ifc type>)

Interface can not be associated with action specifications(prohibited).

Source	Severity
QoS	Serious

Remedial action

Enter a different port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid egress mask value specified log

Invalid egress mask value specified

The egress mask must be either null or 64 in length.

Source	Severity
QoS	Serious

Remedial action

Specify a valid egress mask.



Invalid entry creation attempted (index index#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid entry creation attempted (index index#) log

Invalid entry creation attempted (index index#)

Creation of the specified QoS entry is not allowed (modifications may be supported) – possible entries: COS-to-DSCP assignment default values created at initialization; default DSCP-to-queue assignments and default CoS-to-queue assignments created when a new queue set is defined.

Source	Severity
QoS	Information

Remedial action

Modify the existing entry if necessary.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid EtherType value specified (Ether Type 0xXXXX)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid EtherType value specified (Ether Type 0xXXXX) log

Invalid EtherType value specified (Ether Type 0xXXXX)

EtherType must be between 0x0-0xFFFF.

Source	Severity
QoS	Serious

Remedial action

Specify an EtherType value between 0x0-0xFFFF.



Invalid expired session data specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid expired session data specified log

Invalid expired session data specified

The session data provided does not exist or has expired.

Source	Severity
QoS	Serious

Remedial action

Specify a current session data.



Invalid FCoE controller ingress interface specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid FCoE controller ingress interface specified log

Invalid FCoE controller ingress interface specified

An invalid FCoE controller ingress interface was specified.

Source	Severity
FCoE Redirect	Information

Remedial action

Specify a valid interface.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid FCoE controller VLAN specified log

Invalid FCoE controller VLAN specified

An invalid FCoE controller VLAN was specified..

Source	Severity
FCoE Redirect	Information

Remedial action

Specify a valid VLAN.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid filter set priority value detected log

Invalid filter set priority value detected

The filter set priority must be within 1 to 255.

Source	Severity
QoS	Serious

Remedial action

Check the log for related details on the issue. Try again later, reset the QoS agent, or reset the stack



Invalid interface found in egress mask (egress mask bit#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid interface found in egress mask (egress mask bit#) log

Invalid interface found in egress mask (egress mask bit#)

The Interface doesn't exist or is not supported.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface/port number.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid interface index data specified (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid interface index data specified (ifc#) log

Invalid interface index data specified (ifc#)

The interface index not in range (1-1024).

Source	Severity
QoS	Serious

Remedial action

Check unit/stack limitations.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid interface index data specified (ifc index)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid interface index data specified (ifc index) log

Invalid interface index data specified (ifc index)

The interface index does not exist.

Source	Severity
QoS	Serious

Remedial action

Check the port range of the platform or stack, and use a valid interface index.



Invalid interface index data (system-owned) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid interface index data (system-owned) specified log

Invalid interface index data (system-owned) specified

Only system-owned policies can reference system-owned interfaces.

Source	Severity
QoS	Serious

Remedial action

Enter an interface that is not system-owned.



Invalid IP destination address prefix detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid IP destination address prefix detected log

Invalid IP destination address prefix detected

The specified destination address prefix exceeds the maximum allowed for ipv4 addresses (32).

Source	Severity
QoS	Serious

Remedial action

Enter the correct prefix.



Invalid IP source address prefix detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid IP source address prefix detected log

Invalid IP source address prefix detected

The specified source address prefix exceeds the maximum allowed for ipv4 addresses (32).

Source	Severity
QoS	Serious

Remedial action

Enter the correct prefix.



Invalid master block member value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid master block member value specified log

Invalid master block member value specified

The master block member value can only have two values: True or False.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid maximum inner VLAN ID value specified (VLAN ID)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid maximum inner VLAN ID value specified (VLAN ID) log

Invalid maximum inner VLAN ID value specified (VLAN ID)

The maximum inner VLAN ID is 4094 .

Source	Severity
QoS	Serious

Remedial action

Specify a valid VLAN ID value.



Invalid maximum VLAN ID value specified (VLAN ID)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid maximum VLAN ID value specified (VLAN ID) log

Invalid maximum VLAN ID value specified (VLAN ID)

The maximum VLAN ID is 4094.

Source	Severity
QoS	Serious

Remedial action

Specify a valid VLAN ID value.



Invalid metering data (bucket size) specified for interface(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid metering data (bucket size) specified for interface(s) log

Invalid metering data (bucket size) specified for interface(s)

The current metering bucket size is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the metering bucket size.



Invalid metering data (granularity) specified for interface(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid metering data (granularity) specified for interface(s) log

Invalid metering data (granularity) specified for interface(s)

The metering granularity is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the metering granularity.



Invalid metering data (rate) specified for interface(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid metering data (rate) specified for interface(s) log

Invalid metering data (rate) specified for interface(s)

The metering rate is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the metering rate.



Invalid metering data (srTCM trTCM) specified for interface(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid metering data (srTCM trTCM) specified for interface(s) log

Invalid metering data (srTCM trTCM) specified for interface(s)

The metering type is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the metering type.



Invalid minimum inner VLAN ID value specified (VLAN ID)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid minimum inner VLAN ID value specified (VLAN ID) log

Invalid minimum inner VLAN ID value specified (VLAN ID)

The inner VLAN ID must be greater than 1.

Source	Severity
QoS	Serious

Remedial action

Enter an VLAN ID greater than 1.



Invalid minimum VLAN ID value specified (VLAN ID)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid minimum VLAN ID value specified (VLAN ID) log

Invalid minimum VLAN ID value specified (VLAN ID)

The VLAN ID must be bigger than.

Source	Severity
QoS	Serious

Remedial action

Enter an ID bigger than 1.



Invalid mix of IP address data (Dst IP type) in set detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid mix of IP address data (Dst IP type) in set detected log

Invalid mix of IP address data (Dst IP type) in set detected

Different filter criteria can be specified in the same classifier but they must be compatible. Conflict(s) detected when validating Dst IP/type data.

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple classifier sets.



Invalid mix of IP and non-IP data in set detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid mix of IP and non-IP data in set detected log

Invalid mix of IP and non-IP data in set detected

Even though different classifier element types can be specified in the same classifier they must be compatible. IP and non-IP data are mutually exclusive.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Separate the IP and non-IP pattern data in different classifier sets.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid mix of IP data (IPv4 IPv6) in set detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid mix of IP data (IPv4 IPv6) in set detected log

Invalid mix of IP data (IPv4 IPv6) in set detected

Different filter criteria can be specified in the same classifier but they must be compatible. IPv4 and Ipv6 data are mutually exclusive.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Separate the conflicting elements into multiple classifier sets.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for BcastFrames attribute log

Invalid option specified for BcastFrames attribute

BcastFrames attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid option specified for KnownIpMcast attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for KnownIpMcast attribute log

Invalid option specified for KnownIpMcast attribute

KnownIpMcast attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid option specified for KnownMcastFrames attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for KnownMcastFrames attribute log

Invalid option specified for KnownMcastFrames attribute

KnownMcastFrames attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid option specified for KnownNonIpMcast attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for KnownNonIpMcast attribute log

Invalid option specified for KnownNonIpMcast attribute

KnownNonIpMcast attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid option specified for KnownUcastFrames attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for KnownUcastFrames attribute log

Invalid option specified for KnownUcastFrames attribute

KnownUcastFrames attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid option specified for NonIpPkt attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for NonIpPkt attribute log

Invalid option specified for NonIpPkt attribute

NonIpPkts attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid option specified for PatternIpVersion attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for PatternIpVersion attribute log

Invalid option specified for PatternIpVersion attribute

Valid PatternIpVersion are non-ip, ipv4, ipv6.

Source	Severity
QoS	Serious

Remedial action

Enter a valid version or remove option.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid option specified for UnknownMcastFrames attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for UnknownMcastFrames attribute log

Invalid option specified for UnknownMcastFrames attribute

UnknownMcastFrames attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid option specified for UnknownNonIpMcast attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for UnknownNonIpMcast attribute log

Invalid option specified for UnknownNonIpMcast attribute

UnknownNonIpMcast attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid option specified for UnknownUcastFrames attribute

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid option specified for UnknownUcastFrames attribute log

Invalid option specified for UnknownUcastFrames attribute

UnknownUcastFrames attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid pattern data length (untagged format) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid pattern data length (untagged format) specified log

Invalid pattern data length (untagged format) specified

Pattern data length does not correspond with the specified data format (untagged).

Source	Severity
QoS	Serious

Remedial action

Modify the pattern data or use the correct data format.



Invalid pattern data string length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid pattern data string length specified log

Invalid pattern data string length specified

Patter data string length must be between 0 and 128.

Source	Severity
QoS	Serious

Remedial action

Specify a valid length.



Invalid pattern format data specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid pattern format data specified log

Invalid pattern format data specified

Supported formats: untagged, tagged or double tagged.

Source	Severity
QoS	Serious

Remedial action

Specify a supported format data.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid pattern position string length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid pattern position string length specified log

Invalid pattern position string length specified

Patter position string length must be between 0 and 128.

Source	Severity
QoS	Serious

Remedial action

Specify a valid length.



Invalid port detected in specified port mask

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid port detected in specified port mask log

Invalid port detected in specified port mask

An unknown/invalid port was detected in the specified port mask.

Source	Severity
QoS	Serious

Remedial action

Inspect the mask and remove the invalid port(s).



Invalid 802.1p user priority value specified (priority value)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid 802.1p user priority value specified (priority value) log

Invalid 802.1p user priority value specified (priority value)

The only valid user priorities values are between 0 and 7.

Source	Severity
QoS	Serious

Remedial action

Specify a valid user priority.



Invalid RAV id %d, on port %d, cannot be Switched UNI or B-VLAN

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid RAV id %d, on port %d, cannot be Switched UNI or B-VLAN log

Invalid RAV id %d, on port %d, cannot be Switched UNI or B-VLAN

You cannot use a Switched UNI or B-VLAN as a RAV

Source	Severity
EAP	Information

Remedial action

Set a proper RAV in RADIUS user entry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid RAV id %d, on port %d, it isn't a CVLAN log

Invalid RAV id %d, on port %d, it isn't a CVLAN

In SPB environment with EAP enabled you can only use CVLANs as RAVs

Source	Severity
EAP	Information

Remedial action

Set a proper RAV in RADIUS user entry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid resetToDefaults value specified log

Invalid resetToDefaults value specified

ResetToDefaults must be "true" when trying to reset the QoS agent. This also goes for the partial reset.

Source	Severity
QoS	Critical

Remedial action

Try again later or reset the unit.



Invalid set drop precedence value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid set drop precedence value specified log

Invalid set drop precedence value specified

The drop precedence can have two values, low or high.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and use a valid drop precedence value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid shaping data (bucket size) specified for interface(s) log

Invalid shaping data (bucket size) specified for interface(s)

The shaping bucket size is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the shaping bucket size.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid shaping data (granularity) specified for interface(s) log

Invalid shaping data (granularity) specified for interface(s)

The shaping granularity is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the shaping granularity.



Invalid shaping data (minimum rate granularity) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid shaping data (minimum rate granularity) specified log

Invalid shaping data (minimum rate granularity) specified

The minimum shaping rate granularity is invalid or not supported.

Source	Severity
QoS	Serious

Remedial action

Modify the minimum shaping rate granularity to a valid or supported value.



Invalid shaping data (minimum rate maximum rate) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid shaping data (minimum rate maximum rate) specified log

Invalid shaping data (minimum rate maximum rate) specified

The limits of the shaping rate are not in order; the minimum rate must be lesser than the maximum rate.

Source	Severity
QoS	Serious

Remedial action

Change the shaping rate limits.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid shaping data (minimum rate) specified log

Invalid shaping data (minimum rate) specified

The minimum shaping rate is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the minimum shaping rate.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid shaping data (rate) specified for interface(s) log

Invalid shaping data (rate) specified for interface(s)

The shaping rate is not supported on the current interface.

Source	Severity
QoS	Serious

Remedial action

Change the target interface or modify the shaping rate.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid source MAC address length specified log

Invalid source MAC address length specified

Source MAC address length is greater than 6.

Source	Severity
QoS	Serious

Remedial action

Specify a valid MAC address.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid source MAC address mask length specified log

Invalid source MAC address mask length specified

Source MAC address mask length is greater than 6.

Source	Severity
QoS	Serious

Remedial action

Specify a valid MAC address mask.



Invalid statistics counter identification specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid statistics counter identification specified log

Invalid statistics counter identification specified

The statistics counter identifier provided is invalid.

Source	Severity
QoS	Serious

Remedial action

Enter a valid statistics tracking identifier.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid statistics tracking value log

Invalid statistics tracking value

Invalid policy tracking statistics. The supported types are: individual aggregate or disabled.

Source	Severity
QoS	Serious

Remedial action

Specify a supported policy tracking statistics.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid statistics type value log

Invalid statistics type value

The only valid statistics types are individual and aggregate.

Source	Severity
QoS	Serious

Remedial action

Enter a valid statistics type or ignore option.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid track statistics value specified log

Invalid track statistics value specified

The only valid tracking statistics values are disabled, individual and aggregate.

Source	Severity
QoS	Serious

Remedial action

Assign a valid tracking statistics value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown access assignment entry state encountered (entry state) log

Invalid unknown access assignment entry state encountered (entry state)

Unable to make changes because of an invalid or inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown access element entry state encountered (entry state) log

Invalid unknown access element entry state encountered (entry state)

Unable to make any changes due to of the invalid or inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown action entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown action entry state encountered (entry state) log

Invalid unknown action entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent action entry state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown bandwidth type specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown bandwidth type specified log

Invalid unknown bandwidth type specified

Two bandwidth types are supported: absolute and relative.

Source	Severity
QoS	Serious

Remedial action

Enter a valid bandwidth type.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown classifier block entry state encountered (entry state) log

Invalid unknown classifier block entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown CoS shaping entry state encountered (entry state) log

Invalid unknown CoS shaping entry state encountered (entry state)

Unable to make changes because of an invalid or inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown DSCP mapping entry state encountered (entry state) log

Invalid unknown DSCP mapping entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent DSCP mapping entry state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown entry state (class class#) encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown entry state (class class#) encountered (entry state) log

Invalid unknown entry state (class class#) encountered (entry state)

Unable to make the changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid/unknown FCoE redirection egress trunk ID specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid/unknown FCoE redirection egress trunk ID specified log

Invalid/unknown FCoE redirection egress trunk ID specified

An invalid FCoE redirection trunk ID was specified.

Source	Severity
--------	----------

FCoE Redirect	Information
---------------	-------------

Remedial action

Specify a valid trunk ID.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown interface action entry state encountered (entry state) log

Invalid unknown interface action entry state encountered (entry state)

Unable to make changes because of an invalid state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid/unknown interface app entry state encountered (<entry state>) log

Invalid/unknown interface app entry state encountered (<entry state>)

Unable to make the changes because of an invalid or inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Invalid unknown interface assignment entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown interface assignment entry state encountered (entry state) log

Invalid unknown interface assignment entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unknown interface queue entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown interface queue entry state encountered (entry state) log

Invalid unknown interface queue entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent interface queue entry state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown interface shaping entry state encountered (entry#) log

Invalid unknown interface shaping entry state encountered (entry#)

Unable to make changes because of an invalid or inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try later, reset the QoS agent or reset the unit.



Invalid unknown IP filter entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown IP filter entry state encountered (entry state) log

Invalid unknown IP filter entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown Layer 2 filter entry state encountered (entry state) log

Invalid unknown Layer 2 filter entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown meter entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown meter entry state encountered (entry state) log

Invalid unknown meter entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown policy entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown policy entry state encountered (entry state) log

Invalid unknown policy entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown 802.1p user priority mapping entry state (entry state) log

Invalid unknown 802.1p user priority mapping entry state (entry state)

Unable to make changes because of an invalid/inconsistent 802.1p user priority state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown queue set assignment entry state encountered (entry state) log

Invalid unknown queue set assignment entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown queue shaping entry state encountered (entry state) log

Invalid unknown queue shaping entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown queuing discipline enum specified (queuing discipline)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown queuing discipline enum specified (queuing discipline) log

Invalid unknown queuing discipline enum specified (queuing discipline)

Only the following queuing disciplines are valid: FIFO, Priority Queuing, Fair Queuing, Weighted Fair Queuing and Weighted Round Robin Queuing.

Source	Severity
QoS	Critical

Remedial action

Enter a valid/supported queuing discipline.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown role combination entry state encountered (entry state) log

Invalid unknown role combination entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent role combination state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown System filter entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown System filter entry state encountered (entry state) log

Invalid unknown System filter entry state encountered (entry state)

Invalid entry state detected. Unable to commit changes.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown token bucket entry state encountered (entry state) log

Invalid unknown token bucket entry state encountered (entry state)

Unable to make changes because of an invalid/inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Invalid unknown user policy entry state encountered (entry state)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unknown user policy entry state encountered (entry state) log

Invalid unknown user policy entry state encountered (entry state)

Unable to make the changes because of an invalid or inconsistent state.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported buffering capabilities value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported buffering capabilities value specified log

Invalid unsupported buffering capabilities value specified

The buffering capabilities are not supported.

Source	Severity
QoS	Serious

Remedial action

Check platform documentation and use a compatible buffering setting.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported copy-to-cpu option specified log

Invalid unsupported copy-to-cpu option specified

The copy-to-CPU can have two values, true or false. It's possible that the only supported value for the target entry is false.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and use a valid copy-to-CPU option.



Invalid unsupported DAPP enable value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported DAPP enable value specified log

Invalid unsupported DAPP enable value specified

DAAP can be enabled with or without status.

Source	Severity
QoS	Serious

Remedial action

Specify a valid enable value or disable DAAP.



Invalid unsupported DAPP maximum IPv4 ICMP length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported DAPP maximum IPv4 ICMP length specified log

Invalid unsupported DAPP maximum IPv4 ICMP length specified

The maximum IPv4 ICMP length must be between 0 and 1023.

Source	Severity
QoS	Serious

Remedial action

Enter a valid/supported length in that range.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported DAPP maximum IPv6 ICMP length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported DAPP maximum IPv6 ICMP length specified log

Invalid unsupported DAPP maximum IPv6 ICMP length specified

The maximum Ipv6 ICMP length must be between 0 and 16383.

Source	Severity
QoS	Serious

Remedial action

Enter a valid/supported length in that range.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported DAPP minimum TCP header length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported DAPP minimum TCP header length specified log

Invalid unsupported DAPP minimum TCP header length specified

The minimum TCP header length must be within 0 to 255.

Source	Severity
QoS	Serious

Remedial action

Enter a valid/supported length in the specified range.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported default gateway address length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported default gateway address length specified log

Invalid unsupported default gateway address length specified

The default gateway address length must be 4 (IPv4) and 16 (IPv6).

Source	Severity
QoS	Serious

Remedial action

Specify a valid default gateway address length.



Invalid unsupported default gateway address specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported default gateway address specified log

Invalid unsupported default gateway address specified

The default gateway provided is not a valid interface application IP address.

Source	Severity
QoS	Serious

Remedial action

Specify a valid IP default gateway address.



Invalid unsupported destination IP address length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported destination IP address length specified log

Invalid unsupported destination IP address length specified

Destination address is too short/long.

Source	Severity
QoS	Serious

Remedial action

Enter a proper address with length 4 (ipv4) or 16 (ipv6).

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported DHCP server address length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported DHCP server address length specified log

Invalid unsupported DHCP server address length specified

The DHCP server address length must be 4 (IPv4) and 16 (IPv6).

Source	Severity
QoS	Serious

Remedial action

Specify a valid DHCP server address length.



Invalid unsupported DHCP server address specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported DHCP server address specified log

Invalid unsupported DHCP server address specified

The DHCP address provided is not a valid interface application IP address.

Source	Severity
QoS	Serious

Remedial action

Specify a valid IP DHCP server address.



Invalid unsupported interface type specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported interface type specified log

Invalid unsupported interface type specified

The valid interface types for the interface applications are access and core.

Source	Severity
QoS	Serious

Remedial action

Enter one of the valid interface types.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported mirror frame option specified log

Invalid unsupported mirror frame option specified

The mirror frame option can have two values, true or false. It's possible that the only supported value for the target entry is false.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and use a valid mirror frame option.



Invalid unsupported NT application mode value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported NT application mode value specified log

Invalid unsupported NT application mode value specified

The only supported AutoQoS modes are disabled, pure and mixed.

Source	Severity
QoS	Serious

Remedial action

The only supported AutoQoS modes are disabled, pure and mixed.



Invalid unsupported packet type value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported packet type value specified log

Invalid unsupported packet type value specified

Invalid value specified. Packet-types supported: etherII, IIc, snap.

Source	Severity
QoS	Serious

Remedial action

Specify a supported packet type.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported QoS system operational mode value specified log

Invalid unsupported QoS system operational mode value specified

If the current platform supports QoS system disabled state then the operational mode can be either disabled or enabled. Otherwise the QoS system operational mode can only be enabled.

Source	Severity
QoS	Serious

Remedial action

Specify a supported QoS operational mode regarding the current platform.



Invalid unsupported queue configuration value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported queue configuration value specified log

Invalid unsupported queue configuration value specified

The queue set value must be between 1 and 8.

Source	Severity
QoS	Serious

Remedial action

Specify a queue set value in the range described.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported role assoc compatibility specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported role assoc compatibility specified log

Invalid unsupported role assoc compatibility specified

The supported role association are loose and strict.

Source	Severity
QoS	Serious

Remedial action

Specify a supported/valid role association.



Invalid unsupported source IP address length specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported source IP address length specified log

Invalid unsupported source IP address length specified

Source address is too short/long.

Source	Severity
QoS	Serious

Remedial action

Enter a proper address with length 4 (ipv4) or 16 (ipv6).

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid unsupported Trusted processing mode value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported Trusted processing mode value specified log

Invalid unsupported Trusted processing mode value specified

Trusted processing modes can be partial or full. Any other modes are invalid or unsupported.

Source	Severity
QoS	Serious

Remedial action

Specify a valid trusted processing mode.



Invalid unsupported UBP support level value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported UBP support level value specified log

Invalid unsupported UBP support level value specified

There are 4 user based policies levels supported, the first one being "disabled".

Source	Severity
QoS	Serious

Remedial action

Enter a valid user based policy support.



Invalid unsupported VLAN tag value specified (VLAN tag)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid unsupported VLAN tag value specified (VLAN tag) log

Invalid unsupported VLAN tag value specified (VLAN tag)

Invalid VLAN tag, it must be tagged, untagged or not specified (ignore).

Source	Severity
QoS	Serious

Remedial action

Enter an appropriate VLAN tag (tagged, untagged or ignore).



Invalid update DSCP value specified (DSCP value)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid update DSCP value specified (DSCP value) log

Invalid update DSCP value specified (DSCP value)

The valid DSCP values are between 0 and 63.

Source	Severity
QoS	Information

Remedial action

Enter a valid DSCP value (in the specified range).



Invalid update DSCP value specified (not currently supported)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid update DSCP value specified (not currently supported) log

Invalid update DSCP value specified (not currently supported)

The specified update DSCP value is currently not supported.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and use a supported update DSCP value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid update priority value specified log

Invalid update priority value specified

The only valid update priorities values are between 0 and 7.

Source	Severity
QoS	Serious

Remedial action

Enter a valid update priority value.



Invalid update VLAN Id specified (VLAN Id)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid update VLAN Id specified (VLAN Id) log

Invalid update VLAN Id specified (VLAN Id)

The update VLAN Id must be between 1 and 4094.

Source	Severity
QoS	Serious

Remedial action

Enter a valid update VLAN Id in that range.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Invalid user priority match selection specified (priority value)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Invalid user priority match selection specified (priority value) log

Invalid user priority match selection specified (priority value)

The user priority value must be between 0 and 7 or all.

Source	Severity
QoS	Serious

Remedial action

Enter a valid user priority value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP blocking now 1 2 (1=ON 2=OFF) log

IP blocking now 1 2 (1=ON 2=OFF)

The IP status is blocked on the unit when it leaves a stack.

Source	Severity
L3Mgr	Information

Remedial action

No action required.



IP classifier distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP classifier distribution across stack failed log

IP classifier distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IP classifier entry still referenced (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP classifier entry still referenced (deletion prohibited) log

IP classifier entry still referenced (deletion prohibited)

Cannot delete an ip classifier element if it's referenced in a classifier.

Source	Severity
QoS	Serious

Remedial action

Remove the classifier first.



IP classifier modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP classifier modifications not supported log

IP classifier modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP destination address and mask values out-of-sync log

IP destination address and mask values out-of-sync

The destination address and prefix do not correspond (at least one address bit not included in mask is set).

Source	Severity
QoS	Serious

Remedial action

Modify the address or mask.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP destination Layer 4 port maximum value out-of-range (dest port# log

IP destination Layer 4 port maximum value out-of-range (dest port#

The maximum IP protocol destination port value must be between 0 and 65535.

Source	Severity
QoS	Serious

Remedial action

Enter a valid maximum IP protocol destination port in the range specified.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP destination Layer 4 port minimum value out-of-range (dest port#) log

IP destination Layer 4 port minimum value out-of-range (dest port#)

The minimum IP protocol destination port value must be between 0 and 65535.

Source	Severity
QoS	Serious

Remedial action

Enter a valid minimum IP protocol destination port in the range specified.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPFIX enable failure log

IPFIX enable failure

This message indicates that the task cannot start.

Source	Severity
IPFIX	Information

Remedial action

No action required.



IpFwdNhop Err Filter Install mod_inst=0x%08x vid=%d rv=%d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop Err Filter Install mod_inst=0x%08x vid=%d rv=%d log

IpFwdNhop Err Filter Install mod_inst=0x%08x vid=%d rv=%d

Error when installing policy based routing filter in hardware.

Source

Severity

Source Based Routing

Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IpFwdNhop Err Filter Modify mod_inst=0x%08x vid=%d rv=%d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop Err Filter Modify mod_inst=0x%08x vid=%d rv=%d log

IpFwdNhop Err Filter Modify mod_inst=0x%08x vid=%d rv=%d

Error when modifying policy based routing filter in hardware.

Source

Source Based Routing

Severity

Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop Err Filter UnInstall mod_inst=0x%08x vid=%d rv=%d log

IpFwdNhop Err Filter UnInstall mod_inst=0x%08x vid=%d rv=%d

Error when uninstalling policy based routing filter in hardware.

Source	Severity
Source Based Routing	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop Err Save DB to NVRAM General File myMod=%d isBU=%d rw=%d log

IpFwdNhop Err Save DB to NVRAM General File myMod=%d isBU=%d rw=%d

Error when saving global SBR settings to NVRAM.

Source

Source Based Routing

Severity

Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop Err Save DB to NVRAM Instance File myMod=%d isBU=%d rw=%d log

IpFwdNhop Err Save DB to NVRAM Instance File myMod=%d isBU=%d rw=%d

Error when saving SBR instances to NVRAM.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop Err Save DB to NVRAM Policy File myMod=%d isBU=%d rw=%d log

IpFwdNhop Err Save DB to NVRAM Policy File myMod=%d isBU=%d rw=%d

Error when saving SBR policies to NVRAM.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Feature enable temporarily blocked - resources unavailable log

IpFwdNhop: Feature enable temporarily blocked - resources unavailable

Indicates that the required resources for enabling the SBR feature are not available.

Source	Severity
Source Based Routing	Information

Remedial action

No action required.



IpFwdNhop: Filter installation issue - resources unavailable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Filter installation issue - resources unavailable log

IpFwdNhop: Filter installation issue - resources unavailable

Error when installing policy based routing filter in hardware.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during data restore (interface entry %d) log

IpFwdNhop: Issue detected during data restore (interface entry %d)

Indicates an error when try to install filters for attached policies after boot.

Source	Severity
Source Based Routing	Information

Remedial action

No action required.



IpFwdNhop: Issue detected during enable retry (interface entry %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during enable retry (interface entry %d) log

IpFwdNhop: Issue detected during enable retry (interface entry %d)

Indicates an error when try to install filters for instances missing them.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during feature enable (interface entry %d) log

IpFwdNhop: Issue detected during feature enable (interface entry %d)

Indicates an error when enabling the SBR feature globally (failed installing filter).

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during interface creation (interface entry %d) log

IpFwdNhop: Issue detected during interface creation (interface entry %d)

When create interface event is processed, this indicates a failure when installing the filter for SBR policy.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.



IpFwdNhop: Issue detected during VLAN %d routing status update

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during VLAN %d routing status update log

IpFwdNhop: Issue detected during VLAN %d routing status update

When ip routing enable (per VLAN interface) event is processed, this Indicates a failure when installing the filter for SBR policy.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during VLAN membership addition (VID %d) log

IpFwdNhop: Issue detected during VLAN membership addition (VID %d)

Indicates an error when adding a port to an installed ip-fwd policy.

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.



IpFwdNhop: Issue detected during VLAN membership deletion (VID %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during VLAN membership deletion (VID %d) log

IpFwdNhop: Issue detected during VLAN membership deletion (VID %d)

Indicates an error when deleting a port from an installed ip-fwd policy.

Source

Source Based Routing

Severity

Information

Remedial action

No action required.



IpFwdNhop: Issue detected during VLAN policy association (entry %d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Issue detected during VLAN policy association (entry %d) log

IpFwdNhop: Issue detected during VLAN policy association (entry %d)

Indicates an error when attaching a SBR policy to a VLAN (failed installing filter).

Source	Severity
--------	----------

Source Based Routing	Information
----------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Requested precedence and/or filter resources unavailable log

IpFwdNhop: Requested precedence and/or filter resources unavailable

Indicates that no valid precedence values are available.

Source	Severity
Source Based Routing	Information

Remedial action

No action required.



IpFwdNhop: Requested range checking resources unavailable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: Requested range checking resources unavailable log

IpFwdNhop: Requested range checking resources unavailable

Indicates that range check resources are not available.

Source	Severity
Source Based Routing	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IpFwdNhop: VLAN membership update (VID %d) issue - resources unavailable log

IpFwdNhop: VLAN membership update (VID %d) issue - resources unavailable

When a VLAN membership update event is processed, this indicates that the required resources for port addition are not available.

Source	Severity
Source Based Routing	Information

Remedial action

No action required.



IP protocol value out-of-range (IP protocol#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP protocol value out-of-range (IP protocol#) log

IP protocol value out-of-range (IP protocol#)

The IP protocol must be between 0 and 255.

Source	Severity
QoS	Serious

Remedial action

Enter a valid IP protocol value.



IP protocol value TCP or UDP needed with Layer 4 port filtering

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP protocol value TCP or UDP needed with Layer 4 port filtering log

IP protocol value TCP or UDP needed with Layer 4 port filtering

Port filtering can only be used with TCP or UDP protocols.

Source	Severity
QoS	Information

Remedial action

Specify the IP protocol to avoid any confusions.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPSG Insufficient resources available to enable IPSG on port unit# port# log

IPSG Insufficient resources available to enable IPSG on port unit# port#

There are not enough resources available to enable the IPSG on the specified port.

Source	Severity
ipsg	Information

Remedial action

Verify Qos masks and filter usage using the command:

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IPSG Maximum IP entries on port unit# port# has been reached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPSG Maximum IP entries on port unit# port# has been reached log

IPSG Maximum IP entries on port unit# port# has been reached

Maximum IP entries on port has been reached.

Source	Severity
IPSG	Information

Remedial action

Scale down the number of IP entries on port.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPSG nvRam file error param1 param2 param3 log

IPSG nvRam file error param1 param2 param3

The system detected an error while trying to access the IPSG NVRAM file param1=0 (open error), param1=1 (write error), param1=2 (read error).

Source	Severity
ipsg	Information

Remedial action

Retry again and if it fails, then reboot the switch.



IPSG Reached Max. IP entries supported on this port port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPSG Reached Max. IP entries supported on this port port# log

IPSG Reached Max. IP entries supported on this port port#

The port reached the maximum number of IP entries.

Source	Severity
ipsg	Information

Remedial action

Scale down the number of IPSG clients.



IPSG Reached Max. IP entries supported on this port unit# port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPSG Reached Max. IP entries supported on this port unit# port# log

IPSG Reached Max. IP entries supported on this port unit# port#

The unit/port reached the maximum number of IP entries.

Source	Severity
ipsg	Information

Remedial action

Scale down the number of IPSG clients.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPSG Resource allocated for Ports unit# port# log

IPSG Resource allocated for Ports unit# port#

The resources necessary for the specified ports cannot be allocated by the QoS application.

Source	Severity
ipsg	Information

Remedial action

Retry and if it fails, then reboot the switch.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP source address and mask values out-of-sync log

IP source address and mask values out-of-sync

The source address and prefix do not correspond (at least one bit not included in mask is set).

Source	Severity
QoS	Serious

Remedial action

Modify the address or mask.



IP Source Guard disabled on Unit unit# Port port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP Source Guard disabled on Unit unit# Port port# log

IP Source Guard disabled on Unit unit# Port port#

The IP Source Guard has been disabled on the specified Unit Port.

Source	Severity
ipsg	Information

Remedial action

No action required.



IP Source Guard enabled on Unit unit# Port port#

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP Source Guard enabled on Unit unit# Port port# log

IP Source Guard enabled on Unit unit# Port port#

The IP Source Guard has been enabled on the specified Unit Port.

Source	Severity
ipsg	Information

Remedial action

No action required.



IP source Layer 4 port minimum value out-of-range (src port#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP source Layer 4 port minimum value out-of-range (src port#) log

IP source Layer 4 port minimum value out-of-range (src port#)

The minimum IP protocol source port value must be between 0 and 65535.

Source	Severity
QoS	Serious

Remedial action

Enter a valid minimum IP protocol source port in the range specified.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IP source Layer 4 port minimum value out-of-range (src port#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IP source Layer 4 port minimum value out-of-range (src port#) log

IP source Layer 4 port minimum value out-of-range (src port#)

The minimum IP protocol source port value must be between 0 and 65535.

Source	Severity
QoS	Serious

Remedial action

Enter a valid minimum IP protocol source port in the range specified.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IPT BootP Disabled (response not received from server)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPT BootP Disabled (response not received from server) log

IPT BootP Disabled (response not received from server)

This message appears when the BootP mode is disabled after the stack is reset and for 10 minutes no BootP/DHCP messages are received (DUT stops sending BootP Requests).

Source	Severity
IPT	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IPT IP Address changed by BOOTP Server

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPT IP Address changed by BOOTP Server log

IPT IP Address changed by BOOTP Server

The switch or the stack has received the IP address from the BOOTP Server.

Source	Severity
IPT	Information

Remedial action

No action required.



IPT: IP Address not in use (duplicate detected)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPT: IP Address not in use (duplicate detected) log

IPT: IP Address not in use (duplicate detected)

The IP address configured on the management VLAN was also found configured on another unit in the network.

Source	Severity
Inband IP address	Information

Remedial action

Use different IP addresses.



IPv6 enabled with hardware support and FMGR filters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv6 enabled with hardware support and FMGR filters log

IPv6 enabled with hardware support and FMGR filters

IPv6 enabled with hardware support and FMGR filters.

Source	Severity
IPv6	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IPv6 enabled with hardware support only

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv6 enabled with hardware support only log

IPv6 enabled with hardware support only

IPv6 enabled with hardware support only.

Source	Severity
IPv6	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



IPv6 Forwarding disabled due to inadequate license

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv6 Forwarding disabled due to inadequate license log

IPv6 Forwarding disabled due to inadequate license

The IPV6 Forwarding mode is automatically disabled as there is no valid license.

Source	Severity
IPV6	Information

Remedial action

Install a valid license and enable the IPV6 forwarding.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv6 malloc failure log

IPv6 malloc failure

IPv6 malloc failure.

Source	Severity
IPv6	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

IPv4-only filter criteria mixed with IPv6 criteria log

IPv4-only filter criteria mixed with IPv6 criteria

Ipv4 and IPv6 fields detected in the same filter.

Source	Severity
QoS	Serious

Remedial action

Separate IPv4 and Ipv6 options in two filters.



Issue detected during QoS stack synchronization

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue detected during QoS stack synchronization log

Issue detected during QoS stack synchronization

Delays are exhausted and the stack synchronization could not be verified.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue detected enabling/disabling DSCP Mapping Table usage (port %d) log

Issue detected enabling/disabling DSCP Mapping Table usage (port %d)

Unable to enable/disable usage of the DSCP Mapping table for the port number displayed in the log message.

Source	Severity
QoS Agent	Serious

Remedial action

Reset device and retry.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue detected enabling disabling DSCP table usage (port#) log

Issue detected enabling disabling DSCP table usage (port#)

" Failed to set on the specified interface the port mode for usage of the global DSCP mapping table. "

Source	Severity
QoS	Information

Remedial action

Try again later, reset the QoS agent or reset the unit.



Issue detected restoring QPA data from NV (class class#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue detected restoring QPA data from NV (class class#) log

Issue detected restoring QPA data from NV (class class#)

Unable to restore the QPA data from NVRAM (possible corrupt table(s)).

Source	Severity
QoS	Critical

Remedial action

Reset the QoS agent or reset the unit.



Issue detected setting native DSCP Mapping Table values

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue detected setting native DSCP Mapping Table values log

Issue detected setting native DSCP Mapping Table values

Unable to update settings in the DSCP Mapping table.

Source	Severity
QoS Agent	Serious

Remedial action

Reset device and retry.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue detected setting native DSCP table values log

Issue detected setting native DSCP table values

Unable to set the native/default DSCP table values.

Source	Severity
QoS	Information

Remedial action

Reset the QoS agent or reset the unit.



Issues detected with QoS operational mode disable (ifcs# ifcs)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issues detected with QoS operational mode disable (ifcs# ifcs) log

Issues detected with QoS operational mode disable (ifcs# ifcs)

Unable to make changes (disable QoS) because of the specified interface configuration.

Source	Severity
QoS	Critical

Remedial action

Check log for possible related details on the issue for and remove the conflicting configurations.



Issues detected with QoS operational mode enable (ifcs# ifcs)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issues detected with QoS operational mode enable (ifcs# ifcs) log

Issues detected with QoS operational mode enable (ifcs# ifcs)

Unable to make changes (enable QoS) because of the specified interface configuration.

Source	Severity
QoS	Critical

Remedial action

Check log for possible related details on the issue and remove the conflicting configurations.



Issue with classifier component mask detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Issue with classifier component mask detected log

Issue with classifier component mask detected

Unable to create the classifier data mask structure form the classifier data provided.

Source	Severity
QoS	Serious

Remedial action

Identify and separate the conflicting elements into multiple classifier blocks.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

JOIN event sent unit mask value appl mask value log

JOIN event sent unit mask value appl mask value

The Join event is sent during the stack formation process.

Source	Severity
Stack Manager	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC MLT error on far end. 0 - 0 - 0 log

LAC MLT error on far end. 0 - 0 - 0

The LACP link is selected by the system, but not participating in traffic rx/tx.

Source	Severity
LAC	Information

Remedial action

Check LACP settings on both sides. Disable/re-enable LACP on ports.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC: MLT error, partner aggregation bit not set log

LAC: MLT error, partner aggregation bit not set

The LACP link is selected by the system, but not participating in the traffic rx/tx because the partner port is marked as not aggregable.

Source	Severity
LACP	Information

Remedial action

Check LACP settings on both sides. Disable/re-enable LACP on ports.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC: MLT error, partner expired bit set. log

LAC: MLT error, partner expired bit set.

The LACP link is selected by the system, but not participating in the traffic rx/tx because the partner port is marked as expired.

Source	Severity
LACP	Information

Remedial action

Check LACP settings on both sides. Disable/re-enable LACP on ports.



LAC: MLT error, partner synchronization bit not set.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC: MLT error, partner synchronization bit not set. log

LAC: MLT error, partner synchronization bit not set.

The LACP link is selected by the system, but not participating in the traffic rx/tx because the partner port is marked as not synchronized.

Source	Severity
LACP	Information

Remedial action

Check LACP settings on both sides. Disable/re-enable LACP on ports.



LAC No more trunk group available for LAC. 0 - 0 - 0

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC No more trunk group available for LAC. 0 - 0 - 0 log

LAC No more trunk group available for LAC. 0 - 0 - 0

All trunk group IDs are already allocated.

Source	Severity
LAC	Information

Remedial action

Check if an unnecessary trunk ID is used.



LAC with admin key %d failed configuration verification. Bad ARP INSPECTION configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad ARP INSPECTION configuration. log

LAC with admin key %d failed configuration verification. Bad ARP INSPECTION configuration.

ARP-Inspection configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check ARP-Inspection config and set the same ARP-Inspection parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LAC with admin key %d failed configuration verification. Bad DHCP-SNOOPING configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad DHCP-SNOOPING configuration. log

LAC with admin key %d failed configuration verification. Bad DHCP-SNOOPING configuration.

DHCP-snooping configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check DHCP-snooping configuration and set the same DHCP-snooping parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LAC with admin key %d failed configuration verification. Bad IGMP configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad IGMP configuration. log

LAC with admin key %d failed configuration verification. Bad IGMP configuration.

IGMP configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check IGMP configuration and set the same IGMP parameters for all trunk members.



LAC with admin key %d failed configuration verification. Bad MAC Security configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad MAC Security configuration. log

LAC with admin key %d failed configuration verification. Bad MAC Security configuration.

MAC Security configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check MAC Security configuration and set the same MAC Security parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LAC with admin key %d failed configuration verification. Bad qos status.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad qos status. log

LAC with admin key %d failed configuration verification. Bad qos status.

QOS status is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check QOS status and set the same QOS status for all trunk members.



LAC with admin key %d failed configuration verification. Bad rate-limiting configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad rate-limiting configuration. log

LAC with admin key %d failed configuration verification. Bad rate-limiting configuration.

Rate-limiting configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check Rate-limiting configuration and set the same Rate-limiting parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LAC with admin key %d failed configuration verification. Bad VLAN configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Bad VLAN configuration. log

LAC with admin key %d failed configuration verification. Bad VLAN configuration.

VLAN configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check VLAN config and set the same VLAN parameters for all trunk members.



LAC with admin key %d failed configuration verification. Error #: %d-%d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Error #: %d-%d log

LAC with admin key %d failed configuration verification. Error #: %d-%d

An error not covered by other LAC inconsistency logs.

Source	Severity
LACP	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LAC with admin key %d failed configuration verification. Ports have different qos config.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification. Ports have different qos config. log

LAC with admin key %d failed configuration verification. Ports have different qos config.

QOS configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check QOS configuration and set the same QOS parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LAC with admin key %d failed configuration verification.Ports have different SPBM configurations.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LAC with admin key %d failed configuration verification.Ports have different SPBM configurations. log

LAC with admin key %d failed configuration verification.Ports have different SPBM configurations.

SPBM configuration is not consistent on all trunk members.

Source	Severity
LACP	Information

Remedial action

Check SPBM configuration and set the same SPBM parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Last MLT trunk was allocated by LAC.
No more free trunk groups.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Last MLT trunk was allocated by LAC. No more free trunk groups. log

Last MLT trunk was allocated by LAC. No more free trunk groups.

The last free trunk group was allocated by a dynamic LAC.

Source	Severity
MLT	Information

Remedial action

Free a trunk group no longer in need to be able to allocate another MLT trunk group.



Last MLT trunk was allocated by MLT.
No more free trunk groups.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Last MLT trunk was allocated by MLT. No more free trunk groups. log

Last MLT trunk was allocated by MLT. No more free trunk groups.

The last free trunk group was allocated by a static MLT.

Source	Severity
MLT	Information

Remedial action

Free a trunk group no longer in need to be able to allocate another MLT trunk group.



Layer 2 classifier modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Layer 2 classifier modifications not supported log

Layer 2 classifier modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Layer 2 classifier still referenced (deletion prohibited) log

Layer 2 classifier still referenced (deletion prohibited)

Cannot delete a classifier if it is referenced in a classifier-block or policy.

Source	Severity
QoS	Serious

Remedial action

Remove the classifier-block/policy first.



Layer 2 filter distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Layer 2 filter distribution across stack failed log

Layer 2 filter distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Layer 4 port filtering with IPv6 requires UDP TCP Next Header log

Layer 4 port filtering with IPv6 requires UDP TCP Next Header

Port filtering is supported only for TCP and UDP protocols.

Source	Severity
QoS	Serious

Remedial action

Specify next header: 6 for TCP or 17 for UDP or drop port filtering usage.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Layer 4 port range could not be reduced sufficiently log

Layer 4 port range could not be reduced sufficiently

The port range could not be reduce sufficiently for it's installation to be supported.

Source	Severity
QoS	Serious

Remedial action

Modify the port range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LEAVE event sent unit mask value appl mask value log

LEAVE event sent unit mask value appl mask value

The unit on which this message is logged has left the stack. The 'unit mask' is a bit mask representation of the unit that left the stack.

Source	Severity
Stack Manager	Information

Remedial action

Make sure that the unit removal is intended.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Link Down Trap log

Link Down Trap

Link Down.

Source	Severity
--------	----------

IFMGR, SNMP	Information
-------------	-------------

Remedial action

No action required.



LinkStateTracking: First interface %d/d
went up in link state group %d,
enabling downstream ports

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: First interface %d/d went up in link state group %d, enabling downstream ports log

LinkStateTracking: First interface %d/d went up in link state group %d, enabling downstream ports

The first upstream interface went up, downstream ports are enabled.

Source

Severity

Link State Tracking

Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



LinkStateTracking: First interface mlt %d went up in link state group %d, enabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: First interface mlt %d went up in link state group %d, enabling downstream interfaces log

LinkStateTracking: First interface mlt %d went up in link state group %d, enabling downstream interfaces

The first upstream interface (trunk) switches state to 'up' from 'down' state. LST group transitions to 'up' operational state.

Source

Severity

Link State Tracking

Information

Remedial action

No action required.



LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces log

LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces

Issued when all upstream interfaces are in down state and one (port) switches state to up. This marks a LST group transition to up operational state.

Source

Link State Tracking

Severity

Information

Remedial action

No action required.



LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces log

LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces

Issued when all upstream interfaces are in down state and one (trunk) switches state to up. This marks a LST group transition to up operational state.

Source

Link State Tracking

Severity

Information

Remedial action

No action required.



LinkStateTracking: Interface %d/d went down in link state group %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Interface %d/d went down in link state group %d log

LinkStateTracking: Interface %d/d went down in link state group %d

One upstream member (port) switches state to 'down', without affecting the LST group operational state.

Source	Severity
--------	----------

Link State Tracking	Information
---------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Interface %d/d went up in link state group %d log

LinkStateTracking: Interface %d/d went up in link state group %d

One upstream member (port) switches state to 'up', without affecting the LST group operational state.

Source	Severity
--------	----------

Link State Tracking	Information
---------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Interface mlt %d went down in link state group %d log

LinkStateTracking: Interface mlt %d went down in link state group %d

One upstream member (trunk) switches state to 'down', without affecting the LST group operational state.

Source	Severity
--------	----------

Link State Tracking	Information
---------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Interface mlt %d went up in link state group %d log

LinkStateTracking: Interface mlt %d went up in link state group %d

One upstream member (trunk) switches state to 'up', without affecting the LST group operational state.

Source	Severity
--------	----------

Link State Tracking	Information
---------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Interface %s went down in link state group %d log

LinkStateTracking: Interface %s went down in link state group %d

Issued when one upstream member (port) switches state to

Source	Severity
--------	----------

Link State Tracking	Information
---------------------	-------------

Remedial action

No action required.



LinkStateTracking: Interface %s went up in link state group %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Interface %s went up in link state group %d log

LinkStateTracking: Interface %s went up in link state group %d

Issued when one upstream member (port) switches state to

Source	Severity
--------	----------

Link State Tracking	Information
---------------------	-------------

Remedial action

No action required.



LinkStateTracking: Last interface %d/d went down in link state group %d, disabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Last interface %d/d went down in link state group %d, disabling downstream interfaces log

LinkStateTracking: Last interface %d/d went down in link state group %d, disabling downstream interfaces

The last upstream interface (port) with an 'up' state switches to 'down' state. LST group transitions to 'down' operational state.

Source

Severity

Link State Tracking

Information

Remedial action

No action required.



LinkStateTracking: Last interface mlt %d went down in link state group %d, disabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Last interface mlt %d went down in link state group %d, disabling downstream interfaces log

LinkStateTracking: Last interface mlt %d went down in link state group %d, disabling downstream interfaces

The last upstream interface (trunk) with an 'up' state switches to 'down' state. LST group transitions to 'down' operational state.

Source

Severity

Link State Tracking

Information

Remedial action

No action required.



LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces log

LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces

Issued when the last upstream interface (port) with an up state switches to downstate. This marks a LST group transition to down operational state.

Source

Link State Tracking

Severity

Information

Remedial action

No action required.



LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces log

LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces

Issued when the last upstream interface (trunk) with an up state switches to downstate. This marks a LST group transition to down operational state.

Source

Link State Tracking

Severity

Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Link Up Trap log

Link Up Trap

Link up.

Source	Severity
--------	----------

IFMGR, SNMP	Information
-------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Loading configuration block # block_number log

Loading configuration block # block_number

This message appears when the configuration is loaded from block n.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Local authentication disabled on serial log

Local authentication disabled on serial

Authentication on serial port using local credentials has been disabled.

Source	Severity
CLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Local authentication disabled on telnet log

Local authentication disabled on telnet

Authentication over telnet using local credentials has been disabled.

Source	Severity
CLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Local authentication enabled on serial log

Local authentication enabled on serial

Authentication on serial port using local credentials has been enabled.

Source	Severity
CLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Local authentication enabled on telnet log

Local authentication enabled on telnet

Authentication over telnet using local credentials has been enabled.

Source	Severity
CLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Login timeout serial connection log

Login timeout serial connection

The serial connection login prompt message is available for the user input for one minute with maximum of three attempts, if you fail to login the product banner is displayed.

Source	Severity
Console	Information

Remedial action

Enter a valid username and password within a minute.



Lossless and Lossless-PFC modes are only supported in queue set 2

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Lossless and Lossless-PFC modes are only supported in queue set 2 log

Lossless and Lossless-PFC modes are only supported in queue set 2

Lossless and Lossless-PFC modes are only supported in queue set 2.

Source	Severity
QOS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MAC security table full log

MAC security table full

The MAC security table is full.

Source	Severity
Bay secure	Information

Remedial action

No action required.



MAC

%02x:%02x:%02x:%02x:%02x:%02x
not authenticated; only one client is
allowed in MHSA mode

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MAC %02x:%02x:%02x:%02x:%02x:%02x not authenticated; only one client is allowed in MHSA mode log

MAC %02x:%02x:%02x:%02x:%02x:%02x not authenticated; only one client is allowed in MHSA mode

MHSA mode only allows one user to be authenticated

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Management IP: excess traffic received on Management port%s log

Management IP: excess traffic received on Management port%s

Excess traffic received on the management port. The port is down.

Source	Severity
PDT	Serious

Remedial action

Take notice of excess traffic and restart the port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Management IP: OOB port%s log

Management IP: OOB port%s

Management port is down.

Source	Severity
PDT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Management IP: OOB port%s log

Management IP: OOB port%s

Management port is up.

Source	Severity
PDT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Maximum number of dynamic routes reached log

Maximum number of dynamic routes reached

The maximum number of total routes (static or dynamic) supported on the platform are reached.

Source	Severity
L3Mgr	Information

Remedial action

Reconfigure the network so that the routes on the ERS device remain within the maximum allowed.



MCM group node corrupted:

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MCM group node corrupted: log

MCM group node corrupted:

The multicast manager group note is corrupted.

Source	Severity
Multicast manager	Critical

Remedial action

No action Required

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Memory Allocation Error log

Memory Allocation Error

The system failed to get memory buffer.

Source	Severity
Console	Serious

Remedial action

Report the error.



Memory on unit %d is under %d MBytes.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Memory on unit %d is under %d MBytes. log

Memory on unit %d is under %d MBytes.

The system memory has dropped under a certain value.

Source	Severity
Memory Tool	Critical

Remedial action

Call Avaya to collect memory information. Monitor free memory and prepare for rebooting the device if the memory continues to drop.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter distribution across stack failed log

Meter distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.



Meter entry referenced by clfr block (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter entry referenced by clfr block (deletion prohibited) log

Meter entry referenced by clfr block (deletion prohibited)

Cannot delete a meter if it's referenced in a classifier block.

Source	Severity
QoS	Serious

Remedial action

Remove the classifier block first.



Meter entry referenced by meter (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter entry referenced by meter (deletion prohibited) log

Meter entry referenced by meter (deletion prohibited)

Cannot delete a meter if it's referenced by another.

Source	Severity
QoS	Serious

Remedial action

Delete the other meter first.



Meter entry referenced by policy (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter entry referenced by policy (deletion prohibited) log

Meter entry referenced by policy (deletion prohibited)

Cannot delete a meter if it's referenced by a policy.

Source	Severity
QoS	Serious

Remedial action

Remove the policy first.



Meter (from clfr block) usage in multiple policies prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter (from clfr block) usage in multiple policies prohibited log

Meter (from clfr block) usage in multiple policies prohibited

The meter specified in classifier block is already used by a policy.

Source	Severity
QoS	Serious

Remedial action

Specify a different meter/classifier block, create a new one or remove the conflicting policy.



Meter (from policy) usage in multiple policies prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter (from policy) usage in multiple policies prohibited log

Meter (from policy) usage in multiple policies prohibited

The meter specified is already used by a policy.

Source	Severity
QoS	Serious

Remedial action

Specify a different meter, create a new one or remove the conflicting policy.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter identifier out-of-range (meter id) log

Meter identifier out-of-range (meter id)

If it is a user entry the meter identifier must be between 1 and 55000. For a system entry the range is 55001-65535.

Source	Severity
QoS	Serious

Remedial action

Enter a valid meter identifier.



Metering not supported with DS L2 access control lists

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Metering not supported with DS L2 access control lists log

Metering not supported with DS L2 access control lists

Metering is not supported for ACLs DS(IP) or L2.

Source	Severity
QoS	Serious

Remedial action

Enter DS/L2 classifier element or drop metering option.



Meter modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Meter modifications not supported log

Meter modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Mirroring (requested via action) not configured correctly

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Mirroring (requested via action) not configured correctly log

Mirroring (requested via action) not configured correctly

The metering is not configured correctly.

Source	Severity
QoS	Serious

Remedial action

Inspect and correct the necessary entries, check documentation if necessary.



MLD: Maximum number of mld enabled interfaces reached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLD: Maximum number of mld enabled interfaces reached log

MLD: Maximum number of mld enabled interfaces reached

Maximum number of MLD enabled interfaces reached.

Source	Severity
MLD	Information

Remedial action

No action required.



MLD: The maximum number of available hardware MLD entries has been reached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLD: The maximum number of available hardware MLD entries has been reached log

MLD: The maximum number of available hardware MLD entries has been reached

Ipmc entries exceeded.

Source	Severity
MLD	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLD: The maximum number of available hardware MLD entries has been reached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLD: The maximum number of available hardware MLD entries has been reached log

MLD: The maximum number of available hardware MLD entries has been reached

The maximum number of available hardware MLD entries has been reached.

Source	Severity
MLD	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT %d failed configuration verification.
Bad ARP INSPECTION configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad ARP INSPECTION configuration. log

MLT %d failed configuration verification. Bad ARP INSPECTION configuration.

ARP INSPECTION config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check ARP INSPECTION config and set the same ARP INSPECTION parameters for all trunk members.



MLT %d failed configuration verification.
Bad DHCP-SNOOPING configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad DHCP-SNOOPING configuration. log

MLT %d failed configuration verification. Bad DHCP-SNOOPING configuration.

DHCP-SNOOPING config is not consistent on all trunk members for the MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check DHCP-SNOOPING config and set the same DHCP-SNOOPING parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT %d failed configuration verification.
Bad IGMP configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad IGMP configuration. log

MLT %d failed configuration verification. Bad IGMP configuration.

IGMP config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check IGMP config and set the same IGMP parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT %d failed configuration verification.
Bad IPSG CLASS configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad IPSG CLASS configuration. log

MLT %d failed configuration verification. Bad IPSG CLASS configuration.

IPSG config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check IPSG CLASS config and set the same IPSG CLASS parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT %d failed configuration verification.
Bad MAC learning configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad MAC learning configuration. log

MLT %d failed configuration verification. Bad MAC learning configuration.

Mac-learning config is not consistent on all trunk members.

Source	Severity
MLT	Information

Remedial action

Check MAC-learning config and set the same MAC-learning parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT %d failed configuration verification.
Bad rate-limiting configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad rate-limiting configuration. log

MLT %d failed configuration verification. Bad rate-limiting configuration.

Rate-limit config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check rate-limit config and set the same rate-limit parameters for all trunk members.



MLT %d failed configuration verification.
Bad SPBM configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad SPBM configuration. log

MLT %d failed configuration verification. Bad SPBM configuration.

SPBM config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check SPBM config and set the same SPBM parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT %d failed configuration verification. Bad VLACP configuration

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad VLACP configuration log

MLT %d failed configuration verification. Bad VLACP configuration

VLACP config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check VLACP config and set the same VLACP parameters for all trunk members.



MLT %d failed configuration verification.
Bad VLAN configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT %d failed configuration verification. Bad VLAN configuration. log

MLT %d failed configuration verification. Bad VLAN configuration.

VLAN config is not consistent on all trunk members for the displayed MLT trunk number.

Source	Severity
MLT	Information

Remedial action

Check VLAN config and set the same VLAN parameters for all trunk members.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



MLT ID# failed configuration verification. Error # error num

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT ID# failed configuration verification. Error # error num log

MLT ID# failed configuration verification. Error # error num

The MLT #(1-32) verification check failed.

Source	Severity
MLT	Information

Remedial action

Change the configuration and re-enable the MLT.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MLT NV File error log

MLT NV File error

The system failed to read or write to the NVRAM file.

Source	Severity
MLT	Information

Remedial action

Run the diagnostics to see if the NVRAM is still correct.



Modification of action (non-match usage) prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Modification of action (non-match usage) prohibited log

Modification of action (non-match usage) prohibited

The action can not be modified currently as it is associated with a policy and not an individual classifier.

Source	Severity
QoS	Serious

Remedial action

Remove the policy or create a new action.



Modify the pattern data or use the correct data format

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Modify the pattern data or use the correct data format log

Modify the pattern data or use the correct data format

UnknownIpMcast attribute must be true or false. QPA internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

MODULE_INACTIVE event sent unit mask value appl mask value log

MODULE_INACTIVE event sent unit mask value appl mask value

A unit has left the stack. The 'unit mask' is a bit mask representation of the unit that left the stack.

Source	Severity
Stack Manager	Information

Remedial action

Make sure that the unit removal is intended.



More than value units discovered

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

More than value units discovered log

More than value units discovered

Too many units are in the stack.

Source	Severity
Stack Manager	Information

Remedial action

Remove the extra unit(s).

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Multiple base units detected log

Multiple base units detected

The system detected more than one configured base unit.

Source	Severity
Stack Manager	Information

Remedial action

Reconfigure the extra base unit(s) to non-base units.



Multiple Waverunner units detected when base is a Flagship

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Multiple Waverunner units detected when base is a Flagship log

Multiple Waverunner units detected when base is a Flagship

Too many ERS56XX units are in stack.

Source	Severity
Stack Manager	Information

Remedial action

Remove the extra 56XX unit(s) or make 56XX the base unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NEAP Accounting - Memory allocation failure log

NEAP Accounting - Memory allocation failure

A NEAP accounting packet could not be allocated.

Source	Severity
EAP	Serious

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Network access settings for FCoE Redirect must be modified locally log

Network access settings for FCoE Redirect must be modified locally

Enable/disable of FCoE Redirect functionality limited to CLI.

Source	Severity
FCoE Redirect	Information

Remedial action

Utilize CLI for feature enable/disable.



Non-EAP Client blocked (Block Subsequent MAC Authentication): Different VID than expected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-EAP Client blocked (Block Subsequent MAC Authentication): Different VID than expected log

Non-EAP Client blocked (Block Subsequent MAC Authentication): Different VID than expected

A Non-EAP client was blocked because it had a different Radius Assigned VLAN than the previous one

Source	Severity
EAP	Information

Remedial action

Check the Attributes sent by RADIUS Server.



Non-EAP Client blocked (Block Subsequent MAC Authentication): EAP Use Rav Not enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-EAP Client blocked (Block Subsequent MAC Authentication): EAP Use Rav Not enabled log

Non-EAP Client blocked (Block Subsequent MAC Authentication): EAP Use Rav Not enabled

An EAP client was blocked because Non-EAP Radius Assigned VLAN is not enabled

Source	Severity
EAP	Information

Remedial action

Check the Attributes sent by RADIUS Server.



Non-match action contains conflicting data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-match action contains conflicting data log

Non-match action contains conflicting data

Unable to install the specified non-match action, conflicting data detected.

Source	Severity
QoS	Serious

Remedial action

Identify conflicts and separate them into different non-match actions.



Non-match action not available for use with filter sets

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-match action not available for use with filter sets log

Non-match action not available for use with filter sets

The non-match action drop must be deferred for access assign type NSNA, user based policy and traffic profile.

Source	Severity
QoS	Serious

Remedial action

Remove the non-match action option.



Non-match action support not available on certain interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-match action support not available on certain interfaces log

Non-match action support not available on certain interfaces

Non-match actions can only be applied to certain interfaces.

Source	Severity
QoS	Serious

Remedial action

Specify a compatible interface or drop the non-match action.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Non-QoS interfaces may not be assigned to a role combination

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-QoS interfaces may not be assigned to a role combination log

Non-QoS interfaces may not be assigned to a role combination

Interface type is prohibited. For example cascade (internal) ports should not be associated with a roleCombination since classification is prohibited on these interfaces.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Enter an interface compatible with QoS.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Non-supported action option (green action) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (green action) specified log

Non-supported action option (green action) specified

Action criteria or storage type is not compatible with the action criteria type specified (green action).

Source	Severity
QoS	Serious

Remedial action

Enter a compatible action.



Non-supported action option (in-profile action) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (in-profile action) specified log

Non-supported action option (in-profile action) specified

Failed to validate the in-profile action that is associated. Certain actions may be required or forbidden.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid in-profile action.



Non-supported action option (match action) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (match action) specified log

Non-supported action option (match action) specified

Failed to validate the match action that is associated. Certain actions may be required or forbidden.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid match action.



Non-supported action option (out-of-profile action) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (out-of-profile action) specified log

Non-supported action option (out-of-profile action) specified

Failed to validate the out-of-profile action that is associated. Certain actions may be required or forbidden.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid out-of-profile action.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (policy non-match action) specified log

Non-supported action option (policy non-match action) specified

Failed to validate the non-match action that is associated. Certain actions may be required or forbidden.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid non-match action.



Non-supported action option (red action) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (red action) specified log

Non-supported action option (red action) specified

Action criteria or storage type is not compatible with the action criteria type specified (red action).

Source	Severity
QoS	Serious

Remedial action

Enter a compatible action.



Non-supported action option (yellow action) specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-supported action option (yellow action) specified log

Non-supported action option (yellow action) specified

Action criteria or storage type is not compatible with the action criteria type specified (yellow action).

Source	Severity
QoS	Serious

Remedial action

Enter a compatible action.



Non-unique element label detected (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-unique element label detected (prohibited) log

Non-unique element label detected (prohibited)

The same label is used to identify a different entry of the same type.

Source	Severity
QoS	Information

Remedial action

Enter a different label.



Non-unique precedence order value detected (prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-unique precedence order value detected (prohibited) log

Non-unique precedence order value detected (prohibited)

There is already an existing mask on the specified precedence on the current interface.

Source	Severity
QoS	Serious

Remedial action

Enter a different precedence/interface or remove the conflicting mask.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-volatile QoS data discarded during restoration log

Non-volatile QoS data discarded during restoration

Certain QoS data was discarded (possible because of an upgrade).

Source	Severity
QoS	Serious

Remedial action

Check the QoS data and complete it manually.



Non-volatile storage commit delay too large

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Non-volatile storage commit delay too large log

Non-volatile storage commit delay too large

The maximum non-volatile storage commit delay is 604800.

Source	Severity
QoS	Serious

Remedial action

Enter a smaller commit delay value.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



No resources available for classifier port range checking

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

No resources available for classifier port range checking log

No resources available for classifier port range checking

The resources required are not available on all the ports in the specified range.

Source	Severity
QoS	Serious

Remedial action

Modify either the port range or the demanding resources.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

No Response from RADIUS Server log

No Response from RADIUS Server

FailOpenVLAN Continuity mode was triggered because there was no response from Radius for a MAC address of a certain client.

Source	Severity
Radius	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Not Enough Memory log

Not Enough Memory

This message appears when there is not enough buffer

Source	Severity
Console	Serious

Remedial action

Report the error.



Notice: DAC Cable on %s is below HW rev "H" and may cause link issues with a small number of PHYs

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Notice: DAC Cable on %s is below HW rev "H" and may cause link issues with a small number of PHYs log

Notice: DAC Cable on %s is below HW rev "H" and may cause link issues with a small number of PHYs

Informs the user that he has inserted an outdated HW revision DAC.

Source	Severity
PDT	Information

Remedial action

Replace with DAC that has HW Revision "H" or above.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



NT application mode enable failure - inadequate resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NT application mode enable failure - inadequate resources log

NT application mode enable failure - inadequate resources

The required resources for AutoQos to become enable are not available.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded resources and try again.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Number of VLANs does not match BU
number of VLANs. VLAN config
defaulted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Number of VLANs does not match BU number of VLANs. VLAN config defaulted log

Number of VLANs does not match BU number of VLANs. VLAN config defaulted

VLAN configuration was defaulted because the current number of VLANs does not match the Base Unit number of VLANs.

Source	Severity
VLAN	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Number of VLANs does not match BU
number of VLANs. VLAN config
defaulted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Number of VLANs does not match BU number of VLANs. VLAN config defaulted log

Number of VLANs does not match BU number of VLANs. VLAN config defaulted

The Non-Base Unit has a different number of VLANs than the Base Unit at dbexchange point.

Source	Severity
VLAN	Information

Remedial action

Reconfigure the port settings for this Non-Base Unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NUQC - Disabled log

NUQC - Disabled

The NUQC feature is disabled.

Source	Severity
NUQC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NUQC - Enabled log

NUQC - Enabled

The NUQC feature is enabled.

Source	Severity
NUQC	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NUQC - Execution of the cli template failed log

NUQC - Execution of the cli template failed

The NUQC script execution failed.

Source	Severity
NUQC	Information

Remedial action

Verify the syntax of the NUQC script.



NUQC - Execution of the cli template succeeded

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

NUQC - Execution of the cli template succeeded log

NUQC - Execution of the cli template succeeded

The NUQC script executed successfully.

Source	Severity
NUQC	Information

Remedial action

No action required.



Only one frame type supported per classifier

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Only one frame type supported per classifier log

Only one frame type supported per classifier

The maximum frame types supported in a classifier is one.

Source	Severity
QoS	Serious

Remedial action

Separate the frame types into multiple system classifiers.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Area Mismatch RxArea ra.rb.rc.rd IntfArea ia.ib.ic.id log

Ospf Area Mismatch RxArea ra.rb.rc.rd IntfArea ia.ib.ic.id

An OSPF Area mismatch is detected between the OSPF packet Area ID and the interface Area ID.

Source	Severity
ospf(drpmgr)	Information

Remedial action

show ip ospf interface VLAN <VID>; reconfigure OSPF Area ID at the switch or at the neighbor to match.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Auth Failed IpAddr ia.ib.ic.id log

Ospf Auth Failed IpAddr ia.ib.ic.id

OSPF authentication failed at the given Interface IP Address when verifying the OSPF packet.

Source	Severity
ospf(drpmgr)	Information

Remedial action

show ip ospf interface VLAN <VID>; reconfigure OSPF authType and related information at the switch or at the neighbor to match.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Auth Type Mismatch in Hello log

Ospf Auth Type Mismatch in Hello

Reports the OSPF authentication mismatch on the neighboring interfaces.

Source	Severity
OSPF	Information

Remedial action

Verify that OSPF authentication parameters match on the neighboring interfaces.



Ospf Auto Virt Link Failed area a1.a2.a3.a4 rtid r1.r2.r3.r4

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Auto Virt Link Failed area a1.a2.a3.a4 rtid r1.r2.r3.r4 log

Ospf Auto Virt Link Failed area a1.a2.a3.a4 rtid r1.r2.r3.r4

OSPF auto creation of virtual link failed as it exceeds the maximum 4 allowed.

Source	Severity
ospf(drpmgr)	Information

Remedial action

Show IP OSPF virtual-link to see if any of the existing ones need to be removed; worst case, bounce OSPF to see if this clears it.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Bad Version log

Ospf Bad Version

Reports the OSPF version mismatch.

Source	Severity
OSPF	Information

Remedial action

Verify the OSPF version.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OSPF Callback function of timer is NULL log

OSPF Callback function of timer is NULL

Reports an OSPF bad timer failure (ex: bad LSA received).

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Cost Exceeds Limit Skip route Lsid I1.I2.I3.I4 Adv-rtr a1.a2.a3.a4 log

Ospf Cost Exceeds Limit Skip route Lsid I1.I2.I3.I4 Adv-rtr a1.a2.a3.a4

OSPF LSA Calculated cost exceeds limit of 0xFFFFF.

Source	Severity
ospf(drpmgr)	Information

Remedial action

Show IP OSPF redistribute and show route-map; check metric; correct as needed; may need actions at the neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg Done Filter Init log

OspfDbg Done Filter Init

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg Done Global Init log

OspfDbg Done Global Init

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg Done NV-Restore log

OspfDbg Done NV-Restore

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg Done ReDist Init log

OspfDbg Done ReDist Init

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.



OspfDbg Init Instance vrfId=%d nodeP=0x%0x

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg Init Instance vrfId=%d nodeP=0x%0x log

OspfDbg Init Instance vrfId=%d nodeP=0x%0x

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg PostInit Done vrfId=%d nodeP=0x%0x log

OspfDbg PostInit Done vrfId=%d nodeP=0x%0x

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg PostInit EnableOspf vrfId=%d nodeP=0x%0x log

OspfDbg PostInit EnableOspf vrfId=%d nodeP=0x%0x

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OspfDbg Started ospfTxHelloTimerTask log

OspfDbg Started ospfTxHelloTimerTask

Describes the start-up sequence of OSPF initializations on reboot.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Dead Int Mismatch in Hello log

Ospf Dead Int Mismatch in Hello

Reports the OSPF Dead interval mismatch on the neighboring interfaces.

Source	Severity
OSPF	Information

Remedial action

Verify that OSPF Dead Int parameters match on the neighboring interfaces.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Enable Failed as Resource Unavailable log

Ospf Enable Failed as Resource Unavailable

The system detected an OSPF Hardware Resource Allocation Failure in the ERS5510 Mode.

Source	Severity
ospf(drpmgr)	Information

Remedial action

Re-do QoS filter allocations and restart the switch or OSPF or global routing.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Hello Int Mismatch in Hello log

Ospf Hello Int Mismatch in Hello

Reports the OSPF Hello interval mismatch on the neighboring interfaces.

Source	Severity
OSPF	Information

Remedial action

Verify that OSPF Hello parameters match on the neighboring interfaces.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Hello: RId Same as Neighbor: rtid <r1.r2.r3.r4>, IpAddr <i1.i2.i3.i4> log

Ospf Hello: RId Same as Neighbor: rtid <r1.r2.r3.r4>, IpAddr <i1.i2.i3.i4>

Ospf Hello received at given Interface has the same RouterId as the switch.

Source	Severity
ospf(drpmgr)	Information

Remedial action

Show IP OSPF at the switch and at the neighbor; ensure the router IDs are different.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf HW Mode Change: log

Ospf HW Mode Change:

The OSPF Hardware Mode changed to the given new mode.

Source	Severity
ospf(drpmgr)	Information

Remedial action

No action required.



Ospf Invalid packet received: Pkt type <ospfPacketType>

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Invalid packet received: Pkt type <ospfPacketType> log

Ospf Invalid packet received: Pkt type <ospfPacketType>

The OSPF Link State Update packet received is invalid; packet is dropped.

Source	Severity
ospf(drpmgr)	Information

Remedial action

Either lsa is too small (<20 bytes) or too big (> (1500-64 for headers)); or wrong number of lsas; retry bouncing OSPF at the neighbor or redo parts of neighbor configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf License Is Missing, Disable OSPF log

Ospf License Is Missing, Disable OSPF

OSPF License is missing; inconsistency expected if the OSPF is enabled in the NVRAM configuration.

Source	Severity
ospf(drpmgr)	Information

Remedial action

Show license; Check for available licenses; A valid license is needed for the OSPF functionality.



Ospf Nbr State Change: rtid
<ra.rb.rc.rd> ipa <ia.ib.ic.id> state
<neighborState>

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Nbr State Change: rtid <ra.rb.rc.rd> ipa <ia.ib.ic.id> state <neighborState> log

Ospf Nbr State Change: rtid <ra.rb.rc.rd> ipa <ia.ib.ic.id> state <neighborState>

OSPF Nbr State Change: for given Neighbor Router ID, Address and State.

Source	Severity
ospf(drpmgr)	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Netmask Mismatch in Hello IpAddr ia.ib.ic.id log

Ospf Netmask Mismatch in Hello IpAddr ia.ib.ic.id

There is an OSPF Netmask Mismatch between the netmask of IP Address in the hello packet and the netmask of the Interface IP Address.

Source	Severity
ospf(drpmgr)	Information

Remedial action

show VLAN IP VID <VLANID> at the switch and the neighbor - reconfigure IP address/mask as needed to match.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Option Mismatch in Hello IpAddr ia.ib.ic.id RxOption optionVal IntfOption optionVal log

Ospf Option Mismatch in Hello IpAddr ia.ib.ic.id RxOption optionVal IntfOption optionVal

OSPF Hello option Mismatch for stub or nssa area selection in the packet vs that of the interface area.

Source	Severity
ospf(drpmgr)	Information

Remedial action

show ip ospf interface VLAN <VID> to find areaId of interface; show ip ospf area <areaID> to check if area type ; reconfigure these as needed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OSPF Timer Link Error log

OSPF Timer Link Error

Reports an OSPF bad timer failure (ex: bad LSA received).

Source	Severity
OSPF	Information

Remedial action

No action required.



OSPF Timer List is corrupted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OSPF Timer List is corrupted log

OSPF Timer List is corrupted

Reports an OSPF bad timer failure (ex: bad LSA received).

Source	Severity
OSPF	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

OSPF Timer Unlink Error log

OSPF Timer Unlink Error

Reports an OSPF bad timer failure (ex: bad LSA received).

Source	Severity
OSPF	Information

Remedial action

No action required.



Ospf Virt Nbr State Change: rtid
<r1.r2.r3.r4>, virtAreaId
<v1.v2.v3.v4>, state <neighborState>

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Ospf Virt Nbr State Change: rtid <r1.r2.r3.r4>, virtAreaId <v1.v2.v3.v4>, state <neighborState> log

Ospf Virt Nbr State Change: rtid <r1.r2.r3.r4>, virtAreaId <v1.v2.v3.v4>, state <neighborState>

OSPF Virtual Neighbor of given routerID and areaID changed to a given state.

Source	Severity
ospf(drpmgr)	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Out-of-profile action contains conflicting data log

Out-of-profile action contains conflicting data

Unable to install the specified out-of-profile action, conflicting data detected.

Source	Severity
QoS	Serious

Remedial action

Identify conflicts and separate them into different out-of-profile actions.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Out-of-range CoS index value (COS index value) log

Out-of-range CoS index value (COS index value)

The valid CoS index range is 0 to 7.

Source	Severity
QoS	Serious

Remedial action

Enter a CoS index value within the specified valid range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Out-of-range queue index value (queue index) for in-use queue set log

Out-of-range queue index value (queue index) for in-use queue set

The queue set must be between 1 and the runtime default queue set.

Source	Severity
QoS	Serious

Remedial action

Check the agent default queue set and modify the value accordingly.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Out-of-range queue index value (queue index) for pending queue set log

Out-of-range queue index value (queue index) for pending queue set

The queue set must be between 1 and the runtime default queue set.

Source	Severity
QoS	Serious

Remedial action

Check the agent default queue set and modify your value accordingly.



Packet redirection support limited by target interfaces

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Packet redirection support limited by target interfaces log

Packet redirection support limited by target interfaces

Target interfaces are version 2 (Currently, all version 2 interfaces support redirection for all packet types or none) and do not support redirection for non-unicast packets.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Enter a different interface/port number.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Pattern matching data in excess of bytes# bytes specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern matching data in excess of bytes# bytes specified log

Pattern matching data in excess of bytes# bytes specified

The maximum pattern data length is 16 for 45XX and 32 for the rest of the platforms.

Source	Severity
QoS	Serious

Remedial action

Separate the pattern matching data into multiple system classifiers so it fits the maximum length specified.



Pattern matching (Dst IP) not supported with IP addr type data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern matching (Dst IP) not supported with IP addr type data log

Pattern matching (Dst IP) not supported with IP addr type data

System classifiers with pattern matching (Dst IP) cannot be used with IP address type data.

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple classifier sets.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern matching (Dst MAC) not supported with address type data log

Pattern matching (Dst MAC) not supported with address type data

System classifiers with pattern matching (Dst MAC) cannot be used with address type data.

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple classifier sets.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern matching (IP) not supported with non-IP addr type data log

Pattern matching (IP) not supported with non-IP addr type data

IP pattern matching (ipv4 or ipv6) used with UnknownNonIpMcast, NonIpMcast or NonIpPkt option.

Source	Severity
QoS	Serious

Remedial action

Remove IP patter matching or non-IP type data from the system classifier.



Pattern matching not supported with other classification data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern matching not supported with other classification data log

Pattern matching not supported with other classification data

System classifiers with pattern matching can only be used with default ip or/and I2 classifiers in the same classifier set.

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple classifier sets.



Pattern modifier data specified without actual pattern data

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern modifier data specified without actual pattern data log

Pattern modifier data specified without actual pattern data

Pattern-related attributes have been set but pattern data is not specified.

Source	Severity
QoS	Serious

Remedial action

Remove pattern-related attributes or specify patter data to avoid confusion.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pattern position and data strings must be same length log

Pattern position and data strings must be same length

Different lengths detected: pattern position and data strings.

Source	Severity
QoS	Serious

Remedial action

Use pattern position and data strings of the same length.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim E-BSR change log

Pim E-BSR change

A BSR with higher priority is detected. Logged only on BSR that changes.

Source	Severity
PIM	Information

Remedial action

Check priority of the configured BSRs.



Pim Invalid packet received

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim Invalid packet received log

Pim Invalid packet received

PIM Control packets received are not conforming to the PIMv2 RFC 2362.

Source	Severity
PIM	Information

Remedial action

Check if sending router conforms to PIMv2 specifications, or if packets are being corrupted in the network.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim License Is Missing Disable PIM log

Pim License Is Missing Disable PIM

PIM is a licensed feature. PIM can only be configured, but cannot be activated without a license.

Source	Severity
PIM	Information

Remedial action

Contact the support personnel for an appropriate license.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim Mode Change log

Pim Mode Change

Change from PIM SM mode to SSM or vice-versa.

Source	Severity
PIM	Information

Remedial action

Check and ensure that a proper mode has been selected. Will lead to change in IP Multicast traffic flows in VLANs where mode has been changed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim Nbr State Change Up log

Pim Nbr State Change Up

PIM_NBR_UP: A new neighbor is detected. It occurs when a PIM Hello message is received from an active PIM router. This can result in a change in IP multicast traffic flow if this neighbor is towards RP or BSR especially if combined with change in unicast routing.

Source	Severity
PIM	Information

Remedial action

If the same neighbor is repeatedly appearing and disappearing, this is due to congestion in the link towards this neighbor. Check to see if unicast routing is also being affected as well as CPU utilization.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PIM Neighbor status change Down log

PIM Neighbor status change Down

PIM_NBR_DOWN: An existing neighbor has timed out. This occurs when PIM Hello messages are not received from a neighbor within 3.5 times the query interval for an active PIM interface. This may lead to changes in the IP Multicast traffic flow.

Source	Severity
PIM	Information

Remedial action

Check if the neighbor router is functional and is sending out PIM Hellos.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PIM Neighbor status change Up log

PIM Neighbor status change Up

PIM_NBR_UP: A new neighbor is detected, This occurs when a PIM Hello message is received from an active PIM router. This may result in change in IP multicast traffic flow if this neighbor is towards RP or BSR especially if combined with change in unicast routing.

Source	Severity
PIM	Information

Remedial action

If the same neighbor is repeatedly appearing and disappearing, this is due to congestion in the link towards this neighbor. Check if unicast routing and CPU utilization is also being affected.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim RP type state log

Pim RP type state

This message indicates the change from dynamic to static RP or the other way around.

Source	Severity
PIM	Information

Remedial action

If changing to static RP, ensure this is configured in the entire PIM domain. Also, BSR information will be lost and will need to be re-configured if moving to Dynamic RPs.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim Unicast route change log

Pim Unicast route change

Unicast route towards a source or RP has changed. This can result in changes in IP multicast traffic flow. Indicates if the route towards source or RP has been modified or deleted.

Source	Severity
PIM	Information

Remedial action

Check unicast routing / ARP tables and ensure that these are correct.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim Virt Nbr State Change Down log

Pim Virt Nbr State Change Down

PIM_NBR_DOWN: A configured virtual neighbor is deleted.

Source	Severity
PIM	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Pim Virt Nbr State Change Up log

Pim Virt Nbr State Change Up

PIM_NBR_UP: A virtual neighbor has been configured.

Source	Severity
PIM	Information

Remedial action

Check the multicast routes and ensure proper flows, especially if used with static unicast routes.



PM in port mirroring the old data were modified - feature Allow Traffic in mirror port was added.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - feature Allow Traffic in mirror port was added. log

PM in port mirroring the old data were modified - feature Allow Traffic in mirror port was added.

The Feature Allow Traffic in mirror port was added. In the upgrade situations when current image file will be replaced by the other image file in port mirroring module some features are possible to be added.

Source	Severity
PMT	Information

Remedial action

No action required.



PM in port mirroring the old data were modified - feature Many to Many was added.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - feature Many to Many was added. log

PM in port mirroring the old data were modified - feature Many to Many was added.

The Many to Many feature was added. In upgrade situations when current image file will be replaced by the other image file in port mirroring module some features are possible to be added.

Source	Severity
PMT	Information

Remedial action

No action required.



PM in port mirroring the old data were modified - feature Many to One was added.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - feature Many to One was added. log

PM in port mirroring the old data were modified - feature Many to One was added.

The Many to One feature was added. In upgrade situations when the current image file will be replaced by the other image file in port mirroring module ome features are possible to be added.

Source	Severity
PMT	Information

Remedial action

No action required.



PM in port mirroring the old data were modified - feature Many to One with 128bits was added.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - feature Many to One with 128bits was added. log

PM in port mirroring the old data were modified - feature Many to One with 128bits was added.

The Many to One feature with 128bits was added. In upgrade situations when the current image file will be replaced by the other image file in port mirroring module some features is possible to be added.

Source	Severity
PMT	Information

Remedial action

No action required.



PM: in port mirroring the old data were modified - feature RSPAN was added

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM: in port mirroring the old data were modified - feature RSPAN was added log

PM: in port mirroring the old data were modified - feature RSPAN was added

After upgrade, the RSPAN feature was added

Source	Severity
--------	----------

Port Mirroring	Information
----------------	-------------

Remedial action

No action required.



PM in port mirroring the old data were modified - mode type was out of range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - mode type was out of range. log

PM in port mirroring the old data were modified - mode type was out of range.

The mode type data saved in NVRAM is out of range for one port mirroring instance (ERS 2500, ERS 4000, ERS 55xx) or for one of the four port mirroring instances (ERS56xx).

Source	Severity
PMT	Information

Remedial action

No action required.



PM in port mirroring the old data were modified - monitored portA was out of range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - monitored portA was out of range. log

PM in port mirroring the old data were modified - monitored portA was out of range.

The monitored port A data saved in the NVRAM is out of range for one port mirroring instance (ERS 2500,ERS 4000,ERS 55xx) or for one of the four ort mirroring instances (ERS56xx).

Source	Severity
PMT	Information

Remedial action

No action required.



PM in port mirroring the old data were modified - monitored portB was out of range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - monitored portB was out of range. log

PM in port mirroring the old data were modified - monitored portB was out of range.

The monitored port B data saved in the NVRAM is out of range for one port mirroring instance (ERS 2500, ERS 4000, ERS 55xx) or for one of the four port mirroring instances (ERS 56xx).

Source	Severity
PMT	Information

Remedial action

No action required.



PM in port mirroring the old data were modified - NVRAM file structure was changed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - NVRAM file structure was changed. log

PM in port mirroring the old data were modified - NVRAM file structure was changed.

NVRAM file structure was changed. This message appears when the downgrade/upgrade of images is completed.

Source	Severity
PMT	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



PM in port mirroring the old data were modified - probe port was out of range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM in port mirroring the old data were modified - probe port was out of range. log

PM in port mirroring the old data were modified - probe port was out of range.

The probe port data saved in the NVRAM is out of range for one port mirroring instance (ERS 2500, ERS 4000, ERS 55xx) or for one of the four port mirroring instances (ERS 56xx).

Source	Severity
PMT	Information

Remedial action

No action required.



PM: instance %d has been deleted
because of insufficient HW resource

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM: instance %d has been deleted because of insufficient HW resource log

PM: instance %d has been deleted because of insufficient HW resource

The instance is erased, because no hardware resources are available for the current port mirroring configuration.

Source	Severity
--------	----------

Port Mirroring	Information
----------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM some port mirroring messages were stored to be displayd with delay. log

PM some port mirroring messages were stored to be displayd with delay.

This message appears when the SYSLOG task runs before the port mirroring initialization function is called from the PORT MIRRORING task. This message is written first and is succeeded every time by the other port mirroring messages.

Source	Severity
PMT	Information

Remedial action

No action required.



PM unable to create mirror for instance instance number due to lack of available filter resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PM unable to create mirror for instance instance number due to lack of available filter resources log

PM unable to create mirror for instance instance number due to lack of available filter resources

Port mirroring initialization failed due to lack of hardware filters.

Source	Severity
PM	Information

Remedial action

Disable other features which are using the filter resources. Use

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE Main Power Usage Off log

PoE Main Power Usage Off

The power usage drops below the previously set threshold.

Source	Severity
PoE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE Main Power Usage On log

PoE Main Power Usage On

Power consumption exceeded the configured threshold.

Source	Severity
PoE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE Module Reset log

PoE Module Reset

The PoE controller has been reset.

Source	Severity
PoE	Information

Remedial action

No action required.



PoE Port Detection Status port# Status powerStatus

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE Port Detection Status port# Status powerStatus log

PoE Port Detection Status port# Status powerStatus

The system reports the current PoE port status each time a status change occurs.

Source	Severity
PoE	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



PoE The PoE power limit for port unit port has been changed to x Watts based on IP phone discovery settings

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE The PoE power limit for port unit port has been changed to x Watts based on IP phone discovery settings log

PoE The PoE power limit for port unit port has been changed to x Watts based on IP phone discovery settings

The PoE power limit is changed according to the PoE IP phone settings, because of the IP phone discovery mechanism.

Source	Severity
PoE	Information

Remedial action

No action required.



PoE The PoE power limit for port unit port has been restored to previous value x Watts

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE The PoE power limit for port unit port has been restored to previous value x Watts log

PoE The PoE power limit for port unit port has been restored to previous value x Watts

The PoE power limit is restored to the previous value, because of the IP phone disconnection.

Source	Severity
PoE	Information

Remedial action

No action required.



PoE The PoE priority for port unit port has been changed to x based on IP phone discovery settings

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE The PoE priority for port unit port has been changed to x based on IP phone discovery settings log

PoE The PoE priority for port unit port has been changed to x based on IP phone discovery settings

The PoE priority changed according to the PoE IP phone settings, because of the IP phone discovery mechanism.

Source	Severity
PoE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

PoE The PoE priority for port unit port has been restored to previous value x log

PoE The PoE priority for port unit port has been restored to previous value x

The PoE power priority is restored to the previous value, as the IP phone is disconnected.

Source	Severity
PoE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policies with session data must be port-based log

Policies with session data must be port-based

Session policies must be port-based.

Source	Severity
QoS	Serious

Remedial action

Modify the user policy entry or remove the session data.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy action out-of-range (action#) log

Policy action out-of-range (action#)

If this is a user policy the action id must be between 1 and 55000. For a system entry the range is 55001-65535.

Source	Severity
QoS	Serious

Remedial action

Specify a valid action id.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy content incompatible with target interface(s) log

Policy content incompatible with target interface(s)

The classifier(s) filter options used in the policy are not compatible with the target interface.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface or adapt classifier/policy.



Policy distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy distribution across stack failed log

Policy distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy mask availability issue (space exhausted) log

Policy mask availability issue (space exhausted)

Unable to find next available mask precedence for the specified port.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded resources on that port.



Policy modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy modifications not supported log

Policy modifications not supported

The system detected an Internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy modification support limited log

Policy modification support limited

Policies under system control can be deleted but not modified. For user policies only certain modification are supported (if-group, port, name).

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

To change a different option remove policy and create a new one.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy non-match action out-of-range (non-match action#) log

Policy non-match action out-of-range (non-match action#)

If this is a user policy the non-match action id must be between 1 and 55000. For a system entry the range is 55001-65535.

Source	Severity
QoS	Serious

Remedial action

Specify a valid non-match action id.



Policy precedence conflict detected with non-QoS application

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy precedence conflict detected with non-QoS application log

Policy precedence conflict detected with non-QoS application

A non-QoS application is already using the precedence specified.

Source	Severity
QoS	Serious

Remedial action

Enter a different precedence.



Policy precedence value out-of-range for target interface(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy precedence value out-of-range for target interface(s) log

Policy precedence value out-of-range for target interface(s)

Precedence limits differ based on the underlying hardware support.

Source	Severity
QoS	Serious

Remedial action

Enter a precedence compatible with the hardware limits for the specified interface or use a different one.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Policy requirements exceed available resources (slot slot#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy requirements exceed available resources (slot slot#) log

Policy requirements exceed available resources (slot slot#)

Not all the resources required for the policy are available on the base or non-base unit(s).

Source	Severity
QoS	Serious

Remedial action

Modify either the interfaces or the demanding resources.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy statistics index out-of-range (stats index) log

Policy statistics index out-of-range (stats index)

Invalid policy tracking statistics. The supported types are: individual aggregate or disabled.

Source	Severity
QoS	Serious

Remedial action

Specify a supported policy tracking statistics.



Policy with this filtering values is already installed on this precedence

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Policy with this filtering values is already installed on this precedence log

Policy with this filtering values is already installed on this precedence

An identical policy detected on the same precedence and port.

Source	Severity
QoS	Serious

Remedial action

Enter the existing policy.



Port %d blocked by VLACP due to end-partner down state

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port %d blocked by VLACP due to end-partner down state log

Port %d blocked by VLACP due to end-partner down state

VLACP packets are not reaching partner. Port is blocked because we are receiving Subtype Down packets

Source	Severity
VLACP	Information

Remedial action

Check links between units or settings.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port %d blocked by VLACP until end-partner connection reestablished log

Port %d blocked by VLACP until end-partner connection reestablished

Blocking displayed port due to not receiving VLACP packages from partner.

Source	Severity
VLACP	Information

Remedial action

Check links between units or settings.



Port %d/%d blocked by VLACP due to end-partner down state

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port %d/%d blocked by VLACP due to end-partner down state log

Port %d/%d blocked by VLACP due to end-partner down state

VLACP packets are not reaching partner. Port is blocked because we are receiving Subtype Down packets

Source	Severity
VLACP	Information

Remedial action

Check links between units or settings.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port %d reenabled by VLACP log

Port %d reenabled by VLACP

VLACP message received from partner, re-enabling the displayed port.

Source	Severity
VLACP	Information

Remedial action

No action required.



Port unit# port# blocked by VLACP until end-partner connection reestablished

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port unit# port# blocked by VLACP until end-partner connection reestablished log

Port unit# port# blocked by VLACP until end-partner connection reestablished

Port put to Listening by VLACP.

Source	Severity
VLACP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Port unit# port# reenabled by VLACP log

Port unit# port# reenabled by VLACP

Port put back to its state by VLACP.

Source	Severity
VLACP	Information

Remedial action

No action required.



Post-join ACL installation issue detected (ifc ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Post-join ACL installation issue detected (ifc ifc#) log

Post-join ACL installation issue detected (ifc ifc#)

ACL installation failed after a join stack event.

Source	Severity
QoS	Serious

Remedial action

Try again or check the stack health. Further conclusions are drawn as this message appears either on base, non-base, all or some units in stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Post-join filter set installation issue detected (ifc ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Post-join filter set installation issue detected (ifc ifc#) log

Post-join filter set installation issue detected (ifc ifc#)

Filter set installation failed after a join stack event.

Source	Severity
QoS	Serious

Remedial action

Try again or check the stack health. Further conclusions are drawn as this message appears either on base, non-base, all or some of the units in stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Post-join policy installation issue detected (ifc ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Post-join policy installation issue detected (ifc ifc#) log

Post-join policy installation issue detected (ifc ifc#)

Unable to configure policies after a join stack event.

Source	Severity
QoS	Critical

Remedial action

Try again or check stack health. Further conclusions can be drawn is this message appears either on base, non-base, all or some units in stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Post-join traffic-profile installation issue detected (ifc ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Post-join traffic-profile installation issue detected (ifc ifc#) log

Post-join traffic-profile installation issue detected (ifc ifc#)

Traffic-profile installation failed after a join stack event.

Source	Severity
QoS	Serious

Remedial action

Try again or check the stack health. Further conclusions are drawn as this message appears either on base, non-base, all or some of the units in stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Potential inconsistent access asgn state (Undo fail) detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Potential inconsistent access asgn state (Undo fail) detected log

Potential inconsistent access asgn state (Undo fail) detected

Inconsistent access assign state detected on the non base unit.

Source	Severity
QoS	Serious

Remedial action

Try again later, reset the QoS agent, reset the unit or check the stack health.



Potential inconsistent access elem state (Undo fail) detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Potential inconsistent access elem state (Undo fail) detected log

Potential inconsistent access elem state (Undo fail) detected

The system detected inconsistent access element state on the non base unit.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Potential inconsistent block state (Undo fail) detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Potential inconsistent block state (Undo fail) detected log

Potential inconsistent block state (Undo fail) detected

Inconsistent block state detected on non base unit.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Potential inconsistent ifc assignment state (Undo fail) detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Potential inconsistent ifc assignment state (Undo fail) detected log

Potential inconsistent ifc assignment state (Undo fail) detected

Inconsistent interface assignment state detected on non base unit.

Source	Severity
QoS	Serious

Remedial action

Try again later, reset the QoS agent or reset the unit.



Potential inconsistent policy state (Undo fail) detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Potential inconsistent policy state (Undo fail) detected log

Potential inconsistent policy state (Undo fail) detected

Inconsistent policy state detected on non base unit.

Source	Severity
QoS	Serious

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Precedence value out-of-range log

Precedence value out-of-range

Precedence range depends on the platform.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid precedence.



Primary Configuration files are corrupted. Restored to default

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Primary Configuration files are corrupted. Restored to default log

Primary Configuration files are corrupted. Restored to default

The default primary configuration is restored.

Source	Severity
config	Information

Remedial action

No action required.



Primary Configuration Version is updated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Primary Configuration Version is updated log

Primary Configuration Version is updated

The primary configuration version is updated.

Source	Severity
config	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Provided metering information incomplete

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Provided metering information incomplete log

Provided metering information incomplete

Insufficient or invalid information provided.

Source	Severity
QoS	Serious

Remedial action

Specify a valid meter.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

802.1p user priority mapping modifications not supported log

802.1p user priority mapping modifications not supported

The system detected an internal error; the specified modifier option is not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

802.1p user priority value modification prohibited log

802.1p user priority value modification prohibited

Since the COS-to-DSCP default assignment association is created at initialization, the CoS may not be modified.

Source	Severity
QoS	Information

Remedial action

Verify that the COS being specified is indeed the original COS.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QOS filter-limiting mode modified and unit reset log

QOS filter-limiting mode modified and unit reset

The QOS filter-limiting mode was modified and the unit rebooted.

Source	Severity
Stack Manager	Serious

Remedial action

No action required.



QoS inter-module communication issue detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS inter-module communication issue detected log

QoS inter-module communication issue detected

Unable to make changes across the stack. If the request failed because of an RPC timeout, then this is due to a processing delay on the remote unit.

Source	Severity
QoS	Information

Remedial action

Check if a timeout issue, else try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS policies may not be applied to uplink or daisy chain ports (port#) log

QoS policies may not be applied to uplink or daisy chain ports (port#)

ESU Policies cannot be applied on daisy chain ports.

Source	Severity
QoS	Serious

Remedial action

Enter different ports.



Queue configuration inconsistency detected (local queue conf stack queue conf)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue configuration inconsistency detected (local queue conf stack queue conf) log

Queue configuration inconsistency detected (local queue conf stack queue conf)

The queue set is not same on all units in stack.

Source	Severity
QoS	Serious

Remedial action

Try again later, reset the QoS agent or reset the unit.



Queue data distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue data distribution across stack failed log

Queue data distribution across stack failed

Unable to commit queue data distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Queue set assignment distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue set assignment distribution across stack failed log

Queue set assignment distribution across stack failed

Unable to make changes across the stack.

Source	Severity
QoS	Serious

Remedial action

Try later or check stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Queue set assignment modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue set assignment modifications not supported log

Queue set assignment modifications not supported

The system detected an Internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue set unacceptable - pending range excludes in-use queues log

Queue set unacceptable - pending range excludes in-use queues

Cannot configure as a default queue set one that is currently used by a traffic shaping.

Source	Severity
QoS	Serious

Remedial action

Enter an available queue set.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue set value modification prohibited log

Queue set value modification prohibited

The queue set may not be modified since the queue set association is created when the queue set is defined.

Source	Severity
QoS	Serious

Remedial action

Verify that the queue set being specified is indeed the original queue set.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue set value modification prohibited log

Queue set value modification prohibited

The queue set may not be modified since the queue set association is created when the queue set is defined.

Source	Severity
QoS	Warning

Remedial action

Verify that the queue set being specified is indeed the original queue set.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue shaping distribution across stack failed log

Queue shaping distribution across stack failed

Unable to commit queue shaping distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.



Queue shaping modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Queue shaping modifications not supported log

Queue shaping modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall console configuration error. log

QuickInstall console configuration error.

Quick Install could not use the configuration from the console menu.

Source	Severity
Quick Install	Information

Remedial action

Use from console configuration or retry the menu with install command.



QuickInstall:console configuration success.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall:console configuration success. log

QuickInstall:console configuration success.

Quick Install successfully executed the configuration from the console menu.

Source	Severity
Quick Install	Information

Remedial action

No action required.



QuickInstall: Error! Unable to locate agent software file

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall: Error! Unable to locate agent software file log

QuickInstall: Error! Unable to locate agent software file

The agent file specified in " ip.cfg" was not found.

Source	Severity
Quick Install	Information

Remedial action

Put agent file specified in "ip.cfg" file on USB device.



QuickInstall: Error! Unable to locate ASCII configuration file

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall: Error! Unable to locate ASCII configuration file log

QuickInstall: Error! Unable to locate ASCII configuration file

The ASCII file specified in " ip.cfg" was not found.

Source	Severity
Quick Install	Information

Remedial action

Put ASCII File specified in "ip.cfg" file on USB device.



QuickInstall: Error! Unable to locate diagnostics software file.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall: Error! Unable to locate diagnostics software file. log

QuickInstall: Error! Unable to locate diagnostics software file.

The diagnostic file specified in " ip.cfg" was not found.

Source	Severity
Quick Install	Information

Remedial action

Put diagnostic file specified in "ip.cfg" file on USB device.



QuickInstall: Processing of USB config file has commenced.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall: Processing of USB config file has commenced. log

QuickInstall: Processing of USB config file has commenced.

USB file "ip.cfg" was found and script execution has commenced.

Source	Severity
Quick Install	Information

Remedial action

No action Required.



QuickInstall: Processing of USB config file is complete

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall: Processing of USB config file is complete log

QuickInstall: Processing of USB config file is complete

The execution of script from "ip.cfg" is finished.

Source	Severity
Quick Install	Information

Remedial action

No action Required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall USB config file not found. log

QuickInstall USB config file not found.

Quick Install could not locate the USB file.

Source	Severity
Quick Install	Information

Remedial action

Put a file to USB script and set it to default if you want to run Quick Install.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall USB file config error at line line# log

QuickInstall USB file config error at line line#

Quick Install detected an error in the script at the given line.

Source	Severity
Quick Install	Information

Remedial action

Correct the detected error at the specified line on the USB script and set it to default.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall USB file config error - file exceed 4096 bytes log

QuickInstall USB file config error - file exceed 4096 bytes

The script file is too large and exceeds the limit of 4096 bytes.

Source	Severity
Quick Install	Information

Remedial action

Remove some of the comments and the unnecessary lines.



QuickInstall USB file config error - file exceed 200 lines.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall USB file config error - file exceed 200 lines. log

QuickInstall USB file config error - file exceed 200 lines.

The script file is too large and exceeds the limit of 200 lines.

Source	Severity
Quick Install	Information

Remedial action

Remove some of the comments and the unnecessary lines.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QuickInstall:USB file config success. log

QuickInstall:USB file config success.

The script file from the USB is successfully executed by the Quick Install.

Source	Severity
Quick Install	Information

Remedial action

No action required.



RADIUS authentication on stack serial disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on stack serial disabled log

RADIUS authentication on stack serial disabled

Informs user that RADIUS authentication was disabled on stack serial.

Source	Severity
RADIUS	Information

Remedial action

No action required.



RADIUS authentication on stack serial enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on stack serial enabled log

RADIUS authentication on stack serial enabled

Informs user that RADIUS authentication was enabled on stack serial.

Source	Severity
RADIUS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



RADIUS authentication on stack telnet disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on stack telnet disabled log

RADIUS authentication on stack telnet disabled

Informs user that RADIUS authentication was disabled on stack telnet.

Source	Severity
RADIUS	Information

Remedial action

No action required.



RADIUS authentication on stack telnet enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on stack telnet enabled log

RADIUS authentication on stack telnet enabled

Informs user that RADIUS authentication was enabled on stack telnet.

Source	Severity
RADIUS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



RADIUS authentication on switch serial disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on switch serial disabled log

RADIUS authentication on switch serial disabled

Informs user that RADIUS authentication was disabled on switch serial.

Source	Severity
RADIUS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



RADIUS authentication on switch serial enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on switch serial enabled log

RADIUS authentication on switch serial enabled

Informs user that RADIUS authentication was enabled on switch serial.

Source	Severity
RADIUS	Information

Remedial action

No action required.



RADIUS authentication on switch telnet disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on switch telnet disabled log

RADIUS authentication on switch telnet disabled

Informs user that RADIUS authentication was disabled on switch telnet.

Source	Severity
RADIUS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



RADIUS authentication on switch telnet enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS authentication on switch telnet enabled log

RADIUS authentication on switch telnet enabled

Informs user that RADIUS authentication was enabled on switch telnet.

Source	Severity
RADIUS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d log

RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d

The Radius Accounting task synchronization semaphore could not be created.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.



RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d log

RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d

The Radius Accounting task synchronization semaphore could not be created.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.



RADIUS: ERROR - Couldn't create RADIUS semaphore, errno %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't create RADIUS semaphore, errno %d log

RADIUS: ERROR - Couldn't create RADIUS semaphore, errno %d

The Radius task synchronization semaphore could not be created.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.



RADIUS: ERROR - Couldn't start RADIUS_AcctClient() task, errno %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't start RADIUS_AcctClient() task, errno %d log

RADIUS: ERROR - Couldn't start RADIUS_AcctClient() task, errno %d

The Radius Accounting task could not start.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.



RADIUS: ERROR - Couldn't start RADIUS_client() task, errno %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't start RADIUS_client() task, errno %d log

RADIUS: ERROR - Couldn't start RADIUS_client() task, errno %d

The Radius client task could not start.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.



RADIUS: ERROR - Couldn't start radius_recv() task, errno %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't start radius_recv() task, errno %d log

RADIUS: ERROR - Couldn't start radius_recv() task, errno %d

The Radius Receive task could not start.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS: ERROR - Couldn't start RADIUS_ServerCheck() task, errno %d log

RADIUS: ERROR - Couldn't start RADIUS_ServerCheck() task, errno %d

The Radius periodic reachability check task could not start.

Source	Severity
Radius	Information

Remedial action

Reboot the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS MS-CHAPv2: Failed to change password log

RADIUS MS-CHAPv2: Failed to change password

This could mean either wrong user , as in the user does not exist on the server or wrong old password for a valid user

Source	Severity
RADIUS	Information

Remedial action

Verify user is properly configured on RADIUS Server; Assure that the new password doesn't match any previous password; verify password complexity on RADIUS Server.



RADIUS MS-CHAPv2: No response from RADIUS server

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS MS-CHAPv2: No response from RADIUS server log

RADIUS MS-CHAPv2: No response from RADIUS server

A timeout has occurred from RADIUS Server

Source	Severity
RADIUS	Information

Remedial action

Check if RADIUS Server is running and reachable.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



RADIUS MS-CHAPv2: Password changed successfully

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS MS-CHAPv2: Password changed successfully log

RADIUS MS-CHAPv2: Password changed successfully

Password was changed successfully for the desired user

Source	Severity
RADIUS	Information

Remedial action

No action required.



RADIUS MS-CHAPv2: RADIUS server not properly configured

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS MS-CHAPv2: RADIUS server not properly configured log

RADIUS MS-CHAPv2: RADIUS server not properly configured

RADIUS Server is not configured on the switch

Source	Severity
RADIUS	Information

Remedial action

Configure the RADIUS Server.



RADIUS MS-CHAPv2: Server does not speak RADIUS

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS MS-CHAPv2: Server does not speak RADIUS log

RADIUS MS-CHAPv2: Server does not speak RADIUS

Programming error

Source	Severity
RADIUS	Information

Remedial action

No action; useful only for engineers.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

RADIUS MS-CHAPv2: Unable to change password at RADIUS server log

RADIUS MS-CHAPv2: Unable to change password at RADIUS server

RADIUS Server could not change its password

Source	Severity
RADIUS	Information

Remedial action

Verify if RADIUS Server has MS-CHAPv2 support.



Radius: Server with index %d is down

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Radius: Server with index %d is down log

Radius: Server with index %d is down

The identified radius server is down.

Source	Severity
Radius	Information

Remedial action

Check connectivity with server.



Radius: Server with index %d is up

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Radius: Server with index %d is up log

Radius: Server with index %d is up

The identified radius server is up.

Source	Severity
Radius	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Radius use-mgmt-ip must be disabled first log

Radius use-mgmt-ip must be disabled first

RADIUS use-management-ip parameter is turned on.

Source	Severity
L3Mgr	Information

Remedial action

Disable RADIUS use-management-ip before continuing with configuration.



Rate granularity limited to increments of 1 Mbps or 64 Kbps

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Rate granularity limited to increments of 1 Mbps or 64 Kbps log

Rate granularity limited to increments of 1 Mbps or 64 Kbps

There are only two rate granularities supported: 1 Mbps and 64 Kbps.

Source	Severity
QoS	Serious

Remedial action

Enter a rate with one of the supported granularities.



Rate (min) granularity limited (increments of 1 Mbps or 64 Kbps)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Rate (min) granularity limited (increments of 1 Mbps or 64 Kbps) log

Rate (min) granularity limited (increments of 1 Mbps or 64 Kbps)

There are only two rate granularities supported: 1 Mbps and 64 Kbps.

Source	Severity
QoS	Serious

Remedial action

Enter a rate with one of the supported granularities.



Referenced block (by policy) deletion prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Referenced block (by policy) deletion prohibited log

Referenced block (by policy) deletion prohibited

Cannot delete a classifier-block if it's referenced in a policy.

Source	Severity
QoS	Serious

Remedial action

Remove the policy first.



Referenced set (by block) modifications prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Referenced set (by block) modifications prohibited log

Referenced set (by block) modifications prohibited

No modifications can be made to a classifier set referenced in a classifier-block.

Source	Severity
QoS	Serious

Remedial action

Remove block, perform modifications and recreate classifier-block.



Referenced set (by policy) modifications prohibited

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Referenced set (by policy) modifications prohibited log

Referenced set (by policy) modifications prohibited

No modifications can be made to a classifier set used by a policy.

Source	Severity
QoS	Serious

Remedial action

Remove policy, perform modifications and recreate policy.



Remote QoS-disable request failure (port# on unit unit#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Remote QoS-disable request failure (port# on unit unit#) log

Remote QoS-disable request failure (port# on unit unit#)

Failed to disable the Policy/Interface.

Source	Severity
QoS	Serious

Remedial action

Check for the conflicting entries, try again later, reset the QoS agent, reset the unit or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



REMOVE_DATA event sent unit mask value appl mask value

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

REMOVE_DATA event sent unit mask value appl mask value log

REMOVE_DATA event sent unit mask value appl mask value

The application could not exchange its database successfully.

Source	Severity
Stack Manager	Information

Remedial action

No action required.



Replaced "Wrong QoS Agent buffer setting, expected %u, actual %u, unit cannot join stack" with "Wrong QoS Agent buffer setting, expected %s, actual %s, unit cannot join stack"

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Replaced "Wrong QoS Agent buffer setting, expected %u, actual %u, unit cannot join stack" with "Wrong QoS Agent buffer setting, expected %s, actual %s, unit cannot join stack" log

Replaced "Wrong QoS Agent buffer setting, expected %u, actual %u, unit cannot join stack" with "Wrong QoS Agent buffer setting, expected %s, actual %s, unit cannot join stack"

Unit cannot join the stack because of the difference in buffer setting.

Source

Severity

Stack Manager

Information

Remedial action

Re-configure QoS agent buffer setting to the expected value and power cycle unit.



Requested attribute usage is currently not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Requested attribute usage is currently not supported log

Requested attribute usage is currently not supported

The requested attribute is not compatible – attribute value support is limited.

Source	Severity
QoS	Serious

Remedial action

Eliminate option or use a different attribute.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Requested filter manager support unavailable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Requested filter manager support unavailable log

Requested filter manager support unavailable

The requested operation is not supported on the current hardware.

Source	Severity
QoS	Serious

Remedial action

Change/drop the request.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Requested reserve data invalid log

Requested reserve data invalid

Trying to remove an entry that is not actually reserved.

Source	Severity
QoS	Serious

Remedial action

Check if the specified entry wasn't already removed.



Request invalid - QoS interface apps enabled on interface(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Request invalid - QoS interface apps enabled on interface(s) log

Request invalid - QoS interface apps enabled on interface(s)

Request is denied as the interface applications are enabled on this port.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface or disable the interface application on this port.



Request invalid - specified interface currently QoS-disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Request invalid - specified interface currently QoS-disabled log

Request invalid - specified interface currently QoS-disabled

All request are denied when the target interface is QoS disabled.

Source	Severity
QoS	Serious

Remedial action

Enter a different interface index.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Request temporarily denied - QoS support is currently disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Request temporarily denied - QoS support is currently disabled log

Request temporarily denied - QoS support is currently disabled

All request are denied when QoS overall is disabled.

Source	Severity
QoS	Serious

Remedial action

Enable QoS overall before committing any request.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Required bandwidth information not specified log

Required bandwidth information not specified

The queue bandwidth parameter has not been provided.

Source	Severity
QoS	Serious

Remedial action

Specify the queue bandwidth parameter based on the bandwidth allocation attribute.



Reset - Error Failed to get the Reset sem

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Reset - Error Failed to get the Reset sem log

Reset - Error Failed to get the Reset sem

The system failed to get ownership of the reset semaphore to prevent reset during download.

Source	Severity
--------	----------

Flash Driver	Critical
--------------	----------

Remedial action

Retry the operation.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Reset initiated by console log

Reset initiated by console

Reset is initiated through a serial connection.

Source	Severity
Console	Serious

Remedial action

No action required.



Reset initiated through SSH by IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Reset initiated through SSH by IP address log

Reset initiated through SSH by IP address

Reset initiated through the SSH connection.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.



Reset initiated through telnet by IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Reset initiated through telnet by IP address log

Reset initiated through telnet by IP address

Reset is initiated through a telnet connection.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Reset to default initiated by console log

Reset to default initiated by console

Reset to the default settings initiated through serial connection.

Source	Severity
Console	Serious

Remedial action

No action required.



Reset to default initiated through telnet by IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Reset to default initiated through telnet by IP address log

Reset to default initiated through telnet by IP address

Reset to default settings initiated through the telnet connection.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Resource alloc event timeout (tgt all apps except QoS Agent rcv event) log

Resource alloc event timeout (tgt all apps except QoS Agent rcv event)

Filter Manager failed to allocate the necessary resources in time.

Source	Severity
QoS	Critical

Remedial action

Reset the unit.



Resources exhausted (maximum class entries reached)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Resources exhausted (maximum class entries reached) log

Resources exhausted (maximum class entries reached)

The maximum entries allowed for the class you are trying to configure an entry has been reached.

Source	Severity
QoS	Serious

Remedial action

Check for and remove the related QoS entries that are not needed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Resources exhausted (out-of-memory) log

Resources exhausted (out-of-memory)

Memory allocation for the new entry failed.

Source	Severity
QoS	Serious

Remedial action

Check for and remove the QoS entries that are not needed.



Restore Backup Configuration to Manufacture Default

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Restore Backup Configuration to Manufacture Default log

Restore Backup Configuration to Manufacture Default

The manufactured default back up configuration is restored.

Source	Severity
config	Information

Remedial action

No action required.



Restore Primary Configuration to Manufacture Default

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Restore Primary Configuration to Manufacture Default log

Restore Primary Configuration to Manufacture Default

The manufactured default primary configuration is restored.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role combination associated with interface (deletion prohibited) log

Role combination associated with interface (deletion prohibited)

Cannot remove a role combination if it's associated with an interface.

Source	Severity
QoS	Serious

Remedial action

Associate a different interface role combination to the interface before requesting the removal.



Role combination contains unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role combination contains unacceptable characters log

Role combination contains unacceptable characters

A valid role combination contains letters, digits, special characters (period, line, plus, underline but not on the first position) and '\$' but only as the first character.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Enter valid characters for the access element's label.



Role combination distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role combination distribution across stack failed log

Role combination distribution across stack failed

Unable to commit role combination distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Role combination length outside of acceptable limits

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role combination length outside of acceptable limits log

Role combination length outside of acceptable limits

The maximum role combination length supported is 32.

Source	Severity
QoS	Information

Remedial action

Enter a valid role combination.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Role combination modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role combination modifications not supported log

Role combination modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Role combination referenced by policy (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role combination referenced by policy (deletion prohibited) log

Role combination referenced by policy (deletion prohibited)

Cannot remove a role combination if it's referenced by a policy.

Source	Severity
QoS	Serious

Remedial action

Remove the policy first.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Role (interface) capabilities incompatible with policy data log

Role (interface) capabilities incompatible with policy data

The policy and the specified role(the component interfaces) have different version capabilities.

Source	Severity
QoS	Serious

Remedial action

Enter either a role with compatible interface(s) or adapt the policy to match the required version.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

%s card inserted (in unit %s) log

%s card inserted (in unit %s)

This message appears when an MDA card is inserted.

Source	Severity
MDA	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

%s card removed (from unit %s) log

%s card removed (from unit %s)

This message appears when MDA card is removed.

Source	Severity
MDA	Information

Remedial action

No action required.



Script was successfully executed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Script was successfully executed log

Script was successfully executed

Script finished with success.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

No action required.



Session closed (inactivity logout) IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session closed (inactivity logout) IP address log

Session closed (inactivity logout) IP address

The telnet session is disconnected after 15 minutes of console inactivity.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.



Session closed (inactivity logout) IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session closed (inactivity logout) IP address log

Session closed (inactivity logout) IP address

Telnet session was disconnected after 15 minutes of console inactivity.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.



Session closed (lost connection) IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session closed (lost connection) IP address log

Session closed (lost connection) IP address

Client aborted the connection by sending a RST message. The server disconnected the session.

Source	Severity
--------	----------

Telnet Server	Information
---------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session closed (user logout) IP address log

Session closed (user logout) IP address

You have disconnected the telnet session.

Source	Severity
Telnet Server	Information

Remedial action

No action required.



Session closed (user logout) serial connection

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session closed (user logout) serial connection log

Session closed (user logout) serial connection

You have disconnected the serial connection session.

Source	Severity
Console	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session opened from IP address log

Session opened from IP address

The telnet session has begun. You now have the access to the terminal using the CTRL-Y key or you have successfully logged-in, in case of authentication requirement.

Source	Severity
Telnet Server	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session opened from serial connection log

Session opened from serial connection

Session has begun on the serial connection. You now have access to the terminal using the CTRL-Y key or successfully logged-in, in the case of authentication requirement.

Source	Severity
Console	Information

Remedial action

No action required.



Session opened (local auth) from IP address:

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session opened (local auth) from IP address: log

Session opened (local auth) from IP address:

Successful authentication with local credentials over telnet session.

Source	Severity
--------	----------

Telnet server	Information
---------------	-------------

Remedial action

No action required.



Session opened (local auth) from serial connection

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session opened (local auth) from serial connection log

Session opened (local auth) from serial connection

Successful authentication with local credentials on serial port.

Source	Severity
Console	Information

Remedial action

No action required.



Session opened(radius auth) from IP add

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session opened(radius auth) from IP add log

Session opened(radius auth) from IP add

You have successfully logged in with the Radius Server. Telnet session has begun.

Source	Severity
Telnet Server	Information

Remedial action

No action required.



Session opened(radius auth) from serial conn

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Session opened(radius auth) from serial conn log

Session opened(radius auth) from serial conn

You have successfully logged-in with the Radius Server. The serial connection session is opened.

Source	Severity
Console	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Set port to default log

Set port to default

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is at high alarm level on s log

SFP internal supply voltage is at high alarm level on s

The internal supply voltage of a transceiver inserted on a certain unit/port is at high alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is at high warning level on %s log

SFP internal supply voltage is at high warning level on %s

The internal supply voltage of a transceiver inserted on a certain unit/port is at high warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP internal supply voltage is at low alarm level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is at low alarm level on %s log

SFP internal supply voltage is at low alarm level on %s

The internal supply voltage of a transceiver inserted on a certain unit/port is at low alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is at low warning level on %s log

SFP internal supply voltage is at low warning level on %s

The internal supply voltage of a transceiver inserted on a certain unit/port is at low warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP internal supply voltage is no longer at the high alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is no longer at the high alarm level log

SFP internal supply voltage is no longer at the high alarm level

Will be logged only after the actual value of the internal voltage has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is no longer at the high warning level log

SFP internal supply voltage is no longer at the high warning level

Will be logged only after the actual value of the internal voltage has previously exceeded the warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP internal supply voltage is no longer at the low alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is no longer at the low alarm level log

SFP internal supply voltage is no longer at the low alarm level

Will be logged only after the actual value of the internal voltage has previously exceeded the alarm threshold, and at the current moment the value is above that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP internal supply voltage is no longer at the low warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal supply voltage is no longer at the low warning level log

SFP internal supply voltage is no longer at the low warning level

Will be logged only after the actual value of the internal voltage has previously exceeded the warning threshold, and at the current moment the value is above that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is at high alarm level on %s log

SFP internal temperature is at high alarm level on %s

The internal temperature of a transceiver inserted on a certain unit/port is at high alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP internal temperature is at high warning level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is at high warning level on %s log

SFP internal temperature is at high warning level on %s

The internal temperature of a transceiver inserted on a certain unit/port is at high warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is at low alarm level on %s log

SFP internal temperature is at low alarm level on %s

The internal temperature of a transceiver inserted on a certain unit/port is at low alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP internal temperature is at low warning level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is at low warning level on %s log

SFP internal temperature is at low warning level on %s

The internal temperature of a transceiver inserted on a certain unit/port is at low warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP internal temperature is no longer at the high alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is no longer at the high alarm level log

SFP internal temperature is no longer at the high alarm level

Will be logged only after the actual value of the internal temperature has previously exceeded the high alarm threshold, and at the moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP internal temperature is no longer at the high warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is no longer at the high warning level log

SFP internal temperature is no longer at the high warning level

Will be logged only after the actual value of the internal temperature has previously exceeded the high warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SFP internal temperature is no longer at the low alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is no longer at the low alarm level log

SFP internal temperature is no longer at the low alarm level

Will be logged only after the actual value of the internal temperature has previously exceeded the low alarm threshold, and at the current moment the value is above that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SFP internal temperature is no longer at the low warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP internal temperature is no longer at the low warning level log

SFP internal temperature is no longer at the low warning level

Will be logged only after the actual value of the internal temperature has previously exceeded the low warning threshold, and at the current moment the value is above that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is at high alarm level on %s log

SFP Received power is at high alarm level on %s

The received power of a transceiver inserted on a certain unit/port is at high alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is at high warning level on %s log

SFP Received power is at high warning level on %s

The received power of a transceiver inserted on a certain unit/port is at high warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP Received power is at low alarm level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is at low alarm level on %s log

SFP Received power is at low alarm level on %s

The received power of a transceiver inserted on a certain unit/port is at low alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is at low warning level on %s log

SFP Received power is at low warning level on %s

The received power of a transceiver inserted on a certain unit/port is at low warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP Received power is no longer at the high alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is no longer at the high alarm level log

SFP Received power is no longer at the high alarm level

Will be logged only after the actual value of the RX power has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP Received power is no longer at the high warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is no longer at the high warning level log

SFP Received power is no longer at the high warning level

Will be logged only after the actual value of the RX power has previously exceeded the warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP Received power is no longer at the low alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is no longer at the low alarm level log

SFP Received power is no longer at the low alarm level

Will be logged only after the actual value of the RX power has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP Received power is no longer at the low warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP Received power is no longer at the low warning level log

SFP Received power is no longer at the low warning level

Will be logged only after the actual value of the RX power has previously exceeded the warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias current is at high alarm level on %s log

SFP TX Bias current is at high alarm level on %s

The TX Bias current of a transceiver inserted on a certain unit/port is at high alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias current is at high warning level on %s log

SFP TX Bias current is at high warning level on %s

The TX Bias current of a transceiver inserted on a certain unit/port is at high warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias current is at low alarm level on %s log

SFP TX Bias current is at low alarm level on %s

The TX Bias current of a transceiver inserted on a certain unit/port is at low alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias current is at low warning level on %s log

SFP TX Bias current is at low warning level on %s

The TX Bias current of a transceiver inserted on a certain unit/port is at low warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP TX Bias is no longer at the high alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias is no longer at the high alarm level log

SFP TX Bias is no longer at the high alarm level

Will be logged only after the actual value of the bias has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX Bias is no longer at the high warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias is no longer at the high warning level log

SFP TX Bias is no longer at the high warning level

Will be logged only after the actual value of the bias has previously exceeded the warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX Bias is no longer at the low alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias is no longer at the low alarm level log

SFP TX Bias is no longer at the low alarm level

Will be logged only after the actual value of the bias has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX Bias is no longer at the low warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX Bias is no longer at the low warning level log

SFP TX Bias is no longer at the low warning level

Will be logged only after the actual value of the bias has previously exceeded the warning threshold and at the current moment the value is above that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX output power is at high alarm level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is at high alarm level on %s log

SFP TX output power is at high alarm level on %s

The TX output power of a transceiver inserted on a certain unit/port is at high alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is at high warning level on %s log

SFP TX output power is at high warning level on %s

The TX output power of a transceiver inserted on a certain unit/port is at high warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP TX output power is at low alarm level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is at low alarm level on %s log

SFP TX output power is at low alarm level on %s

The TX output power of a transceiver inserted on a certain unit/port is at low alarm level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP TX output power is at low warning level on %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is at low warning level on %s log

SFP TX output power is at low warning level on %s

The TX output power of a transceiver inserted on a certain unit/port is at low warning level.

Source	Severity
Port driver	Information

Remedial action

Check pluggable part and replace if necessary.



SFP TX output power is no longer at the high alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is no longer at the high alarm level log

SFP TX output power is no longer at the high alarm level

Will be logged only after the actual value of the tx power has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX output power is no longer at the high warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is no longer at the high warning level log

SFP TX output power is no longer at the high warning level

Will be logged only after the actual value of the tx power has previously exceeded the warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX output power is no longer at the low alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is no longer at the low alarm level log

SFP TX output power is no longer at the low alarm level

Will be logged only after the actual value of the tx power has previously exceeded the alarm threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.



SFP TX output power is no longer at the low warning level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SFP TX output power is no longer at the low warning level log

SFP TX output power is no longer at the low warning level

Will be logged only after the actual value of the tx power has previously exceeded the warning threshold, and at the current moment the value is below that threshold.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Simultaneous operations involving access asgn ifcs prohibited log

Simultaneous operations involving access asgn ifcs prohibited

Other similar operations involving the specified access assignment/interface(s) used by the policy are in progress.

Source	Severity
QoS	Information

Remedial action

Try again later after all the pending operations are completed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Simultaneous operations involving policies and blocks prohibited log

Simultaneous operations involving policies and blocks prohibited

Other similar operations involving the specified block used by the policy are in progress.

Source	Severity
QoS	Information

Remedial action

Try again later after all the pending operations finished.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Simultaneous operations involving policies and ifcs prohibited log

Simultaneous operations involving policies and ifcs prohibited

Interfaces directly associated with a policy must be stable (active, not being created/deleted).

Source	Severity
QoS	Information

Remedial action

Try again later after all the pending operations finished.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Simultaneous operations involving policy blocks ifcs prohibited log

Simultaneous operations involving policy blocks ifcs prohibited

Other similar operations involving the interface used by the block/policy are in progress.

Source	Severity
QoS	Information

Remedial action

Try again later after all the pending operations are finished.



SLAMon Agent: agent IP address reset to default value

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: agent IP address reset to default value log

SLAMon Agent: agent IP address reset to default value

SLA Mon agent IP address set to default

Source	Severity
SLAMon	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent CLI support not available log

SLAMon Agent CLI support not available

SLM CLI support not included in image - current N/A

Source	Severity
SLAMon	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent CLI timeout value out of range log

SLAMon Agent CLI timeout value out of range

The specified SLA Monitor agent CLI timeout value lies outside the acceptable range (60 seconds to 600 seconds).

Source	Severity
SLAMon	Information

Remedial action

Specify an in-range value for the agent CLI timeout.



SLAMon Agent disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent disabled log

SLAMon Agent disabled

SLA Monitor agent state change detected — agent disabled.

Source	Severity
SLAMon	Information

Remedial action

No action required.



SLAMon Agent enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent enabled log

SLAMon Agent enabled

SLA Monitor agent state change detected — agent enabled.

Source	Severity
SLAMon	Information

Remedial action

No action required.



SLAMon Agent: inconsistent IP address data specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: inconsistent IP address data specified log

SLAMon Agent: inconsistent IP address data specified

IP address for SLA Mon agent is not existing on the device

Source	Severity
SLAMon	Information

Remedial action

Configure IP address before using for SLA Mon agent.



SLAMon Agent inconsistent UDP port data specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent inconsistent UDP port data specified log

SLAMon Agent inconsistent UDP port data specified

Agent UDP (command) port and agent-to-agent communication UDP port values conflict with each other. The port values must be unique.

Source	Severity
SLAMon	Information

Remedial action

Utilize defaults or specify unique agent UDP port values.



SLAMon Agent info: %d %d %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent info: %d %d %d log

SLAMon Agent info: %d %d %d

General debug message — currently N/A

Source	Severity
SLAMon	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent invalid agent-to-agent port (must be even value) log

SLAMon Agent invalid agent-to-agent port (must be even value)

Agent-to-agent communication UDP port must be an even value.

Source	Severity
SLAMon	Information

Remedial action

Specify an even value for port.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: message channel creation failure log

SLAMon Agent: message channel creation failure

Internal resource error - engineering log message.

Source	Severity
SLAMon	Critical

Remedial action

Reset device



SLAMon Agent message channel creation failure

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent message channel creation failure log

SLAMon Agent message channel creation failure

Internal resource errore — engineering log message

Source	Severity
SLAMon	Critical

Remedial action

Reset device.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent operation is restricted CLI-only

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent operation is restricted CLI-only log

SLAMon Agent operation is restricted CLI-only

The requested operation is only supported through the platform CLI.

Source	Severity
SLAMon	Information

Remedial action

Utilize the platform CLI to perform the requested operation.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent platform CLI command interface initialization issue log

SLAMon Agent platform CLI command interface initialization issue

Internal resource errore — engineering log message

Source	Severity
SLAMon	Critical

Remedial action

Reset device.



SLAMon Agent platform timer initialization issue

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent platform timer initialization issue log

SLAMon Agent platform timer initialization issue

Internal resource errore — engineering log message

Source	Severity
SLAMon	Critical

Remedial action

Reset device.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent: terminated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: terminated log

SLAMon Agent: terminated

Internal resource error.

Source	Severity
SLAMon	Critical

Remedial action

Reset device.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent terminated

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent terminated log

SLAMon Agent terminated

The agent task logic has been terminated.

Source	Severity
SLAMon	Critical

Remedial action

System reset required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent: terminated - command/frame processing issue detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: terminated - command/frame processing issue detected log

SLAMon Agent: terminated - command/frame processing issue detected

An internal resource error has occurred.

Source	Severity
SLAMon	Critical

Remedial action

Reset device

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent terminated — command/frame processing issue detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent terminated — command/frame processing issue detected log

SLAMon Agent terminated — command/frame processing issue detected

The agent command/packet receive logic detected an error, causing the agent operation to be terminated.

Source	Severity
SLAMon	Critical

Remedial action

System reset required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent: terminated - NTR test exception detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: terminated - NTR test exception detected log

SLAMon Agent: terminated - NTR test exception detected

An internal resource error has occurred.

Source	Severity
SLAMon	Critical

Remedial action

Reset device

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent terminated NTR test exception detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent terminated NTR test exception detected log

SLAMon Agent terminated NTR test exception detected

The agent NTR test support detected a failure during test processing, causing agent operation to be terminated.

Source	Severity
SLAMon	Critical

Remedial action

System reset required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent: terminated - resources unavailable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: terminated - resources unavailable log

SLAMon Agent: terminated - resources unavailable

An internal resource error has occurred.

Source	Severity
SLAMon	Critical

Remedial action

Reset device

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent terminated - resources unavailable

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent terminated - resources unavailable log

SLAMon Agent terminated - resources unavailable

Resources required for agent initialization are not available, causing agent operation to be terminated. An invalid configuration, such as when the same port values are specified for agent-server and agent-agent communication, can also impact resource availability.

Source	Severity
--------	----------

SLAMon	Critical
--------	----------

Remedial action

System reset required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent: terminated - RTP test exception detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent: terminated - RTP test exception detected log

SLAMon Agent: terminated - RTP test exception detected

An internal resource error has occurred.

Source	Severity
SLAMon	Critical

Remedial action

Reset device

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLAMon Agent terminated - RTP test exception detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLAMon Agent terminated - RTP test exception detected log

SLAMon Agent terminated - RTP test exception detected

The agent RTP test support detected a failure during test processing, causing agent operation to be terminated.

Source	Severity
SLAMon	Critical

Remedial action

System reset required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SLPP-guard: hold-down timer has expired on port with SLPP-guard enabled. Port %s has been re-enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLPP-guard: hold-down timer has expired on port with SLPP-guard enabled. Port %s has been re-enabled log

SLPP-guard: hold-down timer has expired on port with SLPP-guard enabled. Port %s has been re-enabled

The hold-down timer has expired and the port was re-enabled.

Source	Severity
--------	----------

SLPP Guard	Information
------------	-------------

Remedial action

No action required.



SLPP-guard: SLPP-guard has not been enabled on port %s as no filters or filter precedences are available to setup an Ethertype filter

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLPP-guard: SLPP-guard has not been enabled on port %s as no filters or filter precedences are available to setup an Ethertype filter log

SLPP-guard: SLPP-guard has not been enabled on port %s as no filters or filter precedences are available to setup an Ethertype filter

SLPP-guard filters error.

Source	Severity
--------	----------

SLPP Guard	Information
------------	-------------

Remedial action

No action required.



SLPP-guard: SLPP packet received on port with SLPP-guard enabled. Port %s has been disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLPP-guard: SLPP packet received on port with SLPP-guard enabled. Port %s has been disabled log

SLPP-guard: SLPP packet received on port with SLPP-guard enabled. Port %s has been disabled

A SLPP packet was received and SLPP-guard disabled the port.

Source	Severity
--------	----------

SLPP Guard	Information
------------	-------------

Remedial action

No action required.



SLPP Warning - PDU was received on Vlan VlanId Unit UnitNo Port PortNo .

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SLPP Warning - PDU was received on Vlan VlanId Unit UnitNo Port PortNo . log

SLPP Warning - PDU was received on Vlan VlanId Unit UnitNo Port PortNo .

The system detected an SLPP error when the SLPP packet sent is received back on a different VLAN.

Source	Severity
SMLT	Information

Remedial action

Check for the correct port configuration

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT IMC invalid cmd 1– StkCmd log

SMLT IMC invalid cmd 1– StkCmd

An invalid SMLT Imc command received in the stack.

Source	Severity
SMLT	Information

Remedial action

Restart the system.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT IMC tx error log

SMLT IMC tx error

The system failed to transmit the IMC message in the stack.

Source	Severity
SMLT	Information

Remedial action

Restart the system.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT input parameter error mlt port vlan log

SMLT input parameter error mlt port vlan

The system failed to enable the SMLT as the IST ports are not a part of the VLAN.

Source	Severity
SMLT	Information

Remedial action

Check for the correct VLAN membership of the IST ports.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Stack db ex event num -0 –0*22221111 log

SMLT Stack db ex event num -0 –0*22221111

Log SMLT db exchange events.

Source	Severity
SMLT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT stackEventNotify Invalid Msg Cmd - 0 – 0 log

SMLT stackEventNotify Invalid Msg Cmd - 0 – 0

The system received an invalid stack related event.

Source	Severity
SMLT	Information

Remedial action

Restart the system.



SMLT Stack inactive event 0-0- modMask

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Stack inactive event 0-0- modMask log

SMLT Stack inactive event 0-0- modMask

Log SMLT unit inactive events.

Source	Severity
SMLT	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



SMLT Stack joined event num - 0 – 0*33331111

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Stack joined event num - 0 – 0*33331111 log

SMLT Stack joined event num - 0 – 0*33331111

Log SMLT stack Join events.

Source	Severity
SMLT	Information

Remedial action

No action required.



SMLT Stack leaved event 0 - 0 - modMask

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Stack leaved event 0 - 0 - modMask log

SMLT Stack leaved event 0 - 0 - modMask

Log SMLT stack leave events.

Source	Severity
SMLT	Information

Remedial action

No action required.



SMLT STP enabled on IST trunk trkNo stp group grp

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT STP enabled on IST trunk trkNo stp group grp log

SMLT STP enabled on IST trunk trkNo stp group grp

STP enabled on the IST trunk error.

Source	Severity
SMLT	Information

Remedial action

Disable the STP on IST trunk ports.



SMLT Warning - LAC SMLT with more than 8 links - key - count

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Warning - LAC SMLT with more than 8 links - key - count log

SMLT Warning - LAC SMLT with more than 8 links - key - count

LAC/SMLT with more than 8 links with specified key count.

Source	Severity
SMLT	Information

Remedial action

Do not configure more than 8 links in the SMLT over the LAC configuration.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Warning - smltEnable Software License Error- 0 – 0 log

SMLT Warning - smltEnable Software License Error- 0 – 0

This is a SMLT related warning indicating, software License error.

Source	Severity
SMLT	Information

Remedial action

Check if a valid software license is available.



SMLT Warning - SMLT mismatched Lac_Sys_ID error shutdown all SMLT lac po

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SMLT Warning - SMLT mismatched Lac_Sys_ID error shutdown all SMLT lac po log

SMLT Warning - SMLT mismatched Lac_Sys_ID error shutdown all SMLT lac po

This is an SMLT related warning indicating, SMLT system ID mismatch.

Source	Severity
SMLT	Information

Remedial action

The SMLT system ID did not match. Configure the correct system ID.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SNMP-access is disabled log

SNMP-access is disabled

Logged when SNMP-access is disabled from CLI.

Source	Severity
SNMP	Information

Remedial action

No action Required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SNMP-access is enabled log

SNMP-access is enabled

Logged when SNMP-access is enabled from CLI.

Source	Severity
SNMP	Information

Remedial action

No action Required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SNTP Could not sync to NTP servers. log

SNTP Could not sync to NTP servers.

The SNTP could not synchronize with any of the two NTP servers.

Source	Severity
SNTP	Critical

Remedial action

Try synchronizing to a valid NTP server. Make sure that the SNTP is connected to the NTP servers you are trying to synchronize with.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SNTP: First synchronization successful. log

SNTP: First synchronization successful.

The SNTP is synchronized with one of the NTP servers.

Source	Severity
SNTP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Source MAC address and mask values out-of-sync log

Source MAC address and mask values out-of-sync

The source MAC address and mask do not correspond (at least one address bit not included in mask is set).

Source	Severity
QoS	Serious

Remedial action

Modify the source MAC address or mask.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM adjacency with neighbor log

SPBM adjacency with neighbor

When IS-IS forms more than 1 adjacency with the same IS.

Source	Severity
ISIS	Information

Remedial action

No action required.



SPB-MC Dynamic i-sid range conflicts with existing i-sid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPB-MC Dynamic i-sid range conflicts with existing i-sid log

SPB-MC Dynamic i-sid range conflicts with existing i-sid

I-SIDs greater than 16,000,000 are reserved for SPBM multicast functionality

Source	Severity
SPB	Information

Remedial action

Remove configure I-SIDs greater than 16,000,000.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM detect adj log

SPBM detect adj

When the IS-IS adjacency state changes (down, init, up).

Source	Severity
ISIS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding C-VLAN UNI for i-sid %d, vlan %d - no resources log

SPBM: ERROR adding C-VLAN UNI for i-sid %d, vlan %d - no resources

UNIs, NNIs and remote nodes use one or more Virtual Ports, depending on the configuration. The number of Virtual Ports that can be configured on the switch is limited.

Source	Severity
SPBM	Error

Remedial action

See the "Limitations" section in the user manual. Remove unneeded UNIs.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding i-sid %x to i-sid table - table full log

SPBM: ERROR adding i-sid %x to i-sid table - table full

The number of I-SIDs that can be configured on the switch is limited.

Source	Severity
SPBM	Critical

Remedial action

See the "Limitations" section in the user manual. Remove unneeded I-SIDs.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding i-sid %x to i-sid table - table full log

SPBM: ERROR adding i-sid %x to i-sid table - table full

The number of I-SIDs that can be configured on the switch is limited.

Source	Severity
SPBM	Critical

Remedial action

See the "Limitations" section in the user manual. Remove unneeded I-SIDs.



SPBM: ERROR adding NNI on port %d vlan %d - no resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding NNI on port %d vlan %d - no resources log

SPBM: ERROR adding NNI on port %d vlan %d - no resources

UNIs, NNIs and remote nodes use one or more Virtual Ports, depending on the configuration. The number of Virtual Ports that can be configured on the switch is limited.

Source	Severity
--------	----------

SPBM	Error
------	-------

Remedial action

See the "Limitations" section in the user manual. Remove unneeded UNIs.



SPBM: ERROR adding peer %04x.%04x.%04x - no resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding peer %04x.%04x.%04x - no resources log

SPBM: ERROR adding peer %04x.%04x.%04x - no resources

UNIs, NNIs and remote nodes use one or more Virtual Ports, depending on the configuration. The number of Virtual Ports that can be configured on the switch is limited. The remote system with the system-id listed in the text of the message will not receive.

Source	Severity
SPBM	Error

Remedial action

See the "Limitations" section in the user manual. Remove unneeded UNIs.



SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources log

SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources

UNIs, NNIs and remote nodes use one or more Virtual Ports, depending on the configuration. The number of Virtual Ports that can be configured on the switch is limited.

Source	Severity
SPBM	Error

Remedial action

See the "Limitations" section in the user manual. Remove unneeded UNIs.



SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources log

SPBM: ERROR adding switched UNI for i-sid %d, port %d, vlan %d - no resources

When a trunk is disabled, the software automatically configures a UNI for each physical port in the trunk. UNIs, NNIs and remote nodes use one or more Virtual Ports, depending on the configuration.

Source	Severity
SPBM	Error

Remedial action

See the "Limitations" section in the user manual. Remove unneeded UNIs.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR adding Transparent UNI for i-sid %d, port %d - no resources log

SPBM: ERROR adding Transparent UNI for i-sid %d, port %d - no resources

Error adding Transparent UNI.

Source	Severity
SPBM	Information

Remedial action

No action required.



SPBM: ERROR enabling SPBM due to Software License error

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR enabling SPBM due to Software License error log

SPBM: ERROR enabling SPBM due to Software License error

SPBM License missing or invalid; IS-IS protocol will not run.

Source	Severity
SPBM	Critical

Remedial action

Run



SPBM: ERROR updating UNI for port %d/%d - no resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM: ERROR updating UNI for port %d/%d - no resources log

SPBM: ERROR updating UNI for port %d/%d - no resources

UNIs, NNIs and remote nodes use one or more Virtual Ports, depending on the configuration. The number of Virtual Ports that can be configured on the switch is limited.

Source	Severity
--------	----------

SPBM	Error
------	-------

Remedial action

See the "Limitations" section in the user manual. Remove unneeded UNIs.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM ISIS log

SPBM ISIS

An IS-IS trap indicating that a Hello packet with a duplicate system-id has been received.

Source	Severity
ISIS	Information

Remedial action

Correct IS-IS system-id configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM ISIS detect duplicate nick-name log

SPBM ISIS detect duplicate nick-name

An IS-IS trap indicating that a LSP with a duplicate nickname has received.

Source	Severity
ISIS	Information

Remedial action

Correct IS-IS SPBM nick-name configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SPBM ISIS node log

SPBM ISIS node

An IS-IS trap was sent indicating that a LSP with a different value of I1-metric has been received

Source	Severity
ISIS	Information

Remedial action

Correct SPBM I1-metric configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified Destination Layer 4 min max range not supported log

Specified Destination Layer 4 min max range not supported

The destination port range is not supported.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and adapt it to a supported port range.



Specified filter criteria is invalid inconsistent

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified filter criteria is invalid inconsistent log

Specified filter criteria is invalid inconsistent

Invalid/inconsistent filter criteria detected in classifier.

Source	Severity
QoS	Serious

Remedial action

Identify and remove the inconsistent/invalid data.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified filter information not found log

Specified filter information not found

Failed to find the corresponding classifier in the datapath filter manager table.

Source	Severity
QoS	Critical

Remedial action

Check that the entry queried exists, if so try resetting the QoS agent or the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified filter manager resource invalid log

Specified filter manager resource invalid

Filter manager detected an invalid unit.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Specified filter manager resource uninitialized

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified filter manager resource uninitialized log

Specified filter manager resource uninitialized

Unable to initialize the resource support.

Source	Severity
QoS	Critical

Remedial action

Reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Specified inner VLAN ID min max range not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified inner VLAN ID min max range not supported log

Specified inner VLAN ID min max range not supported

Inner VLAN ID range not supported.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and adapt it to a supported port range.



Specified metering operation not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified metering operation not supported log

Specified metering operation not supported

The metering operation is not supported on the target hardware.

Source	Severity
QoS	Serious

Remedial action

Create and use a compatible meter.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Specified metering statistics entry already in-use (by policy)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified metering statistics entry already in-use (by policy) log

Specified metering statistics entry already in-use (by policy)

Installing a meter with the same statistics entry already in use by a policy is not allowed, even though sharing a counter entry across meters is supported.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Enter a different statistics entry or remove the policy(s).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified policy components (classifiers) conflicting log

Specified policy components (classifiers) conflicting

All the masks/filters must correspond.

Source	Severity
QoS	Serious

Remedial action

Separate conflicting classifiers into multiple policies.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified policy components (classifiers) conflicting log

Specified policy components (classifiers) conflicting

All the masks/filters must correspond.

Source	Severity
QoS	Serious

Remedial action

Separate conflicting classifiers into multiple policies.



Specified policy identifier (cookie) invalid

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified policy identifier (cookie) invalid log

Specified policy identifier (cookie) invalid

Filter Manager was unable to find the corresponding cookie for the specified policy.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Specified policy statistics entry already in-use (by meter)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified policy statistics entry already in-use (by meter) log

Specified policy statistics entry already in-use (by meter)

The same statistics entry is already associated with a meter. This is currently not allowed. Sharing a count entry across policies is supported.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Enter a different statistics entry or remove the meter.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified queue set information invalid log

Specified queue set information invalid

Invalid information regarding queue set (queue number must be in supported range and the egress flag must be set).

Source	Severity
QoS	Serious

Remedial action

Correct queue information and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified Source Layer 4 min max range not supported log

Specified Source Layer 4 min max range not supported

The source port range is not supported.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and adapt it to a supported port range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified token bucket criteria out of range log

Specified token bucket criteria out of range

Unsupported meter rate range specified.

Source	Severity
QoS	Serious

Remedial action

Enter a supported meter rate range.



Specified token bucket refresh interval not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified token bucket refresh interval not supported log

Specified token bucket refresh interval not supported

The refresh interval must be 8.

Source	Severity
QoS	Serious

Remedial action

Enter the correct refresh interval.



Specified token bucket size (burst size) not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified token bucket size (burst size) not supported log

Specified token bucket size (burst size) not supported

The only supported token bucket sizes are $2^n K$ where n must be between 2 and 14.

Source	Severity
QoS	Serious

Remedial action

Enter one of the valid token bucket sizes.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Specified user policy interface currently QoS-disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified user policy interface currently QoS-disabled log

Specified user policy interface currently QoS-disabled

You cannot configure a user policy entry if the target interface is QoS disabled.

Source	Severity
QoS	Serious

Remedial action

Choose a different interface.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Specified VLAN ID min max range not supported log

Specified VLAN ID min max range not supported

VLAN ID range not supported.

Source	Severity
QoS	Serious

Remedial action

Check the documentation if necessary and adapt it to a supported port range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Src Layer 4 port min max values invalid (max must be = to min) log

Src Layer 4 port min max values invalid (max must be = to min)

The maximum source port must be bigger than the minimum destination port.

Source	Severity
QoS	Serious

Remedial action

Correct source port range limits.



srTCM meter issue - CIR must be the same in both meters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

srTCM meter issue - CIR must be the same in both meters log

srTCM meter issue - CIR must be the same in both meters

Different CIRs detected in the two meters.

Source	Severity
QoS	Serious

Remedial action

Enter the same CIR for both meters.



srTCM meter issue - EBS must be greater than CBS

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

srTCM meter issue - EBS must be greater than CBS log

srTCM meter issue - EBS must be greater than CBS

The burst size is not consistent.

Source	Severity
QoS	Serious

Remedial action

Enter a EBS that is greater than CBS.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

srTCM trTCM meter issue - diff algorithms in associated meters log

srTCM trTCM meter issue - diff algorithms in associated meters

Meter types and rate values are not synchronized .

Source	Severity
QoS	Serious

Remedial action

Associate a single algorithm for a meter.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

srTCM trTCM meter issue - referenced meter incompatible unknown log

srTCM trTCM meter issue - referenced meter incompatible unknown

The referenced meter is compatible (srTCM/trTCM issue).

Source	Severity
QoS	Serious

Remedial action

Check for and remove any conflicts or incompatible data.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

srTCM trTCM meter issue - too many cascaded meters log

srTCM trTCM meter issue - too many cascaded meters

Meter cascade level is limited to two.

Source	Severity
QoS	Serious

Remedial action

Enter only two meter cascade levels.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC: ASCII CFG download SFTP failure log

SSHC: ASCII CFG download SFTP failure

Download of ASCII config file to SFTP failed.

Source	Severity
SFTP	Information

Remedial action

Check IP address settings, host reachability, host key existence and username.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC ASCII CFG download SFTP failure log

SSHC ASCII CFG download SFTP failure

SSHC Client failed to download the ASCII CFG file from SFTP.

Source	Severity
SSHC (SFTP and SSH Client)	Information

Remedial action

Check IP address settings, host reachability, host key existence and username.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC: ASCII CFG upload SFTP failure log

SSHC: ASCII CFG upload SFTP failure

Upload of ASCII config file to SFTP failed.

Source	Severity
SFTP	Information

Remedial action

Check IP address settings, host reachability, host key existence and username.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC ASCII CFG upload SFTP failure log

SSHC ASCII CFG upload SFTP failure

SSHC Client failed to upload the ASCII CFG file to SFTP.

Source	Severity
SSHC (SFTP and SSH Client)	Information

Remedial action

Check IP address settings, host reachability, host key existence and username.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC: CFG download SFTP failure log

SSHC: CFG download SFTP failure

Communication with server failed for some reason, therefore download failed.

Source	Severity
SSH Client	Information

Remedial action

Check if ping works (if not dropped by firewall) for SFTP server. If full path is used verify if the path exist on the server. Check the server settings for sshd/sftp.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC CFG download SFTP failure log

SSHC CFG download SFTP failure

SSHC Client failed to download the CFG file from SFTP.

Source	Severity
SSHC (SFTP and SSH Client)	Information

Remedial action

Check IP address settings, host reachability, host key existence and username.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC: CFG upload SFTP failure log

SSHC: CFG upload SFTP failure

Communication with server failed for some reason, therefore upload failed.

Source	Severity
SSH Client	Information

Remedial action

Check if ping works (if not dropped by firewall) for SFTP server. If full path is used verify if the path exist on the server. Check the server settings for sshd/sftp.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC CFG upload SFTP failure log

SSHC CFG upload SFTP failure

SSHC Client failed to upload the CFG file to SFTP.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

Check IP address settings, host reachability, host key existence and username.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC DSA Authentication failure log

SSHC DSA Authentication failure

Failed to authenticate to the SFTP server using the current DSA key as the current public DSA key of the switch/stack was not added to the SFTP server's "authorized keys" list..

Source	Severity
--------	----------

SFTP Client	Information
-------------	-------------

Remedial action

Upload the key to TFTP/USB and add it to the server's "authorized keys" list.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC DSA key generation failure log

SSHC DSA key generation failure

SSHC Client failed to generate the DSA key.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC DSA key save failure log

SSHC DSA key save failure

SSHC Client failed to save the DSA key.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC DSA key upload TFTP failure log

SSHC DSA key upload TFTP failure

SSHC Client failed to upload the DSA key to TFTP.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

Check the TFTP server connection, and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC DSA key upload USB failure log

SSHC DSA key upload USB failure

SSHC Client failed to upload the DSA key to the USB as, the memory stick is full or corrupted.

Source	Severity
SSHC (SFTP and SSH Client)	Information

Remedial action

Create space on memory stick or replace the memory stick, and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH_CLIENT Key couldnt be saved for host ip address log

SSH_CLIENT Key couldnt be saved for host ip address

New host's key could not be saved as NVRAM is full or defective.

Source	Severity
SSH Client	Information

Remedial action

Remove other host's keys to create space on NVRAM, and try again.



SSH CLIENT SSH Connection to IP ip address was closed because parent console session console session ID was closed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH CLIENT SSH Connection to IP ip address was closed because parent console session console session ID was closed log

SSH CLIENT SSH Connection to IP ip address was closed because parent console session console session ID was closed

SSH Connection is closed as the console session, from which SSH Client was launched closed. (for example, ssh DUT, then ssh PC, then close ssh to DUT session)

Source	Severity
SSH Client	Information

Remedial action

No action required.



SSH CLIENT SSH Connection to %s was disconnected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH CLIENT SSH Connection to %s was disconnected log

SSH CLIENT SSH Connection to %s was disconnected

Successfully disconnected the SSH connection.

Source	Severity
SSH Client	Information

Remedial action

No action required.



SSH CLIENT: SSH Connection to %s
was disconnected by host. Connection
time: %s

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH CLIENT: SSH Connection to %s was disconnected by host. Connection time: %s log

SSH CLIENT: SSH Connection to %s was disconnected by host. Connection time: %s

Host disconnected the SSH connection.

Source	Severity
SSH Client	Information

Remedial action

No action required.



SSH CLIENT: SSH Connection to %s was disconnected by user. Connection time: %s.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH CLIENT: SSH Connection to %s was disconnected by user. Connection time: %s. log

SSH CLIENT: SSH Connection to %s was disconnected by user. Connection time: %s.

SSH user ended SSH connection.

Source	Severity
SSH Client	Information

Remedial action

No action Required.



SSH CLIENT Successful SSH Connection to %s using %s authentication

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH CLIENT Successful SSH Connection to %s using %s authentication log

SSH CLIENT Successful SSH Connection to %s using %s authentication

Successful SSH Connection.

Source	Severity
SSH Client	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC Password Authentication failure log

SSHC Password Authentication failure

SFTP download/upload operation failed due to incorrect password

Source	Severity
--------	----------

SFTP Client	Information
-------------	-------------

Remedial action

Retry operation using the correct password.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC: Password Authentication failure log

SSHC: Password Authentication failure

Wrong username or password used, or password exceeded 30 characters.

Source	Severity
SSH Client	Information

Remedial action

Check if user and password are correct and have 30 or less characters.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA Authentication failure log

SSHC RSA Authentication failure

Failed to authenticate to the SFTP server using the current RSA key as it was not added to the SFTP server's "authorized keys" list..

Source	Severity
SFTP Client	Information

Remedial action

Upload the key to TFTP/USB and add it to the server's "authorized keys" list.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC: RSA Authentication failure log

SSHC: RSA Authentication failure

Mismatch or inconsistency between the generated key and the key uploaded on server.

Source	Severity
SSH Client	Information

Remedial action

Check if the DSA/RSA key was handled correctly. If not sure regenerate the key and upload the new key using tftp server and then try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA key generation failure log

SSHC RSA key generation failure

SSHC Client failed to generate the RSA.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA key save failure log

SSHC RSA key save failure

SSHC Client failed to save the RSA key.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA key upload TFTP failure log

SSHC RSA key upload TFTP failure

SSHC Client failed to upload the RSA key to TFTP.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

Check TFTP server connection, and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA key upload TFTP failure log

SSHC RSA key upload TFTP failure

SSHC Client failed to upload the RSA key to TFTP.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

Check TFTP server connection, and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA key upload USB failure log

SSHC RSA key upload USB failure

SSHC Client failed to upload the RSA key to the USB as, the memory stick is full or corrupted.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

Create space on memory stick or replace the memory stick, and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC RSA key upload USB failure log

SSHC RSA key upload USB failure

SSHC Client failed to upload the RSA key to the USB as, the memory stick is full or corrupted.

Source	Severity
--------	----------

SSHC (SFTP and SSH Client)

Information

Remedial action

Create space on memory stick or replace the memory stick, and try again.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSHC server connection failure log

SSHC server connection failure

Failed to connect to SFTP server; following a command involving SFTP.

Source	Severity
SFTP Client	Information

Remedial action

Check the connectivity to SFTP server. However, this error occurs when you attempt any authentication; it is not caused by authentication failures.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH disabled log

SSH disabled

The SSH is disabled

Source	Severity
SSH	Information

Remedial action

No action required.



SSH DSA key deleted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH DSA key deleted log

SSH DSA key deleted

The SSH DSA key deleted.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH DSA KEY generation completed log

SSH DSA KEY generation completed

The SSH DSA key generation completed.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH enabled in non-secure mode log

SSH enabled in non-secure mode

The SSH is enabled in a non-secure mode.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH enabled in secure mode log

SSH enabled in secure mode

The SSH is enabled in the secure mode.

Source	Severity
SSH	Information

Remedial action

No action required.



SSH Maximum number of ssh sessions has been reached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH Maximum number of ssh sessions has been reached log

SSH Maximum number of ssh sessions has been reached

The maximum number of SSH session is reached.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH RSA KEY generation completed log

SSH RSA KEY generation completed

The SSH RSA key is successfully generated.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH RSA key overwritten log

SSH RSA key overwritten

The SSH RSA key is overwritten.

Source	Severity
SSH	Information

Remedial action

No action required.



SSH session closed by ip address
remote host. Connection time h hours
m minutes

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH session closed by ip address remote host. Connection time h hours m minutes log

SSH session closed by ip address remote host. Connection time h hours m minutes

Remote host closed the SSH session.

Source	Severity
SSH Client	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH session login using port log

SSH session login using port

Login session.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH System is generating DSA KEY wait ... log

SSH System is generating DSA KEY wait ...

The system is generating the DSA key.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH TFTP DSA key download complete log

SSH TFTP DSA key download complete

Download the SSH DSA key through the completed TFTP.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH TFTP RSA key download complete log

SSH TFTP RSA key download complete

SSH RSA key is successfully downloaded through TFTP.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH USB DSA key download complete log

SSH USB DSA key download complete

The SSH DSA key downloading through the USB is completed.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSH USB RSA key download complete log

SSH USB RSA key download complete

The SSH RSA key is successfully downloaded through the USB.

Source	Severity
SSH	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL certificate creation completed log

SSL certificate creation completed

SSL certificate creation completed.

Source	Severity
SSL	Information

Remedial action

No action required.



SSL certificate creation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL certificate creation failed log

SSL certificate creation failed

SSL certificate creation failed.

Source	Severity
SSL	Information

Remedial action

Retry.



SSL certificate deleted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL certificate deleted log

SSL certificate deleted

SSL certificate deleted.

Source	Severity
SSL	Information

Remedial action

No action required.



SSL disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL disabled log

SSL disabled

SSL is disabled.

Source	Severity
SSL	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL enabled log

SSL enabled

SSL is enabled.

Source	Severity
SSL	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

SSL server reset log

SSL server reset

SSL server reset.

Source	Severity
SSL	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable Down 1 is misconfigured log

Stack cable Down 1 is misconfigured

This message appears when the first downstream port is mis-configured.

Source	Severity
Hello Module	Error

Remedial action

Connect the first downstream port to the first upstream port of the neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable Down 2 is misconfigured log

Stack cable Down 2 is misconfigured

This message appears when the second downstream port is mis-configured.

Source	Severity
Hello Module	Error

Remedial action

Connect the second downstream port to the second upstream port of the neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable "Down 1" is misconfigured log

Stack cable "Down 1" is misconfigured

Top cable of Downstream direction is misconfigured.

Source	Severity
HMOD	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable "Down 2" is misconfigured log

Stack cable "Down 2" is misconfigured

Bottom cable of Downstream direction is misconfigured.

Source	Severity
HMOD	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable Up 1 is misconfigured log

Stack cable Up 1 is misconfigured

This message appears when the first upstream port is mis-configured.

Source	Severity
Hello Module	Error

Remedial action

Connect the first upstream port to the first downstream port of the neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable Up 2 is misconfigured log

Stack cable Up 2 is misconfigured

This message appears when the second upstream port is mis-configured.

Source	Severity
Hello Module	Error

Remedial action

Connect the second upstream port to the second downstream port of the neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable "Up 1" is misconfigured log

Stack cable "Up 1" is misconfigured

Top cable of Upstream direction is misconfigured.

Source	Severity
HMOD	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack cable "Up 2" is misconfigured log

Stack cable "Up 2" is misconfigured

Bottom cable of Upstream direction is misconfigured.

Source	Severity
HMOD	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack IP changed log

Stack IP changed

This message indicates that the Stack IP has changed.

Source	Severity
IPT	Information

Remedial action

No action required.



Stack must have a configured base unit!

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack must have a configured base unit! log

Stack must have a configured base unit!

No Base Unit is configured in the stack.

Source	Severity
Stack Manager	Information

Remedial action

Configure one Base Unit in the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Stack operation mode modified to Hybrid and unit reset

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack operation mode modified to Hybrid and unit reset log

Stack operation mode modified to Hybrid and unit reset

Operational Mode was automatically changed and unit was restarted.

Source	Severity
Stack Manager	Serious

Remedial action

No action required.



Stack operation mode modified to Pure and unit reset

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack operation mode modified to Pure and unit reset log

Stack operation mode modified to Pure and unit reset

Operational Mode was automatically changed and unit was restarted.

Source	Severity
Stack Manager	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack RO password changed from IP add log

Stack RO password changed from IP add

Stack RO (Read Only) password changed from telnet or SSH session.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack RO password changed from serial conn log

Stack RO password changed from serial conn

Stack RO (Read Only) password changed from the serial connection session.

Source	Severity
Console	Serious

Remedial action

No action required.



Stack RW password changed from IP add

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack RW password changed from IP add log

Stack RW password changed from IP add

Stack RW (Read Write) password changed from telnet or SSH session.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack RW password changed from serial conn log

Stack RW password changed from serial conn

Stack RW (Read Write) password changed from the serial connection session.

Source	Severity
Console	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack sync failed stack failed to form log

Stack sync failed stack failed to form

The stack did not form as the stack synchronization failed.

Source	Severity
Stack Manager	Serious

Remedial action

Reboot the stack.



Stack synchronization failed Exp value Act value Missing value

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack synchronization failed Exp value Act value Missing value log

Stack synchronization failed Exp value Act value Missing value

Stack synchronization failed on the unit. Missing value yields the application(s) that caused failure.

Source	Severity
Stack Manager	Serious

Remedial action

Reboot the unit if it is unsuccessful in joining the stack.



Stack synchronization failed stack formation delayed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Stack synchronization failed stack formation delayed log

Stack synchronization failed stack formation delayed

The Stack Manager did not receive an acknowledgement after sending the Join message to all the Non Base units for three times in a row.

Source	Severity
--------	----------

Stack Monitor	Information
---------------	-------------

Remedial action

No action required. The switch/stack reboots itself. The logs are saved to NVRAM for future reference.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Successful connection from IP address log

Successful connection from IP address

The client is successfully connected to the telnet server.

Source	Severity
Telnet Server	Information

Remedial action

No action required.



Successfully loaded backup configuration files

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Successfully loaded backup configuration files log

Successfully loaded backup configuration files

Logs a successful configuration read from the backup block on the Flash.

Source	Severity
MCFG	Serious

Remedial action

No action required.



Successfully loaded backup configuration files

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Successfully loaded backup configuration files log

Successfully loaded backup configuration files

Successfully loaded backup configuration files.

Source	Severity
--------	----------

Multi Config	Serious
--------------	---------

Remedial action

No action required.



Successfully loaded configuration files from block %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Successfully loaded configuration files from block %d log

Successfully loaded configuration files from block %d

Logs a successful configuration read from the flash.

Source	Severity
MCFG	Information

Remedial action

No action required.



Successfully loaded configuration files
from block %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Successfully loaded configuration files from block %d log

Successfully loaded configuration files from block %d

Successfully loaded configuration files.

Source	Severity
--------	----------

Multi Config	Information
--------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Successful SSH connection to ip address log

Successful SSH connection to ip address

SSH connection completed successfully.

Source	Severity
SSH Client	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Sw Exception log

Sw Exception

A task caused an exception and is suspended. The exception information is logged and can be accessed through the CLI.

Source	Severity
Exception	Critical

Remedial action

The Exception information contains the problem task, the exception type, the register values, the exception stack trace and memory of the related DRAM area. With this information, you can find out the cause of the exception. (The most common method is to follow the stack trace).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Switch IP changed log

Switch IP changed

This message indicates that the Switch IP has changed.

Source	Severity
IPT	Information

Remedial action

No action required.



Switch RO password changed from IP add

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Switch RO password changed from IP add log

Switch RO password changed from IP add

Switch RO (Read Only) password changed from telnet or SSH session.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.



Switch RO password changed from serial conn

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Switch RO password changed from serial conn log

Switch RO password changed from serial conn

Switch RO (read-only) password changed from the serial connection session.

Source	Severity
Console	Serious

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Switch RW password changed from IP add log

Switch RW password changed from IP add

Switch RW (Read Write) password changed from the telnet or the SSH session.

Source	Severity
--------	----------

Telnet Server	Serious
---------------	---------

Remedial action

No action required.



Switch RW password changed from serial conn

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Switch RW password changed from serial conn log

Switch RW password changed from serial conn

Switch RW (Read Write) password changed from the serial connection session.

Source	Severity
Console	Serious

Remedial action

No action required.



System classifier modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

System classifier modifications not supported log

System classifier modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



System classifier still referenced (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

System classifier still referenced (deletion prohibited) log

System classifier still referenced (deletion prohibited)

Cannot delete a system classifier element if it's referenced in a classifier.

Source	Severity
QoS	Serious

Remedial action

Remove the classifier first.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

System filter distribution across stack failed log

System filter distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.



System: Rear-Port Mode has been set to disable (reboot required to take effect)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

System: Rear-Port Mode has been set to disable (reboot required to take effect) log

System: Rear-Port Mode has been set to disable (reboot required to take effect)

System: Rear-Port Mode has been set to disable, reboot required to take effect.

Source	Severity
Rear-Port	Information

Remedial action

Reboot.



System: Rear-Port Mode has been set to enable (reboot required to take effect).

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

System: Rear-Port Mode has been set to enable (reboot required to take effect). log

System: Rear-Port Mode has been set to enable (reboot required to take effect).

Rear-Port Mode has been set to enable. Reboot required to take effect.

Source	Severity
Rear-Port	Information

Remedial action

Reboot.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ accounting disabled log

TACACS+ accounting disabled

Command logging (accounting) is disabled.

Source	Severity
TACACS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ accounting enabled log

TACACS+ accounting enabled

Command logging (accounting) is enabled.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS+ authenticated serial connection closed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authenticated serial connection closed log

TACACS+ authenticated serial connection closed

TACACS authenticated serial console session was closed.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS+ authenticated telnet session closed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authenticated telnet session closed log

TACACS+ authenticated telnet session closed

Telnet session authenticated through TACACS closed.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS+ authenticated telnet session max retries exceeded

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authenticated telnet session max retries exceeded log

TACACS+ authenticated telnet session max retries exceeded

The maximum number of retries for a TACACS authenticated telnet session exceeded.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TACACS+ authentication on switch serial port disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authentication on switch serial port disabled log

TACACS+ authentication on switch serial port disabled

TACACS authentication disabled on the switch serial console.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS+ authentication on switch serial port enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authentication on switch serial port enabled log

TACACS+ authentication on switch serial port enabled

TACACS authentication enabled on switch serial console.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS+ authentication on switch telnet disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authentication on switch telnet disabled log

TACACS+ authentication on switch telnet disabled

TACACS+ authentication is disabled on switch telnet.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TACACS+ authentication on switch telnet disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authentication on switch telnet disabled log

TACACS+ authentication on switch telnet disabled

TACACS authentication disabled on switch telnet.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TACACS+ authentication on switch telnet enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authentication on switch telnet enabled log

TACACS+ authentication on switch telnet enabled

TACACS+ authentication is disabled on switch telnet.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS+ authentication on switch telnet enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authentication on switch telnet enabled log

TACACS+ authentication on switch telnet enabled

TACACS authentication enabled on switch telnet.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TACACS+ authorization disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authorization disabled log

TACACS+ authorization disabled

Command authorization is disabled.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ authorization enabled log

TACACS+ authorization enabled

Command authorization is enabled.

Source	Severity
TACACS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ successful authentication log

TACACS+ successful authentication

User authentication succeeded.

Source	Severity
TACACS	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS+ unsuccessful authentication log

TACACS+ unsuccessful authentication

User authentication failed.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS authenticated SSH session closed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS authenticated SSH session closed log

TACACS authenticated SSH session closed

TACACS authenticated SSH session has closed.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS authentication on stack serial disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS authentication on stack serial disabled log

TACACS authentication on stack serial disabled

TACACS authentication disabled on stack serial console.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TACACS authentication on stack serial enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS authentication on stack serial enabled log

TACACS authentication on stack serial enabled

TACACS authentication enabled on stack serial console.

Source	Severity
TACACS	Information

Remedial action

No action required.



TACACS authentication on stack telnet disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS authentication on stack telnet disabled log

TACACS authentication on stack telnet disabled

TACACS authentication disabled on stack telnet.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



TACACS authentication on stack telnet enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TACACS authentication on stack telnet enabled log

TACACS authentication on stack telnet enabled

TACACS authentication enabled on stack telnet.

Source	Severity
TACACS	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Task task-name is suspended log

Task task-name is suspended

One of the tasks running on the device encountered a critical error and was suspended.

Source	Severity
Stack Monitor	Critical

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Task task_name is suspended log

Task task_name is suspended

Stack Monitor detected that a task has been suspended for more than 5 minutes.

Source	Severity
Stack Monitor	Information

Remedial action

No action required. The switch/stack reboots itself. The logs are saved to NVRAM for future reference.



Task whose index is Index1 Index2 is suspended

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Task whose index is Index1 Index2 is suspended log

Task whose index is Index1 Index2 is suspended

Stack Monitor detected that a task has been suspended for more than 5 minutes.

Source	Severity
Stack Monitor	Information

Remedial action

No action required. The switch/stack reboots itself. The logs are saved to NVRAM for future reference.



Task whose index is taskID taskID is suspended

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Task whose index is taskID taskID is suspended log

Task whose index is taskID taskID is suspended

One of the tasks running on the device encountered a critical error and was suspended.

Source	Severity
--------	----------

Stack Monitor	Critical
---------------	----------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TCP Control Flag filter criteria requires TCP protocol log

TCP Control Flag filter criteria requires TCP protocol

TCP Control Flag filter criteria must be used with TCP protocol filter criteria.

Source	Severity
QoS	Serious

Remedial action

Add the TCP protocol option.



Telnet-access is disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Telnet-access is disabled log

Telnet-access is disabled

Logged when Telnet-access is disabled from CLI.

Source	Severity
Telnet	Information

Remedial action

No action Required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Telnet-access is disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Telnet-access is disabled log

Telnet-access is disabled

Telnet access was disabled

Source	Severity
Telnet Server	Information

Remedial action

No action required.



Telnet-access is enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Telnet-access is enabled log

Telnet-access is enabled

Logged when Telnet-access is enabled from CLI.

Source	Severity
Telnet	Information

Remedial action

No action Required.



Telnet-access is enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Telnet-access is enabled log

Telnet-access is enabled

Telnet access was enabled

Source	Severity
Telnet Server	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

TFTP Failed log

TFTP Failed

The system failed to get an image through the TFTP.

Source	Severity
Console	Serious

Remedial action

Check the TFTP server.



The base (unit# number) has left the stack. Unit# number is now the base

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The base (unit# number) has left the stack. Unit# number is now the base log

The base (unit# number) has left the stack. Unit# number is now the base

The Base unit has left the stack, a new unit has replaced it.

Source	Severity
Stack Manager	Serious

Remedial action

Examine the base unit that left the stack.



The BU switch is enabled. Cannot join existing stack

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The BU switch is enabled. Cannot join existing stack log

The BU switch is enabled. Cannot join existing stack

The switch has BU switch set and is added to an existing stack.

Source	Severity
Stack Manager	Information

Remedial action

Unset BU switch before adding it to a new stack.



The IP phone PoE limit has been changed to x Watts due to the stack modules configuration

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The IP phone PoE limit has been changed to x Watts due to the stack modules configuration log

The IP phone PoE limit has been changed to x Watts due to the stack modules configuration

As a global parameter, the IP phone PoE limit has dynamically changed to x Watts value in stack configuration, as being the maximum common value supported on all units from stack.

Source	Severity
PoE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The number of stack units is number instead of expected number log

The number of stack units is number instead of expected number

The number of units in the stack differs from the one configured in Stack Monitor.

Source	Severity
Stack Monitor	Information

Remedial action

Check if any units are down or unresponsive. Also check if the Stack Monitor is misconfigured (that is the configured number of units is different from the real number of units in stack)



The password for user <%s> has expired.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The password for user <%s> has expired. log

The password for user <%s> has expired.

The password for the user indicated has expired.

Source	Severity
AAA	Information

Remedial action

Change the password for the user.



The password for user <%s> was changed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The password for user <%s> was changed log

The password for user <%s> was changed

The password for the user indicated was changed.

Source	Severity
AAA	Information

Remedial action

No action required.



The user <%s> was locked

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The user <%s> was locked log

The user <%s> was locked

The user indicated was locked because the threshold for incorrect user-entered information was exceeded.

Source	Severity
AAA	Information

Remedial action

Unlock the user or wait for the login timeout to expire.



The user <%s> was locked.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The user <%s> was locked. log

The user <%s> was locked.

The message logs when an account is locked after the number of wrong logins exceeded the number of allowed retries.

Source	Severity
CONSOLE	Serious

Remedial action

Wait until user account lockout time expires or unlock it with "username <user> unlock" command.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



The user <%s> was unlocked

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

The user <%s> was unlocked log

The user <%s> was unlocked

The user indicated was unlocked because the login timeout expired or other user unlocked it manually.

Source	Severity
AAA	Information

Remedial action

No action Required.



This unit has wrong F W version
expected version actual version

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

This unit has wrong F W version expected version actual version log

This unit has wrong F W version expected version actual version

The unit did not join the stack because the F/W is different than base unit's F/W .

Source

Severity

Stack Manager

Information

Remedial action

Download the correct F/W or configure the unit to automatically download it from the base unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



This unit has wrong S W version
expected version actual version

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

This unit has wrong S W version expected version actual version log

This unit has wrong S W version expected version actual version

The unit did not join the stack because the S/W is different than the base unit's S/W .

Source

Severity

Stack Manager

Information

Remedial action

You should download the correct S/W or configure the unit to automatically download it from base unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Toggle the Agent Primary Image log

Toggle the Agent Primary Image

The NVRAM block can be toggled between 1 and 2.

Source	Severity
config	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket algorithm identifier invalid log

Token bucket algorithm identifier invalid

Invalid token bucket algorithm identifier.

Source	Severity
QoS	Serious

Remedial action

Specify a valid token bucket identifier.



Token bucket algorithm identifier unknown unsupported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket algorithm identifier unknown unsupported log

Token bucket algorithm identifier unknown unsupported

Scheduling algorithm not found.

Source	Severity
QoS	Serious

Remedial action

Specify an existing and valid algorithm identifier.



Token bucket data distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket data distribution across stack failed log

Token bucket data distribution across stack failed

Unable to commit changes across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Token bucket entry referenced by meter (deletion prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket entry referenced by meter (deletion prohibited) log

Token bucket entry referenced by meter (deletion prohibited)

Cannot delete a token bucket entry if it's referenced in a meter.

Source	Severity
QoS	Serious

Remedial action

Remove the meter first.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket entry referenced by shaper (deletion prohibited) log

Token bucket entry referenced by shaper (deletion prohibited)

Cannot delete a token bucket if it's referenced in a shaper.

Source	Severity
QoS	Serious

Remedial action

Remove shaper first.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket minimum rate outside limits (64 - 10230000 Kbps) log

Token bucket minimum rate outside limits (64 - 10230000 Kbps)

The minimum bucket rate must be in the range specified.

Source	Severity
QoS	Serious

Remedial action

Enter a bucket rate bigger than 64Kbps and smaller than 10230000 Kbps.



Token bucket modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket modifications not supported log

Token bucket modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket rate outside limits (64 - 10230000 Kbps) log

Token bucket rate outside limits (64 - 10230000 Kbps)

The token bucket rate must be between 0 and 32Gbps.

Source	Severity
QoS	Serious

Remedial action

Enter a rate value within that range.



Token bucket size not compatible with committed fill rate

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Token bucket size not compatible with committed fill rate log

Token bucket size not compatible with committed fill rate

For cos/queue shaping only MinRate and Rate are set so BurstSize must be \geq Rate only when MinRate = 0.

Source	Severity
QoS	Serious

Remedial action

Enter a valid token bucket size.



Traffic Prof filter set delete operation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Traffic Prof filter set delete operation failed log

Traffic Prof filter set delete operation failed

Unable to carry out the delete operation on the traffic profile filter set across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Traffic Prof filter set elem count exceeds available resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Traffic Prof filter set elem count exceeds available resources log

Traffic Prof filter set elem count exceeds available resources

Although the element count is within the documented limit, the actual resources necessary may not be available due to the runtime configuration.

Source	Severity
QoS	Serious

Remedial action

Check for and remove the resources that are not needed.



Traffic Prof filter set install operation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Traffic Prof filter set install operation failed log

Traffic Prof filter set install operation failed

Unable to carry out the installation on the traffic profile filter set across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Traffic Prof filter set policy count (policy count) exceeds limit (policy limit) log

Traffic Prof filter set policy count (policy count) exceeds limit (policy limit)

The traffic profile filter set policy limit depends on the target hardware platform.

Source	Severity
QoS	Serious

Remedial action

Check the documentation for the maximum number of traffic profile filter set policies allowed.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Traffic Prof filter set rule count (rule count) exceeds limit (rule limit) log

Traffic Prof filter set rule count (rule count) exceeds limit (rule limit)

The maximum number of rules for a traffic profile filter set is 75.

Source	Severity
QoS	Serious

Remedial action

Separate the excess into multiple traffic profile filter sets.



Traffic Prof filter set update operation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Traffic Prof filter set update operation failed log

Traffic Prof filter set update operation failed

Unable to carry out the update operation on the traffic profile filter set across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsAdacPortConfigNotification log

Trap bsAdacPortConfigNotification

ADAC Port Configuration.

Source	Severity
ADAC	Information

Remedial action

No action required.



Trap bsAdacPortOperDisabledNotification

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsAdacPortOperDisabledNotification log

Trap bsAdacPortOperDisabledNotification

ADAC Port operation disabled.

Source	Severity
ADAC	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure log

Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure

This notification is generated after unsuccessfully restoring the DHCP snooping binding table from a SFTP server external file.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess log

Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess

This notification is generated after successfully restoring the DHCP snooping binding table from a SFTP server external file.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: bsDhcpSnoopingExtSaveSFTPSyncFailure

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsDhcpSnoopingExtSaveSFTPSyncFailure log

Trap: bsDhcpSnoopingExtSaveSFTPSyncFailure

This notification is generated after unsuccessfully saving the DHCP Snooping binding table to a SFTP server external file.

Source	Severity
--------	----------

DHCP Snoop	Information
------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess log

Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess

Maximum number of MAC addresses that can be learned on a trunk is reached.

Source

Severity

Bay Secure

Warning/Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess log

Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess

This notification is generated after successfully saving the DHCP snooping binding table to a SFTP server external file.

Source	Severity
SNMP	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsLstGroupOperStateChanged log

Trap: bsLstGroupOperStateChanged

This notification is generated when the operational status of a link-state tracking group changes due to an interface status change.

Source	Severity
LST	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsLstInterfaceStatusChanged log

Trap: bsLstInterfaceStatusChanged

This notification is generated when a physical or logical interface changes its status in a particular link-state tracking group.

Source	Severity
LST	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnAaaAlreadyConnected log

Trap: bsnAaaAlreadyConnected

The message logs when a user connects more than one time.

Source	Severity
CONSOLE	Information

Remedial action

No action required.



Trap: bsnAaaIncorrectLogOnThresholdExceeded

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnAaaIncorrectLogOnThresholdExceeded log

Trap: bsnAaaIncorrectLogOnThresholdExceeded

The message logs when an account is locked after the number of wrong logins exceeded the number of allowed retries.

Source	Severity
CONSOLE	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnAaaMaxNoOfSessionsExceeded log

Trap: bsnAaaMaxNoOfSessionsExceeded

The message logs when the maxim number of current sessions for a user account is exceeded. Informational.

Source	Severity
CONSOLE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnAaaUserAccountNotUsed log

Trap: bsnAaaUserAccountNotUsed

The message logs when a user account, represented by an username, has never been used during a time interval.

Source	Severity
CONSOLE	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnAaaUserPasswordExpired log

Trap: bsnAaaUserPasswordExpired

Logged when user password expiration occurs.

Source	Severity
AAA	Information

Remedial action

Change user password.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnConfigurationSavedToNvram log

Trap bsnConfigurationSavedToNvram

The configuration is saved to NVRAM.

Source	Severity
CONFIG DATA	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnEapAccessViolation log

Trap bsnEapAccessViolation

EAP access violation.

Source	Severity
EAP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnEapUbpFailure log

Trap bsnEapUbpFailure

EAP UBP failure.

Source	Severity
EAP	Information

Remedial action

No action required.



Trap

bsnLacPortDisabledDueToLossOfVLACPDU

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnLacPortDisabledDueToLossOfVLACPDU log

Trap bsnLacPortDisabledDueToLossOfVLACPDU

Lac Port Disabled Due To Loss Of VLACPDU

Source	Severity
LAC	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap bsnLacPortEnabledDueToReceiptOfVLACPDU

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnLacPortEnabledDueToReceiptOfVLACPDU log

Trap bsnLacPortEnabledDueToReceiptOfVLACPDU

LAC Port Enabled as the VLACPDU was received.

Source	Severity
LAC	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: bsnROPasswordExpired: Read-only password expired

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnROPasswordExpired: Read-only password expired log

Trap: bsnROPasswordExpired: Read-only password expired

Notify user that local read-only password has expired.

Source	Severity
--------	----------

Password Security	Information
-------------------	-------------

Remedial action

No action Required



Trap: bsnRWPASSWORDExpired: Read-write password expired

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnRWPASSWORDExpired: Read-write password expired log

Trap: bsnRWPASSWORDExpired: Read-write password expired

Notify user that local read-write password has expired.

Source	Severity
--------	----------

Password Security	Information
-------------------	-------------

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnSFPInsertion on port log

Trap: bsnSFPInsertion on port

SFP was inserted.

Source	Severity
SNMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnSFPRemoval on port log

Trap: bsnSFPRemoval on port

SFP was removed.

Source	Severity
SNMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnStackConfigurationError log

Trap bsnStackConfigurationError

Stack Configuration Error.

Source	Severity
Stack Monitor	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnStackManagerReconfiguration log

Trap bsnStackManagerReconfiguration

Stack manager re-configuration.

Source	Severity
Stack Manager	Information

Remedial action

No action required.



Trap: bsnSystemUp365Days sent from unit %d

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnSystemUp365Days sent from unit %d log

Trap: bsnSystemUp365Days sent from unit %d

The message is logged with the SNMP trap. The notification indicates the system has been up for 365 days.

Source	Severity
--------	----------

TOTAL SYS UPTIME (TSU)	Information
------------------------	-------------

Remedial action

No action required



Trap bsnTrialLicenseExpiration Trial license license# has expired. Disable licensed features to avoid network interruption

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnTrialLicenseExpiration Trial license license# has expired. Disable licensed features to avoid network interruption log

Trap bsnTrialLicenseExpiration Trial license license# has expired. Disable licensed features to avoid network interruption

The trial license has expired.

Source	Severity
SOFTLIC	Information

Remedial action

Disable the licensed features to avoid network interruption.



Trap bsnTrialLicenseExpiration Trial
license license# will expire in # days
day(s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsnTrialLicenseExpiration Trial license license# will expire in # days day(s) log

Trap bsnTrialLicenseExpiration Trial license license# will expire in # days day(s)

This message indicates that the trial license will expire.

Source	Severity
SOFTLIC	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnUSBInsertion on unit log

Trap: bsnUSBInsertion on unit

USB was inserted.

Source	Severity
SNMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: bsnUSBRemoval on unit log

Trap: bsnUSBRemoval on unit

USB was removed.

Source	Severity
SNMP	Information

Remedial action

No action required.



Trap bspePethPsePortCurrentStatusNotification

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bspePethPsePortCurrentStatusNotification log

Trap bspePethPsePortCurrentStatusNotification

Peth Pse Port Current Status.

Source	Severity
POL	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap bsUnicastStormControlAboveHighWatermark

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsUnicastStormControlAboveHighWatermark log

Trap bsUnicastStormControlAboveHighWatermark

Unicast Storm Control reached the high watermark level.

Source	Severity
DRIVER	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap bsUnicastStormControlBelowLowWatermark

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsUnicastStormControlBelowLowWatermark log

Trap bsUnicastStormControlBelowLowWatermark

Unicast Storm Control has gone below low watermark level.

Source	Severity
DRIVER	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap bsveVrrpTrapStateTransition log

Trap bsveVrrpTrapStateTransition

VRRP Trap State Transition.

Source	Severity
VRRP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap DAPP - DoS Attack Detected log

Trap DAPP - DoS Attack Detected

The system detected a DAPP - DoS attack.

Source	Severity
QPAV2	Information

Remedial action

No action required.



Trap Device has entered Forced Stack Mode (MAC Address)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap Device has entered Forced Stack Mode (MAC Address) log

Trap Device has entered Forced Stack Mode (MAC Address)

Device has entered Forced Stack Mode.

Source	Severity
IPT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap entConfigChange log

Trap entConfigChange

Ent Config Change.

Source	Severity
ENTMIB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap fallingAlarm log

Trap fallingAlarm

Falling Alarm.

Source	Severity
RMON	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: FCoE - Egress Issue Detected log

Trap: FCoE - Egress Issue Detected

Issue detected with link/trunk used for FCoE Redirect.

Source	Severity
FCoE Redirect	Serious

Remedial action

Check FCoE config/link status.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap IldpRemTableChange Ageouts = count log

Trap IldpRemTableChange Ageouts = count

IldpRemTableChange Ageouts Number

Source	Severity
802.1AB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap IldpRemTableChange Deletes = count log

Trap IldpRemTableChange Deletes = count

IldpRemTableChange Deletes Number.

Source	Severity
802.1AB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap IldpRemTableChange Drops = count log

Trap IldpRemTableChange Drops = count

IldpRemTableChange Drops Number

Source	Severity
802.1AB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap IldpRemTableChange Inserts = count log

Trap IldpRemTableChange Inserts = count

IldpRemTableChange Inserts Number

Source	Severity
802.1AB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap IldpXMedTopologyChangeDetected Subtype = subtype Class = class log

Trap IldpXMedTopologyChangeDetected Subtype = subtype Class = class

The system detected a LldpXMed Topology Change.

Source	Severity
802.1AB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap newRoot log

Trap newRoot

New root.

Source	Severity
NNCLI	Information

Remedial action

No action required.



Trap ntnQosPolicyEvoLocalUbpSessionFailure

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ntnQosPolicyEvoLocalUbpSessionFailure log

Trap ntnQosPolicyEvoLocalUbpSessionFailure

QoS Policy Evo Local UBP Session Failed.

Source	Severity
QPAV2	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfIfAuthFailure log

Trap ospfIfAuthFailure

The OSPF Interface Authentication failed.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfIfConfigError log

Trap ospfIfConfigError

OSPF Interface Configuration Error.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfIfStateChange log

Trap ospfIfStateChange

The OSPF Interface state changed.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfNbrStateChange log

Trap ospfNbrStateChange

OSPF Neighbor State Change.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfVirtIfAuthFailure log

Trap ospfVirtIfAuthFailure

The OSPF Virtual Interface Authentication failed.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfVirtIfConfigError log

Trap ospfVirtIfConfigError

The system detected an OSPF Virtual Interface Configuration Error.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfVirtIfStateChange log

Trap ospfVirtIfStateChange

OSPF Virtual Interface State Change.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ospfVirtNbrStateChange log

Trap ospfVirtNbrStateChange

OSPF Virtual Neighbor State Change.

Source	Severity
OSPF	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap pethMainPowerUsageOffNotification log

Trap pethMainPowerUsageOffNotification

Peth Main Power Usage Off.

Source	Severity
POL	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap pethMainPowerUsageOnNotification log

Trap pethMainPowerUsageOnNotification

Peth Main Power Usage On.

Source	Severity
POL	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap pethPsePortOnOffNotification log

Trap pethPsePortOnOffNotification

Peth Pse Port On Off.

Source	Severity
POL	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: rclsisPlsbBvidMismatchTrap log

Trap: rclsisPlsbBvidMismatchTrap

Trap was sent when the B-VID TLV from a neighbor node does not match the local configuration.

Source	Severity
ISIS	Information

Remedial action

Correct SPBM B-VID configuration.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: rclsisPlsbLsdbUpdateTrap log

Trap: rclsisPlsbLsdbUpdateTrap

An IS-IS trap indicating that LSDB information has changed.

Source	Severity
ISIS	Information

Remedial action

No action required.



Trap: rcIsisPlsbSmltPeerBmacMismatchTrap

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: rcIsisPlsbSmltPeerBmacMismatchTrap log

Trap: rcIsisPlsbSmltPeerBmacMismatchTrap

A PLSB ISIS trap signifies that the Smlt Split-Beb configured in the local switch and IST peer are the same. Configure One IST switch as Split-Beb primary and configure IST peer as Split-Beb secondary.

Source	Severity
SPB	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: rcIsisPlsbSmltSplitBebMismatchTrap

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: rcIsisPlsbSmltSplitBebMismatchTrap log

Trap: rcIsisPlsbSmltSplitBebMismatchTrap

A PLSB ISIS trap signifies that the Smlt Split-Beb configured in the local switch and IST peer are same. Configure One IST switch as Split-Beb primary and configure IST peer as Split-Beb secondary.

Source	Severity
SBR	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap: rcIsisPlsbSmltVirtBmacMismatchTrap

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: rcIsisPlsbSmltVirtBmacMismatchTrap log

Trap: rcIsisPlsbSmltVirtBmacMismatchTrap

A PLSB ISIS trap signifies that the Virtual BMAC configured in the switch is different from virtual BMAC configured in the IST peer.

Source	Severity
SPB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap risingAlarm log

Trap risingAlarm

Rising alarm.

Source	Severity
RMON	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap RSTP Error Event log

Trap RSTP Error Event

RSTP Error Event.

Source	Severity
NNRST	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap RSTP General Event log

Trap RSTP General Event

RSTP General Event.

Source	Severity
NNRST	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap RSTP New Root log

Trap RSTP New Root

RSTP New Root.

Source	Severity
NNRST	Information

Remedial action

No action required.



Trap RSTP Protocol Migration

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap RSTP Protocol Migration log

Trap RSTP Protocol Migration

RSTP Protocol Migration.

Source	Severity
NNRST	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap RSTP Topology Change log

Trap RSTP Topology Change

RSTP Topology Change.

Source	Severity
NNRST	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: Run %s %s log

Trap: Run %s %s

Script %s failed/was successfully executed.

Source	Severity
SNMP	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: s5CtrFanDirectionError log

Trap: s5CtrFanDirectionError

The message is logged with the SNMP trap s5CtrFanDirectionError. This notification indicates that a fan component's direction is incorrect.

Source	Severity
DCE	Information

Remedial action

Verify the fan component's direction.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: s5CtrHighTemperatureError log

Trap: s5CtrHighTemperatureError

The message is logged with the SNMP trap s5CtrHighTemperatureError. This notification indicates that the system is overheated.

Source	Severity
DCE	Information

Remedial action

Verify system temperature.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5CtrHotSwap log

Trap s5CtrHotSwap

Hot Swap.

Source	Severity
--------	----------

MCMGR, DRPMGR	Information
---------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5CtrUnitDown log

Trap s5CtrUnitDown

Unit down.

Source	Severity
L3, MLT	Serious

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5CtrUnitDown log

Trap s5CtrUnitDown

Unit down.

Source	Severity
L3, MLT	Warning

Remedial action

No action required.



Trap: s5EtrMacAddressTablesThresholdReached

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: s5EtrMacAddressTablesThresholdReached log

Trap: s5EtrMacAddressTablesThresholdReached

s5EtrMacAddressTablesThresholdReached trap signifies that the MAC address tables threshold is reached.

Source	Severity
CDT	Information

Remedial action

Remove at least one MAC address.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5EtrSbsMacAccessViolation log

Trap s5EtrSbsMacAccessViolation

MAC access violation.

Source	Severity
--------	----------

BAYSECURE, DCE	Information
----------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5EtrSbsMacAccessViolation log

Trap s5EtrSbsMacAccessViolation

MAC access violation.

Source	Severity
--------	----------

BAYSECURE, DCE	Information
----------------	-------------

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5EtrSbsMacRemoved log

Trap s5EtrSbsMacRemoved

MAC removed.

Source	Severity
NNCLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5EtrSbsMacTableCleared log

Trap s5EtrSbsMacTableCleared

MAC Table Cleared.

Source	Severity
NNCLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap s5EtrSbsMacTableClearedForPort log

Trap s5EtrSbsMacTableClearedForPort

The MAC table cleared for the Port.

Source	Severity
NNCLI	Information

Remedial action

No action required.



Trap: SFP Transceiver's Bias is no longer at warning/alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: SFP Transceiver's Bias is no longer at warning/alarm level log

Trap: SFP Transceiver's Bias is no longer at warning/alarm level

Will be logged only after the specified bias trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap:\$#160;SFP Transceiver's Bias is no longer at warning/alarm level log

Trap:\$#160;SFP Transceiver's Bias is no longer at warning/alarm level

Will be logged only after the specified bias trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.



Trap: SFP Transceiver's Temperature is no longer at warning/alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: SFP Transceiver's Temperature is no longer at warning/alarm level log

Trap: SFP Transceiver's Temperature is no longer at warning/alarm level

Will be logged only after the specified temperature trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.



Trap: \$#160;SFP Transceiver's Temperature is no longer at warning/alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap:\$#160;SFP Transceiver's Temperature is no longer at warning/alarm level log

Trap:\$#160;SFP Transceiver's Temperature is no longer at warning/alarm level

Will be logged only after the specified temperature trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current oment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level log

Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level

Will be logged only after the tx specified power trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level log

Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level

Will be logged only after the tx specified power trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.



Trap: \$#160;SFP Transceiver's Tx Power is no longer at warning/alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap:\$#160;SFP Transceiver's Tx Power is no longer at warning/alarm level log

Trap:\$#160;SFP Transceiver's Tx Power is no longer at warning/alarm level

Will be logged only after the tx specified power trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.



Trap: \$#160;SFP Transceiver's Tx Power is no longer at warning/alarm level

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap:\$#160;SFP Transceiver's Tx Power is no longer at warning/alarm level log

Trap:\$#160;SFP Transceiver's Tx Power is no longer at warning/alarm level

Will be logged only after the tx specified power trap was sent. The trap will be sent if the alarm/warning bits were set previously and at the current moment they are unset. The user will know how to distinguish between alarms and warnings because if there was recorded alarm ,an alarm trap will be sent. The same case for warnings.

Source	Severity
Port Driver	Information

Remedial action

No action required.



Trap: slaMonitorAgentExceptionDetected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap: slaMonitorAgentExceptionDetected log

Trap: slaMonitorAgentExceptionDetected

SLAMon agent operation terminated.

Source	Severity
SLAMon	Critical

Remedial action

Reset device.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Trap SLPP Port Down Event

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap SLPP Port Down Event log

Trap SLPP Port Down Event

SLPP Port Down Event.

Source	Severity
SMLT	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap Smlt Ist Link Down log

Trap Smlt Ist Link Down

SMLT IST Link Down.

Source	Severity
SMLT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap Smlt Ist Link Up log

Trap Smlt Ist Link Up

SMLT IST Link Up

Source	Severity
SMLT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap Smlt Link Down log

Trap Smlt Link Down

SMLT Link Down.

Source	Severity
SMLT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap Smlt Link Up log

Trap Smlt Link Up

SMLT Link Up.

Source	Severity
SMLT	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap topologyChange log

Trap topologyChange

Topology Change.

Source	Severity
NNCLI	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ubpEAPSessionEnd log

Trap ubpEAPSessionEnd

EAP Session end.

Source	Severity
QPAV2	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap ubpEAPSessionStart log

Trap ubpEAPSessionStart

EAP Session Start.

Source	Severity
QPAV2	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trap vrrpTrapNewMaster log

Trap vrrpTrapNewMaster

VRRP Trap New Master.

Source	Severity
VRRP	Information

Remedial action

No action required.



trTCM meter issue - PBS must be greater than CBS

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

trTCM meter issue - PBS must be greater than CBS log

trTCM meter issue - PBS must be greater than CBS

PBS is not grater that CBS.

Source	Severity
QoS	Serious

Remedial action

Modify options so that PIR is greater than CIR.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

trTCM meter issue - PIR must be greater than CIR log

trTCM meter issue - PIR must be greater than CIR

PIR is not greater than CIR .

Source	Severity
QoS	Serious

Remedial action

Modify options so that PIR is greater than CIR.



Trusted processing mode change rejected - inadequate resources

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Trusted processing mode change rejected - inadequate resources log

Trusted processing mode change rejected - inadequate resources

Unable to commit trusted processing mode transition form partial to full. Not enough resources available.

Source	Severity
QoS	Serious

Remedial action

Check for and remove unneeded resources.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to add block member (block elem# component set id) to existing policy

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to add block member (block elem# component set id) to existing policy log

Unable to add block member (block elem# component set id) to existing policy

Failed to install the specified classifier-block.

Source	Severity
QoS	Serious

Remedial action

Check for available resources, interface capabilities or possible conflicts.



Unable to apply existing policy data to interface (unit# port#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to apply existing policy data to interface (unit# port#) log

Unable to apply existing policy data to interface (unit# port#)

The interface assignment change needs to add the port to an existing policy.

Source	Severity
QoS	Serious

Remedial action

Check the available/not needed resources.



Unable to apply existing user-based policy data to new user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to apply existing user-based policy data to new user log

Unable to apply existing user-based policy data to new user

The system failed to clone the policy and the meter data that is associated with the current user.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack



Unable to apply filter set to ports (unsupported capabilities)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to apply filter set to ports (unsupported capabilities) log

Unable to apply filter set to ports (unsupported capabilities)

The filter set cannot be applied to the specified ports as the required interface capabilities are not compatible with all the interfaces.

Source	Severity
QoS	Serious

Remedial action

Check the interface capabilities, and adapt the port mask for the operation to succeed.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to apply newly-defined UBP filter set to existing user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to apply newly-defined UBP filter set to existing user log

Unable to apply newly-defined UBP filter set to existing user

The system failed to apply the defined user based policy filter set to the existing user.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to apply pre-defined UBP filter set to new user

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to apply pre-defined UBP filter set to new user log

Unable to apply pre-defined UBP filter set to new user

Unable to install/update a UBP filter set for a new user.

Source	Severity
QoS	Serious

Remedial action

Free resources/update UBP filter set

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to apply pre-defined UBP filter set to new user (port %d/%d) log

Unable to apply pre-defined UBP filter set to new user (port %d/%d)

The agent failed to install the corresponding UBP filter.

Source	Severity
Serious	Information

Remedial action

Check the log for a previous more detailed message or the current available hardware resources.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to complete requested access asgn system operation (oper type) log

Unable to complete requested access asgn system operation (oper type)

The system failed to enable or disable the access assignment on the base or non-base unit (in the stack).

Source	Severity
QoS	Critical

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to complete requested policy system operation (operation type) log

Unable to complete requested policy system operation (operation type)

The operation failed either on base or on non-base unit.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, reset the unit or check stack health.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to compress classification criteria in set adequately log

Unable to compress classification criteria in set adequately

Failed to compress the combination of classification data elements from the individual classifiers.

Source	Severity
QoS	Serious

Remedial action

Separate the conflicting elements into multiple classifier sets.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to compress specified policy criteria log

Unable to compress specified policy criteria

Unable to compress the rule and/or mask for the specified filter. Filter Manager internal error.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unable to create action for access element

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create action for access element log

Unable to create action for access element

Creation of action for the specified access element failed.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unable to create classifier block entry for access element

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create classifier block entry for access element log

Unable to create classifier block entry for access element

Creation of the classifier block entry failed.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unable to create classifier component entry for access element

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create classifier component entry for access element log

Unable to create classifier component entry for access element

Creation of the classifier component entry failed.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unable to create count action (meter) for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create count action (meter) for access assignment log

Unable to create count action (meter) for access assignment

Failed to count action (from meter) for access assignment on base or non-base unit (if the stack is preset).

Source	Severity
QoS	Serious

Remedial action

Check log for the related details on the issue. Try again later, reset the QoS agent or reset the stack.



Unable to create count action (policy) for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create count action (policy) for access assignment log

Unable to create count action (policy) for access assignment

Failed to count action (from policy) for access assignment on base or non-base unit.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create count action (secondary meter) for access asgn log

Unable to create count action (secondary meter) for access asgn

Failed to create the count action component for ACL.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to create DS MF classifier for access element

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create DS MF classifier for access element log

Unable to create DS MF classifier for access element

DS(IP) MF Classifier creation failed.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unable to create L2 MF classifier for access element

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create L2 MF classifier for access element log

Unable to create L2 MF classifier for access element

Creation of the L2 MF classifier failed.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to create metering data for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create metering data for access assignment log

Unable to create metering data for access assignment

Failed to create metering data for access assignment on base or non-base unit.

Source	Severity
QoS	Serious

Remedial action

Check log for the related details on the issue. Try again later, reset the QoS agent or reset the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to create non-match components for ACL

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create non-match components for ACL log

Unable to create non-match components for ACL

Failed to create a non-match action component for ACL.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to create out-of-profile action for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create out-of-profile action for access assignment log

Unable to create out-of-profile action for access assignment

Failed to create out-of-profile action for access assignment on base or non-base unit.

Source	Severity
QoS	Serious

Remedial action

Check the log for the related details on the issue. Try again later, reset the QoS agent or reset the stack.



Unable to create policy data for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create policy data for access assignment log

Unable to create policy data for access assignment

Failed to create policy data for access assignment on base or non-base unit.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create secondary metering data for access assignment log

Unable to create secondary metering data for access assignment

Failed to create secondary metering data for ACL.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to create secondary token bucket data for access asgn

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create secondary token bucket data for access asgn log

Unable to create secondary token bucket data for access asgn

The system failed to create a secondary token bucket component for ACL.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to create token bucket data for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create token bucket data for access assignment log

Unable to create token bucket data for access assignment

Failed to create the token bucket data for the access assignment on base or non-base unit.

Source	Severity
QoS	Serious

Remedial action

Check log for the related details on the issue. Try again later, reset the QoS agent or reset the stack.



Unable to create yellow action for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to create yellow action for access assignment log

Unable to create yellow action for access assignment

Failed to create yellow action component for ACL.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to deactivate policy associated with interface log

Unable to deactivate policy associated with interface

The resource policy deallocation failed.

Source	Severity
QoS	Serious

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unable to delete block member (block element# component set id) from existing policy

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to delete block member (block element# component set id) from existing policy log

Unable to delete block member (block element# component set id) from existing policy

Failed to remove the specified classifier-block .

Source	Severity
QoS	Serious

Remedial action

Check for existing references, possible conflicts or try again later.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to delete UBP filter set on interface ifc# log

Unable to delete UBP filter set on interface ifc#

Failed to remove the user based policy filter set on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to derive suitable filter set element eval precedence

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to derive suitable filter set element eval precedence log

Unable to derive suitable filter set element eval precedence

A precedence must be assigned to a filter set; else it cannot be installed on the interface.

Source	Severity
QoS	Serious

Remedial action

Check the available un-needed resources, try again later, reset the QoS agent or reset the unit.



Unable to determine clfr interface(s) compatibility

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to determine clfr interface(s) compatibility log

Unable to determine clfr interface(s) compatibility

Unable to make changes because the system failed to determine classifier/interface(s) compatibility version.

Source	Severity
QoS	Serious

Remedial action

Enter a different classifier/interface, try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to disable ARP Spoofing support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable ARP Spoofing support on interface (ifc#) log

Unable to disable ARP Spoofing support on interface (ifc#)

The system failed to disable the ARP Spoofing support on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to disable BPDUBIkr support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable BPDUBIkr support on interface (ifc#) log

Unable to disable BPDUBIkr support on interface (ifc#)

Failed to disable BPDUBIkr policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent or reset the stack.



Unable to disable DHCP Snooping support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable DHCP Snooping support on interface (ifc#) log

Unable to disable DHCP Snooping support on interface (ifc#)

The system failed to disable the DHCP Snooping support on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent or reset the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to disable DHCP Spoofing support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable DHCP Spoofing support on interface (ifc#) log

Unable to disable DHCP Spoofing support on interface (ifc#)

The system failed to disable the DHCP Spoofing support on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to disable DNSPort support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable DNSPort support on interface (ifc#) log

Unable to disable DNSPort support on interface (ifc#)

The system failed to disable the DNSPort policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable existing policy data on interface (unit# port#) log

Unable to disable existing policy data on interface (unit# port#)

The interface assignment change needs to remove the port form an existing policy. This operation failed.

Source	Severity
QoS	Serious

Remedial action

Check for and remove any conflicts regarding the interface.



Unable to disable FTPPort support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable FTPPort support on interface (ifc#) log

Unable to disable FTPPort support on interface (ifc#)

The system failed to disable the FTPPort policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to disable Nachia support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable Nachia support on interface (ifc#) log

Unable to disable Nachia support on interface (ifc#)

The system failed to disable the Nachia policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to disable policy data for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable policy data for access assignment log

Unable to disable policy data for access assignment

Failed to disable the policy data.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to disable SQLSlam support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable SQLSlam support on interface (ifc#) log

Unable to disable SQLSlam support on interface (ifc#)

The system failed to disable the SQLSlam policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to disable SynFinScan support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable SynFinScan support on interface (ifc#) log

Unable to disable SynFinScan support on interface (ifc#)

The system failed to disable the SynFinScan policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to disable Xmas support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to disable Xmas support on interface (ifc#) log

Unable to disable Xmas support on interface (ifc#)

The system failed to disable the Xmas policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.



Unable to enable ARP Spoofing support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable ARP Spoofing support on interface (ifc#) log

Unable to enable ARP Spoofing support on interface (ifc#)

The system failed to enable the ARP Spoofing support on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable BPDUBIkr support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable BPDUBIkr support on interface (ifc#) log

Unable to enable BPDUBIkr support on interface (ifc#)

The system failed to enable the BDUBIkr policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable DHCP Snooping support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable DHCP Snooping support on interface (ifc#) log

Unable to enable DHCP Snooping support on interface (ifc#)

The system failed to enable the DHCP Snooping support on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable DHCP Spoofing support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable DHCP Spoofing support on interface (ifc#) log

Unable to enable DHCP Spoofing support on interface (ifc#)

The system failed to enable the DHCP Spoofing support on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable DNSPort support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable DNSPort support on interface (ifc#) log

Unable to enable DNSPort support on interface (ifc#)

The system failed to enable the DNSPort policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable FTPPort support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable FTPPort support on interface (ifc#) log

Unable to enable FTPPort support on interface (ifc#)

The system failed to enable the FTPPort policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable Nachia support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable Nachia support on interface (ifc#) log

Unable to enable Nachia support on interface (ifc#)

The system failed to enable the Nachia policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable policy data for access assignment

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable policy data for access assignment log

Unable to enable policy data for access assignment

Failed to enable the policy data.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, or reset the stack.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to enable SQLSlam support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable SQLSlam support on interface (ifc#) log

Unable to enable SQLSlam support on interface (ifc#)

The system failed to enable the SQLSlam policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable SynFinScan support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable SynFinScan support on interface (ifc#) log

Unable to enable SynFinScan support on interface (ifc#)

The system failed to enable the SynFinScan policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to enable Xmas support on interface (ifc#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to enable Xmas support on interface (ifc#) log

Unable to enable Xmas support on interface (ifc#)

The system failed to enable the Xmas policy data on the specified interface.

Source	Severity
QoS	Serious

Remedial action

Check log for related details on the issue. Try again later, reset the QoS agent, reset the stack, or use a different interface.



Unable to inform SPB of ifc assignment change (%d/%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to inform SPB of ifc assignment change (%d/%d) log

Unable to inform SPB of ifc assignment change (%d/%d)

SPB might not be aware of the current QoS interface type class of the specified interface.

Source	Severity
QoS	Critical

Remedial action

Force a transition on the specified interface.



Unable to inform SPB of ifc assignment change (%d/%d)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to inform SPB of ifc assignment change (%d/%d) log

Unable to inform SPB of ifc assignment change (%d/%d)

The information regarding an interface type class assigned to the identified port, failed to reach SPB.

Source	Severity
QoS Agent	Information

Remedial action

If you are seeing this because of a QoS interface class modification and SPB is not used, the message can be ignored. Otherwise, a QoS class transition for the specified port forces the creation of a new message.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to install access assignment - component creation issue

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to install access assignment - component creation issue log

Unable to install access assignment - component creation issue

Unable to create many of the access assignment components like: base action, token bucket entry, count action, meter, policy.

Source	Severity
QoS	Serious

Remedial action

Check for the available or not needed resources.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to install access element - component creation issue

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to install access element - component creation issue log

Unable to install access element - component creation issue

The Access element installation failed.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to locate corresponding DS L2 access elements

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to locate corresponding DS L2 access elements log

Unable to locate corresponding DS L2 access elements

The corresponding DS(IP)/L2 classifier(s) does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unable to manipulate DAPP support (no applicable interfaces)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to manipulate DAPP support (no applicable interfaces) log

Unable to manipulate DAPP support (no applicable interfaces)

The target interfaces data does not exist.

Source	Severity
QoS	Serious

Remedial action

Enter an existing interface data.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unable to modify access assignment - component modify issue log

Unable to modify access assignment - component modify issue

Unable to make changes as one of the modifications required for an access assignment component failed.

Source	Severity
QoS	Serious

Remedial action

Check the log for a more detailed information on the issue. Try again later, reset the QoS agent, or reset the stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unicast block unit port unit_port level level watermark watermark log

Unicast block unit port unit_port level level watermark watermark

Unicast blocking is enabled on the indicated port as it reached the high water mark level.

Source	Severity
port driver	Information

Remedial action

Investigate the cause of the unicast storm to ensure optimal network performance.



Unicast (Interface#) and Non-Unicast (interface#) interfaces in conflict

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unicast (Interface#) and Non-Unicast (interface#) interfaces in conflict log

Unicast (Interface#) and Non-Unicast (interface#) interfaces in conflict

The interface number for unicast and non-unicast does not correspond.

Source	Severity
QoS	Serious

Remedial action

Enter the same interface/port number.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unicast unblock unit port unit_port level level watermark watermark log

Unicast unblock unit port unit_port level level watermark watermark

Unicast blocking is disabled on the indicated port as it reached below the high water mark level.

Source	Severity
port driver	Information

Remedial action

No action required.



Unknown access assignment entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown access assignment entry specified (entry#) log

Unknown access assignment entry specified (entry#)

Internal QPA error, the access assignment entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown access element entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown access element entry specified (entry#) log

Unknown access element entry specified (entry#)

The system detected an internal QPA error; The count action entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown action entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown action entry specified (entry#) log

Unknown action entry specified (entry#)

The system detected an internal QPA error; the action entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown classifier block entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown classifier block entry specified (entry#) log

Unknown classifier block entry specified (entry#)

The system detected an internal QPA error; The classifier component entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown classifier component entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown classifier component entry specified (entry#) log

Unknown classifier component entry specified (entry#)

The system detected an internal QPA error; The classifier component entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown CoS shaping entry specified (entry# CoS)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown CoS shaping entry specified (entry# CoS) log

Unknown CoS shaping entry specified (entry# CoS)

The system detected an Internal QPA error; The interface shaping entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown count action entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown count action entry specified (entry#) log

Unknown count action entry specified (entry#)

The system detected an internal QPA error; The count action entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown DSCP mapping entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown DSCP mapping entry specified (entry#) log

Unknown DSCP mapping entry specified (entry#)

The system detected an internal QPA error; The DSCP mapping entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown entry (class class#) specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown entry (class class#) specified (entry#) log

Unknown entry (class class#) specified (entry#)

The system detected an internal QPA error; The specified entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown incompatible access element specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible access element specified log

Unknown incompatible access element specified

The access element specified does not exist or the storage type is not compatible.

Source	Severity
QoS	Serious

Remedial action

Specify a compatible access element.



Unknown incompatible action component specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible action component specified log

Unknown incompatible action component specified

Specified action doesn't exist or it's system/agent entry.

Source	Severity
QoS	Serious

Remedial action

Enter an existing action or create a new one.



Unknown incompatible classifier block specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible classifier block specified log

Unknown incompatible classifier block specified

The classifier block does not exist.

Source	Severity
QoS	Serious

Remedial action

Enter an existing classifier block or create a new one.



Unknown incompatible classifier set specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible classifier set specified log

Unknown incompatible classifier set specified

The specified classifier set does not exist.

Source	Severity
QoS	Serious

Remedial action

Enter an existing classifier set or create a new one.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown incompatible in-profile action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible in-profile action specified log

Unknown incompatible in-profile action specified

The in-profile action specified is unknown or incompatible.

Source	Severity
QoS	Serious

Remedial action

Check log for other possible details on the issue. Verify that the in-profile action exists and is compatible with the entry.



Unknown incompatible in-profile (green) action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible in-profile (green) action specified log

Unknown incompatible in-profile (green) action specified

Action criteria or storage type is not compatible with the action criteria type specified (in-profile green).

Source	Severity
QoS	Serious

Remedial action

Enter a compatible in-profile action.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown incompatible match action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible match action specified log

Unknown incompatible match action specified

The specified action does not exist.

Source	Severity
QoS	Serious

Remedial action

Enter an existing action or create a new one.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible metering component specified log

Unknown incompatible metering component specified

The metering component is unknown or not compatible.

Source	Severity
QoS	Serious

Remedial action

Verify that the metering component exists and also that the storage types of the entries are compatible.



Unknown incompatible metering statistics entry specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible metering statistics entry specified log

Unknown incompatible metering statistics entry specified

Unknown or incompatible statistics with policy storage type.

Source	Severity
QoS	Serious

Remedial action

Enter different statistics type.



Unknown incompatible out-of-profile action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible out-of-profile action specified log

Unknown incompatible out-of-profile action specified

The out-of-profile action specified is unknown or incompatible.

Source	Severity
QoS	Serious

Remedial action

Check log for other possible details on the issue. Verify that the out-of-profile action exists and is compatible with the entry.



Unknown incompatible out-of-profile (red) action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible out-of-profile (red) action specified log

Unknown incompatible out-of-profile (red) action specified

Action criteria or storage type is not compatible with the action criteria type specified (out-of-profile red).

Source	Severity
QoS	Serious

Remedial action

Enter a compatible out-of-profile action.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown incompatible out-of-profile (yellow) action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible out-of-profile (yellow) action specified log

Unknown incompatible out-of-profile (yellow) action specified

Action criteria or storage type is not compatible with the action criteria type specified (out-of-profile yellow).

Source	Severity
QoS	Serious

Remedial action

Enter a compatible out-of-profile action.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown incompatible policy non-match action specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible policy non-match action specified log

Unknown incompatible policy non-match action specified

The specified non-match action does not exist.

Source	Severity
QoS	Serious

Remedial action

Enter an existing non-match action or create a new one.



Unknown incompatible policy statistics entry specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible policy statistics entry specified log

Unknown incompatible policy statistics entry specified

Unknown or incompatible statistics with policy storage type.

Source	Severity
QoS	Serious

Remedial action

Enter different statistics type.



Unknown incompatible queue set specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible queue set specified log

Unknown incompatible queue set specified

The queue set specified is unknown.

Source	Severity
QoS	Serious

Remedial action

Use an existing queue set.



Unknown incompatible role combination specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible role combination specified log

Unknown incompatible role combination specified

Referenced role must exist/be stable prior to entry creation/modification.

Source	Severity
QoS	Serious

Remedial action

Make sure the role combination exists or create a new one.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown incompatible token bucket reference specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible token bucket reference specified log

Unknown incompatible token bucket reference specified

Referenced token bucket not found.

Source	Severity
QoS	Critical

Remedial action

Enter an existing/compatible token bucket.



Unknown incompatible token bucket reference specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown incompatible token bucket reference specified log

Unknown incompatible token bucket reference specified

The token bucket specified is not valid.

Source	Severity
QoS	Serious

Remedial action

Check the documentation and use a valid token bucket.



Unknown interface application entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown interface application entry specified (entry#) log

Unknown interface application entry specified (entry#)

The system detected an internal QPA error; The interface application entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown interface assignment entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown interface assignment entry specified (entry#) log

Unknown interface assignment entry specified (entry#)

The system detected an internal QPA error; The interface assignment entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown interface queue entry specified (ifc queue id)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown interface queue entry specified (ifc queue id) log

Unknown interface queue entry specified (ifc queue id)

The system detected an internal QPA error; The interface queue entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown interface shaping entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown interface shaping entry specified (entry#) log

Unknown interface shaping entry specified (entry#)

The system detected an internal QPA error; The interface shaping entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown IP classifier entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown IP classifier entry specified (entry#) log

Unknown IP classifier entry specified (entry#)

The system detected an internal QPA error; The IP classifier does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown Layer 2 classifier entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown Layer 2 classifier entry specified (entry#) log

Unknown Layer 2 classifier entry specified (entry#)

The system detected an internal QPA error; The I2 classifier does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown meter entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown meter entry specified (entry#) log

Unknown meter entry specified (entry#)

The system detected an internal QPA error; The meter component entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown out-of-range interface index value (ifc#) log

Unknown out-of-range interface index value (ifc#)

The interface index does not exist.

Source	Severity
QoS	Serious

Remedial action

Check the platform's/stack's port range and use a valid interface index.



Unknown out-of-range interface index value (ifc index)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown out-of-range interface index value (ifc index) log

Unknown out-of-range interface index value (ifc index)

The interface index does not exist.

Source	Severity
QoS	Serious

Remedial action

Check the port range of the platform or the stack, and use a valid interface index.



Unknown policy entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown policy entry specified (entry#) log

Unknown policy entry specified (entry#)

The system detected an internal QPA error; The classifier component entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown 802.1p user priority mapping entry specified (entry#) log

Unknown 802.1p user priority mapping entry specified (entry#)

The system detected an internal QPA error; The 802.1p user priority mapping entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.



Unknown queue set assignment entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown queue set assignment entry specified (entry#) log

Unknown queue set assignment entry specified (entry#)

The system detected an internal QPA error; The queue set does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown queue set queue reference detected

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown queue set queue reference detected log

Unknown queue set queue reference detected

The specified queue (set) does not exist.

Source	Severity
QoS	Serious

Remedial action

Enter an existing queue/queue set.



Unknown queue shaping entry specified (entry# queue)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown queue shaping entry specified (entry# queue) log

Unknown queue shaping entry specified (entry# queue)

The system detected an internal QPA error; The count action entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown role combination entry specified (role comb id)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown role combination entry specified (role comb id) log

Unknown role combination entry specified (role comb id)

The system detected an internal QPA error; The role combination entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown System classifier entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown System classifier entry specified (entry#) log

Unknown System classifier entry specified (entry#)

The system detected an Internal QPA error; the system classifier does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown token bucket entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown token bucket entry specified (entry#) log

Unknown token bucket entry specified (entry#)

The system detected an internal QPA error; The token bucket does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown unsupported attribute specified (attribute)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported attribute specified (attribute) log

Unknown unsupported attribute specified (attribute)

The specified attribute is not supported or unknown for the class you are trying to configure an entry

Source	Severity
QoS	Information

Remedial action

Check the documentation if necessary and use a supported attribute for that QoS class.



Unknown unsupported interface application type specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported interface application type specified log

Unknown unsupported interface application type specified

The interface application type provided is unknown or unsupported.

Source	Severity
QoS	Serious

Remedial action

Check documentation and use a valid interface application type.



Unknown unsupported interface class specified (ifc class)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported interface class specified (ifc class) log

Unknown unsupported interface class specified (ifc class)

The valid interface classes are trusted, untrusted and unrestricted.

Source	Severity
QoS	Serious

Remedial action

Enter a valid/supported interface class.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported IP Flag specified log

Unknown unsupported IP Flag specified

The specified IP Flag is not supported.

Source	Severity
QoS	Serious

Remedial action

Check documentation if necessary and enter a valid IP Flag.



Unknown unsupported RowStatus specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported RowStatus specified log

Unknown unsupported RowStatus specified

The status is unknown or unsupported for the current entry. Valid statuses are (the supported ones depend on the QoS component): active, create and go, create and wait, destroy, not in service, not ready.

Source	Severity
--------	----------

QoS	Critical
-----	----------

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unknown unsupported StorageType specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported StorageType specified log

Unknown unsupported StorageType specified

The supported storage types are: volatile, non-volatile, permanent, read-only and other. Also, take into account that certain actions/entries require certain storage types.

Source	Severity
--------	----------

QoS	Serious
-----	---------

Remedial action

Check the documentation if necessary and use a compatible/valid storage type.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown unsupported TCP Control Flag specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown unsupported TCP Control Flag specified log

Unknown unsupported TCP Control Flag specified

The specified TCP Control Flag is not supported.

Source	Severity
QoS	Serious

Remedial action

Check documentation if necessary and enter a valid TCP Control Flag.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unknown user policy entry specified (entry#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unknown user policy entry specified (entry#) log

Unknown user policy entry specified (entry#)

The system detected an internal QPA error; The user policy entry does not exist.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unsupported IP address type specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unsupported IP address type specified log

Unsupported IP address type specified

Unsupported address type provided. (It should not get here) Internal error.

Source	Severity
QoS	Serious

Remedial action

Enter a ipv4 or ipv6 address.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Unsupported IPv4 Options value specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unsupported IPv4 Options value specified log

Unsupported IPv4 Options value specified

Invalid IPv4 option detected.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent or reset the unit.



Unsupported pattern offset data specified

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unsupported pattern offset data specified log

Unsupported pattern offset data specified

Position data and pattern data cannot be processed correctly into an appropriate mask.

Source	Severity
QoS	Serious

Remedial action

Change or separate the pattern data into multiple system classifiers.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Unsupported unknown QoS agent configuration attribute (attribute#) log

Unsupported unknown QoS agent configuration attribute (attribute#)

The attribute you are trying to configure is not supported/recognized by the QoS agent.

Source	Severity
QoS	Serious

Remedial action

Remove the attribute.



Up 1 cable inserted or neighbor powered on

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Up 1 cable inserted or neighbor powered on log

Up 1 cable inserted or neighbor powered on

Cable inserted, link up.

Source	Severity
HMOD	Information

Remedial action

No action required.



Up 2 cable inserted or neighbor powered on

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Up 2 cable inserted or neighbor powered on log

Up 2 cable inserted or neighbor powered on

Cable inserted, link up.

Source	Severity
HMOD	Information

Remedial action

No action required.



Up 1 cable removed or neighbor powered off

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Up 1 cable removed or neighbor powered off log

Up 1 cable removed or neighbor powered off

Link down: cable removed or neighbor powered off.

Source	Severity
HMOD	Serious

Remedial action

Do not remove cable, power off neighbor.



Up 2 cable removed or neighbor powered off

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Up 2 cable removed or neighbor powered off log

Up 2 cable removed or neighbor powered off

Link down: cable removed or neighbor powered off.

Source	Severity
HMOD	Serious

Remedial action

Do not remove cable, power off neighbor.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Update priority value and update DSCP value out-of-sync log

Update priority value and update DSCP value out-of-sync

If the priority update is set to be done based on DSCP-to-user priority map (egressmap) the DSCP value must be specified.

Source	Severity
QoS	Serious

Remedial action

Change the update priority type or specify a DSCP value.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Update priority value per ingress DSCP currently not supported log

Update priority value per ingress DSCP currently not supported

Priority update based on 802.1p priority-to-DSCP map (ingressmap) is not currently supported.

Source	Severity
QoS	Serious

Remedial action

Change the update priority type.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Upstream stack direction is down cable removed or neighbor powered off log

Upstream stack direction is down cable removed or neighbor powered off

The upstream stack direction is down, cable removed or neighbor powered off.

Source	Severity
--------	----------

Hello Module	Information
--------------	-------------

Remedial action

Connect the upstream port to the downstream port of the neighbor. Also check if the neighbor is powered on.



Upstream stack direction is mis-configured

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Upstream stack direction is mis-configured log

Upstream stack direction is mis-configured

This message appears when an upstream port is mis-configured.

Source	Severity
Hello Module	Information

Remedial action

Connect the upstream port to the downstream port of the neighbor.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



USB device inserted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

USB device inserted log

USB device inserted

A USB memory stick has been inserted in the unit.

Source	Severity
USB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

USB device removed log

USB device removed

A USB memory stick has been removed from the unit.

Source	Severity
USB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

USC Install SET fail unit port unit_port status = status log

USC Install SET fail unit port unit_port status = status

Installation of the Unicast Storm Control filter during set phase failed for the indicated port.

Source	Severity
port driver	Information

Remedial action

Verify that the hardware filter resources are available for the indicated port. Current hardware filter resource usage can be displayed through the 'show qos diag' command. You may need to disable other applications currently using hardware filter resources in order to free them up for the Unicast Storm Control application.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

USC Install TEST fail unit port unit_port status = status log

USC Install TEST fail unit port unit_port status = status

Installation of the Unicast Storm Control filter during test phase failed for the indicated port.

Source	Severity
port driver	Information

Remedial action

Verify the hardware filter resources are available for the indicated port. Current hardware filter resource usage can be displayed through the 'show qos diag' command. You may need to disable other applications currently using hardware filter resources in order to free them up for the Unicast Storm Control application.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

USC UnInst SET failed for port port status = status log

USC UnInst SET failed for port port status = status

The Unicast Storm Control filter could not be uninstalled during the set phase for the indicated port.

Source	Severity
port driver	Information

Remedial action

Verify the hardware filter resources have been un-installed for the Unicast Storm Control application. If not, reboot it to successfully remove any hardware filter resources that are still attached to the Unicast Storm Control application.



User allowed (radius authentication pass) to log in from Web from Src IP

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User allowed (radius authentication pass) to log in from Web from Src IP log

User allowed (radius authentication pass) to log in from Web from Src IP

Client from the indicated IP address has been authenticated successfully through the Radius server.

Source	Severity
WEB	Information

Remedial action

No action required.



User disallowed (radius authentication fail) to log in from Web from Src IP

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User disallowed (radius authentication fail) to log in from Web from Src IP log

User disallowed (radius authentication fail) to log in from Web from Src IP

Client from the indicated IP address has failed authentication through the Radius server.

Source	Severity
WEB	Information

Remedial action

Provide the correct username and password to gain access.



User disallowed (radius authentication fail) to log in from Web from Src IP

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User disallowed (radius authentication fail) to log in from Web from Src IP log

User disallowed (radius authentication fail) to log in from Web from Src IP

Client from the indicated IP address has failed authentication through the Radius server.

Source	Severity
WEB	Information

Remedial action

Provide the correct username and password to gain access.



User Policy data referencing interface (operation prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User Policy data referencing interface (operation prohibited) log

User Policy data referencing interface (operation prohibited)

There are non-QoS applications that have created entries that reference this interface.

Source	Severity
QoS	Serious

Remedial action

Remove all references before performing other operations.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



User policy distribution across stack failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy distribution across stack failed log

User policy distribution across stack failed

Unable to commit user policy distribution across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



User policy filter set count (<set count>) exceeds limit (<set limit>)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy filter set count (<set count>) exceeds limit (<set limit>) log

User policy filter set count (<set count>) exceeds limit (<set limit>)

The user policy filter set limit depends on the target hardware platform.

Source	Severity
QoS	Serious

Remedial action

Check documentation for the maximum number of user policy filter sets allowed.



User policy filter set delete operation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy filter set delete operation failed log

User policy filter set delete operation failed

Unable to carry out the update operation on the policy filter set across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy filter set element count exceeds available resources log

User policy filter set element count exceeds available resources

The policy filter set element count limit depends on the target hardware platform.

Source	Severity
QoS	Serious

Remedial action

Check the documentation for the maximum number of policy filter set elements allowed.



User policy filter set install operation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy filter set install operation failed log

User policy filter set install operation failed

Unable to carry out the update operation on the policy filter set across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.



User policy filter set update operation failed

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy filter set update operation failed log

User policy filter set update operation failed

Unable to carry out the update operation on the policy filter set across the stack.

Source	Severity
QoS	Information

Remedial action

Try later or check the stack health.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



User policy group contains invalid unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy group contains invalid unacceptable characters log

User policy group contains invalid unacceptable characters

Only printable characters are allowed.

Source	Severity
QoS	Serious

Remedial action

Enter valid characters for the policy group.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy group length outside of acceptable limits log

User policy group length outside of acceptable limits

The maximum user policy group length is 64.

Source	Severity
QoS	Serious

Remedial action

Separate the entries into multiple policy groups.



User policy modifications not supported

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy modifications not supported log

User policy modifications not supported

The system detected an internal error; The specified modifier option not supported.

Source	Severity
QoS	Critical

Remedial action

Try again later, reset the QoS agent, or reset the unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



User policy name contains invalid unacceptable characters

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy name contains invalid unacceptable characters log

User policy name contains invalid unacceptable characters

Only printable characters are allowed.

Source	Severity
QoS	Serious

Remedial action

Enter valid characters for the policy label.



User policy name length outside of acceptable limits

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User policy name length outside of acceptable limits log

User policy name length outside of acceptable limits

The maximum length for a policy name is 64.

Source	Severity
QoS	Serious

Remedial action

Enter a policy name within the specified limit.



User Policy (UBP) filter set in use (QoS disable prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User Policy (UBP) filter set in use (QoS disable prohibited) log

User Policy (UBP) filter set in use (QoS disable prohibited)

Cannot disable the QoS system if there still are user policies in use.

Source	Severity
QoS	Serious

Remedial action

Remove the user policies first.



User Policy (UBP) filter set in use (QoS reset prohibited)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User Policy (UBP) filter set in use (QoS reset prohibited) log

User Policy (UBP) filter set in use (QoS reset prohibited)

Cannot reset the QoS engine if the user policy filter sets are still in use.

Source	Severity
QoS	Serious

Remedial action

Remove or disable the user policy filter sets before re-setting the QoS engine.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User priority specified with untagged frames (invalid) log

User priority specified with untagged frames (invalid)

User priority appears in tagged frames.

Source	Severity
QoS	Serious

Remedial action

Drop either priority or untagged option.



User with %s privilege has been created

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User with %s privilege has been created log

User with %s privilege has been created

A new user with the indicated privileges was created.

Source	Severity
AAA	Information

Remedial action

No action required.



User with %s privilege has been deleted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

User with %s privilege has been deleted log

User with %s privilege has been deleted

A user with the indicated privileges was deleted.

Source	Severity
AAA	Information

Remedial action

No action required.



Vlan Change Aborted, it is in another STP Group

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Vlan Change Aborted, it is in another STP Group log

Vlan Change Aborted, it is in another STP Group

EAP could not add a port to a VLAN that is in a different STG than the STG where the port is.

Source	Severity
EAP	Information

Remedial action

Change the STG of the VLAN.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Vlan Change Aborted on brouter log

Vlan Change Aborted on brouter

EAP could not change VLAN membership of BRouter port.

Source	Severity
EAP	Information

Remedial action

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



VLAN configuration does not match BU
VLAN configuration. VLAN config
defaulted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN configuration does not match BU VLAN configuration. VLAN config defaulted log

VLAN configuration does not match BU VLAN configuration. VLAN config defaulted

VLAN configuration was defaulted because the current VLAN configuration does not match the Base Unit VLAN configuration.

Source	Severity
VLAN	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



VLAN configuration does not match BU
VLAN configuration. VLAN config
defaulted

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN configuration does not match BU VLAN configuration. VLAN config defaulted log

VLAN configuration does not match BU VLAN configuration. VLAN config defaulted

This Non-Base Unit has the same number of VLANs as the Base Unit, but it has a different VLAN configuration than the Base Unit at dbexchange point.

Source	Severity
VLAN	Information

Remedial action

Reconfigure the port settings for this Non-Base Unit.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



VLAN ID min max values invalid (min VLAN ID ! max VLAN ID)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN ID min max values invalid (min VLAN ID ! max VLAN ID) log

VLAN ID min max values invalid (min VLAN ID ! max VLAN ID)

Max VLAN ID value must be bigger that min value.

Source	Severity
QoS	Serious

Remedial action

Correct the VLAN ID range limits.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN IMC callback failed log

VLAN IMC callback failed

There was an error when sending VLAN configuration to stack.

Source	Severity
VLAN	Information

Remedial action

No action required.



VLAN IMC was not sent

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN IMC was not sent log

VLAN IMC was not sent

There was an error when sending VLAN configuration to stack.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN NVRAM read error log

VLAN NVRAM read error

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN NVRAM read error log

VLAN NVRAM read error

Error at NVRAM restore.

Source	Severity
VLAN	Information

Remedial action

Reconfigure VLAN settings and/or port configuration on this unit.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN queue messages discarded log

VLAN queue messages discarded

Internal VLAN messages were discarded.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN queue messages discarded log

VLAN queue messages discarded

Logged for each message that was not successfully sent to the VLAN queue.

Source	Severity
VLAN	Information

Remedial action

No action required.



VLAN range could not be reduced sufficiently

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN range could not be reduced sufficiently log

VLAN range could not be reduced sufficiently

The VLAN range could not be reduce sufficiently for it's installation to be supported.

Source	Severity
QoS	Serious

Remedial action

Modify the VLAN range.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN set error from IMC log

VLAN set error from IMC

BU sends IMC to all NBUs and an error occurs when applying Vlan configuration on a NBU.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VLAN set error from RPC log

VLAN set error from RPC

NBU sends RPC to BU and an error occurs when applying Vlan configuration on BU.

Source	Severity
VLAN	Information

Remedial action

No action required.



Voice VLAN ID and Data VLAN ID cannot have the same value

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Voice VLAN ID and Data VLAN ID cannot have the same value log

Voice VLAN ID and Data VLAN ID cannot have the same value

Voice VLAN and Data VLAN must have different VLAN IDs.

Source	Severity
Run scripts: IP Office, LLDP, ADAC	Information

Remedial action

Check existing settings that could be in conflict with the script parameters. Undo settings or boot default the switch, then re-run the script, entering proper data input.



VRRP Feature globally disabled due to missing license

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP Feature globally disabled due to missing license log

VRRP Feature globally disabled due to missing license

Disable the Global VRRP because the license is missing or expired. VRRP will be disabled till the license is installed.

Source	Severity
VRRP	Information

Remedial action

Install a valid Layer3/VRRP license.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



VRRP: vrrpAdvtQueue is FULL. RX advertisement dropped in vlan %d!

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP: vrrpAdvtQueue is FULL. RX advertisement dropped in vlan %d! log

VRRP: vrrpAdvtQueue is FULL. RX advertisement dropped in vlan %d!

vrrpAdvtQueue is FULL for the identified VLAN.

Source	Severity
VRRP	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



VRRP: vrrpQueue is FULL. Message dropped.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP: vrrpQueue is FULL. Message dropped. log

VRRP: vrrpQueue is FULL. Message dropped.

vrrpQueue is FULL.

Source	Severity
VRRP	Information

Remedial action

No action required.



VRRP VR VR Id VLAN Id Received mismatching advertisement interval (advertisement interval)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP VR VR Id VLAN Id Received mismatching advertisement interval (advertisement interval) log

VRRP VR VR Id VLAN Id Received mismatching advertisement interval (advertisement interval)

The system Received a VRRP packet with different advertisement interval. VRRP advertisements from VRRP routers with different advertisement interval will be dropped until problem is solved.

Source	Severity
VRRP	Information

Remedial action

Use or set the same advertisement interval for the VRRP routers.



VRRP VR VR Id VLAN Id Received mismatching advertisement type (advertisement type)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP VR VR Id VLAN Id Received mismatching advertisement type (advertisement type) log

VRRP VR VR Id VLAN Id Received mismatching advertisement type (advertisement type)

The system received a VRRP packet with different advertisement type. VRRP advertisements from VRRP routers with different advertisement type will be dropped till the problem is solved.

Source	Severity
VRRP	Information

Remedial action

Use or set the same advertisement type for VRRP routers. Fast advertisement should be either enabled or disabled on all VRRP routers.



VRRP VR VR Id VLAN Id Received mismatching fast advertisement interval (fast advertisement interval)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP VR VR Id VLAN Id Received mismatching fast advertisement interval (fast advertisement interval) log

VRRP VR VR Id VLAN Id Received mismatching fast advertisement interval (fast advertisement interval)

The system received a VRRP packet with different fast advertisement interval. VRRP advertisements from VRRP routers with different fast advertisement interval will be dropped till the problem is solved.

Source	Severity
VRRP	Information

Remedial action

Use or set the same fast advertisement interval for all VRRP routers.



VRRP VR VR Id VLAN Id Received mismatching virtual IP address (received virtual ip address)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP VR VR Id VLAN Id Received mismatching virtual IP address (received virtual ip address) log

VRRP VR VR Id VLAN Id Received mismatching virtual IP address (received virtual ip address)

The system received a VRRP packet with different virtual IP address VRRP advertisements from VRRP routers with different virtual IP address will be dropped until problem is solved.

Source	Severity
VRRP	Information

Remedial action

Use or set the same virtual IP address for all VRRP routers.



VRRP VR VR Id VLAN Id Received unknown VRRP packet type (vrrp packet type)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

VRRP VR VR Id VLAN Id Received unknown VRRP packet type (vrrp packet type) log

VRRP VR VR Id VLAN Id Received unknown VRRP packet type (vrrp packet type)

Received unknown or wrong VRRP packet type. VRRP advertisements from VRRP routers with different VRRP type will be dropped till the problem is solved.

Source	Severity
VRRP	Information

Remedial action

Use or set the same VRRP type for all VRRP routers.



Warning failed to connect to %s card (in unit %s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Warning failed to connect to %s card (in unit %s) log

Warning failed to connect to %s card (in unit %s)

This message appears when the system detects MDA card physical connection issues for the identified MDA model.

Source	Severity
MDA	Information

Remedial action

Check the MDA card physical connection.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Warning: non-supported qsfps inserted on %s. Port will be disabled.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Warning: non-supported qsfps inserted on %s. Port will be disabled. log

Warning: non-supported qsfps inserted on %s. Port will be disabled.

Inform the user that an unsupported GBIC was inserted into a port and the port is disabled.

Source	Severity
MDA	Information

Remedial action

Insert a supported GBIC into the specified port.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Warning: non-supported transceiver on %s has been detected.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Warning: non-supported transceiver on %s has been detected. log

Warning: non-supported transceiver on %s has been detected.

Informs the user that the transceiver is unsupported on a certain port.

Source	Severity
PDT	Information

Remedial action

Replace with supported transceiver.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



Warning %s card unsafely removed (from unit %s)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Warning %s card unsafely removed (from unit %s) log

Warning %s card unsafely removed (from unit %s)

This message appears when the identified MDA card is removed without first being disabled.

Source	Severity
MDA	Information

Remedial action

No action required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



WEB-access is disabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

WEB-access is disabled log

WEB-access is disabled

Logged when WEB-access is disabled from CLI.

Source	Severity
WEB	Information

Remedial action

No action Required.

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com



WEB-access is enabled

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

WEB-access is enabled log

WEB-access is enabled

Logged when WEB-access is enabled from CLI.

Source	Severity
WEB	Information

Remedial action

No action Required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web authentication fail from IP address log

Web authentication fail from IP address

Client from the indicated IP address has failed authentication.

Source	Severity
WEB	Information

Remedial action

Provide the correct username and password to gain access to the web server.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web authentication from IP address log

Web authentication from IP address

Client from the indicated IP address has been successfully authenticated.

Source	Severity
WEB	Information

Remedial action

No action required.



Web authentication (RADIUS auth) from IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web authentication (RADIUS auth) from IP address log

Web authentication (RADIUS auth) from IP address

Client from the indicated IP address has been successfully authenticated using RADIUS authentication

Source	Severity
WEB	Information

Remedial action

No action required.



Web authentication (RADIUS auth) from IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web authentication (RADIUS auth) from IP address log

Web authentication (RADIUS auth) from IP address

Client from the indicated IP address has been successfully authenticated using RADIUS authentication

Source	Severity
WEB	Information

Remedial action

No action Required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web connection from IP address log

Web connection from IP address

New client from the indicated IP address is connected to the web server.

Source	Severity
WEB	Information

Remedial action

No action required.



Web disconnect from IP address

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web disconnect from IP address log

Web disconnect from IP address

Client from the indicated IP address is disconnected from the web server.

Source	Severity
WEB	Information

Remedial action

No action required.



Web server attempting to open socket for port HTTP port

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web server attempting to open socket for port HTTP port log

Web server attempting to open socket for port HTTP port

Web server is attempting to change communication to the new HTTP port indicated.

Source	Severity
WEB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web server starts service on port HTTP port log

Web server starts service on port HTTP port

Web server is up and running, communicating through the indicated HTTP port.

Source	Severity
WEB	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Web timeout from IP address log

Web timeout from IP address

Client from the indicated IP address has timed out from the web server due to inactivity.

Source	Severity
WEB	Information

Remedial action

Client may need to login again to gain access to the web server.



Wrong QoS Agent buffer setting, expected %s, actual %s, unit re-configured and reboot

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong QoS Agent buffer setting, expected %s, actual %s, unit re-configured and reboot log

Wrong QoS Agent buffer setting, expected %s, actual %s, unit re-configured and reboot

QoS agent buffer allocation is different that the one of the BU's.

Source	Severity
Stack Manager	Serious

Remedial action

Wait for re-configuration and reboot cycle.



Wrong QOS Agent buffer setting expected value actual value unit cannot join stack.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong QOS Agent buffer setting expected value actual value unit cannot join stack. log

Wrong QOS Agent buffer setting expected value actual value unit cannot join stack.

The QOS buffer setting on this unit is different than that of the base unit's setting.

Source	Severity
Stack Manager	Information

Remedial action

Modify the QOS buffer setting on the unit.



Wrong QoS Agent queue setting, expected %u, actual %u, unit reconfigured and reboot

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong QoS Agent queue setting, expected %u, actual %u, unit reconfigured and reboot log

Wrong QoS Agent queue setting, expected %u, actual %u, unit reconfigured and reboot

Non Bu QoS queue set size is checked at discovery against BU's QoS que set, changed if needed, unit is rebooted if value is changed.

Source	Severity
Stack Manager	Serious

Remedial action

Assure that QoS queue set size on Non Base Units is the same as the BU QoS queue set size.



Wrong QoS Agent queue setting, expected %u, actual %u, unit re-configured and reboot

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong QoS Agent queue setting, expected %u, actual %u, unit re-configured and reboot log

Wrong QoS Agent queue setting, expected %u, actual %u, unit re-configured and reboot

QoS agent queue setting is different that the one of the BU's.

Source	Severity
Stack Manager	Serious

Remedial action

Wait for re-configuration and reboot cycle.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong VLANs nvq_RecDescr actRecs log

Wrong VLANs nvq_RecDescr actRecs

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong VMACs nvq_RecDescr actRecs log

Wrong VMACs nvq_RecDescr actRecs

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Wrong vrec field log

Wrong vrec field

There was an error when reading the VLAN configuration from NVRAM.

Source	Severity
VLAN	Information

Remedial action

No action required.

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with A

This page lists all the logs starting with the letter A that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Access assignment distribution across stack failed](#)
- [Access assignment modifications not supported](#)
- [Access assignment modification support limited](#)
- [Access assignment name contains unacceptable characters](#)
- [Access assignment name length outside of acceptable limits](#)
- [Access assignment name not acceptable - reserved](#)
- [Access assignment template still in use \(siblings active\)](#)
- [Access element block label contains unacceptable characters](#)
- [Access element block label length outside of acceptable limits](#)
- [Access element cluster count \(cluster count \) exceeds limit \(cluster limit \)](#)
- [Access element cluster is referenced \(addition prohibited\)](#)
- [Access element cluster is referenced \(deletion prohibited\)](#)
- [Access element distribution across stack failed](#)
- [Access element modifications not supported](#)
- [Access element name contains unacceptable characters](#)
- [Access element name length outside of acceptable limits](#)
- [Access element name not acceptable - reserved](#)
- [Agent configuration distribution across stack failed](#)
- [Attempt to create an element that already exists \(prohibited\)](#)
- [Attempt to delete modify non-existing element \(prohibited\)](#)
- [Attempt to manipulate system-owned interface \(prohibited\)](#)
- [Attempt to manipulate user policy data rejected \(disabled\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with B

This page lists all the logs starting with the letter B that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Base action distribution across stack failed](#)
- [Base action entry referenced by clfr block \(deletion prohibited\)](#)
- [Base action entry referenced by meter \(deletion prohibited\)](#)
- [Base action entry referenced by policy \(deletion prohibited\)](#)
- [Base action extension identifier invalid](#)
- [Base action modification prohibited due to action usage](#)
- [Base action modifications not supported](#)
- [Buffer configuration inconsistency detected \(local buffer conf stack buffer conf \)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with C

This page lists all the logs starting with the letter C that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Capabilities determined by agent \(not-writable\)](#)
- [Classifier block component set ID out-of-range \(clfr comp set ID \)](#)
- [Classifier block distribution across stack failed](#)
- [Classifier block modifications not supported](#)
- [Classifier block number out-of-range \(block# \)](#)
- [Classifier block precedence value not supported](#)
- [Classifier component distribution across stack failed](#)
- [Classifier component modifications not supported](#)
- [Classifier component set ID out-of-range \(clfrs comp set ID \)](#)
- [Classifier conflict \(duplicate clfr data in block\) detected](#)
- [Classifier content incompatible with target interface\(s\)](#)
- [Classifier set block reference out-of-range \(clfr setblock# \)](#)
- [Classifier type unknown](#)
- [Clfr content \(system\) incompatible with target interface\(s\)](#)
- [Composite filter set addition failure comp filter set unknown](#)
- [Composite filter set addition failure data consistency issue](#)
- [Composite filter set addition failure data invalid](#)
- [Composite filter set addition failure replication failure](#)
- [Composite filter set addition failure resources unavailable](#)
- [Composite filter set addition failure seed filter set unknown](#)
- [Composite filter set creation failure data invalid](#)
- [Composite filter set creation failure MAC data not allowed](#)
- [Composite filter set creation failure replication failure](#)
- [Composite filter set creation failure seed filter set unknown](#)
- [Composite filter set deletion failure base set target invalid](#)
- [Composite filter set deletion failure comp filter set unknown](#)
- [Composite filter set deletion failure data invalid](#)
- [Composite filter set deletion failure seed filter set unknown](#)
- [Composite filter set destruction failure data invalid](#)
- [Composite filter set membership limits exceeded](#)
- [Conflicting action sources detected](#)
- [Conflicting master block member information detected](#)
- [Conflicting policy role policy interface index data detected](#)
- [COS mapping distribution across stack failed](#)
- [CoS shaping distribution across stack failed](#)
- [CoS shaping modifications not supported](#)
- [CoS shaping not supported with specified interface](#)
- [Count action distribution across stack failed](#)
- [Count action entry referenced by meter \(deletion prohibited\)](#)
- [Count action entry referenced by policy \(deletion prohibited\)](#)
- [Count action modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with D

This page lists all the logs starting with the letter D that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [DAPP-detected DoS attack blocked unit unit# \(many ports\)](#)
- [DAPP-detected DoS attack blocked unit unit# port port#](#)
- [DAPP resources not available \(unit unit# \)](#)
- [DAPP support disable failure](#)
- [DAPP support enable failure](#)
- [DAPP with statistics tracking in use \(QoS disable prohibited\)](#)
- [Data distribution class class# across stack failed](#)
- [Data model version attribute value not supported](#)
- [Default ifc assignment failure port# port\(s\) ifc QoS-disabled](#)
- [Destination MAC address and mask values out-of-sync](#)
- [Different classifier component masks keys in block detected](#)
- [DSCP mapping distribution across stack failed](#)
- [DSCP mapping modifications not supported](#)
- [DSCP remarking not supported for IPv6 \(green action\)](#)
- [DSCP remarking not supported for IPv6 \(in-profile action\)](#)
- [DSCP remarking not supported for IPv6 \(match action\)](#)
- [DSCP remarking not supported for IPv6 \(non-match action\)](#)
- [DSCP remarking not supported for IPv6 \(out-of-profile action\)](#)
- [DSCP remarking not supported for IPv6 \(red action\)](#)
- [DSCP remarking not supported for IPv6 \(yellow action\)](#)
- [DSCP value modification prohibited](#)
- [Dst IP addr matching not supported with IP addr type data](#)
- [Dst Layer 4 port min max values invalid \(max must be = to min\)](#)
- [Dst MAC addr matching not supported with address type data](#)
- [Duplicate access asgn name type index detected \(prohibited\)](#)
- [Duplicate classifier class values in set detected](#)
- [Duplicate entry detected \(prohibited\)](#)
- [Duplicate FCoE redirection entry detected](#)
- [Duplicate set values in block detected](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with E

This page lists all the logs starting with the letter E that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [EAP Failed gpa-RoleAssociation unitPort 0x%x mac %08x%04x](#)
- [Egress interface and egress mask are mutually exclusive](#)
- [Element deletion prohibited \(permanent read-only system entry\)](#)
- [Element enable prohibited. Please delete and re-enter data](#)
- [Element label contains unacceptable characters](#)
- [Element label length outside of acceptable limits \(max 16 chars\)](#)
- [Element label not acceptable - reserved](#)
- [Element may only be modified not created or deleted](#)
- [Element modification prohibited \(read-only or system entry\)](#)
- [Evaluation precedence conflict detected \(UBP filter set data\)](#)
- [Evaluation precedence conflict \(Traffic Prof filter set data\)](#)
- [Evaluation precedence value required but not specified](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with F

This page lists all the logs starting with the letter F that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Filter control block resources exhausted](#)
- [Filter creation issue detected - in-profile action component](#)
- [Filter creation issue detected - match action component](#)
- [Filter creation issue detected - metering component](#)
- [Filter creation issue detected - non-match action component](#)
- [Filter creation issue detected - out-of-profile action component](#)
- [Filter manager internal error encountered](#)
- [Filter manager memory resources exhausted](#)
- [Filter manager metering or policy rule space exhausted](#)
- [Filter manager metering resources exhausted](#)
- [Filter manager request parameter invalid](#)
- [Filter manager statistics tracking resources exhausted](#)
- [Filter set requirements incompatible with target interface](#)
- [First TrTCM Meter Index must be in range 1-5000](#)
- [Flow ID filtering not supported for IPv4](#)
- [Flow ID out-of-range \(Flow ID \)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with G

This page lists all the logs starting with the letter G that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Got UserPolicy from Radius but UBP disabled - unitPort 0x%x mac %08x%04x](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with I

This page lists all the logs starting with the letter I that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Ifc app modification issue \(inconsistent default gateway data\)](#)
- [Ifc app modification issue \(inconsistent DHCP server data\)](#)
- [Ifc app modification issue \(inconsistent ifType data\)](#)
- [Ifc app support not currently available on interface \(ifc# \)](#)
- [Ifc assignment issue - prec conflict \(policy policy# disabled\)](#)
- [Inadequate resources available for application policy criteria](#)
- [Incompatible base action extension specified](#)
- [Incompatible classifier reference \(agent-defined clfr\)](#)
- [Incompatible data model version values \(referenced clfr data\)](#)
- [Incompatible data model version values \(referenced meter data\)](#)
- [Incompatible in-profile action \(trusted ifc\)](#)
- [Incompatible in-profile action \(unrestricted ifc\)](#)
- [Incompatible in-profile action \(untrusted ifc\)](#)
- [Incompatible in-profile action \(untrustedv4v6 ifc\)](#)
- [Incompatible match action \(unrestricted ifc\)](#)
- [Incompatible match action \(untrusted ifc\)](#)
- [Incompatible match action \(untrustedv4v6 ifc\)](#)
- [Incompatible non-match action \(trusted ifc\)](#)
- [Incompatible non-match action \(unrestricted ifc\)](#)
- [Incompatible non-match action \(unrestricted ifc\)](#)
- [Incompatible non-match action \(untrusted ifc\)](#)
- [Incompatible out-of-profile action \(trusted ifc\)](#)
- [Incompatible out-of-profile action \(unrestricted ifc\)](#)
- [Incompatible out-of-profile action \(untrusted ifc\)](#)
- [Incompatible out-of-profile action \(untrustedv4v6 ifc\)](#)
- [Incompatible StorageType specified \(re classifier\)](#)
- [Inconsistent action criteria detected across block members](#)
- [Inconsistent classifier component \(clfr comp# \) state detected](#)
- [Inconsistent labels detected for members of same block](#)
- [Inconsistent labels detected for members of same set](#)
- [Inconsistent MAC data detected across filter set members](#)
- [Inconsistent metering criteria detected across block members](#)
- [Index value out-of-range](#)
- [Inner VLAN ID filtering requires double tag](#)
- [Inner VLAN ID min max values invalid \(min VLAN ID ! max VLAN ID \)](#)
- [In-profile action contains conflicting data](#)
- [Insufficient HW resources to support port role association](#)
- [Insufficient policy space available to support access assignment](#)
- [Insufficient resources available to support policy installation](#)
- [Interface action distribution across stack failed](#)
- [Interface action entry referenced by base action](#)
- [Interface action extension identifier invalid](#)
- [Interface action modifications not supported](#)
- [Interface Application data in use \(QoS disable prohibited\)](#)
- [Interface application distribution across stack failed](#)

- [Interface application modifications not supported](#)
- [Interface application Undo failure \(app app# \)](#)
- [Interface assignment distribution across stack failed](#)
- [Interface assignment failure - precedence conflict detected](#)
- [Interface assignment modifications not supported](#)
- [Interface capabilities incompatible with policy data](#)
- [Interface data out-of-sync in Policy and User Policy entries](#)
- [Interface queue modifications not supported](#)
- [Interface resources inadequate to support application enable](#)
- [Interface shaping and CoS shaping conflict \(same ifc specified\)](#)
- [Interface shaping and queue shaping conflict \(same ifc specified\)](#)
- [Interface shaping modifications not supported](#)
- [Interface shaping not supported with specified interface](#)
- [Interfaces QoS-disabled \(port# on unit# \) - restoration issue](#)
- [Invalid access assignment type option specified](#)
- [Invalid access element type option specified](#)
- [Invalid classifier ID specified](#)
- [Invalid classifier reference](#)
- [Invalid classifier reference \(unknown class\)](#)
- [Invalid classifier reference \(unknown incompatible set\)](#)
- [Invalid classifier reference \(unknown instance\)](#)
- [Invalid DAPP state transition detected \(prohibited\)](#)
- [Invalid datapath identifier specified](#)
- [Invalid destination MAC address length specified](#)
- [Invalid destination MAC address mask length specified](#)
- [Invalid drop action option specifiedInvalid drop action option specified](#)
- [Invalid drop precedence value specified \(precedence \)](#)
- [Invalid DSCP value specified \(DSCP value \)](#)
- [Invalid egress interface specified \(ifc# \)](#)
- [Invalid egress interface type specified \(<ifc type>\)](#)
- [Invalid egress mask value specified](#)
- [Invalid entry creation attempted \(index index# \)](#)
- [Invalid EtherType value specified \(Ether Type 0xXXXX \)](#)
- [Invalid expired session data specified](#)
- [Invalid filter set priority value detected](#)
- [Invalid interface found in egress mask \(egress mask bit# \)](#)
- [Invalid interface index data specified \(ifc# \)](#)
- [Invalid interface index data specified \(ifc index \)](#)
- [Invalid interface index data \(system-owned\) specified](#)
- [Invalid IP destination address prefix detected](#)
- [Invalid IP source address prefix detected](#)
- [Invalid master block member value specified](#)
- [Invalid maximum inner VLAN ID value specified \(VLAN ID \)](#)
- [Invalid maximum VLAN ID value specified \(VLAN ID \)](#)
- [Invalid metering data \(bucket size\) specified for interface\(s\)](#)
- [Invalid metering data \(granularity\) specified for interface\(s\)](#)
- [Invalid metering data \(rate\) specified for interface\(s\)](#)
- [Invalid metering data \(srTCM trTCM\) specified for interface\(s\)](#)
- [Invalid minimum inner VLAN ID value specified \(VLAN ID \)](#)
- [Invalid minimum VLAN ID value specified \(VLAN ID \)](#)
- [Invalid mix of IP address data \(Dst IP type\) in set detected](#)
- [Invalid mix of IP and non-IP data in set detected](#)
- [Invalid mix of IP data \(IPv4 IPv6\) in set detected](#)
- [Invalid option specified for BcastFrames attribute](#)
- [Invalid option specified for KnownIpMcast attribute](#)
- [Invalid option specified for KnownMcastFrames attribute](#)
- [Invalid option specified for KnownNonIpMcast attribute](#)
- [Invalid option specified for KnownUcastFrames attribute](#)
- [Invalid option specified for NonIpPkt attribute](#)
- [Invalid option specified for PatternIpVersion attribute](#)
- [Invalid option specified for UnknownMcastFrames attribute](#)
- [Invalid option specified for UnknownNonIpMcast attribute](#)
- [Invalid option specified for UnknownUcastFrames attribute](#)
- [Invalid pattern data length \(untagged format\) specified](#)
- [Invalid pattern data string length specified](#)

- [Invalid pattern format data specified](#)
- [Invalid pattern position string length specified](#)
- [Invalid port detected in specified port mask](#)
- [Invalid 802.1p user priority value specified \(priority value \)](#)
- [Invalid resetToDefaults value specified](#)
- [Invalid set drop precedence value specified](#)
- [Invalid shaping data \(bucket size\) specified for interface\(s\)](#)
- [Invalid shaping data \(granularity\) specified for interface\(s\)](#)
- [Invalid shaping data \(minimum rate granularity\) specified](#)
- [Invalid shaping data \(minimum rate maximum rate\) specified](#)
- [Invalid shaping data \(minimum rate\) specified](#)
- [Invalid shaping data \(rate\) specified for interface\(s\)](#)
- [Invalid source MAC address length specified](#)
- [Invalid source MAC address mask length specified](#)
- [Invalid statistics counter identification specified](#)
- [Invalid statistics tracking value](#)
- [Invalid statistics type value](#)
- [Invalid track statistics value specified](#)
- [Invalid unknown access assignment entry state encountered \(entry state \)](#)
- [Invalid unknown access element entry state encountered \(entry state \)](#)
- [Invalid unknown action entry state encountered \(entry state \)](#)
- [Invalid unknown bandwidth type specified](#)
- [Invalid unknown classifier block entry state encountered \(entry state \)](#)
- [Invalid unknown CoS shaping entry state encountered \(entry state \)](#)
- [Invalid unknown DSCP mapping entry state encountered \(entry state \)](#)
- [Invalid unknown entry state \(class class# \) encountered \(entry state \)](#)
- [Invalid unknown interface action entry state encountered \(entry state \)](#)
- [Invalid/unknown interface app entry state encountered \(<entry state>\)](#)
- [Invalid unknown interface assignment entry state encountered \(entry state \)](#)
- [Invalid unknown interface queue entry state encountered \(entry state \)](#)
- [Invalid unknown interface shaping entry state encountered \(entry# \)](#)
- [Invalid unknown IP filter entry state encountered \(entry state \)](#)
- [Invalid unknown Layer 2 filter entry state encountered \(entry state \)](#)
- [Invalid unknown meter entry state encountered \(entry state \)](#)
- [Invalid unknown policy entry state encountered \(entry state \)](#)
- [Invalid unknown 802.1p user priority mapping entry state \(entry state \)](#)
- [Invalid unknown queue set assignment entry state encountered \(entry state \)](#)
- [Invalid unknown queue shaping entry state encountered \(entry state \)](#)
- [Invalid unknown queuing discipline enum specified \(queuing discipline \)](#)
- [Invalid unknown role combination entry state encountered \(entry state \)](#)
- [Invalid unknown System filter entry state encountered \(entry state \)](#)
- [Invalid unknown token bucket entry state encountered \(entry state \)](#)
- [Invalid unknown user policy entry state encountered \(entry state \)](#)
- [Invalid unsupported buffering capabilities value specified](#)
- [Invalid unsupported copy-to-cpu option specified](#)
- [Invalid unsupported DAPP enable value specified](#)
- [Invalid unsupported DAPP maximum IPv4 ICMP length specified](#)
- [Invalid unsupported DAPP maximum IPv6 ICMP length specified](#)
- [Invalid unsupported DAPP minimum TCP header length specified](#)
- [Invalid unsupported default gateway address length specified](#)
- [Invalid unsupported default gateway address specified](#)
- [Invalid unsupported destination IP address length specified](#)
- [Invalid unsupported DHCP server address length specified](#)
- [Invalid unsupported DHCP server address specified](#)
- [Invalid unsupported interface type specified](#)
- [Invalid unsupported mirror frame option specified](#)
- [Invalid unsupported NT application mode value specified](#)
- [Invalid unsupported packet type value specified](#)
- [Invalid unsupported QoS system operational mode value specified](#)
- [Invalid unsupported queue configuration value specified](#)
- [Invalid unsupported role assoc compatibility specified](#)
- [Invalid unsupported source IP address length specified](#)
- [Invalid unsupported Trusted processing mode value specified](#)
- [Invalid unsupported UBP support level value specified](#)
- [Invalid unsupported VLAN tag value specified \(VLAN tag \)](#)

- [Invalid update DSCP value specified \(DSCP value \)](#)
- [Invalid update DSCP value specified \(not currently supported\)](#)
- [Invalid update priority value specified](#)
- [Invalid update VLAN Id specified \(VLAN Id \)](#)
- [Invalid user priority match selection specified \(priority value \)](#)
- [IP classifier distribution across stack failed](#)
- [IP classifier entry still referenced \(deletion prohibited\)](#)
- [IP classifier modifications not supported](#)
- [IP destination address and mask values out-of-sync](#)
- [IP destination Layer 4 port maximum value out-of-range \(dest port# \)](#)
- [IP destination Layer 4 port minimum value out-of-range \(dest port# \)](#)
- [IP protocol value out-of-range \(IP protocol# \)](#)
- [IP protocol value TCP or UDP needed with Layer 4 port filtering](#)
- [IP source address and mask values out-of-sync](#)
- [IP source Layer 4 port minimum value out-of-range \(src port# \)](#)
- [IP source Layer 4 port minimum value out-of-range \(src port# \)](#)
- [IPv4-only filter criteria mixed with IPv6 criteria](#)
- [Issue detected during OoS stack synchronization](#)
- [Issue detected enabling disabling DSCP table usage \(port#\)](#)
- [Issue detected restoring OPA data from NV \(class class# \)](#)
- [Issue detected setting native DSCP table values](#)
- [Issues detected with OoS operational mode disable \(ifcs# ifcs \)](#)
- [Issues detected with OoS operational mode enable \(ifcs# ifcs \)](#)
- [Issue with classifier component mask detected](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with L

This page lists all the logs starting with the letter L that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Layer 2 classifier modifications not supported](#)
- [Layer 2 classifier still referenced \(deletion prohibited\)](#)
- [Layer 2 filter distribution across stack failed](#)
- [Layer 4 port filtering with IPv6 requires UDP TCP Next Header](#)
- [Layer 4 port range could not be reduced sufficiently](#)
- [Lossless and Lossless-PFC modes are only supported in queue set 2](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with M

This page lists all the logs starting with the letter M that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Meter distribution across stack failed](#)
- [Meter entry referenced by clfr block \(deletion prohibited\)](#)
- [Meter entry referenced by meter \(deletion prohibited\)](#)
- [Meter entry referenced by policy \(deletion prohibited\)](#)
- [Meter \(from clfr block\) usage in multiple policies prohibited](#)
- [Meter \(from policy\) usage in multiple policies prohibited](#)
- [Meter identifier out-of-range \(meter id \)](#)
- [Metering not supported with DS L2 access control lists](#)
- [Meter modifications not supported](#)
- [Mirroring \(requested via action\) not configured correctly](#)
- [Modification of action \(non-match usage\) prohibited](#)
- [Modify the pattern data or use the correct data format](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with N

This page lists all the logs starting with the letter N that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Non-match action contains conflicting data](#)
- [Non-match action not available for use with filter sets](#)
- [Non-match action support not available on certain interfaces](#)
- [Non-QoS interfaces may not be assigned to a role combination](#)
- [Non-supported action option \(green action\) specified](#)
- [Non-supported action option \(in-profile action\) specified](#)
- [Non-supported action option \(match action\) specified](#)
- [Non-supported action option \(out-of-profile action\) specified](#)
- [Non-supported action option \(policy non-match action\) specified](#)
- [Non-supported action option \(red action\) specified](#)
- [Non-supported action option \(yellow action\) specified](#)
- [Non-unique element label detected \(prohibited\)](#)
- [Non-unique precedence order value detected \(prohibited\)](#)
- [Non-volatile QoS data discarded during restoration](#)
- [Non-volatile storage commit delay too large](#)
- [No resources available for classifier port range checking](#)
- [NT application mode enable failure - inadequate resources](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with O

This page lists all the logs starting with the letter O that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Only one frame type supported per classifier](#)
- [Out-of-profile action contains conflicting data](#)
- [Out-of-range CoS index value \(COS index value \)](#)
- [Out-of-range queue index value \(queue index \) for in-use queue set](#)
- [Out-of-range queue index value \(queue index \) for pending queue set](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with P

This page lists all the logs starting with the letter P that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Packet redirection support limited by target interfaces](#)
- [Pattern matching data in excess of bytes# bytes specified](#)
- [Pattern matching \(Dst IP\) not supported with IP addr type data](#)
- [Pattern matching \(Dst MAC\) not supported with address type data](#)
- [Pattern matching \(IP\) not supported with non-IP addr type data](#)
- [Pattern matching not supported with other classification data](#)
- [Pattern modifier data specified without actual pattern data](#)
- [Pattern position and data strings must be same length](#)
- [Policies with session data must be port-based](#)
- [Policy action out-of-range \(action# \)](#)
- [Policy content incompatible with target interface\(s\)](#)
- [Policy distribution across stack failed](#)
- [Policy mask availability issue \(space exhausted\)](#)
- [Policy modifications not supported](#)
- [Policy modification support limited](#)
- [Policy non-match action out-of-range \(non-match action# \)](#)
- [Policy precedence conflict detected with non-QoS application](#)
- [Policy precedence value out-of-range for target interface\(s\)](#)
- [Policy requirements exceed available resources \(slot slot# \)](#)
- [Policy statistics index out-of-range \(stats index \)](#)
- [Policy with this filtering values is already installed on this precedence](#)
- [Post-join ACL installation issue detected \(ifc ifc# \)](#)
- [Post-join filter set installation issue detected \(ifc ifc# \)](#)
- [Post-join policy installation issue detected \(ifc ifc# \)](#)
- [Post-join traffic-profile installation issue detected \(ifc ifc# \)](#)
- [Potential inconsistent access asgn state \(Undo fail\) detected](#)
- [Potential inconsistent access elem state \(Undo fail\) detected](#)
- [Potential inconsistent block state \(Undo fail\) detected](#)
- [Potential inconsistent ifc assignment state \(Undo fail\) detected](#)
- [Potential inconsistent policy state \(Undo fail\) detected](#)
- [Precedence value out-of-range](#)
- [Provided metering information incomplete](#)
- [802.1p user priority mapping modifications not supported](#)
- [802.1p user priority value modification prohibited](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with Q

This page lists all the logs starting with the letter Q that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [Q](#) | [P](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [QoS inter-module communication issue detected](#)
- [QoS policies may not be applied to uplink or daisy chain ports \(port# \)](#)
- [Queue configuration inconsistency detected \(local queue conf stack queue conf \)](#)
- [Queue data distribution across stack failed](#)
- [Queue set assignment distribution across stack failed](#)
- [Queue set assignment modifications not supported](#)
- [Queue set unacceptable - pending range excludes in-use queues](#)
- [Queue set value modification prohibited](#)
- [Queue set value modification prohibited](#)
- [Queue shaping distribution across stack failed](#)
- [Queue shaping modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [Q](#) | [P](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with R

This page lists all the logs starting with the letter R that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Rate granularity limited to increments of 1 Mbps or 64 Kbps](#)
- [Rate \(min\) granularity limited \(increments of 1 Mbps or 64 Kbps\)](#)
- [Referenced block \(by policy\) deletion prohibited](#)
- [Referenced set \(by block\) modifications prohibited](#)
- [Referenced set \(by policy\) modifications prohibited](#)
- [Remote QoS-disable request failure \(port# on unit unit# \)](#)
- [Requested attribute usage is currently not supported](#)
- [Requested filter manager support unavailable](#)
- [Requested reserve data invalid](#)
- [Request invalid - QoS interface apps enabled on interface\(s\)](#)
- [Request invalid - specified interface currently QoS-disabled](#)
- [Request temporarily denied - QoS support is currently disabled](#)
- [Required bandwidth information not specified](#)
- [Resource alloc event timeout \(tgt all apps except QoS Agent rcv event \)](#)
- [Resources exhausted \(maximum class entries reached\)](#)
- [Resources exhausted \(out-of-memory\)](#)
- [Role combination associated with interface \(deletion prohibited\)](#)
- [Role combination contains unacceptable characters](#)
- [Role combination distribution across stack failed](#)
- [Role combination length outside of acceptable limits](#)
- [Role combination modifications not supported](#)
- [Role combination referenced by policy \(deletion prohibited\)](#)
- [Role \(interface\) capabilities incompatible with policy data](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with S

This page lists all the logs starting with the letter S that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Simultaneous operations involving access asgn ifcs prohibited](#)
- [Simultaneous operations involving policies and blocks prohibited](#)
- [Simultaneous operations involving policies and ifcs prohibited](#)
- [Simultaneous operations involving policy blocks ifcs prohibited](#)
- [Source MAC address and mask values out-of-sync](#)
- [Specified Destination Layer 4 min max range not supported](#)
- [Specified filter criteria is invalid inconsistent](#)
- [Specified filter information not found](#)
- [Specified filter manager resource invalid](#)
- [Specified filter manager resource uninitialized](#)
- [Specified inner VLAN ID min max range not supported](#)
- [Specified metering operation not supported](#)
- [Specified metering statistics entry already in-use \(by policy\)](#)
- [Specified policy components \(classifiers\) conflicting](#)
- [Specified policy components \(classifiers\) conflicting](#)
- [Specified policy identifier \(cookie\) invalid](#)
- [Specified policy statistics entry already in-use \(by meter\)](#)
- [Specified queue set information invalid](#)
- [Specified Source Layer 4 min max range not supported](#)
- [Specified token bucket criteria out of range](#)
- [Specified token bucket refresh interval not supported](#)
- [Specified token bucket size \(burst size\) not supported](#)
- [Specified user policy interface currently QoS-disabled](#)
- [Specified VLAN ID min max range not supported](#)
- [Src Layer 4 port min max values invalid \(max must be = to min\)](#)
- [srTCM meter issue - CIR must be the same in both meters](#)
- [srTCM meter issue - EBS must be greater than CBS](#)
- [srTCM trTCM meter issue - diff algorithms in associated meters](#)
- [srTCM trTCM meter issue - referenced meter incompatible unknown](#)
- [srTCM trTCM meter issue - too many cascaded meters](#)
- [System classifier modifications not supported](#)
- [System classifier still referenced \(deletion prohibited\)](#)
- [System filter distribution across stack failed](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with T

This page lists all the logs starting with the letter T that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [TCP Control Flag filter criteria requires TCP protocol](#)
- [Token bucket algorithm identifier invalid](#)
- [Token bucket algorithm identifier unknown unsupported](#)
- [Token bucket data distribution across stack failed](#)
- [Token bucket entry referenced by meter \(deletion prohibited\)](#)
- [Token bucket entry referenced by shaper \(deletion prohibited\)](#)
- [Token bucket minimum rate outside limits \(64 - 10230000 Kbps\)](#)
- [Token bucket modifications not supported](#)
- [Token bucket rate outside limits \(64 - 10230000 Kbps\)](#)
- [Token bucket size not compatible with committed fill rate](#)
- [Traffic Prof filter set delete operation failed](#)
- [Traffic Prof filter set elem count exceeds available resources](#)
- [Traffic Prof filter set install operation failed](#)
- [Traffic Prof filter set policy count \(policy count \) exceeds limit \(policy limit \)](#)
- [Traffic Prof filter set rule count \(rule count \) exceeds limit \(rule limit \)](#)
- [Traffic Prof filter set update operation failed](#)
- [trTCM meter issue - PBS must be greater than CBS](#)
- [trTCM meter issue - PIR must be greater than CIR](#)
- [Trusted processing mode change rejected - inadequate resources](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with U

This page lists all the logs starting with the letter U that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [Unable to add block member \(block elem# component set id \) to existing policy](#)
- [Unable to apply existing policy data to interface \(unit# port# \)](#)
- [Unable to apply existing user-based policy data to new user](#)
- [Unable to apply filter set to ports \(unsupported capabilities\)](#)
- [Unable to apply newly-defined UBP filter set to existing user](#)
- [Unable to apply pre-defined UBP filter set to new user](#)
- [Unable to complete requested access asgn system operation \(oper type \)](#)
- [Unable to complete requested policy system operation \(operation type \)](#)
- [Unable to compress classification criteria in set adequately](#)
- [Unable to compress specified policy criteria](#)
- [Unable to create action for access element](#)
- [Unable to create classifier block entry for access element](#)
- [Unable to create classifier component entry for access element](#)
- [Unable to create count action \(meter\) for access assignment](#)
- [Unable to create count action \(policy\) for access assignment](#)
- [Unable to create count action \(secondary meter\) for access asgn](#)
- [Unable to create DS MF classifier for access element](#)
- [Unable to create L2 MF classifier for access element](#)
- [Unable to create metering data for access assignment](#)
- [Unable to create non-match components for ACL](#)
- [Unable to create out-of-profile action for access assignment](#)
- [Unable to create policy data for access assignment](#)
- [Unable to create secondary metering data for access assignment](#)
- [Unable to create secondary token bucket data for access asgn](#)
- [Unable to create token bucket data for access assignment](#)
- [Unable to create yellow action for access assignment](#)
- [Unable to deactivate policy associated with interface](#)
- [Unable to delete block member \(block element# component set id \) from existing policy](#)
- [Unable to delete UBP filter set on interface ifc#](#)
- [Unable to derive suitable filter set element eval precedence](#)
- [Unable to determine cfr interface\(s\) compatibility](#)
- [Unable to disable ARP Spoofing support on interface \(ifc# \)](#)
- [Unable to disable BPDUBlkr support on interface \(ifc# \)](#)
- [Unable to disable DHCP Snooping support on interface \(ifc# \)](#)
- [Unable to disable DHCP Spoofing support on interface \(ifc# \)](#)
- [Unable to disable DNSPort support on interface \(ifc# \)](#)
- [Unable to disable existing policy data on interface \(unit# port# \)](#)
- [Unable to disable FTTPort support on interface \(ifc# \)](#)
- [Unable to disable Nachia support on interface \(ifc# \)](#)
- [Unable to disable policy data for access assignment](#)
- [Unable to disable SQLSlam support on interface \(ifc# \)](#)
- [Unable to disable SynFinScan support on interface \(ifc# \)](#)
- [Unable to disable Xmas support on interface \(ifc# \)](#)
- [Unable to enable ARP Spoofing support on interface \(ifc# \)](#)
- [Unable to enable BPDUBlkr support on interface \(ifc# \)](#)

- [Unable to enable DHCP Snooping support on interface \(ifc# \)](#)
- [Unable to enable DHCP Spoofing support on interface \(ifc# \)](#)
- [Unable to enable DNSPort support on interface \(ifc# \)](#)
- [Unable to enable FTPPort support on interface \(ifc# \)](#)
- [Unable to enable Nachia support on interface \(ifc# \)](#)
- [Unable to enable policy data for access assignment](#)
- [Unable to enable SQLSlam support on interface \(ifc# \)](#)
- [Unable to enable SynFinScan support on interface \(ifc# \)](#)
- [Unable to enable Xmas support on interface \(ifc# \)](#)
- [Unable to inform SPB of ifc assignment change \(%d/%d\)](#)
- [Unable to install access assignment - component creation issue](#)
- [Unable to install access element - component creation issue](#)
- [Unable to locate corresponding DS L2 access elements](#)
- [Unable to manipulate DAPP support \(no applicable interfaces\)](#)
- [Unable to modify access assignment - component modify issue](#)
- [Unicast \(Interface# \) and Non-Unicast \(interface# \) interfaces in conflict](#)
- [Unknown access assignment entry specified \(entry# \)](#)
- [Unknown access element entry specified \(entry# \)](#)
- [Unknown action entry specified \(entry# \)](#)
- [Unknown classifier block entry specified \(entry# \)](#)
- [Unknown classifier component entry specified \(entry# \)](#)
- [Unknown CoS shaping entry specified \(entry# CoS \)](#)
- [Unknown count action entry specified \(entry# \)](#)
- [Unknown DSCP mapping entry specified \(entry# \)](#)
- [Unknown entry \(class class# \) specified \(entry# \)](#)
- [Unknown incompatible access element specified](#)
- [Unknown incompatible action component specified](#)
- [Unknown incompatible classifier block specified](#)
- [Unknown incompatible classifier set specified](#)
- [Unknown incompatible in-profile action specified](#)
- [Unknown incompatible in-profile \(green\) action specified](#)
- [Unknown incompatible match action specified](#)
- [Unknown incompatible metering component specified](#)
- [Unknown incompatible metering statistics entry specified](#)
- [Unknown incompatible out-of-profile action specified](#)
- [Unknown incompatible out-of-profile \(red\) action specified](#)
- [Unknown incompatible out-of-profile \(yellow\) action specified](#)
- [Unknown incompatible policy non-match action specified](#)
- [Unknown incompatible policy statistics entry specified](#)
- [Unknown incompatible queue set specified](#)
- [Unknown incompatible role combination specified](#)
- [Unknown incompatible token bucket reference specified](#)
- [Unknown incompatible token bucket reference specified](#)
- [Unknown interface application entry specified \(entry# \)](#)
- [Unknown interface assignment entry specified \(entry# \)](#)
- [Unknown interface queue entry specified \(ifc queue id \)](#)
- [Unknown interface shaping entry specified \(entry# \)](#)
- [Unknown IP classifier entry specified \(entry# \)](#)
- [Unknown Layer 2 classifier entry specified \(entry# \)](#)
- [Unknown meter entry specified \(entry# \)](#)
- [Unknown out-of-range interface index value \(ifc# \)](#)
- [Unknown out-of-range interface index value \(ifc index \)](#)
- [Unknown policy entry specified \(entry# \)](#)
- [Unknown 802.1p user priority mapping entry specified \(entry# \)](#)
- [Unknown queue set assignment entry specified \(entry# \)](#)
- [Unknown queue set queue reference detected](#)
- [Unknown queue shaping entry specified \(entry# queue \)](#)
- [Unknown role combination entry specified \(role comb id \)](#)
- [Unknown System classifier entry specified \(entry# \)](#)
- [Unknown token bucket entry specified \(entry# \)](#)
- [Unknown unsupported attribute specified \(attribute \)](#)
- [Unknown unsupported interface application type specified](#)
- [Unknown unsupported interface class specified \(ifc class \)](#)
- [Unknown unsupported IP Flag specified](#)
- [Unknown unsupported RowStatus specified](#)

- [Unknown unsupported StorageType specified](#)
- [Unknown unsupported TCP Control Flag specified](#)
- [Unknown user policy entry specified \(entry# \)](#)
- [Unsupported IP address type specified](#)
- [Unsupported IPv4 Options value specified](#)
- [Unsupported pattern offset data specified](#)
- [Unsupported unknown QoS agent configuration attribute \(attribute# \)](#)
- [Update priority value and update DSCP value out-of-sync](#)
- [Update priority value per ingress DSCP currently not supported](#)
- [User Policy data referencing interface \(operation prohibited\)](#)
- [User policy distribution across stack failed](#)
- [User policy filter set count \(<set count>\) exceeds limit \(<set limit>\)](#)
- [User policy filter set delete operation failed](#)
- [User policy filter set element count exceeds available resources](#)
- [User policy filter set install operation failed](#)
- [User policy filter set update operation failed](#)
- [User policy group contains invalid unacceptable characters](#)
- [User policy group length outside of acceptable limits](#)
- [User policy modifications not supported](#)
- [User policy name contains invalid unacceptable characters](#)
- [User policy name length outside of acceptable limits](#)
- [User Policy \(UBP\) filter set in use \(QoS disable prohibited\)](#)
- [User Policy \(UBP\) filter set in use \(QoS reset prohibited\)](#)
- [User priority specified with untagged frames \(invalid\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

QoS logs starting with V

This page lists all the logs starting with the letter V that are generated by the QoS source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

- [VLAN ID min max values invalid \(min VLAN ID ! max VLAN ID \)](#)
- [VLAN range could not be reduced sufficiently](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Fabric Attach logs starting with F

This page lists all the logs starting with the letter F that are generated by the Fabric Attach source.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

E

- [Fabric Attach: agent settings reset incomplete](#)
- [Fabric Attach: asgn activation failure \(port tagging\)](#)
- [Fabric Attach: asgn activation failure \(VLAN creation\)](#)
- [Fabric Attach: asgn activation failure \(VLAN membership\)](#)
- [Fabric Attach: auto provision setting not supported by platform](#)
- [Fabric Attach: binding acceptance failure \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding accepted \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation failure \(<ISID>/<VID>\)](#)
- [Fabric Attach: binding activation success \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation success \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding deactivation failure \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding deactivation failure \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding deactivation success \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding deactivation success \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding expiration \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: client binding deleted \(<IFINDEX>/<ISID>/<VID>\)](#)
- [Fabric Attach: conflicting uplink data detected](#)
- [Fabric Attach: device deleted \(port <PORT>\)](#)
- [Fabric Attach: device deleted \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Fail - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Fail - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Pass - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Pass - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Not Authenticated - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Not Authenticated - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device expired \(port <PORT>\)](#)
- [Fabric Attach: device expired \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: element type updated](#)
- [Fabric Attach: incompatible device advertisement \(port <PORT>\)](#)
- [Fabric Attach: incompatible device advertisement \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: interface-specific I-SID/VLAN assignments not allowed](#)
- [Fabric Attach: invalid VLAN data \(unknown or incompatible type\)](#)
- [Fabric Attach: I-SID/VLAN assignment creation failure \(unexpected\)](#)
- [Fabric Attach: I-SID/VLAN assignment deletion failure \(unexpected\)](#)
- [Fabric Attach: management VLAN updated \(was <VID>, now <VID>\) by Zero Touch](#)
- [Fabric Attach: message authentication support not available](#)
- [Fabric Attach: multiple FA Servers detected](#)
- [Fabric Attach: non-MLT trunk uplink requires MLT ID/LACP key binding \(missing\)](#)
- [Fabric Attach: operation failure detected](#)
- [Fabric Attach: operation rejected - client-owned entry](#)
- [Fabric Attach: operation rejected - CVLAN already exists](#)
- [Fabric Attach: operation rejected - entry does not exist](#)
- [Fabric Attach: operation rejected - not supported by element type](#)
- [Fabric Attach: operation rejected - service not enabled](#)
- [Fabric Attach: operation rejected - table entry limits reached](#)

- [Fabric Attach: port authentication update - data flushed \(MLT %d\)](#)
- [Fabric Attach: port authentication update - data flushed \(port %d\)](#)
- [Fabric Attach: port authentication update - data flushed \(port %d/%d\)](#)
- [Fabric Attach: primary FA Server lost](#)
- [Fabric Attach: primary FA server selected \(port %d\)](#)
- [Fabric Attach: primary FA server selected \(port %d/%d\)](#)
- [Fabric Attach: primary FA server selected \(trunk %d\)](#)
- [Fabric Attach: proxy not supported by element type](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - application interactions](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - invalid VLAN](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - no FA resources](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - no VLAN resources](#)
- [Fabric Attach: server asgn \(<ISID>/<VID>\) rejection - peer acceptance](#)
- [Fabric Attach: server connection type change](#)
- [Fabric Attach: server connection type change \(different ports\)](#)
- [Fabric Attach: server connection type change \(different trunks\)](#)
- [Fabric Attach: server connection type change \(non-trunk to trunk\)](#)
- [Fabric Attach: server connection type change \(trunk to non-trunk\)](#)
- [Fabric Attach: service disabled](#)
- [Fabric Attach: service enabled](#)
- [Fabric Attach: specified element type not supported](#)
- [Fabric Attach: specified uplink currently a trunk member](#)
- [Fabric Attach: specified uplink currently invalid](#)
- [Fabric Attach: standalone/non-standalone proxy transition \(service reset\)](#)
- [Fabric Attach: static uplink addition failure](#)
- [Fabric Attach: static uplink deletion failure](#)
- [Fabric Attach: temporary I-SID/VLAN binding deletion failure](#)
- [Fabric Attach: trunk link automatically enabled \(MLT %d port %d/%d\)](#)
- [Fabric Attach: uplink operation only supported by FA Proxy](#)
- [Fabric Attach: Zero Touch capabilities disabled](#)
- [Fabric Attach: Zero Touch capabilities enabled](#)
- [Fabric Attach: zero touch operations not completed \(mgmt VLAN <VID>\)](#)
- [Fabric Attach: Zero Touch option processing failure detected](#)
- [Fabric Attach: Zero Touch settings read-only for FA element type](#)

E

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with A

This page lists all the logs starting with the letter A that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [AAUR-Info AAUR default](#)
- [AAUR-Info AAUR disable](#)
- [AAUR-Info AAUR enable](#)
- [AAUR-Info Agent transfer finished](#)
- [AAUR-Info Receive request for agent image start transfer](#)
- [AAUR-Info Receive request for agent image. Unable to start transfer](#)
- [AAUR-Info Send request for new agent image](#)
- [AAUR-Info Slave refuse transfer](#)
- [AAUR-Info The hardware is not compatible with the image version number version](#)
- [AAUR-Warning Cannot get FLASH resource](#)
- [Access assignment distribution across stack failed](#)
- [Access element distribution across stack failed](#)
- [ADAC Error applying main VLAN QoS configuration](#)
- [ADAC Error applying VLAN QoS configuration for unit port unit# port#](#)
- [ADAC Error forcing administrative state to disable enable](#)
- [ADAC Error removing main VLAN QoS configuration](#)
- [ADAC Error removing VLAN QoS configuration for unit port unit# port#](#)
- [ADAC Forced administrative state to disable enable](#)
- [ADAC System operationally disable enable](#)
- [AES activated by schedule](#)
- [AES deactivated by schedule](#)
- [AES globally disabled](#)
- [AES globally enabled](#)
- [AES manually activated](#)
- [AES manually deactivated](#)
- [AES not applying schedule because SNTP not synchronized](#)
- [AES time is synchronized applying schedule](#)
- [Agent configuration distribution across stack failed](#)
- [Allowed connection attempt from user .:](#)
- [Allowed connection attempt from user](#)
- [Another BU tried to join the stack. Unit ignored](#)
- [application_name failed DB-exchange stack formation delayed](#)
- [ASCII failed](#)
- [ASCII finished successfully](#)
- [ASCII finished successfully at load on boot](#)
- [ASCII transfer failed](#)
- [ASCII transfer failed at load on boot](#)
- [ASCII transfer OK](#)
- [ASCII transfer OK at load on boot](#)
- [AUR-Info AUR disable](#)
- [AUR-Info AUR enable](#)
- [AUR-Info AUR Restored to default](#)
- [AUR-Info New unit has different HW config Using cfg from the new unit](#)
- [Authentication Failure Trap](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with B

This page lists all the logs starting with the letter B that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Backup configuration block # block_number in use](#)
- [Backup configuration restored from primary configuration block # block_number](#)
- [Backup configuration updated for next active configuration block # block_number](#)
- [Backup Configuration Version is updated](#)
- [Base action distribution across stack failed](#)
- [BaySec Exceeded number MAC addresses on unit# port#](#)
- [Bay Secure Exceeded number per-port MAC addresses on port unit# port#](#)
- [Bay Secure intruder](#)
- [Bay Secure intruder MAC](#)
- [Bay Secure: MAC DA filtering not enough resources](#)
- [Bay Secure per-port addresses deleted](#)
- [BECOME_TEMP_BU event sent unit mask value appl mask value](#)
- [Boot: system boot status 0x%x](#)
- [BPDU received on port with BPDU-Filtering enabled.](#)
- [BU was unable to send IMC for NBUs VLAN/Port configuration](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with C

This page lists all the logs starting with the letter C that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [cam driver initialized](#)
- [Cannot configure without loopback port available](#)
- [Cannot create CVLAN on vlan: IGMP Snooping enabled and SPBM Mcast disabled](#)
- [Cannot disable IP Source Guard on Unit unit# Port port#](#)
- [Cannot disable SPBM multicast - IGMP Snooping is enabled on C-VLANs](#)
- [Cannot enable SPBM multicast: feature unsupported](#)
- [Cannot enable SPBM multicast while unknown-mcast-no-flood is enabled](#)
- [Cannot enable SPBM while PIM is enabled](#)
- [Capabilities determined by agent \(not-writable\)](#)
- [CDT MAC address mac address was removed because LAG trunk trunked has disaggregated.](#)
- [CDT MAC address mac address was removed because port port no has aggregated in LAG](#)
- [CDT The static FDB entry MAC mac address VLAN vlan Id trunk trunkId was deleted because LAG has disaggregated](#)
- [CDT The static FDB entry MAC mac address VLAN vlan id was deleted because Unit Port unit port has aggregated](#)
- [CFG - Could not acquire FLASH sem](#)
- [CFGSO - Error: Failed to create watchdog timer](#)
- [CFGSO - Error: Failed to get an imc buffer](#)
- [CFGSO - Error: Failed to save data to NBU](#)
- [CFGSO - Error: Failed to start watchdog timer](#)
- [CFGSO - Error: File not read](#)
- [CFGSO - Error: File not write](#)
- [CFM: ERROR adding port filters for VLAN %d - no resources](#)
- [Change of active config block and or reset failed block-number](#)
- [Classifier block distribution across stack failed](#)
- [Classifier component distribution across stack failed](#)
- [Cli add vlan vlan id members port mask](#)
- [Cli create vlan vlan id type port](#)
- [Cli delete vlan vlan id members port mask](#)
- [Cli delete vlan vlan id type port](#)
- [CLI pswd: Stack authentication parameter is obsolete; unified changes have been applied to both stack and switch](#)
- [CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially \(stack IP addr not set\). Local user/pass used](#)
- [CLI pswd: Stack auth type RADIUS/TACACS+ won't apply partially \(switch IP addr not set\). Local user/pass used](#)
- [CLI pswd: Switch authentication parameter is obsolete; changes have not been applied](#)
- [Cli set autopvid disable](#)
- [Cli set autopvid enable](#)
- [Cli set management vlan vlan id](#)
- [Cli set ports port mask tagging disable](#)
- [Cli set ports port mask tagging enable](#)
- [Cli set pvid vlan id ports port mask](#)
- [Cli set vlan vlan id members port mask](#)
- [Cold Start Trap](#)
- [Configuration block %d is now in use](#)
- [Configuration saved to nv block # block number](#)
- [Conflicting egress interface and egress trunk data specified](#)
- [Connection closed \(failed login\) IP address](#)
- [Connection closed \(inactivity logout\) IP address](#)

- [Connection closed \(login timeout\) IP address](#)
- [Connection closed \(lost connection\) IP address](#)
- [Connection closed. Maximum number of sessions reached. IP address:](#)
- [Connection closed. Maximum number of sessions reached. IP address:](#)
- [Connection closed \(user logout\) IP address](#)
- [Cons activate vlan vlan id](#)
- [Cons add vlan vlan id port unit port](#)
- [Cons create vlan vlan id type port](#)
- [Cons delete vlan vlan id port unit port](#)
- [Cons delete vlan vlan id type port](#)
- [Cons set autopvid disable](#)
- [Cons set autopvid enable](#)
- [Cons set management vlan vlan id](#)
- [Cons set port unit port pvid vlan id](#)
- [Cons set port unit port tagging disable](#)
- [Cons set port unit port tagging enable](#)
- [COS mapping distribution across stack failed](#)
- [CoS shaping distribution across stack failed](#)
- [Count action distribution across stack failed](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with D

This page lists all the logs starting with the letter D that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [DAI: ARP packet with invalid IP/MAC binding dropped on untrusted port %d/%d. ARP packet has MAC source %02x-%02x-%02x-%02x-%02x-%02x.](#)
- [DAI ARP packet with invalid IP MAC binding dropped on untrusted port unit# port#](#)
- [DAPP-detected DoS attack blocked unit unit# \(many ports\)](#)
- [DAPP-detected DoS attack blocked unit unit# port port#](#)
- [DAPP support disable failure](#)
- [DAPP support enable failure](#)
- [Data distribution class class# across stack failed](#)
- [DAUR - Info Diag transfer finished](#)
- [DAUR - Info Receive request for diag image start transfer](#)
- [DAUR - Info Receive request for diag image. Unable to transfer](#)
- [DAUR - Info Send request for new diag image](#)
- [DAUR - Info Slave refuse transfer](#)
- [DAUR - Info Start receive image](#)
- [DAUR - The hardware is not compatible with the image version number version](#)
- [DAUR - Warning: Cannot get FLASH resource](#)
- [DHCP packet with mismatch MAC address dropped on un-trusted port unit# port# mac\(MAC ADDRESS\)](#)
- [DHCP Snoop DHCP ACK dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop DHCP binding table is full additional DHCP clients will not be added to the binding table](#)
- [DHCP Snoop: DHCP DISCOVER dropped on port %d/%d \(source MAC not matching client MAC\)](#)
- [DHCP Snoop DHCP NAK dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop DHCP OFFER dropped on untrusted port unit# port# \(not allowed on untrusted port\)](#)
- [DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table](#)
- [DHCP Snoop: DHCP packet dropped on port %d/%d - static entry with the same MAC %02x-%02x-%02x-%02x-%02x-%02x in binding table](#)
- [DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# because MAC Addr\(MACaddress \) is associated to port unit# port#](#)
- [DHCP Snoop DHCP RELEASE DECLINE dropped on untrusted port unit# port# \(MAC Addr\(MACaddress \) does not exist in binding table\)](#)
- [DHCP Snoop DHCP REQUEST dropped on un-trusted port unit# port# due to source MAC address\(MAC ADDRESS\) not matching DHCP client](#)
- [DHCP Snoop DHCP snooping binding table restored successfully from TFTP address](#)
- [DHCP Snoop DHCP snooping binding table restored successfully from USB unit unit#](#)
- [DHCP Snoop: DHCP snooping binding table restore from SFTP address](#)
- [DHCP Snoop DHCP snooping binding table restore from TFTP address A.B.C.D IPv6 address failed](#)
- [DHCP Snoop DHCP snooping binding table restore from USB unit unit# failed](#)
- [DHCP Snoop: DHCP snooping binding table saved successfully to SFTP address](#)
- [DHCP Snoop DHCP snooping binding table saved successfully to TFTP address](#)
- [DHCP Snoop DHCP snooping binding table saved successfully to USB unit unit#](#)
- [DHCP Snoop: DHCP snooping binding table save to SFTP address](#)
- [DHCP Snoop DHCP snooping binding table save to TFTP address A.B.C.D IPv6 address failed](#)
- [DHCP Snoop: DHCP snooping binding table save to TFTP address, failed](#)
- [DHCP Snoop DHCP snooping binding table save to USB unit unit# failed](#)
- [DHCP Snoop: DHCP snooping binding table succesfully restored from SFTP address](#)

- [DHCP Snoop DHCP snooping entry entry number not restored due to expired lease](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to MAC conflict](#)
- [DHCP Snoop DHCP snooping entry entry number not restored due to parsing failure](#)
- [DHCP Snoop DHCP snooping entry with MAC MacAddress not restored on invalid interface unit# port#](#)
- [DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored \(invalid Vlan %d\)](#)
- [DHCP Snoop: DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored on trusted interface %d/%d](#)
- [DHCP Snoop: DHCP snooping entry 0x%08x not restored on trusted interface %d/%d](#)
- [DHCP snooping entry with MAC %02x-%02x-%02x-%02x-%02x-%02x not restored \(invalid Vlan %d\)](#)
- [DHCP Snoop NTP is not synchronized: external save restore of DHCP snooping entries not possible](#)
- [Disallowed connection Access Reject for user](#)
- [Disallowed connection Access Reject for user](#)
- [Disallowed connection attempt from IP address](#)
- [Disallowed connection attempt - too many telnet sessions](#)
- [Disallowed connection Invalid SvcType for user](#)
- [Disallowed connection Invalid SvcType for user](#)
- [DISTRIBUTE_DB event sent unit mask value appl mask value](#)
- [DosFs - Error File not closed](#)
- [Down 1 cable inserted or neighbor powered on](#)
- [Down 2 cable inserted or neighbor powered on](#)
- [Downstream stack direction is down cable removed or neighbor powered off](#)
- [Downstream stack direction is mis-configured](#)
- [Downstream stack direction is up cable inserted or neighbor powered on](#)
- [DSCP mapping distribution across stack failed](#)
- [DSCP value modification prohibited](#)
- [Duplicate address deletion failed ipv6 address](#)
- [Duplicate address detection succeeded ipv6 address](#)
- [Duplicate entry detected \(prohibited\)](#)
- [Duplicate FCoE redirection entry detected](#)
- [Dynamic ARP could not be learned, maximum dynamic ARP limit is reached.](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with E

This page lists all the logs starting with the letter E that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [EAP Bad pkt id](#)
- [EAP Bad pkt len](#)
- [EAP: Cannot assign PVID %d, on port %d it is in another STP group](#)
- [EAP: Cannot auto-create VLAN %d, it is mapped to another STP group](#)
- [EAP CDT Error](#)
- [EAP Client blocked \(Block Subsequent MAC Authentication\): Different VID than expected](#)
- [EAP Client blocked \(Block Subsequent MAC Authentication\): Invalid VID](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All bindings have been rejected](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. All RAVs or Bindings from RADIUS are invalid](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Autocreate is enabled, but no RAV is present](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Cannot use FA bindings in Legacy or Autoprov networks](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. EAP FA context unknown network](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Only MHSA mode supports multiple RAVs](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Receiving unconfigured VLAN from Radius without Autocreate](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid bindings exceeded the maximum threshold of 16](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid not supported in MHMA and SHSA](#)
- [EAP Client blocked - MAC %02x:%02x:%02x:%02x:%02x:%02x. Vlan:Isid with Isid not equal to 0 not supported in Standalone Proxy or Autoprov](#)
- [EAP Could not process pkt](#)
- [EAP Error - Default](#)
- [EAP Error - Failed to free mac info memory](#)
- [EAP Error Radius - ifIndex not found](#)
- [EAP Error while sending Access Violation Trap](#)
- [EAP Error while sending RAV Error Trap](#)
- [EAP Failed qpa-RoleAssociation unitPort ifIndex macHi xx-xx macLo xx-xx-xx-xx](#)
- [EAP Failed qpa-RoleAssociation unitPort 0x%x mac %08x%04x](#)
- [EAP Failed to add host, max number of clients reached](#)
- [EAP Failed to add host, memory allocation error](#)
- [EAP GVlan Disabled for unitPort ifIndex - GVlan\(vid \) in different stg\(id \)](#)
- [EAP IMC Failed to send message](#)
- [EAP IMC Memory allocation error](#)
- [EAP Invalid RAV ID](#)
- [EAP Invalid Vlan ID vid configured for port num](#)
- [EAP Mac AuthFail - unitPort <unit-portnum> macHi <xx-xx> macLo <xx-xx-xx-xx>](#)
- [EAP Neap port was not member of any vlan](#)
- [EAP NULL pkt to send on Success](#)
- [EAP Reached Mac Intruder Count](#)
- [EAP: Reached Mac Intruder Count](#)
- [EAP: Receiving unsupported Auto-Create-VLAN VSA in SHSA or MHMA](#)
- [EAP Unable to Reserve EapAdmin Filter Resources rc retCode unitPort ifIndex](#)
- [EAP Unable to Reserve Filter Resources rc retCode unitPort ifIndex Force- Unauthorised](#)
- [EAP Unable to UnReserve EapAdmin Filter Resources rc retCode unitPort ifIndex](#)
- [EAP Unable to UnReserve Filter Resources rc retCode unitPort unit-portnum](#)
- [EAP Vlan Change Aborted](#)

- [ECMP features disabled due to inadequate license](#)
- [Egp Neighbor Loss Trap](#)
- [Egress interface or trunk data is required - data missing](#)
- [Element deletion prohibited \(permanent read-only system entry\)](#)
- [Element label not acceptable - reserved](#)
- [Element may only be modified not created or deleted](#)
- [Element modification prohibited \(read-only or system entry\)](#)
- [Enterprise Specific Trap](#)
- [Error configuring 802.1AB](#)
- [Error configuring LLDP MED policies](#)
- [Error configuring Management IP Address](#)
- [Error configuring port names](#)
- [Error creating Data VLAN](#)
- [Error creating MLT](#)
- [Error creating Voice VLAN](#)
- [Error deleting previously created cost 1 default route](#)
- [Error deleting previously created Voice and Data VLANs](#)
- [Error disabling global DHCP relay errCode](#)
- [Error enabling ADAC](#)
- [Error enabling ADAC on ports](#)
- [Error enabling global DHCP relay errCode](#)
- [Error enabling IP Routing](#)
- [Error enabling mstp learning on all ports](#)
- [Error enabling rstp learning on all ports](#)
- [Error executing script](#)
- [Error getting VLAN info for Port's pvid](#)
- [Error loading backup configuration block # block_number](#)
- [Error loading configuration block %d](#)
- [Error loading primary configuration block # block_number](#)
- [Error reading nvq_ObjDescr from VLAN file](#)
- [Error reading prec from VLAN file](#)
- [Error reading vmrec from VLAN file](#)
- [Error reading vrec from VLAN file](#)
- [Error restoring from VLAN file](#)
- [Error restoring from VLAN file. Wrong nvq.Descr.devVer](#)
- [Error restoring from VLAN file. Wrong nvq.Descr.notBlank](#)
- [Error restoring management vlan to 1 or disabling ip routing](#)
- [Error restoring nvq.Descr from VLAN file](#)
- [Error restoring object from VLAN file - bad file pointer or mode](#)
- [Error restoring object from VLAN NVRAM file](#)
- [Error restoring Port from VLAN NVRAM file](#)
- [Error restoring Ports from VLAN file](#)
- [Error restoring VLANs from VLAN file](#)
- [Error restoring VMACs from VLAN file](#)
- [Error saving configuration](#)
- [Error saving configuration to block # block_number](#)
- [Error seeking object in VLAN file](#)
- [Error seeking Ports in VLAN file](#)
- [Error seeking VLANs in VLAN file](#)
- [Error seeking VMACs in VLAN file](#)
- [Error setting ADAC operating mode](#)
- [Error setting call server ports](#)
- [Error setting Data VLAN Gateway IP address and network mask](#)
- [Error setting default IP Route](#)
- [Error setting IP Office Call-Server IP address](#)
- [Error setting IP Office File-Server IP address](#)
- [Error setting Management VLAN](#)
- [Error setting poe-priority high on ports](#)
- [Error setting QoS](#)
- [Error setting spanning-tree learning to fast on all ports](#)
- [Error setting uplink ports](#)
- [Error setting VLAN attributes](#)
- [Error setting VLAN Gateway IP address and network mask](#)
- [Error setting Voice VLAN Gateway IP address and network mask](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000

NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with F

This page lists all the logs starting with the letter F that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Fabric Attach: binding accepted \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation success \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding activation success \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding deactivation success \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: binding deactivation success \(trunk %d %d/%d\)](#)
- [Fabric Attach: binding expiration \(ifc <IFINDEX> <ISID>/<VID>\)](#)
- [Fabric Attach: client binding deleted \(<IFINDEX>/<ISID>/<VID>\)](#)
- [Fabric Attach: device deleted \(port <PORT>\)](#)
- [Fabric Attach: device deleted \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Pass - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Authentication Pass - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device discovered \(Not Authenticated - port <PORT>\)](#)
- [Fabric Attach: device discovered \(Not Authenticated - port <UNIT>/<PORT>\)](#)
- [Fabric Attach: device expired \(port <PORT>\)](#)
- [Fabric Attach: device expired \(port <UNIT>/<PORT>\)](#)
- [Fabric Attach: element type updated](#)
- [Fabric Attach: management VLAN updated \(was <VID>, now <VID>\) by Zero Touch](#)
- [Fabric Attach: multiple FA Servers detected](#)
- [Fabric Attach: port authentication update - data flushed \(MLT %d\)](#)
- [Fabric Attach: port authentication update - data flushed \(port %d\)](#)
- [Fabric Attach: port authentication update - data flushed \(port %d/%d\)](#)
- [Fabric Attach: primary FA Server lost](#)
- [Fabric Attach: primary FA server selected \(port %d\)](#)
- [Fabric Attach: primary FA server selected \(port %d/%d\)](#)
- [Fabric Attach: primary FA server selected \(trunk %d\)](#)
- [Fabric Attach: proxy not supported by element type](#)
- [Fabric Attach: server connection type change](#)
- [Fabric Attach: server connection type change \(different ports\)](#)
- [Fabric Attach: server connection type change \(different trunks\)](#)
- [Fabric Attach: server connection type change \(non-trunk to trunk\)](#)
- [Fabric Attach: server connection type change \(trunk to non-trunk\)](#)
- [Fabric Attach: service disabled](#)
- [Fabric Attach: service enabled](#)
- [Fabric Attach: specified element type not supported](#)
- [Fabric Attach: standalone/non-standalone proxy transition \(service reset\)](#)
- [Fabric Attach: trunk link automatically enabled \(MLT %d port %d/%d\)](#)
- [Fabric Attach: Zero Touch capabilities disabled](#)
- [Fabric Attach: Zero Touch capabilities enabled](#)
- [Failed ARP add ip addr 0xFFFFFFFF to HW hw error code](#)
- [Failed login from IP address](#)
- [Failed login from serial connection](#)
- [Failed login \(local auth\) from IP address:](#)
- [Failed login \(local auth\) from serial connection](#)
- [Failed login\(radius auth\) from IP add](#)
- [Failed MVLAN\(vid \) L3 ip addr ip mask](#)

- [Failed to create IP intf vid ip addr in HW hw error code](#)
- [FCoE controller ifIndex not set - FCoE redirection enable prohibited](#)
- [FCoE controller VLAN not set - FCoE redirection enable prohibited](#)
- [Filter limiting mode not supported on 5510-XX unit cannot join stack](#)
- [Flash Erase Failed Sector %d Address 0x%x](#)
- [Flash Erase Warning Sector %d Address 0x%x Erase time %d ms](#)
- [FSH - File not closed .:](#)
- [FSH - Some files are not closed. MsgType #%d](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with G

This page lists all the logs starting with the letter G that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Gateway IP changed](#)
- [Got UserPolicy from Radius but UBP disabled - unitPort 0x%x mac %08x%04x](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with H

This page lists all the logs starting with the letter H that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Hello Module unable to communicate with neighbor\(s\) unit reset](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with I

This page lists all the logs starting with the letter I that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [IGMP Added reserved multicast address](#)
- [IGMP Exceeded reserved multicast address range #Addr numResAddrEntries+1 * #VLANs numActiveVLANs maxReservedRange](#)
- [IGMP: Max hardware Resources reached](#)
- [IGMP No hardware resource available](#)
- [IGMP Proxy disabled on VLAN vlan#](#)
- [IGMP Proxy enabled on VLAN vlan#](#)
- [IGMP Query Time set to num on VLAN vlan#](#)
- [IGMP Removed reserved multicast address](#)
- [IGMP Robust Value set to num on VLAN vlan#](#)
- [IGMP Snooping disabled on VLAN vlan#](#)
- [IGMP Snooping enabled on VLAN vlan#](#)
- [IGMP SSM Range changed](#)
- [IGMP SSM Range changed](#)
- [IGMP Unable to add reserved multicast address](#)
- [IGMP Unknown Multicast Filter disabled](#)
- [IGMP Unknown Multicast Filter enabled](#)
- [IGMP: Unknown Query received on SPBM Multicast C-VLAN](#)
- [IGMP: V2 report drop on reserved GA](#)
- [IGMP: V3 report group skip on invalid GA](#)
- [IGMP: V3 report group skip on reserved GA](#)
- [IGMP V1 router ports mask](#)
- [IGMP V2 router ports mask](#)
- [IMC buffers of size size have been exhausted buffer pool size size](#)
- [Index value out-of-range](#)
- [Info: Transceiver inserted on %s](#)
- [Info: Transceiver removed from %s](#)
- [Interface action distribution across stack failed](#)
- [Interface application distribution across stack failed](#)
- [Interface assignment distribution across stack failed](#)
- [Invalid Configuration Block Number %d](#)
- [Invalid Configuration Magic Number](#)
- [Invalid Configuration Version Number](#)
- [Invalid drop action option specifiedInvalid drop action option specified](#)
- [Invalid entry creation attempted \(index index# \)](#)
- [Invalid FCoE controller ingress interface specified](#)
- [Invalid FCoE controller VLAN specified](#)
- [Invalid RAV id %d, on port %d, cannot be Switched UNI or B-VLAN](#)
- [Invalid RAV id %d, on port %d, it isn't a CVLAN](#)
- [Invalid/unknown FCoE redirection egress trunk ID specified](#)
- [Invalid update DSCP value specified \(DSCP value \)](#)
- [IP blocking now 1 2 \(1=ON 2=OFF\)](#)
- [IP classifier distribution across stack failed](#)
- [IPFIX enable failure](#)
- [IpFwdNhop Err Filter Install mod_inst=0x%08x vid=%d rv=%d](#)

- [IpFwdNhop Err Filter Modify mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Filter UnInstall mod_inst=0x%08x vid=%d rv=%d](#)
- [IpFwdNhop Err Save DB to NVRAM General File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop Err Save DB to NVRAM Instance File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop Err Save DB to NVRAM Policy File myMod=%d isBU=%d rw=%d](#)
- [IpFwdNhop: Feature enable temporarily blocked - resources unavailable](#)
- [IpFwdNhop: Filter installation issue - resources unavailable](#)
- [IpFwdNhop: Issue detected during data restore \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during enable retry \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during feature enable \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during interface creation \(interface entry %d\)](#)
- [IpFwdNhop: Issue detected during VLAN %d routing status update](#)
- [IpFwdNhop: Issue detected during VLAN membership addition \(VID %d\)](#)
- [IpFwdNhop: Issue detected during VLAN membership deletion \(VID %d\)](#)
- [IpFwdNhop: Issue detected during VLAN policy association \(entry %d\)](#)
- [IpFwdNhop: Requested precedence and/or filter resources unavailable](#)
- [IpFwdNhop: Requested range checking resources unavailable](#)
- [IpFwdNhop: VLAN membership update \(VID %d\) issue - resources unavailable](#)
- [IP protocol value TCP or UDP needed with Layer 4 port filtering](#)
- [IPSG Insufficient resources available to enable IPSG on port unit# port#](#)
- [IPSG Maximum IP entries on port unit# port# has been reached](#)
- [IPSG nvRam file error param1 param2 param3](#)
- [IPSG Reached Max. IP entries supported on this port port#](#)
- [IPSG Reached Max. IP entries supported on this port unit# port#](#)
- [IPSG Resource allocated for Ports unit# port#](#)
- [IP Source Guard disabled on Unit unit# Port port#](#)
- [IP Source Guard enabled on Unit unit# Port port#](#)
- [IPT BootP Disabled \(response not received from server\)](#)
- [IPT IP Address changed by BOOTP Server](#)
- [IPT: IP Address not in use \(duplicate detected\)](#)
- [IPv6 enabled with hardware support and FMGR filters](#)
- [IPv6 enabled with hardware support only](#)
- [IPv6 Forwarding disabled due to inadequate license](#)
- [IPv6 malloc failure](#)
- [Issue detected during QoS stack synchronization](#)
- [Issue detected enabling/disabling DSCP table usage \(port#\)](#)
- [Issue detected setting native DSCP table values](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with J

This page lists all the logs starting with the letter J that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [JOIN event sent unit mask value appl mask value](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with L

This page lists all the logs starting with the letter L that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [LAC MLT error on far end. 0 - 0 - 0](#)
- [LAC: MLT error, partner aggregation bit not set](#)
- [LAC: MLT error, partner expired bit set.](#)
- [LAC: MLT error, partner synchronization bit not set.](#)
- [LAC No more trunk group available for LAC. 0 - 0 - 0](#)
- [LAC with admin key %d failed configuration verification. Bad ARP INSPECTION configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad DHCP-SNOOPING configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad IGMP configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad MAC Security configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad qos status.](#)
- [LAC with admin key %d failed configuration verification. Bad rate-limiting configuration.](#)
- [LAC with admin key %d failed configuration verification. Bad VLAN configuration.](#)
- [LAC with admin key %d failed configuration verification. Error #: %d-%d](#)
- [LAC with admin key %d failed configuration verification. Ports have different qos config.](#)
- [LAC with admin key %d failed configuration verification. Ports have different SPBM configurations.](#)
- [Last MLT trunk was allocated by LAC. No more free trunk groups.](#)
- [Last MLT trunk was allocated by MLT. No more free trunk groups.](#)
- [Layer 2 filter distribution across stack failed](#)
- [LEAVE event sent unit mask value appl mask value](#)
- [Link Down Trap](#)
- [LinkStateTracking: First interface %d/d went up in link state group %d, enabling downstream ports](#)
- [LinkStateTracking: First interface mlt %d went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: First interface %s went up in link state group %d, enabling downstream interfaces](#)
- [LinkStateTracking: Interface %d/d went down in link state group %d](#)
- [LinkStateTracking: Interface %d/d went up in link state group %d](#)
- [LinkStateTracking: Interface mlt %d went down in link state group %d](#)
- [LinkStateTracking: Interface mlt %d went up in link state group %d](#)
- [LinkStateTracking: Interface %s went down in link state group %d](#)
- [LinkStateTracking: Interface %s went up in link state group %d](#)
- [LinkStateTracking: Last interface %d/d went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface mlt %d went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces](#)
- [LinkStateTracking: Last interface %s went down in link state group %d, disabling downstream interfaces](#)
- [Link Up Trap](#)
- [Loading configuration block # block_number](#)
- [Local authentication disabled on serial](#)
- [Local authentication disabled on telnet](#)
- [Local authentication enabled on serial](#)
- [Local authentication enabled on telnet](#)
- [Login timeout serial connection](#)
- [Lossless and Lossless-PFC modes are only supported in queue set 2](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with M

This page lists all the logs starting with the letter M that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [MAC security table full](#)
- [MAC %02x:%02x:%02x:%02x:%02x:%02x not authenticated: only one client is allowed in MHSA mode](#)
- [Management IP: OOB port%s](#)
- [Management IP: OOB port%s](#)
- [Maximum number of dynamic routes reached](#)
- [Meter distribution across stack failed](#)
- [MLD: Maximum number of mld enabled interfaces reached](#)
- [MLD: The maximum number of available hardware MLD entries has been reached](#)
- [MLD: The maximum number of available hardware MLD entries has been reached](#)
- [MLT %d failed configuration verification. Bad ARP_INSPECTION configuration.](#)
- [MLT %d failed configuration verification. Bad DHCP-SNOOPING configuration.](#)
- [MLT %d failed configuration verification. Bad IGMP configuration.](#)
- [MLT %d failed configuration verification. Bad IPSG CLASS configuration.](#)
- [MLT %d failed configuration verification. Bad MAC learning configuration.](#)
- [MLT %d failed configuration verification. Bad rate-limiting configuration.](#)
- [MLT %d failed configuration verification. Bad SPBM configuration.](#)
- [MLT %d failed configuration verification. Bad VLACP configuration.](#)
- [MLT %d failed configuration verification. Bad VLAN configuration.](#)
- [MLT ID# failed configuration verification. Error # error num](#)
- [MLT NV File error](#)
- [MODULE_INACTIVE event sent unit mask value appl mask value](#)
- [More than value units discovered](#)
- [Multiple base units detected](#)
- [Multiple Waverunner units detected when base is a Flagship](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with N

This page lists all the logs starting with the letter N that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Network access settings for FCoE Redirect must be modified locally](#)
- [Non-EAP Client blocked \(Block Subsequent MAC Authentication\): Different VID than expected](#)
- [Non-EAP Client blocked \(Block Subsequent MAC Authentication\): EAP Use Rav Not enabled](#)
- [Non-unique element label detected \(prohibited\)](#)
- [No Response from RADIUS Server](#)
- [Notice: DAC Cable on %s is below HW rev "H" and may cause link issues with a small number of PHYs](#)
- [Number of VLANs does not match BU number of VLANs. VLAN config defaulted](#)
- [Number of VLANs does not match BU number of VLANs. VLAN config defaulted](#)
- [NUOC - Disabled](#)
- [NUOC - Enabled](#)
- [NUOC - Execution of the cli template failed](#)
- [NUOC - Execution of the cli template succeeded](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with O

This page lists all the logs starting with the letter O that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Ospf Area Mismatch RxArea ra.rb.rc.rd IntfArea ia.ib.ic.id](#)
- [Ospf Auth Failed IpAddr ia.ib.ic.id](#)
- [Ospf Auth Type Mismatch in Hello](#)
- [Ospf Auto Virt Link Failed area a1.a2.a3.a4 rtid r1.r2.r3.r4](#)
- [Ospf Bad Version](#)
- [OSPF Callback function of timer is NULL](#)
- [Ospf Cost Exceeds Limit Skip route Lsid l1.l2.l3.l4 Adv-rtr a1.a2.a3.a4](#)
- [OspfDbg Done Filter Init](#)
- [OspfDbg Done Global Init](#)
- [OspfDbg Done NV-Restore](#)
- [OspfDbg Done ReDist Init](#)
- [OspfDbg Init Instance vrfId=%d nodeP=0x%0x](#)
- [OspfDbg PostInit Done vrfId=%d nodeP=0x%0x](#)
- [OspfDbg PostInit EnableOspf vrfId=%d nodeP=0x%0x](#)
- [OspfDbg Started ospfTxHelloTimerTask](#)
- [Ospf Dead Int Mismatch in Hello](#)
- [Ospf Enable Failed as Resource Unavailable](#)
- [Ospf Hello Int Mismatch in Hello](#)
- [Ospf Hello: RId Same as Neighbor: rtid <r1.r2.r3.r4>, IpAddr <i1.i2.i3.i4>](#)
- [Ospf HW Mode Change:](#)
- [Ospf Invalid packet received: Pkt type <ospfPacketType>](#)
- [Ospf License Is Missing. Disable OSPF](#)
- [Ospf Nbr State Change: rtid <ra.rb.rc.rd> ipa <ia.ib.ic.id> state <neighborState>](#)
- [Ospf Netmask Mismatch in Hello IpAddr ia.ib.ic.id](#)
- [Ospf Option Mismatch in Hello IpAddr ia.ib.ic.id RxOption optionVal IntfOption optionVal](#)
- [OSPF Timer Link Error](#)
- [OSPF Timer List is corrupted](#)
- [OSPF Timer Unlink Error](#)
- [Ospf Virt Nbr State Change: rtid <r1.r2.r3.r4>, virtAreaId <v1.v2.v3.v4>, state <neighborState>](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with P

This page lists all the logs starting with the letter P that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Pim E-BSR change](#)
- [Pim Invalid packet received](#)
- [Pim License Is Missing Disable PIM](#)
- [Pim Mode Change](#)
- [Pim Nbr State Change Up](#)
- [PIM Neighbor status change Down](#)
- [PIM Neighbor status change Up](#)
- [Pim RP type state](#)
- [Pim Unicast route change](#)
- [Pim Virt Nbr State Change Down](#)
- [Pim Virt Nbr State Change Up](#)
- [PM in port mirroring the old data were modified - feature Allow Traffic in mirror port was added.](#)
- [PM in port mirroring the old data were modified - feature Many to Many was added.](#)
- [PM in port mirroring the old data were modified - feature Many to One was added.](#)
- [PM in port mirroring the old data were modified - feature Many to One with 128bits was added.](#)
- [PM: in port mirroring the old data were modified - feature RSPAN was added](#)
- [PM in port mirroring the old data were modified - mode type was out of range.](#)
- [PM in port mirroring the old data were modified - monitored portA was out of range.](#)
- [PM in port mirroring the old data were modified - monitored portB was out of range.](#)
- [PM in port mirroring the old data were modified - NVRAM file structure was changed.](#)
- [PM in port mirroring the old data were modified - probe port was out of range.](#)
- [PM: instance %d has been deleted because of insufficient HW resource](#)
- [PM some port mirroring messages were stored to be displayd with delay.](#)
- [PM unable to create mirror for instance instance number due to lack of available filter resources](#)
- [PoE Main Power Usage Off](#)
- [PoE Main Power Usage On](#)
- [PoE Module Reset](#)
- [PoE Port Detection Status port# Status powerStatus](#)
- [PoE The PoE power limit for port unit port has been changed to x Watts based on IP phone discovery settings](#)
- [PoE The PoE power limit for port unit port has been restored to previous value x Watts](#)
- [PoE The PoE priority for port unit port has been changed to x based on IP phone discovery settings](#)
- [PoE The PoE priority for port unit port has been restored to previous value x](#)
- [Policy distribution across stack failed](#)
- [Port %d blocked by VLACP due to end-partner down state](#)
- [Port %d blocked by VLACP until end-partner connection reestablished](#)
- [Port %d/%d blocked by VLACP due to end-partner down state](#)
- [Port %d reenabled by VLACP](#)
- [Port unit# port# blocked by VLACP until end-partner connection reestablished](#)
- [Port unit# port# reenabled by VLACP](#)
- [Primary Configuration files are corrupted. Restored to default](#)
- [Primary Configuration Version is updated](#)
- [802.1p user priority value modification prohibited](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with Q

This page lists all the logs starting with the letter Q that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [QoS inter-module communication issue detected](#)
- [Queue data distribution across stack failed](#)
- [Queue shaping distribution across stack failed](#)
- [QuickInstall console configuration error.](#)
- [QuickInstall:console configuration success.](#)
- [QuickInstall: Error! Unable to locate agent software file](#)
- [QuickInstall: Error! Unable to locate ASCII configuration file](#)
- [QuickInstall: Error! Unable to locate diagnostics software file.](#)
- [QuickInstall: Processing of USB config file has commenced.](#)
- [QuickInstall: Processing of USB config file is complete](#)
- [QuickInstall USB config file not found.](#)
- [QuickInstall USB file config error at line line#](#)
- [QuickInstall USB file config error - file exceed 4096 bytes](#)
- [QuickInstall USB file config error - file exceed 200 lines.](#)
- [QuickInstall:USB file config success.](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with R

This page lists all the logs starting with the letter R that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [RADIUS authentication on stack serial disabled](#)
- [RADIUS authentication on stack serial enabled](#)
- [RADIUS authentication on stack telnet disabled](#)
- [RADIUS authentication on stack telnet enabled](#)
- [RADIUS authentication on switch serial disabled](#)
- [RADIUS authentication on switch serial enabled](#)
- [RADIUS authentication on switch telnet disabled](#)
- [RADIUS authentication on switch telnet enabled](#)
- [RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't create RADIUS Acct semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't create RADIUS semaphore, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS AcctClient\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS client\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start radius_recv\(\) task, errno %d](#)
- [RADIUS: ERROR - Couldn't start RADIUS ServerCheck\(\) task, errno %d](#)
- [RADIUS MS-CHAPv2: Failed to change password](#)
- [RADIUS MS-CHAPv2: No response from RADIUS server](#)
- [RADIUS MS-CHAPv2: Password changed succesfully](#)
- [RADIUS MS-CHAPv2: RADIUS server not properly configured](#)
- [RADIUS MS-CHAPv2: Server does not speak RADIUS](#)
- [RADIUS MS-CHAPv2: Unable to change password at RADIUS server](#)
- [Radius: Server with index %d is down](#)
- [Radius: Server with index %d is up](#)
- [Radius use-mgmt-ip must be disabled first](#)
- [REMOVE_DATA event sent unit mask value appl mask value](#)
- [Replaced "Wrong QoS Agent buffer setting, expected %u, actual %u, unit cannot join stack" with "Wrong QoS Agent buffer setting, expected %s, actual %s, unit cannot join stack"](#)
- [Restore Backup Configuration to Manufacture Default](#)
- [Restore Primary Configuration to Manufacture Default](#)
- [Role combination distribution across stack failed](#)
- [Role combination length outside of acceptable limits](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with S

This page lists all the logs starting with the letter S that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [%s card inserted \(in unit %s\)](#)
- [%s card removed \(from unit %s\)](#)
- [Script was successfully executed](#)
- [Session closed \(inactivity logout\) IP address](#)
- [Session closed \(inactivity logout\) IP address](#)
- [Session closed \(lost connection\) IP address](#)
- [Session closed \(user logout\) IP address](#)
- [Session closed \(user logout\) serial connection](#)
- [Session opened from IP address](#)
- [Session opened from serial connection](#)
- [Session opened \(local auth\) from IP address:](#)
- [Session opened \(local auth\) from serial connection](#)
- [Session opened\(radius auth\) from IP add](#)
- [Session opened\(radius auth\) from serial conn](#)
- [Set port to default](#)
- [SFP internal supply voltage is at high alarm level on s](#)
- [SFP internal supply voltage is at high warning level on %s](#)
- [SFP internal supply voltage is at low alarm level on %s](#)
- [SFP internal supply voltage is at low warning level on %s](#)
- [SFP internal supply voltage is no longer at the high alarm level](#)
- [SFP internal supply voltage is no longer at the high warning level](#)
- [SFP internal supply voltage is no longer at the low alarm level](#)
- [SFP internal supply voltage is no longer at the low warning level](#)
- [SFP internal temperature is at high alarm level on %s](#)
- [SFP internal temperature is at high warning level on %s](#)
- [SFP internal temperature is at low alarm level on %s](#)
- [SFP internal temperature is at low warning level on %s](#)
- [SFP internal temperature is no longer at the high alarm level](#)
- [SFP internal temperature is no longer at the high warning level](#)
- [SFP internal temperature is no longer at the low alarm level](#)
- [SFP internal temperature is no longer at the low warning level](#)
- [SFP Received power is at high alarm level on %s](#)
- [SFP Received power is at high warning level on %s](#)
- [SFP Received power is at low alarm level on %s](#)
- [SFP Received power is at low warning level on %s](#)
- [SFP Received power is no longer at the high alarm level](#)
- [SFP Received power is no longer at the high warning level](#)
- [SFP Received power is no longer at the low alarm level](#)
- [SFP Received power is no longer at the low warning level](#)
- [SFP TX Bias current is at high alarm level on %s](#)
- [SFP TX Bias current is at high warning level on %s](#)
- [SFP TX Bias current is at low alarm level on %s](#)
- [SFP TX Bias current is at low warning level on %s](#)
- [SFP TX Bias is no longer at the high alarm level](#)
- [SFP TX Bias is no longer at the high warning level](#)

- [SFP TX Bias is no longer at the low alarm level](#)
- [SFP TX Bias is no longer at the low warning level](#)
- [SFP TX output power is at high alarm level on %s](#)
- [SFP TX output power is at high warning level on %s](#)
- [SFP TX output power is at low alarm level on %s](#)
- [SFP TX output power is at low warning level on %s](#)
- [SFP TX output power is no longer at the high alarm level](#)
- [SFP TX output power is no longer at the high warning level](#)
- [SFP TX output power is no longer at the low alarm level](#)
- [SFP TX output power is no longer at the low warning level](#)
- [Simultaneous operations involving access asgn ifcs prohibited](#)
- [Simultaneous operations involving policies and blocks prohibited](#)
- [Simultaneous operations involving policies and ifcs prohibited](#)
- [Simultaneous operations involving policy blocks ifcs prohibited](#)
- [SLAMon Agent: agent IP address reset to default value](#)
- [SLAMon Agent CLI support not available](#)
- [SLAMon Agent CLI timeout value out of range](#)
- [SLAMon Agent disabled](#)
- [SLAMon Agent enabled](#)
- [SLAMon Agent: inconsistent IP address data specified](#)
- [SLAMon Agent inconsistent UDP port data specified](#)
- [SLAMon Agent info: %d %d %d](#)
- [SLAMon Agent invalid agent-to-agent port \(must be even value\)](#)
- [SLAMon Agent operation is restricted CLI-only](#)
- [SLPP-guard: hold-down timer has expired on port with SLPP-guard enabled. Port %s has been re-enabled](#)
- [SLPP-guard: SLPP-guard has not been enabled on port %s as no filters or filter precedences are available to setup an Ethertype filter](#)
- [SLPP-guard: SLPP packet received on port with SLPP-guard enabled. Port %s has been disabled](#)
- [SLPP Warning - PDU was received on Vlan VlanId Unit UnitNo Port PortNo _](#)
- [SMLT IMC invalid cmd 1- StkCmd](#)
- [SMLT IMC tx error](#)
- [SMLT input parameter error mlt port vlan](#)
- [SMLT Stack db ex event num -0 -0*22221111](#)
- [SMLT stackEventNotify Invalid Msg Cmd - 0 - 0](#)
- [SMLT Stack inactive event 0-0- modMask](#)
- [SMLT Stack joined event num - 0 - 0*33331111](#)
- [SMLT Stack leaved event 0 - 0 - modMask](#)
- [SMLT STP enabled on IST trunk trkNo stp group grp](#)
- [SMLT Warning - LAC SMLT with more than 8 links - key - count](#)
- [SMLT Warning - smltEnable Software License Error- 0 - 0](#)
- [SMLT Warning - SMLT mismatched Lac Sys ID error shutdown all SMLT lac po](#)
- [SNMP-access is disabled](#)
- [SNMP-access is enabled](#)
- [SNTP: First synchronization successful.](#)
- [SPBM adjacency with neighbor](#)
- [SPB-MC Dynamic i-sid range conflicts with existing i-sid](#)
- [SPBM detect adj](#)
- [SPBM: ERROR adding Transparent UNI for i-sid %d, port %d - no resources](#)
- [SPBM ISIS](#)
- [SPBM ISIS detect duplicate nick-name](#)
- [SPBM ISIS node](#)
- [SSHC: ASCII CFG download SFTP failure](#)
- [SSHC ASCII CFG download SFTP failure](#)
- [SSHC: ASCII CFG upload SFTP failure](#)
- [SSHC ASCII CFG upload SFTP failure](#)
- [SSHC: CFG download SFTP failure](#)
- [SSHC CFG download SFTP failure](#)
- [SSHC: CFG upload SFTP failure](#)
- [SSHC CFG upload SFTP failure](#)
- [SSHC DSA Authentication failure](#)
- [SSHC DSA key generation failure](#)
- [SSHC DSA key save failure](#)
- [SSHC DSA key upload TFTP failure](#)
- [SSHC DSA key upload USB failure](#)
- [SSH CLIENT Key couldnt be saved for host ip address](#)

- [SSH CLIENT SSH Connection to IP ip address was closed because parent console session console session ID was closed](#)
- [SSH CLIENT SSH Connection to %s was disconnected](#)
- [SSH CLIENT: SSH Connection to %s was disconnected by host. Connection time: %s](#)
- [SSH CLIENT: SSH Connection to %s was disconnected by user. Connection time: %s.](#)
- [SSH CLIENT Successful SSH Connection to %s using %s authentication](#)
- [SSHC Password Authentication failure](#)
- [SSHC: Password Authentication failure](#)
- [SSHC RSA Authentication failure](#)
- [SSHC: RSA Authentication failure](#)
- [SSHC RSA key generation failure](#)
- [SSHC RSA key save failure](#)
- [SSHC RSA key upload TFTP failure](#)
- [SSHC RSA key upload TFTP failure](#)
- [SSHC RSA key upload USB failure](#)
- [SSHC RSA key upload USB failure](#)
- [SSHC server connection failure](#)
- [SSH disabled](#)
- [SSH DSA key deleted](#)
- [SSH DSA KEY generation completed](#)
- [SSH enabled in non-secure mode](#)
- [SSH enabled in secure mode](#)
- [SSH Maximum number of ssh sessions has been reached](#)
- [SSH RSA KEY generation completed](#)
- [SSH RSA key overwritten](#)
- [SSH session closed by ip address remote host. Connection time h hours m minutes](#)
- [SSH session login using port](#)
- [SSH System is generating DSA KEY wait ...](#)
- [SSH TFTP DSA key download complete](#)
- [SSH TFTP RSA key download complete](#)
- [SSH USB DSA key download complete](#)
- [SSH USB RSA key download complete](#)
- [SSL certificate creation completed](#)
- [SSL certificate creation failed](#)
- [SSL certificate deleted](#)
- [SSL disabled](#)
- [SSL enabled](#)
- [SSL server reset](#)
- [Stack cable "Down 1" is misconfigured](#)
- [Stack cable "Down 2" is misconfigured](#)
- [Stack cable "Up 1" is misconfigured](#)
- [Stack cable "Up 2" is misconfigured](#)
- [Stack IP changed](#)
- [Stack must have a configured base unit!](#)
- [Stack operation mode modified to Pure and unit reset](#)
- [Stack synchronization failed stack formation delayed](#)
- [Successful connection from IP address](#)
- [Successfully loaded configuration files from block %d](#)
- [Successfully loaded configuration files from block %d](#)
- [Successful SSH connection to ip address](#)
- [Switch IP changed](#)
- [System filter distribution across stack failed](#)
- [System: Rear-Port Mode has been set to disable \(reboot required to take effect\)](#)
- [System: Rear-Port Mode has been set to enable \(reboot required to take effect\).](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with T

This page lists all the logs starting with the letter T that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [TACACS+ accounting disabled](#)
- [TACACS+ accounting enabled](#)
- [TACACS+ authenticated serial connection closed](#)
- [TACACS+ authenticated telnet session closed](#)
- [TACACS+ authenticated telnet session max retries exceeded](#)
- [TACACS+ authentication on switch serial port disabled](#)
- [TACACS+ authentication on switch serial port enabled](#)
- [TACACS+ authentication on switch telnet disabled](#)
- [TACACS+ authentication on switch telnet disabled](#)
- [TACACS+ authentication on switch telnet enabled](#)
- [TACACS+ authentication on switch telnet enabled](#)
- [TACACS+ authorization disabled](#)
- [TACACS+ authorization enabled](#)
- [TACACS+ successful authentication](#)
- [TACACS+ unsuccessful authentication](#)
- [TACACS authenticated SSH session closed](#)
- [TACACS authentication on stack serial disabled](#)
- [TACACS authentication on stack serial enabled](#)
- [TACACS authentication on stack telnet disabled](#)
- [TACACS authentication on stack telnet enabled](#)
- [Task task_name is suspended](#)
- [Task whose index is Index1 Index2 is suspended](#)
- [Telnet-access is disabled](#)
- [Telnet-access is disabled](#)
- [Telnet-access is enabled](#)
- [Telnet-access is enabled](#)
- [The BU switch is enabled. Cannot join existing stack](#)
- [The IP phone PoE limit has been changed to x Watts due to the stack modules configuration](#)
- [The number of stack units is number instead of expected number](#)
- [The password for user <%s> has expired.](#)
- [The password for user <%s> was changed](#)
- [The user <%s> was locked](#)
- [The user <%s> was unlocked](#)
- [This unit has wrong F W version expected version actual version](#)
- [This unit has wrong S W version expected version actual version](#)
- [Toggle the Agent Primary Image](#)
- [Token bucket data distribution across stack failed](#)
- [Traffic Prof filter set delete operation failed](#)
- [Traffic Prof filter set install operation failed](#)
- [Traffic Prof filter set update operation failed](#)
- [Trap bsAdacPortConfigNotification](#)
- [Trap bsAdacPortOperDisabledNotification](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPRestoreFailure](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPRestoreSuccess](#)
- [Trap: bsDhcpSnoopingExtSaveSFTPSyncFailure](#)

- [Trap: bsDhcpSnoopingExtSaveSFTPSyncSuccess](#)
- [Trap: bsLstGroupOperStateChanged](#)
- [Trap: bsLstInterfaceStatusChanged](#)
- [Trap: bsnAaaAlreadyConnected](#)
- [Trap: bsnAaaIncorrectLogOnThresholdExceeded](#)
- [Trap: bsnAaaMaxNoOfSessionsExceeded](#)
- [Trap: bsnAaaUserAccountNotUsed](#)
- [Trap: bsnAaaUserPasswordExpired](#)
- [Trap: bsnConfigurationSavedToNvram](#)
- [Trap: bsnEapAccessViolation](#)
- [Trap: bsnEapUbpFailure](#)
- [Trap: bsnLacPortDisabledDueToLossOfVLACPDU](#)
- [Trap: bsnLacPortEnabledDueToReceiptOfVLACPDU](#)
- [Trap: bsnROPasswordExpired: Read-only password expired](#)
- [Trap: bsnRWPasswordExpired: Read-write password expired](#)
- [Trap: bsnSFPIinsertion on port](#)
- [Trap: bsnSFPRemoval on port](#)
- [Trap: bsnStackConfigurationError](#)
- [Trap: bsnStackManagerReconfiguration](#)
- [Trap: bsnSystemUp365Days sent from unit %d](#)
- [Trap: bsnTrialLicenseExpiration Trial license license# has expired. Disable licensed features to avoid network interruption](#)
- [Trap: bsnTrialLicenseExpiration Trial license license# will expire in # days day\(s\)](#)
- [Trap: bsnUSBInsertion on unit](#)
- [Trap: bsnUSBRemoval on unit](#)
- [Trap: bspePethPsePortCurrentStatusNotification](#)
- [Trap: bsUnicastStormControlAboveHighWatermark](#)
- [Trap: bsUnicastStormControlBelowLowWatermark](#)
- [Trap: bsveVrrpTrapStateTransition](#)
- [Trap: DAPP - DoS Attack Detected](#)
- [Trap: Device has entered Forced Stack Mode \(MAC Address \)](#)
- [Trap: entConfigChange](#)
- [Trap: fallingAlarm](#)
- [Trap: lldpRemTableChange Ageouts = count](#)
- [Trap: lldpRemTableChange Deletes = count](#)
- [Trap: lldpRemTableChange Drops = count](#)
- [Trap: lldpRemTableChange Inserts = count](#)
- [Trap: lldpXMedTopologyChangeDetected Subtype = subtype Class = class](#)
- [Trap: newRoot](#)
- [Trap: ntnOosPolicyEvoLocalUbpSessionFailure](#)
- [Trap: ospfIfAuthFailure](#)
- [Trap: ospfIfConfigError](#)
- [Trap: ospfIfStateChange](#)
- [Trap: ospfNbrStateChange](#)
- [Trap: ospfVirtIfAuthFailure](#)
- [Trap: ospfVirtIfConfigError](#)
- [Trap: ospfVirtIfStateChange](#)
- [Trap: ospfVirtNbrStateChange](#)
- [Trap: pethMainPowerUsageOffNotification](#)
- [Trap: pethMainPowerUsageOnNotification](#)
- [Trap: pethPsePortOnOffNotification](#)
- [Trap: rcIisPlsbBvidMismatchTrap](#)
- [Trap: rcIisPlsbLsdbUpdateTrap](#)
- [Trap: rcIisPlsbSmltPeerBmacMismatchTrap](#)
- [Trap: rcIisPlsbSmltSplitBebMismatchTrap](#)
- [Trap: rcIisPlsbSmltVirtBmacMismatchTrap](#)
- [Trap: risingAlarm](#)
- [Trap: RSTP Error Event](#)
- [Trap: RSTP General Event](#)
- [Trap: RSTP New Root](#)
- [Trap: RSTP Protocol Migration](#)
- [Trap: RSTP Topology Change](#)
- [Trap: Run %s %s](#)
- [Trap: s5CtrFanDirectionError](#)
- [Trap: s5CtrHighTemperatureError](#)
- [Trap: s5CtrHotSwap](#)

- [Trap: s5EtrMacAddressTablesThresholdReached](#)
- [Trap s5EtrSbsMacAccessViolation](#)
- [Trap s5EtrSbsMacAccessViolation](#)
- [Trap s5EtrSbsMacRemoved](#)
- [Trap s5EtrSbsMacTableCleared](#)
- [Trap s5EtrSbsMacTableClearedForPort](#)
- [Trap: SFP Transceiver's Bias is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Bias is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Temperature is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Temperature is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap: SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap:\\$#160:SFP Transceiver's Tx Power is no longer at warning/alarm level](#)
- [Trap SLPP Port Down Event](#)
- [Trap Smlt Ist Link Down](#)
- [Trap Smlt Ist Link Up](#)
- [Trap Smlt Link Down](#)
- [Trap Smlt Link Up](#)
- [Trap topologyChange](#)
- [Trap ubpEAPSessionEnd](#)
- [Trap ubpEAPSessionStart](#)
- [Trap vrrpTrapNewMaster](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with U

This page lists all the logs starting with the letter U that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Unable to apply pre-defined UBP filter set to new user \(port %d/%d\)](#)
- [Unable to inform SPB of ifc assignment change \(%d/%d\)](#)
- [Unicast block unit port unit port level level watermark watermark](#)
- [Unicast unblock unit port unit port level level watermark watermark](#)
- [Unknown unsupported attribute specified \(attribute \)](#)
- [Up 1 cable inserted or neighbor powered on](#)
- [Up 2 cable inserted or neighbor powered on](#)
- [Upstream stack direction is down cable removed or neighbor powered off](#)
- [Upstream stack direction is mis-configured](#)
- [USB device inserted](#)
- [USB device removed](#)
- [USC Install SET fail unit port unit port status = status](#)
- [USC Install TEST fail unit port unit port status = status](#)
- [USC UnInst SET failed for port port status = status](#)
- [User allowed \(radius authentication pass\) to log in from Web from Src IP](#)
- [User disallowed \(radius authentication fail\) to log in from Web from Src IP](#)
- [User disallowed \(radius authentication fail\) to log in from Web from Src IP](#)
- [User policy distribution across stack failed](#)
- [User policy filter set delete operation failed](#)
- [User policy filter set install operation failed](#)
- [User policy filter set update operation failed](#)
- [User with %s privilege has been created](#)
- [User with %s privilege has been deleted](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with V

This page lists all the logs starting with the letter V that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Vlan Change Aborted, it is in another STP Group](#)
- [Vlan Change Aborted on brouter](#)
- [VLAN configuration does not match BU VLAN configuration. VLAN config defaulted](#)
- [VLAN configuration does not match BU VLAN configuration. VLAN config defaulted](#)
- [VLAN IMC callback failed](#)
- [VLAN IMC was not sent](#)
- [VLAN NVRAM read error](#)
- [VLAN NVRAM read error](#)
- [VLAN queue messages discarded](#)
- [VLAN queue messages discarded](#)
- [VLAN set error from IMC](#)
- [VLAN set error from RPC](#)
- [Voice VLAN ID and Data VLAN ID cannot have the same value](#)
- [VRRP Feature globally disabled due to missing license](#)
- [VRRP: vrrpAdvtQueue is FULL. RX advertisement dropped in vlan %d!](#)
- [VRRP: vrrpQueue is FULL. Message dropped.](#)
- [VRRP VR VR Id VLAN Id Received mismatching advertisement interval \(advertisement interval\)](#)
- [VRRP VR VR Id VLAN Id Received mismatching advertisement type \(advertisement type \)](#)
- [VRRP VR VR Id VLAN Id Received mismatching fast advertisement interval \(fast advertisement interval\)](#)
- [VRRP VR VR Id VLAN Id Received mismatching virtual IP address \(received virtual ip address \)](#)
- [VRRP VR VR Id VLAN Id Received unknown VRRP packet type \(vrrp packet type \)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Information logs starting with W

This page lists all the logs starting with the letter W that are generated with a severity of Information.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Warning failed to connect to %s card \(in unit %s\)](#)
- [Warning: non-supported gsfps inserted on %s. Port will be disabled.](#)
- [Warning:non-supported transceiver on %s has been detected.](#)
- [Warning %s card unsafely removed \(from unit %s\)](#)
- [WEB-access is disabled](#)
- [WEB-access is enabled](#)
- [Web authentication fail from IP address](#)
- [Web authentication from IP address](#)
- [Web authentication \(RADIUS auth\) from IP address](#)
- [Web authentication \(RADIUS auth\) from IP address](#)
- [Web connection from IP address](#)
- [Web disconnect from IP address](#)
- [Web server attempting to open socket for port HTTP port](#)
- [Web server starts service on port HTTP port](#)
- [Web timeout from IP address](#)
- [Wrong OOS Agent buffer setting expected value actual value unit cannot join stack.](#)
- [Wrong VLANs nvq_RecDescr_actRecs](#)
- [Wrong VMACs nvq_RecDescr_actRecs](#)
- [Wrong vrec field](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [G](#) | [H](#) | [I](#) | [J](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with A

This page lists all the logs starting with the letter A that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [AAUR - Warning Agent image check sum ERROR](#)
- [AAUR - Warning Slave agent image check sum ERROR](#)
- [Access assignment modification support limited](#)
- [Access assignment name contains unacceptable characters](#)
- [Access assignment name length outside of acceptable limits](#)
- [Access assignment name not acceptable - reserved](#)
- [Access assignment template still in use \(siblings active\)](#)
- [Access element block label contains unacceptable characters](#)
- [Access element block label length outside of acceptable limits](#)
- [Access element cluster count \(cluster count \) exceeds limit \(cluster limit \)](#)
- [Access element cluster is referenced \(addition prohibited\)](#)
- [Access element cluster is referenced \(deletion prohibited\)](#)
- [Access element name contains unacceptable characters](#)
- [Access element name length outside of acceptable limits](#)
- [Access element name not acceptable - reserved](#)
- [ADAC: ADAC of Nortel IP Phones not functional](#)
- [ADAC: Error registering CDT handlers](#)
- [application-name failed DB-exchange stack formation delayed](#)
- [Assertion Failure in bcm_l3_hit_check- l3sw ip=%#x,l3hw ip=%#x](#)
- [Attempt to create an element that already exists \(prohibited\)](#)
- [Attempt to delete modify non-existing element \(prohibited\)](#)
- [Attempt to manipulate system-owned interface \(prohibited\)](#)
- [Attempt to manipulate user policy data rejected \(disabled\)](#)
- [Audit data initialized \(bad checksum\)](#)
- [Audit data initialized \(bad magic number\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with B

This page lists all the logs starting with the letter B that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Base action entry referenced by clfr block \(deletion prohibited\)](#)
- [Base action entry referenced by meter \(deletion prohibited\)](#)
- [Base action entry referenced by policy \(deletion prohibited\)](#)
- [Base action extension identifier invalid](#)
- [Base action modification prohibited due to action usage](#)
- [Base unit has loopback port mode %s and the current unit %s. Unit reconfigured and rebooted](#)
- [Base unit has loopback port mode <SPBM reserved port mode> and the current unit <SPBM reserved port mode>. Unit reconfigured and rebooted](#)
- [BaySec Not enough resource on port port# . Check QOS cfg](#)
- [Bay Secure error line line# # of octets read from NVRAM](#)
- [Bay Secure MAC DA filtering not enough resources](#)
- [Bay Secure Policy Error error type line line# 0](#)
- [Buffer configuration inconsistency detected \(local buffer conf stack buffer conf \)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with C

This page lists all the logs starting with the letter C that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [call to cdt api function due to lock timeout \(code= error type total failures= number errno= error code \)](#)
- [CFG - Could not create ram copy buffer.](#)
- [CFG - NVRAM file system check: errors detected. Please reboot the system!](#)
- [CFG - NVRAM file system check: errors detected. Restored to default.](#)
- [CFGSO - Warning Invalid Msg Id](#)
- [Classifier block component set ID out-of-range \(clfr comp set ID \)](#)
- [Classifier block number out-of-range \(block# \)](#)
- [Classifier block precedence value not supported](#)
- [Classifier component set ID out-of-range \(clfrs comp set ID \)](#)
- [Classifier conflict \(duplicate clfr data in block\) detected](#)
- [Classifier content incompatible with target interface\(s\)](#)
- [Classifier set block reference out-of-range \(clfr setblock# \)](#)
- [Classifier type unknown](#)
- [Clfr content \(system\) incompatible with target interface\(s\)](#)
- [Composite filter set addition failure data consistency issue](#)
- [Composite filter set addition failure data invalid](#)
- [Composite filter set addition failure resources unavailable](#)
- [Composite filter set creation failure data invalid](#)
- [Composite filter set creation failure MAC data not allowed](#)
- [Composite filter set deletion failure base set target invalid](#)
- [Composite filter set deletion failure data invalid](#)
- [Composite filter set destruction failure data invalid](#)
- [Composite filter set membership limits exceeded](#)
- [Conflicting action sources detected](#)
- [Conflicting master block member information detected](#)
- [Conflicting policy role policy interface index data detected](#)
- [CoS shaping not supported with specified interface](#)
- [Count action entry referenced by meter \(deletion prohibited\)](#)
- [Count action entry referenced by policy \(deletion prohibited\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with D

This page lists all the logs starting with the letter D that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [DAPP resources not available \(unit unit# \)](#)
- [DAPP with statistics tracking in use \(OoS disable prohibited\)](#)
- [DAUR - Warning Diag image check sum ERROR](#)
- [DAUR - Warning Slave diag image check sum ERROR](#)
- [Default ifc assignment failure port# port\(s\) ifc OoS-disabled](#)
- [Destination MAC address and mask values out-of-sync](#)
- [Different classifier component masks keys in block detected](#)
- [Different spanning-tree mode configured than BU. Unit reconfigured and rebooted.](#)
- [Different spanning-tree mode configured than BU. Unit re-configured and rebooted](#)
- [Down 1 cable removed or neighbor powered off](#)
- [Down 2 cable removed or neighbor powered off](#)
- [Download - image type image image version programmed successfully](#)
- [DSCP remarking not supported for IPv6 \(green action\)](#)
- [DSCP remarking not supported for IPv6 \(in-profile action\)](#)
- [DSCP remarking not supported for IPv6 \(match action\)](#)
- [DSCP remarking not supported for IPv6 \(non-match action\)](#)
- [DSCP remarking not supported for IPv6 \(out-of-profile action\)](#)
- [DSCP remarking not supported for IPv6 \(red action\)](#)
- [DSCP remarking not supported for IPv6 \(yellow action\)](#)
- [Dst IP addr matching not supported with IP addr type data](#)
- [Dst Layer 4 port min max values invalid \(max must be = to min\)](#)
- [Dst MAC addr matching not supported with address type data](#)
- [Duplicate access asgn name type index detected \(prohibited\)](#)
- [Duplicate classifier class values in set detected](#)
- [Duplicate set values in block detected](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with E

This page lists all the logs starting with the letter E that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [EAP Error: Reached maximum number of messages in the queue](#)
- [EAP Failed initialize global arrays](#)
- [EAP Failed to create dyna global arrays](#)
- [EAP Memory allocation error](#)
- [EAP Message queue error](#)
- [EAP NVRAM open error](#)
- [EAP NVRAM read port admin state error](#)
- [EAP NVRAM read system admin state error](#)
- [EAP NVRAM read system ubp state error](#)
- [EAP NVRAM write error](#)
- [EAP Task spawn error](#)
- [Egress interface and egress mask are mutually exclusive](#)
- [Element enable prohibited. Please delete and re-enter data](#)
- [Element label contains unacceptable characters](#)
- [Element label length outside of acceptable limits \(max 16 chars\)](#)
- [Error accessing Image File](#)
- [Error Bad Image Checksum](#)
- [Error in XGS3 memory DMA transfer](#)
- [Error reading Image File](#)
- [Evaluation precedence conflict detected \(UBP filter set data\)](#)
- [Evaluation precedence conflict \(Traffic Prof filter set data\)](#)
- [Evaluation precedence value required but not specified](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with F

This page lists all the logs starting with the letter F that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Fabric Attach: binding deactivation failure \(trunk %d %d/%d\)](#)
- [Failed to Create a Watchdog](#)
- [Failed to Read Image from Memory](#)
- [FCoE redirection default frame filter deletion failure detected](#)
- [FCoE redirection default frame filter installation failure detected](#)
- [FCoE redirection - egress interface issue detected \(ifIndex %d\)](#)
- [FCoE redirection - egress trunk issue detected \(trunk ID %d\)](#)
- [Filter control block resources exhausted](#)
- [Filter creation issue detected - in-profile action component](#)
- [Filter creation issue detected - match action component](#)
- [Filter creation issue detected - metering component](#)
- [Filter creation issue detected - non-match action component](#)
- [Filter creation issue detected - out-of-profile action component](#)
- [Filter manager memory resources exhausted](#)
- [Filter manager metering or policy rule space exhausted](#)
- [Filter manager metering resources exhausted](#)
- [Filter manager statistics tracking resources exhausted](#)
- [Filter set requirements incompatible with target interface](#)
- [First TrTCM Meter Index must be in range 1-5000](#)
- [Flow ID filtering not supported for IPv4](#)
- [Flow ID out-of-range \(Flow ID \)](#)
- [Front-panel UI selected use rear-panel base non-base switch](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with I

This page lists all the logs starting with the letter I that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Ifc app modification issue \(inconsistent default gateway data\)](#)
- [Ifc app modification issue \(inconsistent DHCP server data\)](#)
- [Ifc app modification issue \(inconsistent ifType data\)](#)
- [Ifc app support not currently available on interface \(ifc# \)](#)
- [Ifc assignment issue - prec conflict \(policy policy# disabled\)](#)
- [IGMP Error sending database from unit unit#](#)
- [IGMP Error sending group database from unit unit#](#)
- [IGMP Maximum number of igmp enabled interfaces reached](#)
- [Inadequate resources available for application policy criteria](#)
- [Incompatible base action extension specified](#)
- [Incompatible classifier reference \(agent-defined clfr\)](#)
- [Incompatible in-profile action \(trusted ifc\)](#)
- [Incompatible in-profile action \(unrestricted ifc\)](#)
- [Incompatible in-profile action \(untrusted ifc\)](#)
- [Incompatible in-profile action \(untrustedv4v6 ifc\)](#)
- [Incompatible match action \(unrestricted ifc\)](#)
- [Incompatible match action \(untrusted ifc\)](#)
- [Incompatible match action \(untrustedv4v6 ifc\)](#)
- [Incompatible non-match action \(trusted ifc\)](#)
- [Incompatible non-match action \(unrestricted ifc\)](#)
- [Incompatible non-match action \(unrestricted ifc\)](#)
- [Incompatible non-match action \(untrusted ifc\)](#)
- [Incompatible out-of-profile action \(trusted ifc\)](#)
- [Incompatible out-of-profile action \(unrestricted ifc\)](#)
- [Incompatible out-of-profile action \(untrusted ifc\)](#)
- [Incompatible out-of-profile action \(untrustedv4v6 ifc\)](#)
- [Incompatible StorageType specified \(re classifier\)](#)
- [Inconsistent action criteria detected across block members](#)
- [Inconsistent labels detected for members of same block](#)
- [Inconsistent labels detected for members of same set](#)
- [Inconsistent MAC data detected across filter set members](#)
- [Inconsistent metering criteria detected across block members](#)
- [Inner VLAN ID filtering requires double tag](#)
- [Inner VLAN ID min max values invalid \(min VLAN ID ! max VLAN ID \)](#)
- [In-profile action contains conflicting data](#)
- [Insufficient HW resources to support port role association](#)
- [Insufficient policy space available to support access assignment](#)
- [Insufficient resources available to support policy installation](#)
- [Interface action entry referenced by base action](#)
- [Interface Application data in use \(QoS disable prohibited\)](#)
- [Interface application Undo failure \(app app# \)](#)
- [Interface assignment failure - precedence conflict detected](#)
- [Interface capabilities incompatible with policy data](#)
- [Interface data out-of-sync in Policy and User Policy entries](#)
- [Interface resources inadequate to support application enable](#)

- [Interface shaping and CoS shaping conflict \(same ifc specified\)](#)
- [Interface shaping and queue shaping conflict \(same ifc specified\)](#)
- [Interface shaping not supported with specified interface](#)
- [Interfaces QoS-disabled \(port# on unit# \) - restoration issue](#)
- [Invalid access assignment type option specified](#)
- [Invalid access element type option specified](#)
- [Invalid classifier reference](#)
- [Invalid classifier reference \(unknown incompatible set\)](#)
- [Invalid classifier reference \(unknown instance\)](#)
- [Invalid DAPP state transition detected \(prohibited\)](#)
- [Invalid destination MAC address length specified](#)
- [Invalid destination MAC address mask length specified](#)
- [Invalid drop precedence value specified \(precedence \)](#)
- [Invalid DSCP value specified \(DSCP value \)](#)
- [Invalid egress interface specified \(ifc# \)](#)
- [Invalid egress interface type specified \(<ifc type>\)](#)
- [Invalid egress mask value specified](#)
- [Invalid EtherType value specified \(Ether Type 0xXXXX \)](#)
- [Invalid expired session data specified](#)
- [Invalid filter set priority value detected](#)
- [Invalid interface found in egress mask \(egress mask bit# \)](#)
- [Invalid interface index data specified \(ifc# \)](#)
- [Invalid interface index data specified \(ifc index \)](#)
- [Invalid interface index data \(system-owned\) specified](#)
- [Invalid IP destination address prefix detected](#)
- [Invalid IP source address prefix detected](#)
- [Invalid maximum inner VLAN ID value specified \(VLAN ID \)](#)
- [Invalid maximum VLAN ID value specified \(VLAN ID \)](#)
- [Invalid metering data \(bucket size\) specified for interface\(s\)](#)
- [Invalid metering data \(granularity\) specified for interface\(s\)](#)
- [Invalid metering data \(rate\) specified for interface\(s\)](#)
- [Invalid metering data \(srTCM trTCM\) specified for interface\(s\)](#)
- [Invalid minimum inner VLAN ID value specified \(VLAN ID \)](#)
- [Invalid minimum VLAN ID value specified \(VLAN ID \)](#)
- [Invalid mix of IP address data \(Dst IP type\) in set detected](#)
- [Invalid mix of IP and non-IP data in set detected](#)
- [Invalid mix of IP data \(IPv4 IPv6\) in set detected](#)
- [Invalid option specified for PatternIpVersion attribute](#)
- [Invalid pattern data length \(untagged format\) specified](#)
- [Invalid pattern data string length specified](#)
- [Invalid pattern format data specified](#)
- [Invalid pattern position string length specified](#)
- [Invalid port detected in specified port mask](#)
- [Invalid 802.1p user priority value specified \(priority value \)](#)
- [Invalid set drop precedence value specified](#)
- [Invalid shaping data \(bucket size\) specified for interface\(s\)](#)
- [Invalid shaping data \(granularity\) specified for interface\(s\)](#)
- [Invalid shaping data \(minimum rate granularity\) specified](#)
- [Invalid shaping data \(minimum rate maximum rate\) specified](#)
- [Invalid shaping data \(minimum rate\) specified](#)
- [Invalid shaping data \(rate\) specified for interface\(s\)](#)
- [Invalid source MAC address length specified](#)
- [Invalid source MAC address mask length specified](#)
- [Invalid statistics counter identification specified](#)
- [Invalid statistics tracking value](#)
- [Invalid statistics type value](#)
- [Invalid track statistics value specified](#)
- [Invalid unknown bandwidth type specified](#)
- [Invalid unsupported buffering capabilities value specified](#)
- [Invalid unsupported copy-to-cpu option specified](#)
- [Invalid unsupported DAPP enable value specified](#)
- [Invalid unsupported DAPP maximum IPv4 ICMP length specified](#)
- [Invalid unsupported DAPP maximum IPv6 ICMP length specified](#)
- [Invalid unsupported DAPP minimum TCP header length specified](#)
- [Invalid unsupported default gateway address length specified](#)

- [Invalid unsupported default gateway address specified](#)
- [Invalid unsupported destination IP address length specified](#)
- [Invalid unsupported DHCP server address length specified](#)
- [Invalid unsupported DHCP server address specified](#)
- [Invalid unsupported interface type specified](#)
- [Invalid unsupported mirror frame option specified](#)
- [Invalid unsupported NT application mode value specified](#)
- [Invalid unsupported packet type value specified](#)
- [Invalid unsupported QoS system operational mode value specified](#)
- [Invalid unsupported queue configuration value specified](#)
- [Invalid unsupported role assoc compatibility specified](#)
- [Invalid unsupported source IP address length specified](#)
- [Invalid unsupported Trusted processing mode value specified](#)
- [Invalid unsupported UBP support level value specified](#)
- [Invalid unsupported VLAN tag value specified \(VLAN tag \)](#)
- [Invalid update DSCP value specified \(not currently supported\)](#)
- [Invalid update priority value specified](#)
- [Invalid update VLAN Id specified \(VLAN Id \)](#)
- [Invalid user priority match selection specified \(priority value \)](#)
- [IP classifier entry still referenced \(deletion prohibited\)](#)
- [IP destination address and mask values out-of-sync](#)
- [IP destination Layer 4 port maximum value out-of-range \(dest port# \)](#)
- [IP destination Layer 4 port minimum value out-of-range \(dest port# \)](#)
- [IP protocol value out-of-range \(IP protocol# \)](#)
- [IP source address and mask values out-of-sync](#)
- [IP source Layer 4 port minimum value out-of-range \(src port# \)](#)
- [IP source Layer 4 port minimum value out-of-range \(src port# \)](#)
- [IPv4-only filter criteria mixed with IPv6 criteria](#)
- [Issue detected enabling/disabling DSCP Mapping Table usage \(port %d\)](#)
- [Issue detected setting native DSCP Mapping Table values](#)
- [Issue with classifier component mask detected](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
 NN47216-600 Logs Reference

Version 07.03 August 2015

©Avaya Inc. 2015 All Rights Reserved.

support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with L

This page lists all the logs starting with the letter L that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Layer 2 classifier still referenced \(deletion prohibited\)](#)
- [Layer 4 port filtering with IPv6 requires UDP TCP Next Header](#)
- [Layer 4 port range could not be reduced sufficiently](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with M

This page lists all the logs starting with the letter M that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Management IP: excess traffic received on Management port%s](#)
- [Memory Allocation Error](#)
- [Meter entry referenced by clfr block \(deletion prohibited\)](#)
- [Meter entry referenced by meter \(deletion prohibited\)](#)
- [Meter entry referenced by policy \(deletion prohibited\)](#)
- [Meter \(from clfr block\) usage in multiple policies prohibited](#)
- [Meter \(from policy\) usage in multiple policies prohibited](#)
- [Meter identifier out-of-range \(meter id \)](#)
- [Metering not supported with DS L2 access control lists](#)
- [Mirroring \(requested via action\) not configured correctly](#)
- [Modification of action \(non-match usage\) prohibited](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with N

This page lists all the logs starting with the letter N that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [NEAP Accounting - Memory allocation failure](#)
- [Non-match action contains conflicting data](#)
- [Non-match action not available for use with filter sets](#)
- [Non-match action support not available on certain interfaces](#)
- [Non-QoS interfaces may not be assigned to a role combination](#)
- [Non-supported action option \(green action\) specified](#)
- [Non-supported action option \(in-profile action\) specified](#)
- [Non-supported action option \(match action\) specified](#)
- [Non-supported action option \(out-of-profile action\) specified](#)
- [Non-supported action option \(policy non-match action\) specified](#)
- [Non-supported action option \(red action\) specified](#)
- [Non-supported action option \(yellow action\) specified](#)
- [Non-unique precedence order value detected \(prohibited\)](#)
- [Non-volatile QoS data discarded during restoration](#)
- [Non-volatile storage commit delay too large](#)
- [No resources available for classifier port range checking](#)
- [Not Enough Memory](#)
- [NT application mode enable failure - inadequate resources](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with O

This page lists all the logs starting with the letter O that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Only one frame type supported per classifier](#)
- [Out-of-profile action contains conflicting data](#)
- [Out-of-range CoS index value \(COS index value \)](#)
- [Out-of-range queue index value \(queue index \) for in-use queue set](#)
- [Out-of-range queue index value \(queue index \) for pending queue set](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with P

This page lists all the logs starting with the letter P that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Packet redirection support limited by target interfaces](#)
- [Pattern matching data in excess of bytes# bytes specified](#)
- [Pattern matching \(Dst IP\) not supported with IP addr type data](#)
- [Pattern matching \(Dst MAC\) not supported with address type data](#)
- [Pattern matching \(IP\) not supported with non-IP addr type data](#)
- [Pattern matching not supported with other classification data](#)
- [Pattern modifier data specified without actual pattern data](#)
- [Pattern position and data strings must be same length](#)
- [Policies with session data must be port-based](#)
- [Policy action out-of-range \(action# \)](#)
- [Policy content incompatible with target interface\(s\)](#)
- [Policy mask availability issue \(space exhausted\)](#)
- [Policy modification support limited](#)
- [Policy non-match action out-of-range \(non-match action# \)](#)
- [Policy precedence conflict detected with non-QoS application](#)
- [Policy precedence value out-of-range for target interface\(s\)](#)
- [Policy requirements exceed available resources \(slot slot# \)](#)
- [Policy statistics index out-of-range \(stats index \)](#)
- [Policy with this filtering values is already installed on this precedence](#)
- [Post-join ACL installation issue detected \(ifc ifc# \)](#)
- [Post-join filter set installation issue detected \(ifc ifc# \)](#)
- [Post-join traffic-profile installation issue detected \(ifc ifc# \)](#)
- [Potential inconsistent access asgn state \(Undo fail\) detected](#)
- [Potential inconsistent ifc assignment state \(Undo fail\) detected](#)
- [Potential inconsistent policy state \(Undo fail\) detected](#)
- [Precedence value out-of-range](#)
- [Provided metering information incomplete](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with Q

This page lists all the logs starting with the letter Q that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [QOS filter-limiting mode modified and unit reset](#)
- [QoS policies may not be applied to uplink or daisy chain ports \(port# \)](#)
- [Queue configuration inconsistency detected \(local queue conf stack queue conf.\)](#)
- [Queue set assignment distribution across stack failed](#)
- [Queue set unacceptable - pending range excludes in-use queues](#)
- [Queue set value modification prohibited](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with R

This page lists all the logs starting with the letter R that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Rate granularity limited to increments of 1 Mbps or 64 Kbps](#)
- [Rate \(min\) granularity limited \(increments of 1 Mbps or 64 Kbps\)](#)
- [Referenced block \(by policy\) deletion prohibited](#)
- [Referenced set \(by block\) modifications prohibited](#)
- [Referenced set \(by policy\) modifications prohibited](#)
- [Remote OoS-disable request failure \(port# on unit unit# \)](#)
- [Requested attribute usage is currently not supported](#)
- [Requested filter manager support unavailable](#)
- [Requested reserve data invalid](#)
- [Request invalid - OoS interface apps enabled on interface\(s\)](#)
- [Request invalid - specified interface currently OoS-disabled](#)
- [Request temporarily denied - OoS support is currently disabled](#)
- [Required bandwidth information not specified](#)
- [Reset initiated by console](#)
- [Reset initiated through SSH by IP address](#)
- [Reset initiated through telnet by IP address](#)
- [Reset to default initiated by console](#)
- [Reset to default initiated through telnet by IP address](#)
- [Resources exhausted \(maximum class entries reached\)](#)
- [Resources exhausted \(out-of-memory\)](#)
- [Role combination associated with interface \(deletion prohibited\)](#)
- [Role combination contains unacceptable characters](#)
- [Role combination referenced by policy \(deletion prohibited\)](#)
- [Role \(interface\) capabilities incompatible with policy data](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with S

This page lists all the logs starting with the letter S that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Source MAC address and mask values out-of-sync](#)
- [Specified Destination Layer 4 min max range not supported](#)
- [Specified filter criteria is invalid inconsistent](#)
- [Specified inner VLAN ID min max range not supported](#)
- [Specified metering operation not supported](#)
- [Specified metering statistics entry already in-use \(by policy\)](#)
- [Specified policy components \(classifiers\) conflicting](#)
- [Specified policy components \(classifiers\) conflicting](#)
- [Specified policy statistics entry already in-use \(by meter\)](#)
- [Specified queue set information invalid](#)
- [Specified Source Layer 4 min max range not supported](#)
- [Specified token bucket criteria out of range](#)
- [Specified token bucket refresh interval not supported](#)
- [Specified token bucket size \(burst size\) not supported](#)
- [Specified user policy interface currently QoS-disabled](#)
- [Specified VLAN ID min max range not supported](#)
- [Src Layer 4 port min max values invalid \(max must be = to min\)](#)
- [srTCM meter issue - CIR must be the same in both meters](#)
- [srTCM meter issue - EBS must be greater than CBS](#)
- [srTCM trTCM meter issue - diff algorithms in associated meters](#)
- [srTCM trTCM meter issue - referenced meter incompatible unknown](#)
- [srTCM trTCM meter issue - too many cascaded meters](#)
- [Stack operation mode modified to Hybrid and unit reset](#)
- [Stack RO password changed from IP add](#)
- [Stack RO password changed from serial conn](#)
- [Stack RW password changed from IP add](#)
- [Stack RW password changed from serial conn](#)
- [Stack sync failed stack failed to form](#)
- [Stack synchronization failed Exp value Act value Missing value](#)
- [Successfully loaded backup configuration files](#)
- [Successfully loaded backup configuration files](#)
- [Switch RO password changed from IP add](#)
- [Switch RO password changed from serial conn](#)
- [Switch RW password changed from IP add](#)
- [Switch RW password changed from serial conn](#)
- [System classifier still referenced \(deletion prohibited\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with T

This page lists all the logs starting with the letter T that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [TCP Control Flag filter criteria requires TCP protocol](#)
- [TFTP Failed](#)
- [The base \(unit# number \) has left the stack. Unit# number is now the base](#)
- [The user <%s> was locked.](#)
- [Token bucket algorithm identifier invalid](#)
- [Token bucket algorithm identifier unknown unsupported](#)
- [Token bucket entry referenced by meter \(deletion prohibited\)](#)
- [Token bucket entry referenced by shaper \(deletion prohibited\)](#)
- [Token bucket minimum rate outside limits \(64 - 10230000 Kbps\)](#)
- [Token bucket rate outside limits \(64 - 10230000 Kbps\)](#)
- [Token bucket size not compatible with committed fill rate](#)
- [Traffic Prof filter set elem count exceeds available resources](#)
- [Traffic Prof filter set policy count \(policy count \) exceeds limit \(policy limit \)](#)
- [Traffic Prof filter set rule count \(rule count \) exceeds limit \(rule limit \)](#)
- [Trap: FCoE - Egress Issue Detected](#)
- [Trap_s5CtrUnitDown](#)
- [trTCM meter issue - PBS must be greater than CBS](#)
- [trTCM meter issue - PIR must be greater than CIR](#)
- [Trusted processing mode change rejected - inadequate resources](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with U

This page lists all the logs starting with the letter U that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Unable to add block member \(block elem# component set id \) to existing policy](#)
- [Unable to apply existing policy data to interface \(unit# port# \)](#)
- [Unable to apply existing user-based policy data to new user](#)
- [Unable to apply filter set to ports \(unsupported capabilities\)](#)
- [Unable to apply newly-defined UBP filter set to existing user](#)
- [Unable to apply pre-defined UBP filter set to new user](#)
- [Unable to compress classification criteria in set adequately](#)
- [Unable to create count action \(meter\) for access assignment](#)
- [Unable to create count action \(policy\) for access assignment](#)
- [Unable to create count action \(secondary meter\) for access asgn](#)
- [Unable to create metering data for access assignment](#)
- [Unable to create non-match components for ACL](#)
- [Unable to create out-of-profile action for access assignment](#)
- [Unable to create policy data for access assignment](#)
- [Unable to create secondary metering data for access assignment](#)
- [Unable to create secondary token bucket data for access asgn](#)
- [Unable to create token bucket data for access assignment](#)
- [Unable to create yellow action for access assignment](#)
- [Unable to deactivate policy associated with interface](#)
- [Unable to delete block member \(block element# component set id \) from existing policy](#)
- [Unable to delete UBP filter set on interface ifc#](#)
- [Unable to derive suitable filter set element eval precedence](#)
- [Unable to determine cfr interface\(s\) compatibility](#)
- [Unable to disable ARP Spoofing support on interface \(ifc# \)](#)
- [Unable to disable BPDUBIkr support on interface \(ifc# \)](#)
- [Unable to disable DHCP Snooping support on interface \(ifc# \)](#)
- [Unable to disable DHCP Spoofing support on interface \(ifc# \)](#)
- [Unable to disable DNSPort support on interface \(ifc# \)](#)
- [Unable to disable existing policy data on interface \(unit# port# \)](#)
- [Unable to disable FTPPort support on interface \(ifc# \)](#)
- [Unable to disable Nachia support on interface \(ifc# \)](#)
- [Unable to disable policy data for access assignment](#)
- [Unable to disable SQLSlam support on interface \(ifc# \)](#)
- [Unable to disable SynFinScan support on interface \(ifc# \)](#)
- [Unable to disable Xmas support on interface \(ifc# \)](#)
- [Unable to enable ARP Spoofing support on interface \(ifc# \)](#)
- [Unable to enable BPDUBIkr support on interface \(ifc# \)](#)
- [Unable to enable DHCP Snooping support on interface \(ifc# \)](#)
- [Unable to enable DHCP Spoofing support on interface \(ifc# \)](#)
- [Unable to enable DNSPort support on interface \(ifc# \)](#)
- [Unable to enable FTPPort support on interface \(ifc# \)](#)
- [Unable to enable Nachia support on interface \(ifc# \)](#)
- [Unable to enable policy data for access assignment](#)
- [Unable to enable SQLSlam support on interface \(ifc# \)](#)
- [Unable to enable SynFinScan support on interface \(ifc# \)](#)

- [Unable to enable Xmas support on interface \(ifc# \)](#)
- [Unable to install access assignment - component creation issue](#)
- [Unable to manipulate DAPP support \(no applicable interfaces\)](#)
- [Unable to modify access assignment - component modify issue](#)
- [Unicast \(Interface# \) and Non-Unicast \(interface# \) interfaces in conflict](#)
- [Unknown incompatible access element specified](#)
- [Unknown incompatible action component specified](#)
- [Unknown incompatible classifier block specified](#)
- [Unknown incompatible classifier set specified](#)
- [Unknown incompatible in-profile action specified](#)
- [Unknown incompatible in-profile \(green\) action specified](#)
- [Unknown incompatible match action specified](#)
- [Unknown incompatible metering component specified](#)
- [Unknown incompatible metering statistics entry specified](#)
- [Unknown incompatible out-of-profile action specified](#)
- [Unknown incompatible out-of-profile \(red\) action specified](#)
- [Unknown incompatible out-of-profile \(yellow\) action specified](#)
- [Unknown incompatible policy non-match action specified](#)
- [Unknown incompatible policy statistics entry specified](#)
- [Unknown incompatible queue set specified](#)
- [Unknown incompatible role combination specified](#)
- [Unknown incompatible token bucket reference specified](#)
- [Unknown out-of-range interface index value \(ifc# \)](#)
- [Unknown out-of-range interface index value \(ifc index \)](#)
- [Unknown queue set queue reference detected](#)
- [Unknown unsupported interface application type specified](#)
- [Unknown unsupported interface class specified \(ifc class \)](#)
- [Unknown unsupported IP Flag specified](#)
- [Unknown unsupported StorageType specified](#)
- [Unknown unsupported TCP Control Flag specified](#)
- [Unsupported IP address type specified](#)
- [Unsupported pattern offset data specified](#)
- [Unsupported unknown QoS agent configuration attribute \(attribute# \)](#)
- [Up 1 cable removed or neighbor powered off](#)
- [Up 2 cable removed or neighbor powered off](#)
- [Update priority value and update DSCP value out-of-sync](#)
- [Update priority value per ingress DSCP currently not supported](#)
- [User Policy data referencing interface \(operation prohibited\)](#)
- [User policy filter set count \(<set count>\) exceeds limit \(<set limit>\)](#)
- [User policy filter set element count exceeds available resources](#)
- [User policy group contains invalid unacceptable characters](#)
- [User policy group length outside of acceptable limits](#)
- [User policy name contains invalid unacceptable characters](#)
- [User policy name length outside of acceptable limits](#)
- [User Policy \(UBP\) filter set in use \(QoS disable prohibited\)](#)
- [User Policy \(UBP\) filter set in use \(QoS reset prohibited\)](#)
- [User priority specified with untagged frames \(invalid\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with V

This page lists all the logs starting with the letter V that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [VLAN ID min max values invalid \(min VLAN ID ! max VLAN ID \)](#)
- [VLAN range could not be reduced sufficiently](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Serious logs starting with W

This page lists all the logs starting with the letter W that are generated with a severity of Serious.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

- [Wrong OoS Agent buffer setting, expected %s, actual %s, unit re-configured and reboot](#)
- [Wrong OoS Agent queue setting, expected %u, actual %u, unit reconfigured and reboot](#)
- [Wrong OoS Agent queue setting, expected %u, actual %u, unit re-configured and reboot](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [F](#) | [I](#) | [L](#) | [M](#) | [N](#) | [O](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#) | [V](#) | [W](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with A

This page lists all the logs starting with the letter A that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Access assignment modifications not supported](#)
- [Access element modifications not supported](#)
- [application-name failed DB-exchange stack failed to form](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with B

This page lists all the logs starting with the letter B that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Base action modifications not supported](#)
- [Bay Secure Resource Error error# line line# resource ID](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with C

This page lists all the logs starting with the letter C that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [cam driver initialization failed \(code= error type argument= line# \)](#)
- [cam processing aborted \(code= error type argument= line# \)](#)
- [Classifier block modifications not supported](#)
- [Classifier component modifications not supported](#)
- [Composite filter set addition failure comp filter set unknown](#)
- [Composite filter set addition failure replication failure](#)
- [Composite filter set creation failure replication failure](#)
- [Composite filter set creation failure seed filter set unknown](#)
- [Composite filter set deletion failure comp filter set unknown](#)
- [Composite filter set deletion failure seed filter set unknown](#)
- [CoS shaping modifications not supported](#)
- [Count action modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with D

This page lists all the logs starting with the letter D that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Data model version attribute value not supported](#)
- [Download - DL_CKSUM_ACK_ERROR](#)
- [Download - DL_PROGRAM_STATUS_ACK_ERROR](#)
- [Download - DL_START_PROGRAM_FLASH_ACK_ERROR](#)
- [Download - Error Failed to get the dl resource.](#)
- [Download - Error Watchdog expire No Ack from NBUs download MSG # message ID](#)
- [Download - Failed to get buffer](#)
- [Download - Failed to malloc for buffer](#)
- [Download - Failed to start a watchdog](#)
- [Download - Image Checksum Error](#)
- [Download - Largest mem blk DL_SYMEM_RESERVED](#)
- [Download - NBU Block Checksum Error](#)
- [Download - NBU_DL_PROGRAM_STATUS_ERROR](#)
- [Download - TFTP timeout OR image file not found](#)
- [Download - tftpXfer failed](#)
- [DSCP mapping modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with F

This page lists all the logs starting with the letter F that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Filter manager internal error encountered](#)
- [Filter manager request parameter invalid](#)
- [FSH - Error Calling taskLock\(\) returns Error](#)
- [FSH - Error Failed to erase flash sector](#)
- [FSH - Error Failed to lock flash sector](#)
- [FSH - Error Failed to program flash](#)
- [FSH - Error Failed to unlock flash sector](#)
- [FSH - Error Failed to write to flash address](#)
- [FSH - Time to Download the Image number seconds](#)
- [FSH - Time to Program the Image to flash number seconds](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with H

This page lists all the logs starting with the letter H that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Hello Module unable to communicate with neighbor\(s\) unit reset](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with I

This page lists all the logs starting with the letter I that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [IGMP Initialization failed Error code errCode](#)
- [IMC buffers of size buffer size have been exhausted buffer pool size pool size](#)
- [Incompatible data model version values \(referenced clfr data\)](#)
- [Incompatible data model version values \(referenced meter data\)](#)
- [Inconsistent classifier component \(clfr comp# \) state detected](#)
- [Interface action extension identifier invalid](#)
- [Interface action modifications not supported](#)
- [Interface application modifications not supported](#)
- [Interface assignment modifications not supported](#)
- [Interface queue modifications not supported](#)
- [Interface shaping modifications not supported](#)
- [Invalid classifier ID specified](#)
- [Invalid classifier reference \(unknown class\)](#)
- [Invalid datapath identifier specified](#)
- [Invalid master block member value specified](#)
- [Invalid option specified for BcastFrames attribute](#)
- [Invalid option specified for KnownIpMcast attribute](#)
- [Invalid option specified for KnownMcastFrames attribute](#)
- [Invalid option specified for KnownNonIpMcast attribute](#)
- [Invalid option specified for KnownUcastFrames attribute](#)
- [Invalid option specified for NonIpPkt attribute](#)
- [Invalid option specified for UnknownMcastFrames attribute](#)
- [Invalid option specified for UnknownNonIpMcast attribute](#)
- [Invalid option specified for UnknownUcastFrames attribute](#)
- [Invalid resetToDefaults value specified](#)
- [Invalid unknown access assignment entry state encountered \(entry state \)](#)
- [Invalid unknown access element entry state encountered \(entry state \)](#)
- [Invalid unknown action entry state encountered \(entry state \)](#)
- [Invalid unknown classifier block entry state encountered \(entry state \)](#)
- [Invalid unknown CoS shaping entry state encountered \(entry state \)](#)
- [Invalid unknown DSCP mapping entry state encountered \(entry state \)](#)
- [Invalid unknown entry state \(class class# \) encountered \(entry state \)](#)
- [Invalid unknown interface action entry state encountered \(entry state \)](#)
- [Invalid/unknown interface app entry state encountered \(<entry state>\)](#)
- [Invalid unknown interface assignment entry state encountered \(entry state \)](#)
- [Invalid unknown interface queue entry state encountered \(entry state \)](#)
- [Invalid unknown interface shaping entry state encountered \(entry# \)](#)
- [Invalid unknown IP filter entry state encountered \(entry state \)](#)
- [Invalid unknown Layer 2 filter entry state encountered \(entry state \)](#)
- [Invalid unknown meter entry state encountered \(entry state \)](#)
- [Invalid unknown policy entry state encountered \(entry state \)](#)
- [Invalid unknown 802.1p user priority mapping entry state \(entry state \)](#)
- [Invalid unknown queue set assignment entry state encountered \(entry state \)](#)
- [Invalid unknown queue shaping entry state encountered \(entry state \)](#)
- [Invalid unknown queuing discipline enum specified \(queuing discipline \)](#)

- [Invalid unknown role combination entry state encountered \(entry state \)](#)
- [Invalid unknown System filter entry state encountered \(entry state \)](#)
- [Invalid unknown token bucket entry state encountered \(entry state \)](#)
- [Invalid unknown user policy entry state encountered \(entry state \)](#)
- [IP classifier modifications not supported](#)
- [Issue detected restoring OPA data from NV \(class class# \)](#)
- [Issues detected with QoS operational mode disable \(ifcs# ifcs\)](#)
- [Issues detected with QoS operational mode enable \(ifcs# ifcs\)](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

Avaya Ethernet Routing Switch 2000, 3000, 4000, 5000, and Avaya Virtual Services Platform 7000
NN47216-600 Logs Reference
Version 07.03 August 2015
©Avaya Inc. 2015 All Rights Reserved.
support.Avaya.com

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with L

This page lists all the logs starting with the letter L that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Layer 2 classifier modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with M

This page lists all the logs starting with the letter M that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [MCM group node corrupted.](#)
- [Memory on unit %d is under %d MBytes.](#)
- [Meter modifications not supported](#)
- [Modify the pattern data or use the correct data format](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with P

This page lists all the logs starting with the letter P that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Policy modifications not supported](#)
- [Post-join policy installation issue detected \(ifc ifc# \)](#)
- [Potential inconsistent access elem state \(Undo fail\) detected](#)
- [Potential inconsistent block state \(Undo fail\) detected](#)
- [802.1p user priority mapping modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with Q

This page lists all the logs starting with the letter Q that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Queue set assignment modifications not supported](#)
- [Queue shaping modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with R

This page lists all the logs starting with the letter R that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Reset - Error Failed to get the Reset sem](#)
- [Resource alloc event timeout \(tgt all apps except OoS Agent rcv event \)](#)
- [Role combination modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with S

This page lists all the logs starting with the letter S that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [SLAMon Agent: message channel creation failure](#)
- [SLAMon Agent message channel creation failure](#)
- [SLAMon Agent platform CLI command interface initialization issue](#)
- [SLAMon Agent platform timer initialization issue](#)
- [SLAMon Agent: terminated](#)
- [SLAMon Agent terminated](#)
- [SLAMon Agent: terminated - command/frame processing issue detected](#)
- [SLAMon Agent terminated — command/frame processing issue detected](#)
- [SLAMon Agent: terminated - NTR test exception detected](#)
- [SLAMon Agent terminated NTR test exception detected](#)
- [SLAMon Agent: terminated - resources unavailable](#)
- [SLAMon Agent terminated - resources unavailable](#)
- [SLAMon Agent: terminated - RTP test exception detected](#)
- [SLAMon Agent terminated - RTP test exception detected](#)
- [SNTP Could not sync to NTP servers.](#)
- [SPBM: ERROR adding i-sid %x to i-sid table - table full](#)
- [SPBM: ERROR adding i-sid %x to i-sid table - table full](#)
- [SPBM: ERROR enabling SPBM due to Software License error](#)
- [Specified filter information not found](#)
- [Specified filter manager resource invalid](#)
- [Specified filter manager resource uninitialized](#)
- [Specified policy identifier \(cookie\) invalid](#)
- [Sw Exception](#)
- [System classifier modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with T

This page lists all the logs starting with the letter T that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Task task-name is suspended](#)
- [Task whose index is taskID taskID is suspended](#)
- [Token bucket modifications not supported](#)
- [Trap: slaMonitorAgentExceptionDetected](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

[Home](#) | [Alphabetical listing](#) | [Source listing](#) | [Severity listing](#)

Critical logs starting with U

This page lists all the logs starting with the letter U that are generated with a severity of Critical.

Navigate to the description of each log by clicking the log name, or select a different letter for the logs that start with that letter.

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

- [Unable to complete requested access asgn system operation \(oper type \)](#)
- [Unable to complete requested policy system operation \(operation type \)](#)
- [Unable to compress specified policy criteria](#)
- [Unable to create action for access element](#)
- [Unable to create classifier block entry for access element](#)
- [Unable to create classifier component entry for access element](#)
- [Unable to create DS MF classifier for access element](#)
- [Unable to create L2 MF classifier for access element](#)
- [Unable to inform SPB of ifc assignment change \(%d/%d\)](#)
- [Unable to install access element - component creation issue](#)
- [Unable to locate corresponding DS L2 access elements](#)
- [Unknown access assignment entry specified \(entry# \)](#)
- [Unknown access element entry specified \(entry# \)](#)
- [Unknown action entry specified \(entry# \)](#)
- [Unknown classifier block entry specified \(entry# \)](#)
- [Unknown classifier component entry specified \(entry# \)](#)
- [Unknown CoS shaping entry specified \(entry# CoS \)](#)
- [Unknown count action entry specified \(entry# \)](#)
- [Unknown DSCP mapping entry specified \(entry# \)](#)
- [Unknown entry \(class class# \) specified \(entry# \)](#)
- [Unknown incompatible token bucket reference specified](#)
- [Unknown interface application entry specified \(entry# \)](#)
- [Unknown interface assignment entry specified \(entry# \)](#)
- [Unknown interface queue entry specified \(ifc queue id \)](#)
- [Unknown interface shaping entry specified \(entry# \)](#)
- [Unknown IP classifier entry specified \(entry# \)](#)
- [Unknown Layer 2 classifier entry specified \(entry# \)](#)
- [Unknown meter entry specified \(entry# \)](#)
- [Unknown policy entry specified \(entry# \)](#)
- [Unknown 802.1p user priority mapping entry specified \(entry# \)](#)
- [Unknown queue set assignment entry specified \(entry# \)](#)
- [Unknown queue shaping entry specified \(entry# queue \)](#)
- [Unknown role combination entry specified \(role comb id \)](#)
- [Unknown System classifier entry specified \(entry# \)](#)
- [Unknown token bucket entry specified \(entry# \)](#)
- [Unknown unsupported RowStatus specified](#)
- [Unknown user policy entry specified \(entry# \)](#)
- [Unsupported IPv4 Options value specified](#)
- [User policy modifications not supported](#)

[A](#) | [B](#) | [C](#) | [D](#) | [E](#) | [H](#) | [I](#) | [L](#) | [M](#) | [P](#) | [Q](#) | [R](#) | [S](#) | [T](#) | [U](#)

