



ExtremeSwitching™

# **Configuring QoS and ACL-Based Traffic Filtering on Virtual Services Platform 7200 Series, 8000 Series, and 8600**

Release 6.1 (VSP 8600)  
9035281  
February 2018

© 2017-2018, Extreme Networks, Inc.  
All Rights Reserved.

### Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Extreme Networks, Inc. assumes no liability for any errors. Extreme Networks, Inc. reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

### Documentation disclaimer

"Documentation" means information published in varying mediums which may include product information, operating instructions and performance specifications that are generally made available to users of products. Documentation does not include marketing materials. Extreme Networks shall not be responsible for any modifications, additions, or deletions to the original published version of Documentation unless such modifications, additions, or deletions were performed by or on the express behalf of Extreme Networks. End User agrees to indemnify and hold harmless Extreme Networks, Extreme Networks' agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End User.

### Link disclaimer

Extreme Networks is not responsible for the contents or reliability of any linked websites referenced within this site or Documentation provided by Extreme Networks. Extreme Networks is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Extreme Networks does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

### Warranty

Extreme Networks provides a limited warranty on Extreme Networks hardware and software. Refer to your sales agreement to establish the terms of the limited warranty. In addition, Extreme Networks' standard warranty language, as well as information regarding support for this product while under warranty is available to Extreme Networks customers and other parties through the Extreme Networks Support website: <http://www.extremenetworks.com/support> under the link "Policies" or such successor site as designated by Extreme Networks. Please note that if You acquired the product(s) from an authorized Extreme Networks Channel Partner outside of the United States and Canada, the warranty is provided to You by said Extreme Networks Channel Partner and not by Extreme Networks.

"Hosted Service" means an Extreme Networks hosted service subscription that You acquire from either Extreme Networks or an authorized Extreme Networks Channel Partner (as applicable) and which is described further in Hosted SAS or other service description documentation regarding the applicable hosted service. If You purchase a Hosted Service subscription, the foregoing limited warranty may not apply but You may be entitled to support services in connection with the Hosted Service as described further in your service description documents for the applicable Hosted Service. Contact Extreme Networks or Extreme Networks Channel Partner (as applicable) for more information.

### Hosted Service

THE FOLLOWING APPLIES ONLY IF YOU PURCHASE AN EXTREME NETWORKS HOSTED SERVICE SUBSCRIPTION FROM EXTREME NETWORKS OR AN EXTREME NETWORKS CHANNEL PARTNER (AS APPLICABLE), THE TERMS OF USE FOR HOSTED SERVICES ARE AVAILABLE ON THE EXTREME NETWORKS WEBSITE, <https://extremeportal.force.com> OR SUCH SUCCESSOR SITE AS DESIGNATED BY EXTREME NETWORKS, AND ARE APPLICABLE TO ANYONE WHO ACCESSES OR USES THE HOSTED SERVICE. BY ACCESSING OR USING THE HOSTED SERVICE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE DOING SO (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO THE TERMS OF USE. IF YOU ARE ACCEPTING THE TERMS OF USE ON BEHALF A COMPANY OR OTHER LEGAL ENTITY, YOU

REPRESENT THAT YOU HAVE THE AUTHORITY TO BIND SUCH ENTITY TO THESE TERMS OF USE. IF YOU DO NOT HAVE SUCH AUTHORITY, OR IF YOU DO NOT WISH TO ACCEPT THESE TERMS OF USE, YOU MUST NOT ACCESS OR USE THE HOSTED SERVICE OR AUTHORIZE ANYONE TO ACCESS OR USE THE HOSTED SERVICE.

### Licenses

THE SOFTWARE LICENSE TERMS AVAILABLE ON THE EXTREME NETWORKS WEBSITE, <https://extremeportal.force.com> OR SUCH SUCCESSOR SITE AS DESIGNATED BY EXTREME NETWORKS, ARE APPLICABLE TO ANYONE WHO DOWNLOADS, USES AND/OR INSTALLS EXTREME NETWORKS SOFTWARE, PURCHASED FROM EXTREME NETWORKS, INC., ANY EXTREME NETWORKS AFFILIATE, OR AN EXTREME NETWORKS CHANNEL PARTNER (AS APPLICABLE) UNDER A COMMERCIAL AGREEMENT WITH EXTREME NETWORKS OR AN EXTREME NETWORKS CHANNEL PARTNER. UNLESS OTHERWISE AGREED TO BY EXTREME NETWORKS IN WRITING, EXTREME NETWORKS DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE WAS OBTAINED FROM ANYONE OTHER THAN EXTREME NETWORKS, AN EXTREME NETWORKS AFFILIATE OR AN EXTREME NETWORKS CHANNEL PARTNER; EXTREME NETWORKS RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU AND ANYONE ELSE USING OR SELLING THE SOFTWARE WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE INSTALLING, DOWNLOADING OR USING THE SOFTWARE (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO THESE TERMS AND CONDITIONS AND CREATE A BINDING CONTRACT BETWEEN YOU AND EXTREME NETWORKS, INC. OR THE APPLICABLE EXTREME NETWORKS AFFILIATE ("EXTREME NETWORKS").

Extreme Networks grants You a license within the scope of the license types described below. Where the order documentation does not expressly identify a license type, the applicable license will be a Designated System License as set forth below in the Designated System(s) License (DS) section as applicable. The applicable number of licenses and units of capacity for which the license is granted will be one (1), unless a different number of licenses or units of capacity is specified in the documentation or other materials available to You. "Software" means computer programs in object code, provided by Extreme Networks or an Extreme Networks Channel Partner, whether as stand-alone products, pre-installed on hardware products, and any upgrades, updates, patches, bug fixes, or modified versions thereto. "Designated Processor" means a single stand-alone computing device. "Server" means a set of Designated Processors that hosts (physically or virtually) a software application to be accessed by multiple users. "Instance" means a single copy of the Software executing at a particular time: (i) on one physical machine; or (ii) on one deployed software virtual machine ("VM") or similar deployment.

### License type(s)

Designated System(s) License (DS). End User may install and use each copy or an Instance of the Software only: 1) on a number of Designated Processors up to the number indicated in the order; or 2) up to the number of Instances of the Software as indicated in the order, Documentation, or as authorized by Extreme Networks in writing. Extreme Networks may require the Designated Processor(s) to be identified in the order by type, serial number, feature key, Instance, location or other specific designation, or to be provided by End User to Extreme Networks through electronic means established by Extreme Networks specifically for this purpose.

### Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation, Software, Hosted Service, or hardware provided by Extreme Networks. All content on this site, the documentation, Hosted Service, and the product provided by Extreme Networks including the selection, arrangement and design of the content is owned either by Extreme Networks or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part,

including any code and software unless expressly authorized by Extreme Networks. Unauthorized reproduction, transmission, dissemination, storage, and or use without the express written consent of Extreme Networks can be a criminal, as well as a civil offense under the applicable law.

### Virtualization

The following applies if the product is deployed on a virtual machine. Each product has its own ordering code and license types. Note, unless otherwise stated, that each Instance of a product must be separately licensed and ordered. For example, if the end user customer or Extreme Networks Channel Partner would like to install two Instances of the same type of products, then two products of that type must be ordered.

### Third Party Components

"Third Party Components" mean certain software programs or portions thereof included in the Software or Hosted Service may contain software (including open source software) distributed under third party agreements ("Third Party Components"), which contain terms regarding the rights to use certain portions of the Software ("Third Party Terms"). As required, information regarding distributed Linux OS source code (for those products that have distributed Linux OS source code) and identifying the copyright holders of the Third Party Components and the Third Party Terms that apply is available in the products, Documentation or on Extreme Networks' website at: <http://www.extremenetworks.com/support/policies/software-licensing> or such successor site as designated by Extreme Networks. The open source software license terms provided as Third Party Terms are consistent with the license rights granted in these Software License Terms, and may contain additional rights benefiting You, such as modification and distribution of the open source software. The Third Party Terms shall take precedence over these Software License Terms, solely with respect to the applicable Third Party Components to the extent that these Software License Terms impose greater restrictions on You than the applicable Third Party Terms.

The following applies only if the H.264 (AVC) codec is distributed with the product. THIS PRODUCT IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO (i) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR (ii) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE [HTTP://WWW.MPEGLA.COM](http://WWW.MPEGLA.COM).

### Service Provider

THE FOLLOWING APPLIES TO EXTREME NETWORKS CHANNEL PARTNER'S HOSTING OF EXTREME NETWORKS PRODUCTS OR SERVICES. THE PRODUCT OR HOSTED SERVICE MAY USE THIRD PARTY COMPONENTS SUBJECT TO THIRD PARTY TERMS AND REQUIRE A SERVICE PROVIDER TO BE INDEPENDENTLY LICENSED DIRECTLY FROM THE THIRD PARTY SUPPLIER. AN EXTREME NETWORKS CHANNEL PARTNER'S HOSTING OF EXTREME NETWORKS PRODUCTS MUST BE AUTHORIZED IN WRITING BY EXTREME NETWORKS AND IF THOSE HOSTED PRODUCTS USE OR EMBED CERTAIN THIRD PARTY SOFTWARE, INCLUDING BUT NOT LIMITED TO MICROSOFT SOFTWARE OR CODECS, THE EXTREME NETWORKS CHANNEL PARTNER IS REQUIRED TO INDEPENDENTLY OBTAIN ANY APPLICABLE LICENSE AGREEMENTS, AT THE EXTREME NETWORKS CHANNEL PARTNER'S EXPENSE, DIRECTLY FROM THE APPLICABLE THIRD PARTY SUPPLIER.

WITH RESPECT TO CODECS, IF THE EXTREME NETWORKS CHANNEL PARTNER IS HOSTING ANY PRODUCTS THAT USE OR EMBED THE G.729 CODEC, H.264 CODEC, OR H.265 CODEC, THE EXTREME NETWORKS CHANNEL PARTNER ACKNOWLEDGES AND AGREES THE EXTREME NETWORKS CHANNEL PARTNER IS RESPONSIBLE FOR ANY AND ALL RELATED FEES AND/OR ROYALTIES. THE G.729 CODEC IS LICENSED BY SIPRO LAB TELECOM INC. SEE [WWW.SIPRO.COM/CONTACT.HTML](http://WWW.SIPRO.COM/CONTACT.HTML). THE H.264 (AVC) CODEC IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR

THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO: (I) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR (II) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION FOR H.264 (AVC) AND H.265 (HEVC) CODECS MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE [HTTP://WWW.MPEGLA.COM](http://WWW.MPEGLA.COM).

### Compliance with Laws

You acknowledge and agree that it is Your responsibility for complying with any applicable laws and regulations, including, but not limited to laws and regulations related to call recording, data privacy, intellectual property, trade secret, fraud, and music performance rights, in the country or territory where the Extreme Networks product is used.

### Preventing Toll Fraud

"Toll Fraud" is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there can be a risk of Toll Fraud associated with your system and that, if Toll Fraud occurs, it can result in substantial additional charges for your telecommunications services.

### Security Vulnerabilities

Information about Extreme Networks' security support policies can be found in the Global Technical Assistance Center Knowledgebase at <https://gtacknowledge.extremenetworks.com/>.

### Downloading Documentation

For the most current versions of Documentation, see the Extreme Networks Support website: <http://documentation.extremenetworks.com>, or such successor site as designated by Extreme Networks.

### Contact Extreme Networks Support

See the Extreme Networks Support website: <http://www.extremenetworks.com/support> for product or Hosted Service notices and articles, or to report a problem with your Extreme Networks product or Hosted Service. For a list of support telephone numbers and contact addresses, go to the Extreme Networks Support website: <http://www.extremenetworks.com/support/contact/> (or such successor site as designated by Extreme Networks), scroll to the bottom of the page, and select Contact Extreme Networks Support.

### Contact Avaya Support

See the Avaya Support website: <https://support.avaya.com> for product or Hosted Service notices and articles, or to report a problem with your Avaya product or Hosted Service. For a list of support telephone numbers and contact addresses, go to the Avaya Support website: <https://support.avaya.com> (or such successor site as designated by Avaya), scroll to the bottom of the page, and select Contact Avaya Support.

### Trademarks

The trademarks, logos and service marks ("Marks") displayed in this site, the Documentation, Hosted Service(s), and product(s) provided by Extreme Networks are the registered or unregistered Marks of Extreme Networks, Inc., its affiliates, its licensors, its suppliers, or other third parties. Users are not permitted to use such Marks without prior written consent from Extreme Networks or such third party which may own the Mark. Nothing contained in this site, the Documentation, Hosted Service(s) and product(s) should be construed as granting, by implication, estoppel, or otherwise, any license or right in and to the Marks without the express written permission of Extreme Networks or the applicable third party.

Extreme Networks is a registered trademark of Extreme Networks, Inc.

All non-Extreme Networks trademarks are the property of their respective owners. Linux® is the registered trademark of Linus Torvalds in the U.S. and other countries.

For additional information on Extreme Networks trademarks, please see: <http://www.extremenetworks.com/company/legal/>

# Contents

<b>Chapter 1: Preface</b> .....	9
Purpose.....	9
Training.....	9
Providing Feedback to Us.....	9
Getting Help.....	10
Extreme Networks Documentation.....	11
Subscribing to Service Notifications.....	11
<b>Chapter 2: New in this document</b> .....	12
Notice about feature support.....	12
<b>Chapter 3: QoS fundamentals</b> .....	13
Introduction to QoS.....	13
Traffic management.....	14
Differentiated Services (DiffServ).....	15
Traffic traversing the switch.....	17
Classification and mapping.....	17
Service classes.....	18
Internal QoS level.....	20
Ingress mappings.....	20
Egress mappings.....	24
Ingress port-rate limiting and shaping.....	25
Ingress port-rate limiter.....	26
Queuing.....	27
Queue profiles.....	27
Configuration considerations.....	28
QoS support for 10 GbE interface in 1GbE mode.....	28
Layer 2 and Layer 3 trusted and untrusted ports.....	29
Broadcast and multicast traffic bandwidth limiters per ingress port.....	30
QoS and VoIP.....	30
QoS re-marking on a Transparent Port UNI.....	31
QoS and channelization.....	32
<b>Chapter 4: Traffic filtering fundamentals</b> .....	33
Overview.....	33
QoS and filters.....	33
Access control lists.....	34
Access control entries.....	35
Operators.....	36
Attributes.....	39
Actions.....	40
Internal QoS level and remarking .....	41

Common ACE uses and configuration.....	42
Switched UNI ACL Filters.....	43
Traffic filter configuration.....	44
ACL and ACE configuration guidelines.....	44
ACL filters behavior.....	44
<b>Chapter 5: Basic DiffServ configuration using CLI.....</b>	<b>46</b>
Enabling DiffServ on a port.....	46
Configuring Layer 3 trusted or untrusted ports.....	47
Configuring Layer 2 trusted or untrusted ports.....	48
Viewing the port 802.1p override status.....	49
Configuring the port QoS level.....	50
<b>Chapter 6: Basic DiffServ configuration using EDM.....</b>	<b>51</b>
Enabling DiffServ for a port.....	51
Configuring Layer 3 trusted or untrusted ports.....	52
Configuring Layer 2 trusted or untrusted ports.....	53
Configuring the port QoS level.....	53
<b>Chapter 7: QoS configuration using CLI.....</b>	<b>54</b>
Configuring broadcast and multicast bandwidth limiting.....	54
Viewing the port-based shaper information.....	55
Configuring the port-based shaper.....	55
Configuring a port-based policer.....	56
Variable definitions.....	57
Configuring the ingress port-rate limiter.....	57
Viewing the ingress port-rate limit information.....	58
Configuring ingress mappings.....	59
Configuring egress mappings.....	60
Viewing port egress CoS queue statistics.....	61
Clearing port egress CoS queue statistics.....	63
Viewing CPU queue statistics.....	63
Clearing CPU queue statistics.....	65
Configuring an egress QoS queue profile.....	65
Variable definitions.....	66
<b>Chapter 8: QoS configuration using EDM.....</b>	<b>68</b>
Configuring port-based shaping.....	68
Configuring port-based policing.....	68
Configuring ingress port-rate limiter.....	69
Modifying ingress 802.1p to QoS mappings.....	69
Modifying ingress DSCP to QoS mappings.....	70
Modifying egress QoS to 802.1p mappings.....	71
Modifying egress QoS to DSCP mappings.....	71
Viewing port egress CoS queue statistics.....	72
Clearing CPU statistics for the chassis.....	73
Viewing CPU queue statistics.....	73

Configuring an egress QoS queue profile.....	74
Editing queue profile information.....	74
<b>Chapter 9: Access control list configuration using CLI.....</b>	<b>76</b>
Creating an IPv4 ACL.....	77
Creating an IPv6 ACL.....	78
Associating VLANs with an ACL.....	79
Associating ports with an ACL.....	80
Configuring global and default actions for an ACL.....	81
Renaming an ACL.....	82
Disabling an ACL.....	83
Resetting an ACL to default values.....	84
Deleting an ACL.....	84
<b>Chapter 10: Access control list configuration using EDM.....</b>	<b>86</b>
Configuring an access control list.....	86
<b>Chapter 11: Access control entry configuration using CLI.....</b>	<b>88</b>
Configuring ACEs.....	88
Configuring ACE actions.....	90
Configuring ARP ACEs.....	95
Configuring an Ethernet ACE.....	96
Configuring an IP ACE.....	98
Configuring an IPv6 ACE.....	101
Configuring a protocol ACE.....	102
Viewing ACL and ACE configuration data.....	105
<b>Chapter 12: Access control entry configuration using EDM.....</b>	<b>107</b>
Configuring an ACE.....	107
Configuring ACE actions.....	109
Configuring ACE ARP entries.....	110
Viewing all ACE ARP entries for an ACL.....	111
Configuring an ACE Ethernet source address.....	112
Configuring an ACE Ethernet destination address.....	113
Configuring an ACE LAN traffic type.....	114
Configuring an ACE Ethernet VLAN tag priority.....	115
Configuring an ACE Ethernet port.....	116
Configuring an ACE Ethernet VLAN ID.....	117
Viewing all ACE Ethernet entries for an ACL.....	118
Configuring an ACE IP source address.....	120
Configuring an ACE IP destination address.....	121
Configuring an ACE IP DSCP.....	122
Configuring an ACE IP protocol.....	123
Configuring ACE IP options.....	124
Configuring ACE IP fragmentation.....	124
Viewing all ACE IP entries for an ACL.....	126
Configuring an ACE IPv6 source address.....	127

## Contents

Configuring an ACE IPv6 destination address.....	128
Configuring an ACE IPv6 next header.....	129
Configuring an ACE IPv6 traffic class.....	130
Viewing all ACE IPv6 entries for an ACL.....	131
Configuring an ACE source port.....	132
Configuring an ACE ICMPv6 message type.....	135
Configuring an ACE TCP flag.....	136
Viewing all ACE protocol entries for an ACL.....	137
<b>Chapter 13: Common procedures using CLI.....</b>	<b>139</b>
Saving the configuration.....	139
Restarting the platform.....	140
<b>Chapter 14: Common procedures using EDM.....</b>	<b>142</b>
Saving the configuration.....	142
<b>Chapter 15: Advanced filter examples.....</b>	<b>143</b>
ACE filters for secure networks.....	143
<b>Glossary.....</b>	<b>205</b>



# Chapter 1: Preface

---

## Purpose

This document provides information on features in VSP Operating System Software (VOSS). VOSS runs on the following product families:

- Extreme Networks Virtual Services Platform 4000 Series
- Extreme Networks Virtual Services Platform 7200 Series
- Extreme Networks Virtual Services Platform 8000 Series (includes VSP 8200 and VSP 8400 Series)
- Extreme Networks Virtual Services Platform 8600

This document provides conceptual information and configuration instructions to use Quality of Service (QoS) and ACL-based filters on the switches.

For conceptual information and configuration instructions to use Quality of Service (QoS) and ACL-based filters on Virtual Services Platform 4000 Series, see *Configuring QoS and ACL-Based Traffic Filtering*.

Examples and network illustrations in this document may illustrate only one of the supported platforms. Unless otherwise noted, the concept illustrated applies to all supported platforms.

---

## Training

Ongoing product training is available. For more information or to register, you can access the Web site at [www.extremenetworks.com/education/](http://www.extremenetworks.com/education/).

---

## Providing Feedback to Us

We are always striving to improve our documentation and help you work better, so we want to hear from you! We welcome all feedback but especially want to know about:

- Content errors or confusing or conflicting information.
- Ideas for improvements to our documentation so you can find the information you need faster.

- Broken links or usability issues.

If you would like to provide feedback to the Extreme Networks Information Development team about this document, please contact us using our short [online feedback form](#). You can also email us directly at [internalinfodev@extremenetworks.com](mailto:internalinfodev@extremenetworks.com)

---

## Getting Help

### Product purchased from Extreme Networks

If you purchased your product from Extreme Networks, use the following support contact information to get help.

If you require assistance, contact Extreme Networks using one of the following methods:

- [GTAC \(Global Technical Assistance Center\) for Immediate Support](#)
  - Phone: 1-800-998-2408 (toll-free in U.S. and Canada) or +1 408-579-2826. For the support phone number in your country, visit: [www.extremenetworks.com/support/contact](http://www.extremenetworks.com/support/contact)
  - Email: [support@extremenetworks.com](mailto:support@extremenetworks.com). To expedite your message, enter the product name or model number in the subject line.
- [GTAC Knowledge](#) – Get on-demand and tested resolutions from the GTAC Knowledgebase, or create a help case if you need more guidance.
- [The Hub](#) – A forum for Extreme customers to connect with one another, get questions answered, share ideas and feedback, and get problems solved. This community is monitored by Extreme Networks employees, but is not intended to replace specific guidance from GTAC.
- [Support Portal](#) – Manage cases, downloads, service contracts, product licensing, and training and certifications.

Before contacting Extreme Networks for technical support, have the following information ready:

- Your Extreme Networks service contract number and/or serial numbers for all involved Extreme Networks products
- A description of the failure
- A description of any action(s) already taken to resolve the problem
- A description of your network environment (such as layout, cable type, other relevant environmental information)
- Network load at the time of trouble (if known)
- The device history (for example, if you have returned the device before, or if this is a recurring problem)
- Any related RMA (Return Material Authorization) numbers

### Product purchased from Avaya

If you purchased your product from Avaya, use the following support contact information to get help.

Go to the Avaya Support website at <http://support.avaya.com> for the most up-to-date documentation, product notices, and knowledge articles. You can also search for release notes,

downloads, and resolutions to issues. Use the online service request system to create a service request. Chat with live agents to get answers to questions, or request an agent to connect you to a support team if an issue requires additional expertise.

---

## Extreme Networks Documentation

To find Extreme Networks product guides, visit our documentation pages at:

Current Product Documentation	<a href="http://www.extremenetworks.com/documentation/">www.extremenetworks.com/documentation/</a>
Archived Documentation (for previous versions and legacy products)	<a href="http://www.extremenetworks.com/support/documentation-archives/">www.extremenetworks.com/support/documentation-archives/</a>
Release Notes	<a href="http://www.extremenetworks.com/support/release-notes">www.extremenetworks.com/support/release-notes</a>

### Open Source Declarations

Some software files have been licensed under certain open source licenses. More information is available at: [www.extremenetworks.com/support/policies/software-licensing](http://www.extremenetworks.com/support/policies/software-licensing).

---

## Subscribing to Service Notifications

Subscribe to receive an email notification for product and software release announcements, Vulnerability Notices, and Service Notifications.

### About this task

You can modify your product selections at any time.

### Procedure

1. In an Internet browser, go to <http://www.extremenetworks.com/support/service-notification-form/>.
2. Type your first and last name.
3. Type the name of your company.
4. Type your email address.
5. Type your job title.
6. Select the industry in which your company operates.
7. Confirm your geographic information is correct.
8. Select the products for which you would like to receive notifications.
9. Click **Submit**.

# Chapter 2: New in this document

There are no feature changes in this document.

---

## Notice about feature support

This document includes content for multiple hardware platforms across different software releases. As a result, the content can include features not supported by your hardware in the current software release.

If a documented command, parameter, tab, or field does not appear on your hardware, it is not supported.

For information about feature support, see *Release Notes*.

For information about physical hardware restrictions, see your hardware documentation.

# Chapter 3: QoS fundamentals

Use the information in this section to help you understand Quality of Service (QoS).

This section describes a range of features that you can use on the switch to manage traffic flowing through your network. You can configure your network to prioritize specific types of traffic to ensure that the traffic receives the appropriate QoS level. For those cases where traffic levels are so high that congestion occurs despite management, the switch provides additional congestions handling features that are described in this section.

QoS refers to the ability to control network flows either by prioritizing traffic or by guaranteeing performance levels. QoS does not refer to a specifically achieved service quality. To provide QoS, you can use some combination of the switch's traffic management tools to help deliver provisioned network QoS. It is up to the network administrator to accurately analyze a given situation and select the proper tool(s) for the task.

---

## Introduction to QoS

The switch comes with a set of traffic management tools that you can use to provide QoS for Layer 2 (bridged) or Layer 3 (routed) traffic flows. Many of these flows are multiplexed across a set of network switches and compete for network resources at convergence points. Without traffic management, the congested data flows compete for resources and the result is unpredictable. The resulting QoS can only be described as best-effort. The opposite is also true, without congestion there are sufficient network resources for all traffic to pass without competition. Without congestion, traffic management is not required. In this sense, you cannot separate discussions about QoS and traffic management from those on congestion. The switch provides a set of tools that you can use to provide network services that are far superior to best-effort thereby enabling the delivery of provisioned QoS.

To deliver QoS, the switch uses two types of traffic management tools:

- Congestion management
- Congestion handling

**Congestion management** acts to prevent congestion by prioritizing traffic flows through priority queuing and priority-aware servicing methods. Other functions, such as policing, are also considered congestion management. Policing indirectly prioritizes some traffic by limiting the rates of other traffic.

**Congestion handling** alleviates existing congestion by dropping lower priority traffic before higher priority traffic. The switch handles the congestion by queue-specific tail dropping. The basic QoS architecture of the switch identifies three primary functional areas:

- Ingress QoS identification and classification
- the switch's internals and queuing architecture
- QoS marking/remarking for downstream use

**!** **Important:**

Remarking packets with an ACL filter *does not change* the internal QoS level of the packets. You must add the `permit internal-qos [value]` statement to the ACL filter.

The QoS architecture is coherent end-to-end across a network. The QoS at any particular network element can be marked in the relevant Layer 2 or Layer 3 protocol fields and provided to the next hop. The receiving next hop can then use this information to classify its own ingress traffic, apply its specific internal traffic management features, and remark the results for subsequent hops.

The QoS implementation on the switch supports the following options:

1. Ingress priority mappings including: DSCP to internal QoS, 802.1p-bits to internal QoS, and port-level QoS configuration.
2. Egress priority mappings including: internal QoS to DSCP and internal QoS to 802.1p-bits.
3. Automatic QoS
4. Port-based rate limiting
5. Port-based broadcast and multicast rate limiting
6. Port-based egress shaping
7. Egress queue rate limiting

---

## Traffic management

Prioritized traffic handling requires QoS classification first. The switch typically classifies traffic by using the endpoint switch configuration in conjunction with the protocol elements of the incoming frame such as *priority*. You can add additional classification by using access control lists (ACLs) and other filtering functionality.

The switch's internal traffic management functions use the results of classification to determine the prioritization of traffic. Examples of internal functions that prioritize traffic would be both strict and weighted round robin (WRR) queue scheduling. These mechanisms prioritize data by favorable scheduling or weighting.

The disposition of a particular data frame is not necessarily fully determined as a result of classification. You can apply additional traffic management functions such as **Ingress Port Rate Limiting**, which is a congestion management mechanism to limit the traffic rate accepted by the specified ingress port.

In addition to the traffic management tools which aid in the prevention of congestion, tools are also provided to handle congestion as it occurs. Congestion handling tools monitor congestion levels at convergence points in the switch and selectively discard frames if congestion begins to increase.

Per queue tail dropping is the primary congestion handling function of the switch. you can also use ACLs and filtering as congestion handling tools.

## Differentiated Services (DiffServ)

Differentiated Services (DiffServ) is a traffic management tool that classifies network traffic into eight traffic classes, and then gives each class differentiated treatment. DiffServ networks map the traffic's class into a set of packet forwarding behavior, referred to as a *Per-Hop Behavior (PHB)*. A PHB could specify which egress queue to use. For example, a switch may classify a packet by determining its protocol to be IPv4, subsequently extract the DSCP value, and apply a PHB by directing the packet to a specific queue. DiffServ does not prescribe a set of traffic classes and does not predetermine which types of traffic should be handled by a given class. DiffServ simply provides a generic means of classifying packets so they may be treated differently.

DiffServ applies to IP packets only.

### DiffServ Access and DiffServ Core


A fundamental characteristic of DiffServ networks is the distinction made between switches at the network edges and those residing in the network interior. The switch refers to this distinction as DiffServ Access (edge) and DiffServ Core (interior), respectively.

It is important to note that the switch operates simultaneously as both a DiffServ Access switch and a DiffServ Core switch. The architectural premise is that the edge or access nodes perform the bulk of the work (classification, policing, etc.) and mark the packet for downstream processing. In theory this would permit the interior or core switches to bypass much of the edge processing as they would "trust" the classification and marking performed by the access switch. The notion of trust is key to the access/core switch distinction.

- If you configure a port as an access port, the system does not trust packet markings.
- If you configure a port as a core port, the system trusts packet markings.

On the access side, malicious users can send packets into a network with intent to cause serious harm (e.g., denial of service attacks). However, on core switches, the only traffic sources are one's own upstream switches. As such, a core switch has the opportunity to trust the classification, markings (and implied PHB) determined by the previous hop.

The following figure shows DiffServ network operations. The devices are on the network edge where they perform classification, marking, policing, and shaping functions.



**Figure 1: DiffServ network core and edge devices**

Use a DiffServ Access port at the edge of a DiffServ network. The access port classifies traffic according to port QoS. Outgoing packet DSCP and 802.1p values are derived from port QoS and QoS maps. The system strips Dot1Q headers at ingress, and adds them back at egress only if you configure the egress port as a tagged or trunk port.

A DiffServ Core port does not change packet classification or markings; the port trusts the incoming traffic markings. A core port preserves the DSCP marking of all incoming packets, and uses these markings to assign the packet to an internal QoS level. For tagged packets, the port honors the 802.1p bits within a Dot1Q header, and uses these bits to classify ingress traffic. You can control the honoring (or not) of 802.1p bits by configuring the 802.1p override in CLI or Enterprise Device Manager (EDM).

### Per-Hop Behavior (PHB)

Traffic entering the DiffServ network enter a queue according to their marking, which determines the PHB of the packets. For example, if the system marks a video stream to receive the highest priority, it enters a high-priority queue. As these packets traverse the DiffServ network, the system forwards the video stream before other packets.

As a standard, DiffServ is described in the context of Layer 3. Classification is accomplished by mapping a packet priority field from the packet and then applying a per-hop behavior. DiffServ standards define the IPv4 header's Differentiated Services Code Point (DSCP) field to determine classification and subsequent per-hop behavior.

The RFC2598 standard provides only the following four fundamental per-hop behaviors:

- Default (DF) — This PHB provides best-effort forwarding behavior.
- Expedited Forwarding (EF) — This PHB provides performance-critical forwarding.
- Assured Forwarding (AF) — This PHB classifies traffic based upon **class** (priority) only.

#### Important:

The switch never classifies nor takes action based upon drop precedence. In response to congestion, the only drops available for a given traffic class are tail drops.

- Class Selector (CS) — This PHB provides a simple mapping of a DSCP to one of eight traffic classes. While the switch provides all four PHBs, the CS PHB is most analogous to the switch's internal processing – classification occurs to derive priority, which subsequently determine the per-hop behavior (e.g., queuing).

### DiffServ and filters

QoS (DiffServ) and filters operate independently; you do not have to use filters to provide QoS. However, filters can override QoS operations. For more information, see Traffic filtering fundamentals.

### DiffServ and VXLAN Gateway

DSCP bits in the outer IP header of VXLAN-encapsulated packets are always derived from the internal QoS, irrespective of the ingress port DiffServ configuration. Customer packet IP DSCP bits are not modified as part of VXLAN encapsulation. For more information about VXLAN, see *Configuring VLANs, Spanning Tree, and NLB*.



---

## Traffic traversing the switch

The switch's traffic management capabilities are best understood by examining the functionality that is invoked as packets flow from ingress ports, through the switch, to egress ports. The following list includes the set of features and processing that the switch performs as flows traverse the switch:

- Classification and ingress mapping
- Filtering
- Rate Limiting
- Queueing
- Remarking
- Shaping

The switch classifies packets to determine their priority. While DiffServ is traditionally defined as Layer 3 functionality, the switch extends the logical concept to Layer 2. The switch can, based upon user configuration, determine a packet's priority from either its Layer 2 (p-bits) or Layer 3 (DSCP) information.

- If the packet arrives on an untrusted port (DiffServ Access), then the packet's priority comes from user-configured parameters such as port priority.
- If the packet arrives on a trusted port, priority comes from information contained in the packet's header (p-bits or DSCP).

After the switch determines the packet's configured or marked priority, it maps that value to be used internally. The QoS level used by the switch is referred to as the **Internal QoS Level (IQL)**. The IQL is the internal numerical value that the switch uses to determine the packets per-hop behaviors such as queue selection and bandwidth guarantee.

The following list identifies the order of DiffServ operations for a packet:

- Packet classification: IEEE 802.1p and DSCP markings classify (map) the packet to its appropriate PHB and QoS level.
- Remarking: The switch can remark packets according to QoS actions you configure on the switch (internal QoS mappings).
- Shaping: The switch provides port-based shaping. Port-based shaping shapes all outgoing traffic to a specific rate.

---

## Classification and mapping

Traffic classification includes functions that examine a packet to determine further actions according to defined rules. Classification involves identifying flows so that the router can modify the packet contents or Per-Hop Behavior (PHB), apply conditioning treatments to the packet, and determine how to forward the packet to the egress interface. Packet classification depends on the service type of the packet and the point in the traffic management process where the classification occurs.

The device classifies traffic as it enters the DiffServ network, and assigns appropriate PHB based on the classification. To differentiate between classes of service, the device marks the DiffServ (DS)

parameter in the IP packet header, as defined in RFC2474 and RFC2475. The DSCP marking defines the forwarding treatment of the packet at each network hop. This marking (or classification) occurs at the edge of the DiffServ domain, and is based on the policy (or filter) associated with the particular microflow or aggregate flow.

You can configure the mapping of DSCP-to-forwarding behaviors and DSCP re-markings. Re-marking the DSCP resets the treatment of packets based on new network specifications or desired levels of service.

Layer 3 marking uses the DSCP parameter. Layer 2 (Ethernet) marking involves the 802.1p-bits parameter.

For Layer 2 packets, priority bits (or 802.1p bits) define the traffic priority of the Ethernet packet. You can configure an interface to map DSCP or 802.1p bits to internal QoS levels on ingress. You can configure an interface to map internal QoS levels to DSCP or 802.1p bits at egress. 802.1p bit mapping provides the Ethernet VLAN QoS requirements.

Within the network, a packet PHB associated with the DSCP determines how a device forwards the packet to the next hop—if at all. Consequently, nodes can allocate buffer and bandwidth resources to each competing traffic stream. The initial DSCP value is based on network policies for the type of service required. The objective of DSCP-to-Service Class mapping is to translate the QoS characteristics defined by the packet DSCP marker to a Service Class. The DSCP-to-Service Class mapping occurs at ingress. For each received packet, the mapping function assigns a Service Class.

The switch maintains four mapping tables. These tables translate the ingress 802.1p-bits or DSCP markings to an internal QoS level, and then retranslate the internal QoS level to an egress DSCP or 802.1p-bits marking as follows:

- ingress 802.1p-bits to QoS level
- ingress DSCP to QoS level
- QoS level to egress 802.1p-bits
- QoS level to egress DSCP

---

## Service classes

Service classes define a standard architecture to provide end-to-end QoS on a broad range of Ethernet switching and voice products. They function as default QoS policies built into the product. They incorporate the various QoS technologies to provide a complete end-to-end QoS behavioral treatment. The switch includes a built-in QoS implementation for service classes.

The switch includes eight preconfigured queues (corresponding to the eight service classes) on each port of an interface module.

A service class domain classifies traffic as one of the following:

- Network control traffic (Critical/Network)
- Subscriber traffic (Premium, Metal, or Standard)

### Queue 7 — Critical/Network Service Class (PHB of CS6/CS7)

The switch uses the Critical/Network Service Class for traffic within a single administrative network domain. If such traffic does not get through, the network cannot function.

## Queue 6 — Premium Service Class (PHB of CS5/EF)

The switch uses the Premium Service Class for IP telephony services, and provides the low latency and low jitter required to support such services. IP telephony services include Voice over IP (VoIP), voice signaling, Fax over IP (FoIP), and voice-band data services over IP (for example, analog modem). The switch can also use the Premium Service Class for Circuit Emulation Services over IP (CESoIP).

## Metal Service Classes

The Platinum, Gold, Silver, and Bronze Service Classes are collectively referred to as the metal classes. The metal Service Classes provide a minimum bandwidth guarantee and are for variable bit rate or bursty types of traffic. Applications that use the metal Service Class support mechanisms that dynamically adjust their transmit rate and burst size based on congestion (packet loss) detected in the network. The following list describes the individual metal classes:

- Queue 5 — Platinum Service Class (PHB of CS4/AF41)

The switch uses the Platinum Service Class for applications that require low latency, for example, real-time services such as video conferencing and interactive gaming. Platinum Service Class traffic provides the low latency required for interhuman (interactive) communications. The Platinum Service Class provides a minimum bandwidth assurance for Assured Forwarding (AF) 41 and Class Selector (CS) 4-marked flows.

- Queue 4 — Gold Service Class (PHB of CS3/AF31)

The switch uses the Gold Service Class for applications that require near-real-time service and are not as delay-sensitive as applications that use the Platinum service. Such applications include streaming audio and video, video on demand, and surveillance video.

The Gold Service Class assumes that traffic buffers at the source and destination and, therefore, the traffic is less sensitive to delay and jitter. By default, the Gold Service Class provides a minimum bandwidth assurance for AF31, AF32, AF33 and CS3-marked flows.

- Queue 3— Silver Service Class (PHB of CS2/AF21)

The switch uses the Silver Service Class for responsive (typically client- and server-based) applications. Such applications include Systems Network Architecture (SNA) terminals (for example, a PC or Automatic Teller Machine) to mainframe (host) transactions that use Data Link Switching (SNA over IP), Telnet sessions, web-based ordering and credit card processing, financial wire transfers, and Enterprise Resource Planning applications.

Silver Service Class applications require a fast response and have asymmetrical bandwidth needs. The client sends a short message to the server and the server responds with a much larger data flow back to the client. For example, after a user clicks a hyperlink (that sends a few dozen bytes) on a webpage, a new webpage appears (that downloads kilobytes of data). The Silver Service Class provides a minimum bandwidth assurance for AF21 and CS2-marked flows.

The Silver Service Class favors short-lived, low-bandwidth TCP-based flows.

- Queue 2 — Bronze Service Class (PHB of CS1/AF11)

The switch uses the Bronze Service Class for longer-lived TCP-based flows, such as file transfers, e-mail, or noncritical Operation, Administration, and Maintenance (OAM) traffic. The Bronze Service Class provides a minimum bandwidth assurance for AF11 and CS1-marked flows. It is recommended that you use the Bronze Service Class for noncritical OAM traffic with the CS1 DSCP marking.

## Queue 1 and 0 — Standard (PHB of CS0/DF) and Custom Service Classes

The switch uses the Standard and Custom Service Classes for best-effort services. Delays, loss, or jitter guarantees for these service classes are not specified. However, the Standard Service Class has more forwarding resources than the custom service classes.

## Internal QoS level

The internal QoS level or effective QoS level is a key element in the switch QoS architecture. The internal QoS level specifies the kind of treatment a packet receives. The switch classifies every packet that enters and assigns it an internal QoS level.

Internal QoS levels map to the queues on a port. For example, for an access port the internal QoS level is derived from the port QoS level. For Layer 3 trusted (core) ports, the system honors incoming DSCP or type of service (TOS) bits. The system assigns the internal QoS level using the ingress DSCP to QoS level map.

### Important:

Remarking packets with an ACL filter *does not change* the internal QoS level of the packets. You must add the `permit internal-qos [value]` statement to the ACL filter. For more information, see [Internal QoS level and remarking](#) on page 41.

## Ingress mappings

The system uses ingress maps to translate incoming packet QoS markings to the internal QoS level. The system uses the internal QoS level to classify packets.

Ingress mappings include

- 802.1p to (internal) QoS level
- DSCP to (internal) QoS level

The following logical table shows how the system performs ingress mappings for data packets and for control packets not destined for the Control Processor (CP).

**Table 1: Data packet ingress mapping**

DSCP	Layer 2 trusted	Layer 3 trusted (DiffServ enabled and Access-diffserv disabled)	IP packet	Routed packet	Ingress tagged	Internal QoS
x	No	x	No	x	x	Use port QoS

*Table continues...*

DSCP	Layer 2 trusted	Layer 3 trusted (DiffServ enabled and Access-diffserv disabled)	IP packet	Routed packet	Ingress tagged	Internal QoS
x	Yes	x	No	x	No	Use port QoS
x	Yes	x	No	x	Yes	Use ingress p-bits mapping
0x1B	x	x	Yes	x	x	4
0x23	x	x	Yes	x	x	5
0x29	x	x	Yes	x	x	5
0x2F	x	x	Yes	x	x	6
x	No	No	x	x	x	Use port QoS
x	No	Yes	Yes	x	x	Use ingress DSCP mapping
x	Yes	No	Yes	x	No	Use port QoS
x	Yes	No	Yes	x	Yes	Use ingress p-bits mapping
x	Yes	Yes	Yes	No	No	Use ingress DSCP mapping
x	Yes	Yes	Yes	No	Yes	Use ingress p-bits mapping
x	Yes	Yes	Yes	Yes	Yes	Use ingress DSCP mapping

**! Important:**

On a tagged port that is Layer-2 trusted, Layer-3 trusted and DiffServ enabled, all multicast packets honor the ingress DSCP value.

The QoS level for control packets destined for the CPU is assigned internally to ensure timely packet processing and scaling numbers. You cannot configure the QoS level for these control packets. The system assigns the highest QoS-level to time-critical protocols.

The following table shows ingress IEEE 802.1p to QoS level mappings.

**Table 2: Default ingress 802.1p to QoS mappings**

Ingress IEEE 802.1p	PHB	QoS Level	Network Service Class (NSC)
0	CS0/DF	1	Standard
1	Custom	0	Custom
2	CS1/AF11	2	Bronze
3	CS2/AF21	3	Silver
4	CS3/AF31	4	Gold
5	CS4/AF41	5	Platinum
6	CS5/EF	6	Premium/EF
7	CS6/CS7	7	Network/Critical

The following table shows DSCP to internal QoS level mappings.

**Table 3: Default ingress DSCP to QoS mapping**

Ingress				Internal QoS level	PHB level
DSCP (decimal)	DSCP (binary)	DSCP (hexadecimal)	TOS (hexadecimal)		
00	000000	00	00	1	CS0/DF
00	000000	00	00	1	DF
01	000001	01	04	1	CS0
02	000010	02	08	1	CS0
03	000011	03	0C	1	CS0
04	000100	04	10	1	CS0
05	000101	05	14	1	CS0
06	000110	06	18	1	CS0
07	000111	07	1C	1	CS0
08	001000	08	20	2	CS1
09	001001	09	24	1	CS0
10	001010	0A	28	2	AF11
11	001011	0B	2C	1	CS0
12	001100	0C	30	2	CS1
13	001101	0D	34	1	CS0
14	001110	0E	38	2	CS1
15	001111	0F	3C	1	CS0
16	010000	10	40	3	CS2

*Table continues...*

Ingress				Internal QoS level	PHB level
DSCP (decimal)	DSCP (binary)	DSCP (hexadecimal)	TOS (hexadecimal)		
17	010001	11	44	1	CS0
18	010010	12	48	3	AF21
19	010011	13	4C	1	CS0
20	010100	14	50	3	CS2
21	010101	15	54	1	CS0
22	010110	16	58	3	CS2
23	010111	17	5C	1	CS0
24	011000	18	60	4	CS3
25	011001	19	64	1	CS0
26	011010	1A	68	4	AF31
27	011011	1B	6C	4	CS3
28	011100	1C	70	4	CS3
29	011101	1D	74	1	CS0
30	011110	1E	78	4	CS3
31	011111	1F	7C	1	CS0
32	100000	20	80	5	CS4
33	100001	21	84	1	CS0
34	100010	22	88	5	AF41
35	100011	23	8C	5	CS4
36	100100	24	90	5	CS4
37	100101	25	94	1	CS0
38	100110	26	98	5	CS4
39	100111	27	9C	1	CS0
40	101000	28	A0	6	CS5
41	101001	29	A4	5	CS4
42	101010	2A	A8	1	CS0
43	101011	2B	AC	1	CS0
44	101100	2C	B0	1	CS0
45	101101	2D	B4	1	CS0
46	101110	2E	B8	6	EF
47	101111	2F	BC	6	CS5
48	110000	30	C0	7	CS6

Table continues...

Ingress				Internal QoS level	PHB level
DSCP (decimal)	DSCP (binary)	DSCP (hexadecimal)	TOS (hexadecimal)		
49	110001	31	C4	1	CS0
50	110010	32	C8	1	CS0
51	110011	33	CC	1	CS0
52	110100	34	D0	1	CS0
53	110101	35	D4	1	CS0
54	110110	36	D8	1	CS0
55	110111	37	DC	1	CS0
56	111000	38	E0	7	CS7
57	111001	39	E4	1	CS0
58	111010	3A	E8	1	CS0
59	111011	3B	EC	1	CS0
60	111100	3C	F0	1	CS0
61	111101	3D	F4	1	CS0
62	111110	3E	F8	1	CS0
63	111111	3F	FC	1	CS0

---

## Egress mappings

Egress mappings include:

- QoS level to IEEE 802.1p mappings
- QoS level to DSCP mappings

When a packet is forwarded by the switch, the software does the following:

- Always performs 802.1p remarking before the packet egresses.
- If the ingress port has **enable-diffserv** and **access-diffserv** enabled, then the IP packet is DSCP remarked before the packet egresses.

If the ingress port is not configured this way, the packets are not DSCP remarked.

The following table shows egress QoS level to IEEE 802.1p mappings.



**Table 4: Default egress QoS level to IEEE 802.1p mappings**

QoS level	PHB	Default 1p remarking on egress	Network Service Class (NSC)
0	Custom	1	Custom
1	CS0/DF	0	Standard
2	CS1/AF11	2	Bronze
3	CS2/AF21	3	Silver
4	CS3/AF31	4	Gold
5	CS4/AF41	5	Platinum
6	CS5/EF	6	Premium/EF
7	CS6/CS7	7	Network/Critical

The following table shows QoS level to DSCP mappings.

**Table 5: Default egress QoS level to DSCP mappings**

Egress			
QoS level	DSCP (binary)	DSCP (hexadecimal)	DSCP
0	000000	00	0
1	000000	00	0
2	001010	0A	10
3	010010	12	18
4	011010	1A	26
5	100010	22	34
6	101110	2E	46
7	101110	2E	46

---

## Ingress port-rate limiting and shaping

The switch QoS implementation supports the following two features for bandwidth management and traffic control:

- ingress port-rate limiting—a mechanism to limit the traffic rate accepted by the specified ingress port
- egress traffic shaping—the process by which the system delays and transmits packets to produce an even and predictable flow rate

Each port has eight unicast and multicast queues, Class of Service (CoS) 0 to CoS 7. No traffic shaping exists on CoS 0 to CoS 5. Traffic shaping exists on the egress CoS 6 and CoS 7, but you cannot change the configuration. CoS 6 and CoS 7 are strict priority queues, and the

switch subjects CoS 6 and CoS 7 to traffic shaping at 50 per cent and five per cent of line rate respectively.

You can also configure egress shaping for each port on a port level.

Each feature is important to deliver DiffServ within a QoS network domain.

### Token buckets

Tokens are a key concept in traffic control. A port-rate limiter or shaper calculates the number of packets that passed, and at what data rate. Each packet corresponds to a token, and the port-rate limiter or shaper transmits or passes the packet if the token is available. For more information, see [Figure 2: Token flow](#) on page 26.

The token container is like a bucket. In this view, the bucket represents both the number of tokens that a port-rate limiter or shaper can use instantaneously (the depth of the bucket) and the rate at which the tokens replenish (how fast the bucket refills).

Each policer has two token buckets: one for the peak rate and the other for the service rate. The following figure shows the flow of tokens.




Figure 2: Token flow

## Ingress port-rate limiter

Ingress port-rate limiter limits the traffic rate accepted by the specified ingress port. The port drops or re-marks violating traffic. The line rate of the port is the maximum rate that can be set.

For more information on ingress port-rate limiter, see:

- [Viewing the ingress port-rate limit information](#) on page 58

- [Configuring the ingress port-rate limiter](#) on page 57

---

## Queuing

Queuing is a congestion-avoidance function that prioritizes packet delivery. Queuing ensures discriminate packet discard during network congestion, and can delay a packet in memory until the scheduled transmission.

You can use queuing to manage congestion. Congestion management involves the creation of queues, assignment of packets to the queues based on the classification of the packet, and scheduling of the packets in a queue for transmission.

The system schedules packets for transmission according to their assigned priority and the queuing mechanism configured for the interface. The scheduler determines the order of packet transmission by controlling how the system services queues with respect to each other. The switch uses 16 CPU queues (used by traffic destined to the CPU), and eight unicast and eight multicast queues for each port. The deepest queue does not go beyond 60,000 packets.

A scheduler services the eight queues for each port, using a combination of strict priority and round-robin. Queue zero through five use round robin, and queues six and seven drain completely, or up to certain rate limits.

There are eight priorities on each egress port. Class of Service (CoS) 0 to CoS 5 are Weighted Round Robin (WRR), and the default weights are 5, 20, 30, 40, 50, 50 respectively. CoS 6 and CoS 7 are strict priority queues, and the switch subjects CoS 6 and CoS 7 to traffic shaping at 50 per cent and five per cent of line rate respectively.

The current release does not support Weighted Random Early Detection (WRED).

---

## Queue profiles

This section identifies optional ways to customize the egress queues and scheduling depending on your need to override the default configuration. You can also enable **egress** queue rate limiting, if desired.

Use a queue profile to apply configured egress queue parameters and modify each queue individually. You can use the queue profile to configure a minimum weight for the queue and to enable rate limiting for the queue. The queue profile applies to all ports in the switch.

Currently the switch supports only one queue profile that is automatically created on system boot up, with an ID of 1 and name of default. You cannot delete this profile.

### **Note:**

The egress queues with rate limiting enabled must be **contiguous**. For example, you can configure queues 3–6, but you cannot configure 3 and 6.

After you make a configuration change to a queue profile, you must apply the profile before the changes take effect.

---

## Configuration considerations

If you modify the QoS configuration for a port that is a member of MultiLink Trunking (MLT), all ports in the MLT inherit the same configuration. If you remove the port from the MLT, it keeps the QoS configuration it inherited from the MLT.

---

## QoS support for 10 GbE interface in 1GbE mode

If you use QoS with a 10 gigabit Ethernet (GbE) interface and re-purpose the interface as a 1 GbE interface, you must make the necessary configuration changes to accommodate the new link speed.

Check your rate limiting and shaping settings, if you choose to change the port link speed from 10 GbE to 1 GbE.

Review the following commands to ensure proper configuration for the port speed you use.

Command	Description
<code>qos if-rate-limiting [port {slot/port}] rate &lt;1000-40000000&gt;</code>	Configures ingress port rate limiting in kbps.
<code>rate-limit broadcast {&lt;1-65535&gt;   &lt;50-65000000&gt;}</code>	Configures ingress port broadcast rate limiting in packets/second.  * <b>Note:</b> The range can vary depending on your hardware platform.
<code>rate-limit multicast {&lt;1-65535&gt;   &lt;50-65000000&gt;}</code>	Configures ingress port multicast rate limiting in packets/second.  * <b>Note:</b> The range can vary depending on your hardware platform.
<code>qos if-shaper [port {slot/port}] shape- rate {&lt;64-10000000&gt;   &lt;64-100000000&gt;}</code>	Configures egress port shaping in kbps.  * <b>Note:</b> The range can vary depending on your hardware platform.

## Layer 2 and Layer 3 trusted and untrusted ports

You can configure interface module ports as trusted or untrusted at both Layer 2 (802.1p) or Layer 3 (DSCP) for ingress packet classification.

The switch provides eight internal QoS levels. These eight levels, numbered zero to seven, map to the queues through

- the ingress 8021p to (internal) QoS mapping table
- the ingress DSCP to (internal) QoS mapping table

To configure a port as trusted or untrusted, use the commands and the parameter values as shown in the following tables:

Layer 2 Trusted		Layer 2 Untrusted	
<b>802.1p-override</b>		<b>802.1p-override</b>	
disable		enable	

Layer 3 Trusted		Layer 3 Untrusted	
<b>enable-diffserv</b>	<b>access-diffserv *</b>	<b>enable-diffserv</b>	<b>access-diffserv *</b>
enable	disable	disable	disable
		disable	enable
		enable	enable **

\* — Configure **access-diffserv** as either a core or access port. If enabled, this command specifies an access port and overrides incoming DSCP bits. If disabled, it specifies a core port that honors and services incoming DSCP bits.

\*\* — If the ingress port has **enable-diffserv** and **access-diffserv** enabled, then the packet is DSCP remarked at egress.

### Layer 2 untrusted and Layer 3 untrusted

To configure a port as Layer 2 untrusted and Layer 3 untrusted, refer to the tables above and assign the parameter values accordingly.

For more information, see [Table 1: Data packet ingress mapping](#) on page 20.

### Layer 2 untrusted and Layer 3 trusted

To configure a port as Layer 2 untrusted and Layer 3 trusted, refer to the tables above and assign the parameter values accordingly.

Use these configuration options to classify packet QoS through the DSCP parameter for all IP packets, whether tagged or untagged. Use this configuration when another QoS or DiffServ enabled and configured switch marks the IP packets at the edge. These already-marked packets arrive Layer 3 trusted, and the switch continues with the trust (DiffServ core port operation). For tagged packets, the system does not examine the 802.1p bits. For non-IP packets, this configuration causes classification by port QoS settings.

For more information, see [Table 1: Data packet ingress mapping](#) on page 20.

### **Layer 2 trusted and Layer 3 trusted**

To configure a port as Layer 2 trusted and Layer 3 trusted, refer to the tables above and assign the parameter values accordingly.

Use these configuration options to classify packet QoS through DSCP for all IP packets, and through 802.1p for all tagged non IP packets. If it is an IP packet, DSCP is used. If it is a tagged non IP packet, 802.1p bits are used. If it is an untagged non IP packet, the port QoS is used.

For more information, see [Table 1: Data packet ingress mapping](#) on page 20.

### **Layer 2 trusted and Layer 3 untrusted**

To configure a port as Layer 2 trusted and Layer 3 untrusted, refer to the tables above and assign the parameter values accordingly.

Use these configuration options to classify packet QoS through 802.1p for all tagged packets, and port QoS levels for all untagged (IP or non-IP) packets. If the packet is an IP packet, the system does not modify or examine the DSCP parameter bits.

For more information, see [Table 1: Data packet ingress mapping](#) on page 20.

### **DiffServ disabled**

If you disable the DiffServ parameter, the system ignores the Layer 3 DSCP parameter. For more information, see [Table 1: Data packet ingress mapping](#) on page 20.

---

## **Broadcast and multicast traffic bandwidth limiters per ingress port**

Interface modules support bandwidth limiters for ingress broadcast and multicast traffic. The system drops traffic that violates the bandwidth limit. Enable this feature and configure the rate limit on an individual port basis.

---

## **QoS and VoIP**

VoIP traffic requires low latency and jitter.

If you use edge routers, configure ingress ports as core ports to treat VoIP traffic appropriately. In this case, the system trusts QoS markings that apply to VoIP traffic, and the system does not re-mark QoS settings. However, if this configuration is not sufficient, you can also apply filters, route policies, or re-mark traffic.

### **Automatic QoS**

Automatic QoS specifically supports converged voice deployments. Automatic QoS automatically recognizes the DSCP value voice applications can use, and associates these DSCP values with the proper queue.

When you use Automatic QoS, the system recognizes application traffic and prioritizes the traffic through the system. Automatic QoS offers a simplified and resource-efficient mechanism to prioritize application traffic within the network. Automatic QoS supersedes DiffServ mode configuration.

The following table shows the traffic types, the standard DSCP value, the specific Automatic QoS DSCP values, and the queue mappings for the Automatic QoS DSCP values.

**Table 6: Automatic QoS DSCP values**

Traffic type	Automatic QoS DSCP value	Queue
VoIP data (Premium)	0x2F (47)	6
VoIP signaling (Platinum)	0x29 (41)	5
Video (Platinum)	0x23 (35)	5
Streaming (Gold)	0x1B (27)	4

The traffic that the system identifies, based on these DSCP values, receives preferential queuing treatment within the system and is re-marked for preferential downstream processing.

The system associates additional filtering (ACL filters) to ensure that Auto-QoS DSCP values are honored no matter what the QoS configuration of the ingress is.

These additional filtering components target ingress traffic with the designated private DSCP values. After a match occurs, the system re-marks the traffic based on the application mode. Ingress traffic that is not marked with a recognized private DSCP value receives the same treatment as it receives without the Automatic QoS feature.

The switch activates Automatic QoS automatically; you cannot deactivate this feature but you can remap these DSCP values to use a different queue. The system displays a warning that modifying these values is not recommended.

```
Switch:1(config)#qos ingressmap ds 47 2
DSCP values should not be modified.
Do you want to continue ? (y/n) ? y
```

You do not need to configure individual QoS components across a variety of platforms. Automatic QoS applies end-to-end.

---

## QoS re-marking on a Transparent Port UNI

A Transparent Port UNI port is normally configured as a Layer 2 trusted port. The T-UNI port honors incoming customer 802.1p bits and derives an internal QoS level. The 802.1p bit marking of the Backbone VLAN (BVLAN) is derived from the internal QoS level. If the T-UNI port is set as a Layer 2 untrusted port, a best-effort queue is assigned. Customer packet headers are not modified.

The T-UNI port QoS configurations are:

- DiffServ = disable
- Layer3Trusted = access

### QoS considerations when a port is associated with a T-UNI I-SID

- You cannot configure `access-diffserv` and `enable diffserv` on a T-UNI port.
- When a port is associated with a T-UNI ISID, the T-UNI QoS configuration automatically takes effect.

- When the port is removed from the T-UNI ISID, the default port QoS configuration takes effect.

### **QoS considerations when an MLT is associated with a T-UNI I-SID**

- When an MLT, static or LACP, is added to a T-UNI ISID, the T-UNI QoS configuration take effect on all the ports of the MLT.
- When an MLT, static or LACP, is removed from a T-UNI ISID, the port default QoS configuration is configured on all the member ports of the MLT.
- If a port is added dynamically to a T-UNI MLT, static or LACP, the port inherits the QoS properties of the T-UNI MLT ports.
- If a port is dynamically removed from a T-UNI MLT, static or LACP, the port retains the QoS configuration inherited from the MLT.

---

## **QoS and channelization**

Use channelization to configure a single port to operate as four subports. By default, the ports are not channelized.

You can enable or disable channelization on a channelization-capable port. Enabling or disabling channelization on a port resets the port QoS configuration to default values. For more information on channelization, see *Administering*.



# Chapter 4: Traffic filtering fundamentals

Use the information in this section to help you understand filtering. This section describes a range of features that you can use with the switch to allocate network resources to apply filters.

In a large and busy network, traffic management is very important and can be complex. Traffic filtering can generally provide a mechanism to accurately manage and secure network flows or prioritize crucial information over other network traffic. Some of the primary uses of filtering are:

- accurately manage traffic flows
- implement security permissions on network traffic
- prioritize mission critical traffic flows
- redirecting traffic to firewalls or other devices to efficiently manage bandwidth

---

## Overview

Traffic filtering on the switch is based on an ACL filter implementation. Access Control List (ACL) based filters are a means to provide predictable and flexible traffic filtering. ACL Traffic filters can be configured using the Command line interface (CLI) or the Enterprise Device Manager (EDM). ACL filters set a list of criteria for the network traffic to be matched against, performing a predefined set of actions. Access Control Lists and Action Control Entries provide traffic filtering services on the switch.

Traffic filtering supports IPv6 ingress port/vlan security ACL/filters. IPv6 ingress QoS ACL/filters and IPv6 egress security and QoS ACL/filters are not supported.

---

## QoS and filters

The switch has functions you can use to provide appropriate QoS levels to traffic for each customer, application, or packet. These functions include port-based shapers, DiffServ access or core port settings, and ingress port-rate limiting. The switch also provides access control list (ACL)-based filters. You do not need to use filters to provide QoS; however, filters aid in prioritizing customer traffic. Filters also provide protection by blocking unwanted traffic.

Port rate limiting apply at ingress; shapers apply at egress. ACL-based filters apply at ingress and egress.

---

## Access control lists

Rules can be applied to incoming and outgoing traffic. An ACL can be associated with either a port interface or a VLAN interface.

An ACL can filter either IPv6 or non-IPv6 packets. You must specify the packet type as IPv6 at the ACL level to enable IPv6 filtering. By default, an ACL filters non-IPv6 packets. You cannot change packet type for the ACL once you configure it. If you want a different packet type, you must delete the ACL and re-create it with the other packet type. A VLAN or port can be part of two different ACLs of different types: IPv6 and non-IPv6.

There are three ways an ACL can be associated with interfaces:

- Ingress port (inPort)
- Ingress VLAN (inVLAN)
- Egress port (outPort)

**\* Note:**

IPv6 ingress QoS ACL/Filters and IPv6 egress security and QoS ACL/Filters are not supported.


The ingress VLAN ACL's associations apply to all the active port members of a VLAN. An ACL is created in the enabled state by default.

An ACL can contain multiple filter rules called Access Control Entries (ACE). ACEs provide match criteria and rules for ACL-based filters. An ACE can provide actions such as dropping a packet, monitoring a packet, or remarking QoS on a packet. Complete lists of actions are provided in the Access Control Entries section. After an ingress or egress packet meets the match criteria specified in ACEs within an ACL, the system executes the predefined action.

ACLs provide the ability to configure default and global actions. A default action is applied when no filter rule (ACE) matches on a packet flow. The global action is executed when any filter rule (ACE) matches on a packet flow. The default action mode for ACLs is permit. ACL global actions are:

- monitor-dst-ports or monitor-dst-mlt

The following figure shows the relationships between ACEs and ACLs.



**Figure 3: ACE and ACL relationships**

## Access control entries

The switch filter rules are defined using Access Control Entries (ACE). An ACE is an ordered set of filter rules contained in an Access Control List (ACL). ACE rules are divided into the following three components:

- Operators
- Attributes
- Actions

An ACE generally operates on fields in a packet. If a packet field matches an ACE rule, the system executes the action specified. As each packet enters through an interface with an associated ACL, the system scans the ACE list configured on that ACL and matches on the packet fields. If multiple ACE rules are associated with the ACL, the lower ACE ID will have a higher precedence.

---

## Operators

ACEs use operators to match on packet fields. The switch supports the following operators:

- Equal-to

This rule operator looks for an exact match with the field defined. If the field matches exactly with the rule, the system will return a match (hit). If the rule does not match, the search continues and at the end of the search a miss is returned.

- Mask

ACL-based filters provide the mask operator to match on Layer 2, Layer 3, and Layer 4 packet fields. The mask operator is used to mask bits in packet fields during a search or to match on a partial value of a packet field. This section provides examples of the mask operator.

If a mask bit is set to 1, it means it is not part of the match criteria (treated as do not care), and a mask bit of 0 means that the value represented is part of the match criteria. You can use the mask operator for the following attributes:

- source MAC address
- destination MAC address
- VLAN ID
- Dot1p
- IPv4/IPv6 source address
- IPv4/IPv6 destination address
- destination IP address
- DSCP
- Layer 4 source port
- Layer 4 destination port
- TCP flags

 **Note:**

MAC Address cannot be configured as attributes for IPv6 filters.

The syntax for ACL and ACE configuration of a mask is similar to the use of equal operator, except that you provide the mask value. You can specify a mask value (number) to represent the bits to mask in the attribute. You can define a mask in different ways depending on the attribute you need to mask:

- If you use a decimal number for an IP address mask, it specifies the most significant bits of the provided IP address to match on. For example, a mask of 24 used with an IP address is the same as a mask of 0.0.0.255, and a mask of 8 used with an IP address is the same as a mask of 0.255.255.255.

- If you use a decimal number for a MAC address mask, it specifies the least significant bits of the provided MAC address to ignore. For example, a mask of 32 used with a MAC address is the same as a mask of 0x0000ffffff, and a mask of 16 used with a MAC address is the same as a mask of 0x00000000ffff.

**\* Note:**

Unlike the standard convention, for ACL filter configuration, a mask bit value of '1' specifies a do-not-care bit, and value of '0' signifies must-match bit.

The following table explains the mask operator for MAC addresses.

**Table 7: Mask operator for MAC address**

Rule	Result
<code>filter acl ace ethernet 10 10 dst-mac mask 01:00:5e:00:00:01 0x000000FFFFFF</code>	The rule matches only on the most significant 24 bits as they are not masked, for example, 01:00:5e, and does not care about the least significant 24 bits because they are masked; the least significant 24 bits can have a value of 00:00:00 - FF:FF:FF.
<code>filter acl ace ethernet 10 10 dst-mac mask 0x01:00:5e:00:00:01 0xFFFFFFFF0000</code>	The rule matches only on the least significant 16 bits because they are not masked, for example, 00:01, and does not care about the most significant 32 bits because they are masked; the most significant 32 bits can have a value of 00:00:00:00 – FF:FF:FF:FF.
<code>filter acl ace ethernet 10 10 dst-mac mask 0x01:00:5e:00:00:01 0xFF00FF0000FF</code>	The rule matches only on the unmasked bits, for example, 0xXX:00:XX:00:00:XX. The rule matches only on the bits not masked, for example, all the zeroes and the x represents a do not care (0xXX:00:XX:00:00:XX)

The following table explains the mask operator for IP addresses.

**Table 8: Mask operator for IP address**

Rule	Result
<code>filter acl ace ip 10 10 src-ip mask 2.10.10.12 0.255.255.255</code>	The rule matches only the most significant 8 bits, and does not care about the value of the remaining 24 bits as they are considered masked. For example, 10.10.12. Packets with a source IP address of 2.15.16.122 or 2.3.4.5 match on the filter rule while packets with a source IP address of 3.10.10.12 and 4.10.10.12 do not match on the filter rule.
<code>filter acl ace ip 10 10 src-ip mask 3.4.5.6 255.255.255.0</code>	The rule matches only the least significant 8 bits, for example, 6, and does not care about the most significant 24 bits, 3.4.5. Packets with a source IP address of 17.16.5.6 or 192.168.1.6 match on the filter rule while packets with a source IP address of 3.4.5.4 or 3.4.5.7 do not match on the filter rule.

The following table explains the mask operator for Layer 4 source port.

**Table 9: Mask operator for Layer 4 source port**

Rule	Result
<pre>filter acl ace protocol 10 10 src-port mask 80 0xF</pre>	<p>The filter rule matches on Layer 4 source port 80 (1010000). The mask value 0xF (1111) masks the least significant 4 bits, which means source port 81 (1010001) through 95 (1011111) also match this filter rule. This means the range 80–95 is a match on this rule.</p>

The following table demonstrates the resulting action based on mask configuration and example packets.

**Table 10: Mask operator configuration examples**

Filter configuration	Address examples that match the filter	Address examples that do not match the filter
<p><b>Ethernet mask:</b></p> <pre>filter acl 1000 type inport filter acl port 1000 6/5,9/11 filter acl ace 1000 12 filter acl ace ethernet 1000 12 src-mac mask 00:00:11:11:16:00 0x00ff000000f0 filter acl ace action 1000 12 permit count filter acl ace 1000 12 enable</pre>	<p>Source MAC: 00:01:11:11:16:10 00:10:11:11:16:f0 00:1f: 11:11:16:10 00:ff: 11:11:16:f0 00:00:11:11:16:60 00:e6:11:11:16:e0</p>	<p>Source MAC: 00:00:11:11:16:01 00:ff:11:11:16:f1</p>
<pre>filter acl ace 1000 1000 filter acl ace ethernet 1000 1000 dst-mac mask 00:00:00:64:16:00 0x00000060001f filter acl ace action 1000 1000 deny count filter acl ace 1000 1000 enable</pre>	<p>Destination MAC: 00:00:00:64:16:01 00:00:00:04:16:01 00:00:00:24:16:1f 00:00:00:64:16:1f 00:00:00:44:16:10 00:00:00:04:16:05</p>	<p>Destination MAC: 00:00:00:24:16:20 00:00:00:64:16:20 00:00:00:63:16:01 00:00:00:65:16:01</p>
<p><b>IP mask (dotted decimal notation):</b></p> <pre>filter acl 10 type outport filter acl port 10 5/13 filter acl ace 10 11 filter acl ace ethernet 10 11 ether-type eq ip filter acl ace ip 10 11 src-ip mask 192.168.4.0 0.0.0.31 filter acl ace action 10 11 permit count filter acl ace 10 11 enable</pre>	<p>Source IP: 192.168.4.1 192.168.4.10 192.168.4.30 192.168.4.31</p>	<p>Source IP: 192.168.3.1 192.168.4.32</p>
<pre>filter acl ace 10 12 filter acl ace ethernet 10 12 ether-type eq ip filter acl ace ip 10 12 dst-ip mask 192.168.7.0 0.0.0.3 filter acl ace action 10 12 deny count filter acl ace 10 12 enable</pre>	<p>Destination IP: 192.168.7.1 192.168.7.3</p>	<p>Destination IP: 192.168.7.4 192.168.7.5</p>

*Table continues...*

Filter configuration	Address examples that match the filter	Address examples that do not match the filter
<p>IP mask (decimal notation):</p> <pre>filter acl 10 type outport filter acl port 10 5/13 filter acl ace 10 11 filter acl ace ethernet 10 11 ether-type eq ip filter acl ace ip 10 11 src-ip mask 192.168.4.0 255.255.255.31 filter acl ace action 10 11 permit count filter acl ace 10 11 enable</pre>	<p>Source IP: 192.168.4.1 192.168.4.10 192.168.4.30 192.168.4.31</p>	<p>Source IP: 192.168.3.1 192.168.4.32</p>
<pre>filter acl ace 10 12 filter acl ace ethernet 10 12 ether-type eq ip filter acl ace ip 10 12 dst-ip mask 192.168.7.0 255.255.255.3 filter acl ace action 10 12 deny count filter acl ace 10 12 enable</pre>	<p>Destination IP: 192.168.7.1 192.168.7.3</p>	<p>Destination IP: 192.168.7.4 192.168.7.5</p>
<p>Protocol mask:</p> <pre>filter acl 901 type inport filter acl port 901 6/2 filter acl ace 901 1 filter acl ace ip 901 1 ip-protocol-type eq tcp filter acl ace protocol 901 1 src-port mask 256 0xff filter acl ace action 901 1 deny count filter acl ace 901 1 enable</pre> <p>This mask implies packets with TCP source port 256–511 match the filter, while 0–255 and &gt; 511 miss the filter.</p>	<p>TCP source port 256 TCP source port 356 TCP source port 511</p>	<p>TCP source port 255 TCP source port 512</p>

## Attributes

Attributes are fields in a packet (Layer 2, Layer 3, Layer 4) or other information related to the packet on which an ACE rule is applied like slot/port. The list of all the attributes and the operators that could be applied on them are listed below.

If you want to configure IPv6 attributes, you must configure an ACL to filter either IPv6 or non-IPv6 traffic. You can only configure IPv6 attributes for IPv6 packets. You cannot configure IPv6 attributes for non-IPv6 packets.

**Table 11: Attribute list**

Attribute Name	Operator
Slot/Port	Equal
Destination MAC (IPv4 filters only)	Equal, Mask
Source MAC (IPv4 filters only)	Equal, Mask

*Table continues...*

Attribute Name	Operator
VLAN ID	Equal, Mask
.1p bits	Equal, Mask
Ether Type	Equal
ARP Opcode	Equal
Source IP	Equal, Mask
Destination IP	Equal, Mask
Protocol Type	Equal
Type of Service	Equal, Mask
IP Fragmentation	Equal
IP Options	Equal
Layer 4 Destination Port	Equal, Mask
Layer 4 Source Port	Equal, Mask
TCP Flags	Equal, Mask
ICMP Message Type	Equal
Source IPv6 (IPv6 only)	Equal, Mask
Destination IPv6 (IPv6 only)	Equal, Mask
Next header (IPv6 only)	Equal
Traffic class (IPv6 only)	Equal

---

## Actions

Actions occur when the filter rule is hit or missed. The types of actions filter configuration can execute are split into two categories:

- Security actions supported by the ACE IDs in the range of 1–1000
- QoS actions supported by the ACE IDs in the range of 1001–2000 (IPv4 filters only)

Filter rules that support Security actions and QoS actions are stored separately. If an ACL filter is applied to a traffic flow, the switch performs a parallel search on both Security and QoS ACE lists, which results in distinct and non-conflicting actions.

**\* Note:**

Ingress ACLs support only security and QoS ACE actions. Egress ACLs do not support QoS ACEs.

The supported switch actions are listed below.



**Table 12: Security ACE Actions**

Security ACE Actions	User supplied parameters	Comments
Mode	Permit or Deny	Applies to both ingress and egress ACLs.
• Redirect-next-hop	IP address, Mode	<p>Redirects the packet to the user supplied IP address. If the switch cannot resolve ARP for the user-specified next-hop, packets that match the filter are dropped.</p> <p><b>* Note:</b></p> <p>The filter does not redirect packets with a time-to-live (TTL) of 1 nor does it send them to the CPU where the CPU would generate ICMP TTL expired messages. IP Traceroute reports a timeout for the hop.</p> <p>Applies to ingress ACLs (routed and L2 packets).</p>
Count	None	Collect ACE statistics . Applies to ingress and egress ACLs.
Mirror	Port or list of ports or MLT-ID.	Applies to Ingress ACLs only.
Remove-tag	None	Removes inner VLAN tag of the mirrored packet into the SPB network.
Monitor I-SID offset	None	The actual monitor I-SID value to which packets are mirrored.

**Table 13: QoS ACE Actions**

QOS ACE Actions	User supplied parameters	Comments
Remark	<ul style="list-style-type: none"> <li>• DCSP</li> <li>• .dot1p (ingress only)</li> <li>• Internal-qos</li> </ul>	Applied to Ingress ACLs.
Count	None	Applies to Ingress ACLs only.

---

## Internal QoS level and remarking

Setting the *internal QoS level* is an ingress action. *Remarking* is an egress action.

The internal QoS behavior does not change for remarked packets. This is true even if you use an ACL DSCP/802.1p filter to remark the packets. The packets would still go into the internal QoS queue based on the native packet coming into the switch.

If you want to change the internal QoS for remarked incoming packets, you have to add the `permit internal-qos` command as shown in the following ACL filter example.

```
filter acl 10 type inPort name "ACL-CTI"
filter acl port 10 1/2-1/50
filter acl ace 10 1302 name "CIFS-SCCM Source"
filter acl ace action 10 1302 permit remark-dscp phbaf11 remark-dot1p 1 count
filter acl ace action 10 1302 permit internal-qos 0
filter acl ace ethernet 10 1302 ether-type eq ip
filter acl ace ip 10 1302 src-ip mask 0.0.0.0 255.255.255.255
filter acl ace ip 10 1302 ip-protocol-type eq tcp
filter acl ace protocol 10 1302 src-port mask 0 0xffff
```

When a packet goes through the switch, the internal QoS level governs which queue the packet uses on egress. To verify which queue the packets are egressing on, use the `show qos cosq-stats interface [value]` command. For more information, see [Viewing port egress CoS queue statistics using the CLI](#) on page 61 or [Viewing port egress CoS queue statistics using EDM](#) on page 72.

## Common ACE uses and configuration

The following table describes configurations you can use to perform common actions.

**Table 14: Common ACE uses and configurations**

Function	ACE configuration
Permit a specific host to access the network	<ul style="list-style-type: none"> <li>Use action permit.</li> <li>Configure the source IP address to be the host IP address.</li> </ul> <pre>filter acl ace 1 5 name "Permit_access_to_198.51.100.0" filter acl ace action 1 5 permit filter acl ace ethernet 1 5 ether-type eq ip filter acl ace ip 1 5 src-ip eq 198.51.100.0 filter acl ace 1 5 enable</pre>
Deny a specific host from accessing the network	<ul style="list-style-type: none"> <li>Use action deny.</li> <li>Configure the source IP address to be the host IP address.</li> </ul> <pre>filter acl ace 1 5 name "Deny_access_to_198.51.100.0" filter acl ace action 1 5 deny filter acl ace ethernet 1 5 ether-type eq ip filter acl ace ip 1 5 src-ip eq</pre>

*Table continues...*

Function	ACE configuration
	198.51.100.0 filter acl ace 1 5 enable
Permit a specific range of hosts to access the network	<ul style="list-style-type: none"> <li>Use action permit.</li> <li>Configure the source IP address to be the range of host IP addresses.</li> </ul> <pre>filter acl ace 1 5 name "Permit_access_to_1.2.3.4-1.2.3.7" filter acl ace action 1 5 permit filter acl ace ethernet 1 5 ether-type eq ip filter acl ace ip 1 5 src-ip mask 1.2.3.4 0.0.0.3 filter acl ace 1 5 enable</pre>
Deny Telnet traffic	<ul style="list-style-type: none"> <li>Use action deny.</li> <li>Configure the protocol as TCP and the TCP destination port to be 23.</li> </ul> <pre>filter acl ace 1 5 name "Deny_telnet" filter acl ace action 1 5 deny filter acl ace ethernet 1 5 ethertype eq ip filter acl ace ip 1 5 ip-protocol-type eq tcp filter acl ace protocol 1 5 dst-port eq 23 filter acl ace 1 5 enable</pre>
Deny FTP traffic	<ul style="list-style-type: none"> <li>Use action deny.</li> <li>Configure the protocol as TCP and the TCP destination port to be 21.</li> </ul> <pre>filter acl ace 1 5 name "Deny_ftp" filter acl ace action 1 5 deny filter acl ace ethernet 1 5 ethertype eq ip filter acl ace ip 1 5 ip-protocol-type eq tcp filter acl ace protocol 1 5 dst-port eq 21 filter acl ace 1 5 enable</pre>

## Switched UNI ACL Filters

InPort and OutPort filters are supported on Switched UNI (S-UNI) and Fabric Attach ports.

**\* Note:**

InPort and outPort filters are supported on S-UNI and Fabric Attach ports for the traffic mapped to an I-SID which does not have platform VLAN associated. The Customer VLAN-ID (CVID) can be applied as VLAN-ID qualifier in inPort and outPort filters.

**\* Note:**

InPort, outPort, and inVLAN filters are supported on S-UNI and Fabric Attach ports for the traffic mapped to an I-SID which has platform VLAN associated. The platform VLAN should be used as VLAN-ID in inPort and inVLAN filters, and the CVID as VLAN-ID in the outPort filter.

## Traffic filter configuration

Traffic filtering manages traffic by defining filtering conditions and associating these conditions with specific actions. The following steps summarize the filtering configuration process:

1. Determine your desired match fields.
2. Configure an ACL and associate it with Ingress or Egress traffic flow.
3. Configure an ACE within the ACL.
4. Configure the desired precedence, attributes, and action.
5. Enable the ACE.

## ACL and ACE configuration guidelines

To find the maximum number of ACLs and ACEs that the switch supports, see the *Release Notes*.

## ACL filters behavior

The implementation of ACL filters is similar in VSP 4000, VSP 8000 or VSP 7200, and VSP 8600, but there are some differences as summarized in the following table.

	VSP 4000	VSP 8000 / VSP 7200	VSP 8600
<b>Hardware filter engine resources</b>	Support for four ingress filter groups <ol style="list-style-type: none"> <li>1. port-based Security ACEs</li> <li>2. port-based QoS ACEs</li> <li>3. VLAN-based Security ACEs</li> </ol>	Support for two ingress filter groups <ol style="list-style-type: none"> <li>1. port-based and VLAN-based Security ACEs</li> <li>2. port-based and VLAN-based QoS ACEs</li> </ol>	Supports the following ingress filter groups: <ul style="list-style-type: none"> <li>• port-based and VLAN-based Security ACEs</li> </ul>

*Table continues...*

	VSP 4000	VSP 8000 / VSP 7200	VSP 8600
	4. VLAN-based QoS ACEs		
	For each ingress packet, a parallel search is performed on each of the four groups.	For each ingress packet, a parallel search is performed on each of the two groups.	For each ingress packet, a search is performed on the group.
<b>Behavior of incoming packets</b> An incoming packet can match both port-based and VLAN-based ACL/ACE	Regardless of the type of matching ACEs (Security or QoS), the action of either the highest priority matching ACE or the default action will be performed.	Port-based ACLs have precedence over VLAN-based ACLs. If the matching ACEs are of the same type (both Security or both QoS), then the VLAN-based ACL/ACE will be ignored.	Port-based ACLs have precedence over VLAN-based ACLs. If a packet matches both a Port-based and a VLAN-based ACL, then the VLAN-based ACL will be ignored.

# Chapter 5: Basic DiffServ configuration using CLI

Use Differentiated Services (DiffServ) to provide appropriate Quality of Service (QoS) to specific traffic types.

---

## Enabling DiffServ on a port

Enable DiffServ so that the system provides DiffServ-based QoS on the port. By default, DiffServ is enabled.

### Procedure

1. Enter Interface Configuration mode:

```
enable
configure terminal
interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-
port]][,...]} or interface vlan <1-4059>
```

 **Note:**

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Enable DiffServ:

```
enable-diffserv [port {slot/port[/sub-port] [-slot/port[/sub-port]]
[,...]] [enable]
```

3. Disable Diffserv:

```
no enable-diffserv [port {slot/port[/sub-port] [-slot/port[/sub-
port]][,...]] [enable]
```

---

## Variable definitions

Use the data in the following table to use the `enable-diffserv` command.

Variable	Value
enable	Enables DiffServ for the specified port. The default is enabled.
port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}	Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

## Configuring Layer 3 trusted or untrusted ports

Configure a port as trusted or untrusted to determine the Layer 3 QoS actions the switch performs. A trusted (core) port honors incoming Differentiated Services Code Point (DSCP) markings. An untrusted (access) port overrides DSCP markings. The default configuration is trusted.

### Before you begin

Enable DiffServ.

### Procedure

1. Enter Interface Configuration mode:

```
enable
configure terminal
interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]} OR interface vlan <1-4059>
```

#### \* Note:

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure the port as an access port, use one of the following options:

```
no enable-diffserv [port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]] [enable]
```

**OR** configure both parameters:

```
enable-diffserv [port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]] [enable]
```

```
access-diffserv [port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]] [enable]
```

3. Configure the port as a core port:

```
no access-diffserv [port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]] [enable]
```

---

## Variable definitions

Use the data in the following table to use the `access-diffserv` commands.

Variable	Value
enable	If enabled, specifies an access port and overrides incoming DSCP bits. If disabled, specifies a core port that honors and services incoming DSCP bits.
port <i>{slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}</i>	Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

---

## Configuring Layer 2 trusted or untrusted ports

Configure a port as trusted or untrusted to determine the Layer 2 QoS actions the switch performs. A trusted port (override disabled) honors incoming 802.1p bit markings. An untrusted port (override enabled) overrides 802.1p bit markings.

### Procedure

1. Enter Interface Configuration mode:

```
enable
configure terminal
interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]} or interface vlan <1-4059>
```

**\* Note:**

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure the port as Layer 2 untrusted:

```
qos 802.1p-override [enable]
```

3. Configure the port as Layer 2 trusted:

```
no qos 802.1p-override [enable]
```

---

## Variable definitions

Use the data in the following table to use the `qos 802.1p-override` command.



**Table 15: Variable definitions**

Variable	Value
enable	If you use this variable, the port overrides incoming 802.1p bits; if you do not use this variable, the port honors and services incoming 802.1p bits. The default is disable (Layer 2 trusted).

## Viewing the port 802.1p override status

Use this procedure to view the port 802.1p override status. The system displays the port and 801.1p override status.

### Procedure

1. Enter Global Configuration mode:  

```
enable
configure terminal
```
2. View the port 802.1p override status:  

```
show qos 802.1p-override
```

### Example

```
Switch:1# show qos 802.1p-override
```

```

=====
                        Port 802.1p-Override Status
=====
PORT      802.1P OVERRIDE
-----
1/1       DISABLED
1/2       DISABLED
1/3       DISABLED
1/4       DISABLED
1/5       DISABLED
1/6       DISABLED
1/7       DISABLED
1/8       DISABLED
1/9       DISABLED
1/10      DISABLED
1/11      DISABLED
1/12      DISABLED
1/13      DISABLED
1/14      DISABLED
1/15      DISABLED
1/16      DISABLED

```

## Configuring the port QoS level

Configure the port QoS level to assign a default QoS level for all traffic if the packet does not match an access control list (ACL) that re-marks the packet. If you configure port QoS levels, Layer 2 and Layer 3 traffic from the same port use the same QoS level. The default value is 1.

### About this task

For VoIP traffic, it is recommended that you use QoS level 6.

### Procedure

1. Enter GigabitEthernet Interface Configuration mode:

```
enable

configure terminal

interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-
port]] [, ...]}
```

#### \* Note:

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure the port QoS level:

```
qos level [port {slot/port[sub-port]] <0-6>
```

## Variable definitions

Use the data in the following table to use the `qos level` command.

Variable	Value
<0-6>	Specifies the default QoS level for the port traffic. The system reserves QoS level 7 for network control traffic. The default is 1.
port {slot/port[/sub-port]}	Identifies a single slot and port. If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

# Chapter 6: Basic DiffServ configuration using EDM

Use DiffServ to implement classification and mapping functions at the network boundary or access points to regulate packet behavior. You can configure a port as a trusted (core) or an untrusted (access) port at both Layer 2 and Layer 3.

You can also perform many of the procedures in this section on the Interface tab for the selected port. The procedures in this section show only one configuration method.

---

## Enabling DiffServ for a port

Enable DiffServ so that the switch provides DiffServ-based Quality of Service (QoS) on the port.

### About this task Procedure

1. In the navigation tree, expand the following folders: **Configuration > QoS**.
2. Click **Port QoS Config**.
3. In the row for the port, double-click the cell in the **DiffServ** column.
4. Select **true**.
5. Click **Apply**.

---

## QoS Port Config field descriptions

Use the data in the following table to use the **Port QoS Config** tab.

Name	Description
<b>Index</b>	Specifies an index value that uniquely identifies a port.
<b>DiffServ</b>	Specifies whether DiffServ is enabled (true) or disabled (false) on the port. The default is true. This variable works in conjunction with Layer3Trust. The DiffServ variable is a global parameter that affects QoS DSCP operations. If the DiffServ parameter is false (DiffServ

*Table continues...*

Name	Description
	disabled), the system does not use the DSCP parameter for classification or modify it. If this variable is true, it activates the Layer3Trust parameter.
<b>Layer3Trust</b>	Configures the Layer 3 trusted port as an access or core port. The default is core. Core configures the port to a trusted state and access configures the port to an untrusted state. The DiffServ parameter determines the operation of this variable. If DiffServ is false, Layer3Trust has no effect; no modification of the DSCP or TOS bits occurs. If DiffServ is true, the core and access configuration take affect.
<b>Layer2Override8021p</b>	Specifies whether Layer 2 802.1p override is enabled (true) or disabled (false) on the port. The default is false. This variable primarily affects tagged packet treatment. If Layer2Override8021p is false, the port trusts the 802.1p-bits portion of a Q-tagged packet. The port trusts the 802.1p-bits marking regardless of the port setting (tagged or untagged); however, if the discard tagged packets parameter (DiscardTaggedFrames) on an untagged port is true, the system discards the packet. If Layer2Override8021p is true, the port does not trust the 802.1p bit marking. In this case, the QoS operation depends on other parameters, such as the port QoS level.
<b>QosLevel</b>	Specifies the QoS level to use when the system processes packets carried on this port. Values range from level 0–6 (the system reserves 7 for network control traffic). The default is 1.

---

## Configuring Layer 3 trusted or untrusted ports

Configure a port as trusted or untrusted to determine the Layer 3 QoS actions the switch performs. A trusted port honors incoming DSCP markings. An untrusted port overrides DSCP markings. The default is trusted.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Port QoS Config**.
3. In the row for the port, double-click the cell in the **Layer3Trust** column.
4. Select **core** (trusted) or **access** (untrusted) as the port setting.
5. Click **Apply**.

---

## Configuring Layer 2 trusted or untrusted ports

Configure a port as trusted or untrusted to determine the Layer 2 QoS actions the switch performs. A trusted port (override false) honors incoming 802.1p bit markings. An untrusted port (override true) overrides 802.1p bit markings.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Port QoS Config**.
3. In the row for the port, double-click the cell in the **Layer2 Override 8021p** column.
4. To configure the port as a Layer 2 untrusted port, select **true**. To configure it as a Layer 2 trusted port, select **false**.  
By default, all ports are Layer 2 trusted (Layer2 Override 8021p is false).
5. Click **Apply**.

---

## Configuring the port QoS level

Use the default port QoS level to assign a default QoS level for all traffic, if the packet does not match an access control list (ACL) to remark the packet.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Port QoS Config**.
3. In the row for the port, double-click the cell in the **QoSLevel** column.
4. Select the new level.
5. Click **Apply**.

# Chapter 7: QoS configuration using CLI

Use the procedures in this section to configure Quality of Service (QoS) on the switch.

---

## Configuring broadcast and multicast bandwidth limiting

Configure broadcast and multicast bandwidth limiting to limit the amount of ingress broadcast and multicast traffic on a port. The switch drops traffic that violates the bandwidth limit.

You can configure broadcast and multicast bandwidth limiting through CLI only; you cannot use Enterprise Device Manager (EDM).

### Procedure

1. Enter Interface Configuration mode:

```
enable

configure terminal

interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-
port]][, ...]} or interface vlan <1-4059>
```

**\* Note:**

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure broadcast bandwidth limiting:

```
rate-limit [port {slot/port[/sub-port] [-slot/port[/sub-port]]
[, ...]] broadcast <1-65535>
```

3. Configure multicast bandwidth limiting:

```
rate-limit [port {slot/port[/sub-port] [-slot/port[/sub-port]]
[, ...]] multicast <1-65535>
```

---

## Variable definitions

Use the data in the following table to use the `rate-limit` command.

Variable	Value
<1-65535>	Specifies the bandwidth limit for broadcast and multicast traffic from 1–65535 packets per second.
port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}	Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

## Viewing the port-based shaper information

### About this task

Use this procedure to view the port-based shaper information. The system displays the port, egress rate limit in Kbps, and the rate limit status.

### Procedure

1. Enter Privileged EXEC mode:

```
enable
```

2. View the ingress port-rate limit information:

```
show qos shaper interface gigabitEthernet [{slot/port[/sub-port]}[-slot/port[/sub-port]][,...}}
```

### Example

```
Switch:1# show qos shaper interface gigabitEthernet 1/1
```

```
=====
Port Egress Rate-Limiting(Shape)
=====
PORT      EGRESS RATE-LIMIT(kbps)  ENABLED/DISABLED
-----
1/1       0                        DISABLED
```

## Configuring the port-based shaper

Use port-based shaping to rate-limit all outgoing traffic to a specific rate.

### Procedure

1. Enter GigabitEthernet Interface Configuration mode:

```
enable
```

```
configure terminal
```

```
interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-
port]][, ...]}
```

**\* Note:**

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure port-based shaping for a 10 Gbps port:

```
qos if-shaper [port {slot/port[/sub-port}}] shape-rate
<1000-10000000>
```

3. Configure port-based shaping for a 40 Gbps port:

```
qos if-shaper [port {slot/port[/sub-port}}] shape-rate
<1000-40000000>
```

4. Configure port-based shaping for a 100 Gbps port:

```
qos if-shaper [port {slot/port[/sub-port}}] shape-rate
<1000-100000000>
```

## Variable definitions

Use the data in the following table to use the `qos if-shaper` command.

Variable	Value
port {slot/port[/sub-port]}	Specifies the slot and port number to which to apply shaping. This variable is optional.  Identifies a single slot and port. If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.
shape-rate <1000-10000000> or shape-rate <1000-40000000> or shape-rate <1000-100000000>	Configures the shaping rate in Kbps.  The default is 0, which means shaping is disabled on the port.

## Configuring a port-based policer

Use a port policer to bandwidth-limit incoming traffic. The port drops or re-marks violating traffic.

**\* Note:**

This command does not appear on all hardware platforms.



**Procedure**

1. Enter GigabitEthernet Interface Configuration mode:

```
enable

configure terminal

interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-
port]][,...]}
```

**\* Note:**

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure the policing limit:

```
qos if-policer [port {slot/port[-slot/port][,...]}] peak-rate
<64-100000000> svc-rate <64-100000000>
```

**Example**

Configure the policing limit to a peak-rate of 10000 and the service rate limit to 5000 for port 4/10:

```
Switch:1>enable
Switch:1#configure terminal
Switch:1(config)#interface gigabitethernet 4/10
Switch:1(config-if)#qos if-policer port 4/10 peak-rate 10000 svc-rate 5000
```

**Variable definitions**

Use the data in the following table to use the `qos if-policer` command.

**Table 16: Variable definitions**

Variable	Value
peak-rate<64-100000000>	Specifies the peak rate limit in Kbps.
port {slot/port[-slot/port][,...]}	Identifies the slot and the port.
svc-rate<64-100000000>	Specifies the service rate limit in Kbps.

**Configuring the ingress port-rate limiter**

Use the ingress port-rate limiter to limit the traffic rate accepted by the specified ingress port. The port drops or re-marks violating traffic.

**Procedure**

1. Enter GigabitEthernet Interface Configuration mode:

```
enable

configure terminal

interface GigabitEthernet {slot/port[/sub-port] [-slot/port[/sub-
port]] [,...]}
```

**\* Note:**

If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

2. Configure the ingress port-rate limit:

```
qos if-rate-limiting [port {slot/port[/sub-port] [-slot/port[/sub-
port]] [,...]]] rate <1000-40000000>
```

3. Disable the ingress port-rate limit:

```
no qos if-rate-limiting [port {slot/port[/sub-port] [-slot/port[/
sub-port]] [,...]]]
```

## Variable definitions

Use the data in the following table to use the `qos if-rate-limiting` command.

Variable	Value
<code>1000-40000000</code>	Specifies the ingress rate limit in Kbps. The range is 1000–40000000.
<code>port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}</code>	Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

## Viewing the ingress port-rate limit information

Use this procedure to view the ingress port-rate limit information. The system displays the port, rate limit in Kbps, and rate limit status.

### Procedure

1. Enter Privileged EXEC mode:

```
enable
```

2. View the ingress port-rate limit information:

```
show qos rate-limiting interface gigabitEthernet [{slot/port[/sub-
port] [-slot/port[/sub-port]] [,...]]]
```

**Example**

```
Switch:1# show qos rate-limiting interface gigabitEthernet 1/1
```

Port Ingress Rate-Limiting		
PORT	RATE (kbps)	ENABLED/DISABLED
1/1	0	DISABLED

**Variable definitions**

Use the data in the following table to use the `show qos rate-limiting interface gigabitEthernet` command.

Variable	Value
<code>port {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}</code>	Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

**Configuring ingress mappings**

You can modify the ingress mappings to change traffic priorities. However, it is recommended that you use the default mappings.

**Procedure**

1. Enter Global Configuration mode:
 

```
enable
configure terminal
```
2. Configure 802.1p bit to QoS ingress mappings:
 

```
qos ingressmap 1p <0-7> <0-6>
```
3. Configure DSCP to QoS ingress mappings:
 

```
qos ingressmap ds <0-63> <0-6>
```
4. Ensure the configuration is correct:
 

```
show qos ingressmap [1p <0-7>]
show qos ingressmap [ds <0-63>]
```

## Variable definitions

Use the data in the following table to use the `qos ingressmap` command.

**Table 17: Variable definitions**

Variable	Value
1p <0-7> <0-6>	<p>Maps the IEEE 802.1p bit to QoS level. Each QoS level has a default IEEE 1P value:</p> <ul style="list-style-type: none"> <li>• level 0—1</li> <li>• level 1—0</li> <li>• level 2—2</li> <li>• level 3—3</li> <li>• level 4—4</li> <li>• level 5—5</li> <li>• level 6—6</li> </ul> <p>The system reserves level 7 for Network Control. To use the default configuration, use the default option in the command:</p> <pre>default qos ingressmap 1p</pre>
ds <0-63> <0-6>	<p>Maps the DS byte to QoS level. The system reserves level 7 for Network Control. To use the default configuration, use the default option in the command:</p> <pre>default qos ingressmap ds</pre>

## Configuring egress mappings

You can modify the egress mappings to change traffic priorities. However, it is recommended that you use the default mappings.

### Procedure

1. Enter Global Configuration mode:
 

```
enable
configure terminal
```
2. Configure QoS to 802.1p bit egress mappings:
 

```
qos egressmap 1p <0-6> <0-7>
```
3. Configure QoS to DSCP egress mappings:

```
qos egressmap ds <0-7> WORD<1-6>
```

4. Ensure the configuration is correct:

```
show qos egressmap [1p <0-7>]
```

```
show qos egressmap [ds <0-7>]
```

---

## Variable definitions

Use the data in the following table to use the `qos egressmap` command.

**Table 18: Variable definitions**

Variable	Value
1p <0-6> <0-7>	<p>Maps the QoS level to IEEE 802.1p bit. Each QoS level has a default IEEE 1P value:</p> <ul style="list-style-type: none"> <li>• level 0—1</li> <li>• level 1—0</li> <li>• level 2—2</li> <li>• level 3—3</li> <li>• level 4—4</li> <li>• level 5—5</li> <li>• level 6—6</li> </ul> <p>The system reserves level 7 for Network Control. To use the default configuration, use the default option in the command:</p> <pre>default qos egressmap 1p</pre>
ds <0-7> WORD<1-6>	<p>Maps the QoS level to DS byte. You can specify the DSCP in either hexadecimal, binary, or decimal format. To use the default configuration, use the default option in the command:</p> <pre>default qos egressmap ds</pre>

---

## Viewing port egress CoS queue statistics

View the port egress CoS queue statistics. The system displays the statistics of the forwarded packets and bytes, and the dropped packets and bytes.

### Procedure

1. Enter Privileged EXEC mode:

```
enable
```

2. View the port egress CoS queue statistics:

```
show qos cosq-stats interface <PT_PORT>
```

**\* Note:**

The show command output varies based on your hardware platform. On all VSP platforms except VSP 8600, the show command output displays Out Packets and Out Bytes per interface which shows the number of unicast packets sent out on each queue for an egress port. VSP 8600 uses VoQ queuing architecture which enables to read the Accepted Packets and Accepted Bytes on each queue. The Accepted Packets and Accepted Bytes show the number of packets and bytes that enter the VoQ for a particular queue on the egress port. The Drop Packets and Drop Bytes show the number of packets and bytes that are dropped when the VoQ is full.

## Variable definitions

Use the data in the following table to use the `show qos cosq-stats interface <PT_PORT>` command.

**Table 19: Variable definitions**

Variable	Value
<PT_PORT>	PT indicates the slot number; PORT indicates the port number.

The following table describes the column headings in the command output for `show qos cosq-stats interface <PT_PORT>`.

**Table 20: Variable definitions**

Variable	Value
Cos	Indicates the Cos queue.
Out Packets	Indicates the out packets for the Cos queue.
Accepted Packets	Indicates the accepted packets for the Cos queue.
Out Bytes	Indicates the out bytes for the Cos queue.
Accepted Bytes	Indicates the accepted bytes for the Cos queue.
Drop Packets	Indicates the drop packets for the Cos queue.
Drop Bytes	Indicates the drop bytes for the Cos queue.

---

## Clearing port egress CoS queue statistics

Clear the port egress CoS queue statistics in the hardware.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Clear the port egress CoS queue statistics:

```
clear qos cosq-stats interface <PT_PORT>
```

---

## Variable definitions

Use the data in the following table to use the `clear qos cosq-stats interface <PT_PORT>` command.

**Table 21: Variable definitions**

Variable	Definition
<PT_PORT>	PT indicates the slot number; PORT indicates the port number.

---

## Viewing CPU queue statistics

View the statistics of the forwarded packets and bytes, and the dropped packets and bytes for the traffic sent toward CP. The queue assignment is based on the protocol types, not on the internal CoS value. These statistics are useful for debugging purposes.

### Note:

When a neighbor transitions to the STALE state, to initiate Neighbor Unreachability detection (NUD), a duplicate copy of the traffic destined to this neighbor is sent to the switch Control Processor (CP) on a low priority queue (queue 0). The original packet is forwarded to this neighbor. Once NUD is initiated, the hardware records are updated and the traffic is no longer sent to the CP. When a high rate of such traffic is sent to CP, the switch can drop some of these packets due to the in built CP rate limiting feature, which protects the CP from DOS attacks.

Use the command `show qos cosq-stats cpu-port` to view drop statistics on the CPU queue. This design does not result in loss of traffic.

Use the command `ipv6 nd reachable-time <0-3600000>` to increase the default value of 3000 milliseconds which in turn delays the scenario of data path sending STALE neighbor destined packets to the CP.

## Procedure

1. Enter Privileged EXEC mode:

```
enable
```

2. View the CPU queue statistics:

```
show qos cosq-stats cpu-port
```

### \* Note:

The show command output varies based on your hardware platform. On all VSP platforms except VSP 8600, the show command output displays Out Packets and Out Bytes per interface which shows the number of unicast packets sent out on each queue for an egress port. VSP 8600 uses VoQ queuing architecture which supports an increased number of available queues, hence the output displays the number of packets accepted and dropped on each protocol type going to the CPU.

---

## Variable definitions

The following table describes the column headings in the command output for `show qos cosq-stats cpu-port`.

### \* Note:

The Variables can differ depending on your hardware platform.

**Table 22: Variable definitions**

Variable	Value
CoS	Indicates the CoS queue number.
Protocol	Indicates the type of protocol.
Out Packets	Indicates the out packets for the CoS queue.
Accepted Packets	Indicates the accepted packets for the Cos queue.
Out Bytes	Indicates the out bytes for the CoS queue.
Accepted Bytes	Indicates the accepted bytes for the Cos queue.
Drop Packets	Indicates the drop packets for the CoS queue.
Drop Bytes	Indicates the drop bytes for the CoS queue.



---

## Clearing CPU queue statistics

Clear the CPU queue statistics.

### Procedure

1. Enter Global Configuration mode:  

```
enable  
configure terminal
```
2. Clear CPU queue statistics:  

```
clear qos cosq-stats cpu-port
```

---

## Configuring an egress QoS queue profile

Configure a queue profile to apply the configured egress queue parameters to queues and ports.

### About this task

After you make a configuration change to a queue profile, you must apply the profile before the changes take effect.

#### **Note:**

Currently the switch supports only one queue profile that is automatically created on system boot up, with an ID of 1 and name of default. You cannot delete this profile.

### Procedure

1. Enter Global Configuration mode:  

```
enable  
configure terminal
```
2. Configure the minimum weight for a specific queue:  

```
qos queue-profile queue <1-5> <0-7> min-weight <1-100>
```
3. Enable rate limiting on a weighted queue:  

```
qos queue-profile queue <1-5> <0-7> rate-limit-enable
```
4. Apply the queue profile:  

```
qos queue-profile <1-5> apply
```
5. Verify the egress queue configuration:  

```
show qos queue-profile [<1-5> queue <0-7>|all]
```

## 6. (Optional) Configure the default settings for an egress queue:

- Configure the default minimum weight using one of the following commands:

```
default qos queue-profile queue <1-5> <0-7> min-weight
```

```
no qos queue-profile queue <1-5> <0-7> min-weight
```

- Configure the default rate limiting on a weighted queue using one of the following commands:

```
default qos queue-profile queue <1-5> <0-7> rate-limit-enable
```

```
no qos queue-profile queue <1-5> <0-7> rate-limit-enable
```

### Example

Configure the queue profile for queue 1 to use a weight of 20, and enable rate limiting.

```
Switch:1(config)#qos queue-profile queue 1 1 min-weight 20
Switch:1(config)#qos queue-profile queue 1 1 rate-limit-enable
Switch:1(config)#qos queue-profile 1 apply
```

View the queue profile configuration.

```
Switch:1#show qos queue-profile
```

```
=====
                        Qos Queue Profile
=====

Profile Profile
ID      Name
-----
1       default
```

```
Switch:1(config)#show qos queue-profile 1 queue 1
```

```
=====
                        Qos Queue Profile Table
=====


Profile Profile Queue Weight  Weight      Rate-limit Rate-limit
ID      Name   ID   Applied Configured Applied   Configured
-----
1       default 1    20      10         ENABLE   ENABLE
```

## Variable definitions


Use the data in the following table to use the `qos queue-profile queue` command.

Variable	Value
<1-5>	Specifies the queue profile ID.

*Table continues...*

Variable	Value
	<p> <b>Note:</b></p> <p>The switch supports only one queue profile with profile ID 1.</p>
<0-7>	Specifies the egress queue to configure.
min-weight <1-100>	<p>Configures the queue weight for weighted round robin, or the rate-limit in percentage of the link rate for queue shaping enabled on the queue.</p> <p>The following list identifies the default minimum weight for each queue:</p> <ul style="list-style-type: none"> <li>• Queue 0 — 5</li> <li>• Queue 1 — 20</li> <li>• Queue 2 — 30</li> <li>• Queue 3 — 40</li> <li>• Queue 4 — 50</li> <li>• Queue 5 — 50</li> <li>• Queue 6 — 50</li> <li>• Queue 7 — 5</li> </ul>
rate-limit-enable	Enables rate limiting on the queue. By default, rate limiting is enabled for queues 6 and 7 only; it is disabled for queues 0 through 5.

Use the data in the following table to use the **show qos queue-profile** command.

Variable	Value
<1-5>	<p>Specifies the queue profile ID. If you do not include a queue profile ID, the command output displays all configured profiles.</p> <p> <b>Note:</b></p> <p>The switch supports only one queue profile with a default ID of 1.</p>
<0-7>	<p>Specifies the egress queue.</p> <p>Displays configuration settings of the specified egress queue.</p>
all	The command output displays the configuration settings of all 8 egress queues of the queue profile.

# Chapter 8: QoS configuration using EDM

Configure Quality of Service (QoS) to allocate network resources where you need them most.

---

## Configuring port-based shaping

Configure egress port-based shaping to bind the maximum rate at which traffic leaves the port.

### Procedure

1. In the Device Physical View tab, select a port.
2. In the navigation pane, expand the **Configuration > Edit > Port** folders.
3. Click **General**.
4. Click the **Interface** tab.
5. From **EgressRateLimitState**, select **enable**.
6. In the **EgressRateLimit** box, type an egress rate limit in kilobits per second (Kb/s).
7. Click **Apply**.

---

## Configuring port-based policing

Use a port-based policer to bandwidth-limit ingress traffic. The system drops or re-marks violating traffic.

### Procedure

1. In the Device Physical View tab, select a port.
2. In the navigation tree, expand the following folders: **Configuration > Edit > Port**.
3. Click **General**.
4. Click the **Interface** tab.
5. From **IngressRatePeak**, type the value for the peak rate in Kbps.

The peak rate must be greater than or equal to the service rate.

6. From **IngressRateSvc** , type the value for the service rate in Kbps.
7. Click **Apply**.

---

## Configuring ingress port-rate limiter

Use the ingress port-rate limiter to limit the traffic rate accepted by the specified ingress port. The system drops or re-marks violating traffic.

### Procedure

1. In the Device Physical View tab, select a port.
2. In the navigation pane, expand the **Configuration > Edit > Port** folders.
3. Click **General**.
4. Click the **Interface** tab.
5. From **IngressRateLimit** , type the value in Kbps to set the traffic rate limit.  
The ingress rate limit must be between 1000 and 40000000.
6. Click **Apply**.

---

## Modifying ingress 802.1p to QoS mappings

Modify the ingress mappings to change traffic priorities. It is recommended that you use the default mappings.

### About this task

It is recommended that you do not change the default values. If you change the values, make sure that the values are consistent on all other devices in the network. Inconsistent mapping of table values can result in unpredictable service levels.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Mapping Tables**.
3. Click the **Ingress 8021p to QoS** tab.
4. Double-click a QosLevel field to change the value.
5. Click **Apply**.

---

## Ingress 8021p To QoS field descriptions

Use the data in the following table to use the **Ingress 8021p to QoS** tab.

Name	Description
<b>InIeee8021P</b>	Specifies the value of the IEEE 802.1p bit of the incoming packet.
<b>QoSLevel</b>	Specifies the equivalent egress QoS level (0–7).

---

## Modifying ingress DSCP to QoS mappings

Modify the ingress Differentiated Services Code Point (DSCP) to QoS mappings to change traffic priorities. It is recommended that you use the default mappings. Changes to the mapping table take effect after you restart the system.

### About this task

It is recommended that you do not change the default values. If you change the values, make sure that the values are consistent on all other devices in the network. Inconsistent mapping of table values can result in unpredictable service levels.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Mapping Tables**.
3. Click the **Ingress Dscp To QoS** tab.
4. Double-click a QoSLevel field to change the value.
5. Click **Apply**.

---

## Ingress Dscp To QoS field descriptions

Use the data in the following table to use the **Ingress Dscp To QoS** tab.

Name	Description
<b>InDscp</b>	Specifies the value of the DiffServ codepoint (in decimal format) in the IP header of the incoming packet.
<b>InDscpBinaryFormat</b>	Specifies the value of the DiffServ codepoint (in binary format) in the IP header of the incoming packet.
<b>QoSLevel</b>	Specifies the equivalent QoS level.

---

## Modifying egress QoS to 802.1p mappings

Modify the egress mappings to change the mappings between the QoS levels and the IEEE 802.1p bits.

### About this task

It is recommended that you do not change the default values. If you change the values, make sure that the values are consistent on all other devices in the network. Inconsistent mapping of table values can result in unpredictable service levels.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Mapping Tables**.
3. Click the **Egress QoS to 8021p** tab.
4. Double-click the Outleee8021P field to change the value.
5. Click **Apply**.

---

## Egress QoS to 8021p field descriptions

Use the data in the following table to use the **Egress QoS to 8021p** tab.

Name	Description
<b>QosLevel</b>	Specifies the QoS level of the outgoing packet.
<b>Outleee8021P</b>	Specifies the equivalent value of the IEEE 802.1p bit.

---

## Modifying egress QoS to DSCP mappings

Modify the egress QoS to DSCP mappings to change traffic priorities. It is recommended that you use the default mappings.

### About this task

It is recommended that you do not change the default values. If you change the values, make sure that the values are consistent on all other devices in the network. Inconsistent mapping of table values can result in unpredictable service levels.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **Mapping Tables**.
3. Click the **Egress QoS To Dscp** tab.

4. Double-click the OutDscp file to change the value.
5. Click **Apply**.

---

## Egress QoS To Dscp field descriptions

Use the data in the following table to use the **Egress QoS To Dscp** tab.

Name	Description
<b>QoSLevel</b>	Specifies the QoS level of the outgoing packet.
<b>OutDscp</b>	Specifies the equivalent value of the DiffServ code point (in decimal format).
<b>OutDscpBinaryFormat</b>	Specifies the equivalent value of the DiffServ code point (in binary format).

---

## Viewing port egress CoS queue statistics

Use the following procedure to retrieve the port egress CoS queue statistics. The system displays the statistics of the forwarded packets and bytes, and the dropped packets and bytes.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **CoS Queue Stats**.
3. Select the **Interface** tab.

---

## Interface field descriptions

The following table describes the fields from the CoS Queue Stats Interface tab.

Name	Description
<b>Index</b>	Indicates the loopback port number from 192(1/1) to 241(1/50).
<b>ClearStat</b>	Clears the port egress statistics.
<b>Que&lt;1–8&gt;OutPackets</b>	Indicates the out packets by CoS queue number 1–8.
<b>Que&lt;1–8&gt;OutBytes</b>	Indicates the out bytes by CoS queue number 1–8.
<b>Que&lt;1–8&gt;DropPackets</b>	Indicates the drop packets by CoS queue number 1–8.
<b>Que&lt;1–8&gt;DropBytes</b>	Indicates the drop bytes by CoS queue number 1–8.



---

## Clearing CPU statistics for the chassis

Use the following procedure to clear the CPU statistics for the chassis.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **CoS Queue Stats**.
3. Select the **CPU-Stats-Clear** tab.
4. Select the **CpuStatsClear** check box.
5. Click **Apply**.

---

## Viewing CPU queue statistics

Use the following procedure to retrieve the statistics of the forwarded packets and bytes, and the dropped packets and bytes for the traffic sent toward CP. The queue assignment is based on the protocol types, not on the internal CoS value. These statistics are useful for debugging purposes.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > QOS**.
2. Click **CoS Queue Stats**.
3. Select the **CPU-Port** tab.

---

## CPU-Port field descriptions

The following table describes the fields from the CoS Queue Statistics CPU-Port tab.

**Table 23: Variable definitions**

Name	Description
Index	Indicates the CoS queue number from 0-15.
OutPackets	Indicates the out packets for the CPU port.
OutBytes	Indicates the out bytes for the CPU port.
DropPackets	Indicates the drop packets for the CPU port.
DropBytes	Indicates the drop bytes for the CPU port.

---

## Configuring an egress QoS queue profile

Configure a queue profile to apply the configured egress queue parameters to queues and ports. You must apply the profile before the changes take effect.

Currently the switch supports only one queue profile that is automatically created on system boot up, with an ID of 1 and name of default. You cannot delete this profile.

### Procedure

1. In the navigation pane, expand the following folders: **Configuration > QoS**.
2. Click **Queue Profile**.
3. Click the **Queue Profile** tab.
 

The default queue profile displays.
4. In the **Apply** field, double click and select **true** to apply the profile.
5. Click **Apply**.

---

## Queue Profile field descriptions

Use the data in the following table to use the **Queue Profile** tab.

Field	Description
Id	Displays the default queue profile ID. The default ID is 1.
Name	Displays the name of the queue profile as default.
Apply	Specifies the status of the queue profile, as true or false.

---

## Editing queue profile information

### About this task

Use the following procedure to edit queues of a queue profile, to configure a queue weight or enable rate limiting on the queue.

 **Note:**

After you make the configuration changes, you must apply the queue profile before the changes take effect.

### Procedure

1. In the navigation pane, expand the following folders: **Configuration > QoS**.

2. Click **Queue Profile**.
3. Update a queue to configure queue weight or rate limiting.
  - a. Click the **Queue** tab.
  - b. Edit the **AdminWeight** and **AdminRateLimitStatus** fields by double-clicking on them, and then selecting or typing the new value.
  - c. Click **Apply**.
4. Apply the queue profile for the queue configuration to take effect.
  - a. Click the **Queue Profile** tab.
  - b. In the **Apply** field, double-click and select **true**.
  - c. Click **Apply**.
5. Click the **Queue** tab again, to verify updates to the **OperWeight** and the **OperRateLimitStatus** fields, for the respective queue.

---

## Queue field descriptions


Use the data in the following table to use the **Queue** tab.

Field	Description
PId	Displays the queue profile ID.
Id	Displays the queue ID.
AdminWeight	Specifies the administrative weight of the queue.
OperWeight	Displays the operational weight of the profile, described as a percentage.
AdminRateLimitStatus	Specifies the administrative status of the queue rate limit as true or false.
OperRateLimitStatus	Displays the operational status of the queue rate limit.

# Chapter 9: Access control list configuration using CLI

Use an access control list (ACL) to specify an ordered list of access control entries (ACE), or filter rules. The ACEs provide specific actions that you want the filter to perform.

The following task flow shows you the sequence of procedures you perform to create and configure an ACL.



**Figure 4: Access control list configuration using CLI procedures**

---

## Creating an IPv4 ACL

Create an ACL to specify an ordered list of ACEs, or filter rules.

### Procedure

1. Enter Global Configuration mode:

```
enable
```

```
configure terminal
```

2. Create an ACL:

```
filter acl <1-2048> type <inVlan|inPort|outPort> [name WORD<0-32>]
```

3. Enable an ACL:

```
filter acl [enable]
```

4. Ensure the configuration is correct:

```
show filter acl [<1-2048>]
```

## Variable definitions

Use the data in the following table to use the `filter acl` command.

**Table 24: Variable definitions**

Variable	Value
<1-2048>	Specifies a unique identifier (1–2048) for the ACL.
enable	Enables the ACL state, and all associated ACEs. Enabled is the default state.
name WORD<0-32>	Specifies an optional descriptive name for the ACL.
type <inVlan inPort outPort>	Specifies the ACL type. The values inVlan and inPort are ingress ACLs, and outPort are egress ACLs. A port-based ACL has precedence over a VLAN-based ACL.

## Creating an IPv6 ACL

Create an IPv6 ACL to specify an ordered list of ACEs, or filter rules.

You must specify the packet type as IPv6 at the ACL level to enable IPv6 filtering. By default, an ACL filters non IPv6 packets.

**\* Note:**

You cannot change packet type for the ACL once you have configured it. If you want a different packet type, you must delete the ACL and re-create it using the other packet type.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Create an IPv6 ACL:

```
filter acl <1-2048> type <inVlan|inPort> [name WORD<0-32>] [pktType
ipv6] [enable]
```

**\* Note:**

IPv6 ingress QoS ACL/Filters and IPv6 egress security and QoS ACL/Filters are not supported.

3. Ensure the configuration is correct:

```
show filter acl [<1-2048>]
```

## Variable definitions

Use the data in the following table to use the `filter acl` command.

**Table 25: Variable definitions**

Variable	Value
<1-2048>	Specifies a unique identifier (1–2048) for the ACL.
enable	Enables the ACL state, and all associated ACEs. Enabled is the default state.
name WORD<0-32>	Specifies an optional descriptive name for the ACL.
type <inVlan inPort>	Specifies the ACL type. The values inVlan and inPort are ingress ACLs. IPv6 ingress QoS ACL/Filters and IPv6 egress security and QoS ACL/Filters are not supported. A port-based ACL has precedence over a VLAN-based ACL.
pktType <ipv6>	Specifies the IP version as IPv6. The default is nonipv6.  <b>* Note:</b> You cannot change packet type for the ACL once you have configured it. If you want a different packet type, you must delete the ACL and re-create it using the other packet type.

## Associating VLANs with an ACL

Associate VLANs with an ACL to apply filters to VLAN traffic.

A VLAN can be part of two different ACLs of different types: IPv6 and non-IPv6.

### Before you begin

- The ACL exists.

**Procedure**

1. Enter Global Configuration mode:
 

```
enable
configure terminal
```
2. Add VLAN interfaces to an ACL:
 

```
filter acl vlan <1-2048> <1-4059>
```
3. Remove specified VLAN interfaces from an ACL:
 

```
no filter acl vlan <1-2048> <1-4059>
```

**Variable definitions**

Use the data in the following table to use the `filter acl vlan` command.

Variable	Value
<1-2048>	Specifies an ACL ID from 1–2048.
<1-4059>	Specifies the VLAN ID in the range of 1 to 4059. By default, VLAN IDs 1 to 4059 are configurable and the system reserves VLAN IDs 4060 to 4094 for internal use. On switches that support the vrf-scaling and spbm-config-mode boot configuration flags, if you enable these flags, the system also reserves VLAN IDs 3500 to 3998. VLAN ID 1 is the default VLAN and you cannot create or delete VLAN ID 1.

**Associating ports with an ACL**

Associate ports with an ACL to apply filters to port traffic.

A port can be part of two different ACLs of different types: IPv6 and non-IPv6.

**Before you begin**

- The ACL exists.

**Procedure**

1. Enter Global Configuration mode:
 

```
enable
configure terminal
```
2. Associate port interfaces with a particular ACL:
 

```
filter acl port <1-2048> {slot/port[/sub-port] [-slot/port[/sub-port]][, ...]}
```



### 3. Remove port interfaces from a particular ACL:

```
no filter acl port <1-2048> {slot/port[/sub-port] [-slot/port[/sub-
port]] [,...]}
```

---

## Variable definitions

Use the data in the following table to use the `filter acl port` command.

Variable	Value
<1-2048>	Specifies an ACL ID from 1–2048.
{slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}	Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.

---

## Configuring global and default actions for an ACL

Configure the default action to specify packet treatment if a packet does not match any ACE.

Configure the global action to specify packet treatment if a packet does match an ACE.

Global action can only be configured for Ingress ACLs.

### Before you begin

- The ACL exists.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Configure the global action for an ACL:

```
filter acl set <1-2048> global-action [monitor-dst-ports {slot/
port[/sub-port] [-slot/port[/sub-port]] [,...]] [monitor-dst-mlt <1-
512>]
```

3. Configure an ACL to the default global action settings:

```
default filter acl set <1-2048> global-action [monitor-dst-ports]
```

4. Configure the default action for an ACL:

```
filter acl set <1-2048> default-action <permit|deny>
```

## 5. Configure an ACL to the default action settings:

```
default filter acl set <1-2048> default-action
```

---

## Variable definitions

Use the data in the following table to use the `filter acl set` commands.

Variable	Value
<1-2048>	Specifies the ACL ID.
default-action <deny permit>	Specifies the default action to take when none of the ACEs match. Options are <deny permit>. The default is permit.
monitor-dst-ports {slot/port[/sub-port] [-slot/port[/sub-port]] [...]}	<p>Specifies the global action to take for matching ACEs:</p> <ul style="list-style-type: none"> <li>monitor destination ports—Configures mirroring to a destination port or ports.</li> </ul> <p>Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.</p>
monitor-dst-mlt <1–512>	Configures mirroring to a destination MLT in the range of 1 to 512.

---

## Renaming an ACL

Perform this procedure to change the name of an existing ACL.

### Procedure

## 1. Enter Global Configuration mode:

```
enable
configure terminal
```

## 2. Rename an ACL:

```
filter acl <1-2048> name WORD<0-32>
```

## 3. Reset the ACL name to the default name:

```
default filter acl <1-2048> name
```

---

## Variable definitions

Use the data in the following table to use the `filter acl` command.

**Table 26: Variable definitions**

Variable	Value
<1-2048>	Specifies a unique identifier (1–2048) for the ACL.
enable	Enables the ACL state, and all associated ACEs. Enabled is the default state.
name <i>WORD</i> <0-32>	Specifies an optional descriptive name for the ACL.
type <inVlan inPort outPort>	Specifies the ACL type. The values inVlan and inPort are ingress ACLs, and outPort are egress ACLs. A port-based ACL has precedence over a VLAN-based ACL.

---

## Disabling an ACL

Perform this procedure to disable an ACL and all ACEs that belong to it.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Disable an ACL:

```
no filter acl <1-2048> enable
```

---

## Variable definitions

Use the data in the following table to use the `filter acl` command.

**Table 27: Variable definitions**

Variable	Value
<1-2048>	Specifies a unique identifier (1–2048) for the ACL.
enable	Enables the ACL state, and all associated ACEs. Enabled is the default state.
name <i>WORD</i> <0-32>	Specifies an optional descriptive name for the ACL.
type <inVlan inPort outPort>	Specifies the ACL type. The values inVlan and inPort are ingress ACLs, and outPort are egress ACLs. A port-based ACL has precedence over a VLAN-based ACL.

---

## Resetting an ACL to default values

Reset an ACL to change the ACL name to the default name and the filter ACL mode to a default of enable.

### Procedure

1. Enter Global Configuration mode:
 

```
enable
configure terminal
```
2. Reset an ACL to default values:
 

```
default filter acl <1-2048>
```

---

## Variable definitions

Use the data in the following table to use the `filter acl` command.

**Table 28: Variable definitions**

Variable	Value
<1-2048>	Specifies a unique identifier (1–2048) for the ACL.
enable	Enables the ACL state, and all associated ACEs. Enabled is the default state.
name <i>WORD</i> <0-32>	Specifies an optional descriptive name for the ACL.
type <inVlan inPort outPort>	Specifies the ACL type. The values inVlan and inPort are ingress ACLs, and outPort are egress ACLs. A port-based ACL has precedence over a VLAN-based ACL.

---

## Deleting an ACL

Delete an ACL to remove an ordered list of filter rules.

### Procedure

1. Enter Global Configuration mode:
 

```
enable
configure terminal
```
2. Delete an ACL:
 

```
no filter acl <1-2048>
```

The following message appears:

```
WARNING: All ACE entries under this ACL will be Deleted.
Do you wish to delete this ACL? (y/n)?
```

3. Enter *y*.

---

## Variable definitions

Use the data in the following table to use the `filter acl` command.

**Table 29: Variable definitions**

Variable	Value
<1-2048>	Specifies a unique identifier (1–2048) for the ACL.
enable	Enables the ACL state, and all associated ACEs. Enabled is the default state.
name <i>WORD</i> <0-32>	Specifies an optional descriptive name for the ACL.
type <inVlan inPort outPort>	Specifies the ACL type. The values inVlan and inPort are ingress ACLs, and outPort are egress ACLs. A port-based ACL has precedence over a VLAN-based ACL.

# Chapter 10: Access control list configuration using EDM

Use traffic filtering to provide security by blocking unwanted traffic and prioritizing other traffic.

---

## Configuring an access control list

Use an access control list (ACL) to specify an ordered list of access control entries (ACE), or filter rules. The ACEs provide specific actions for the filter to perform.

### About this task

To modify an ACL parameter, double-click the parameter you wish to change. Change the value, and then click Apply. You cannot change a parameter that appears dimmed; in this case, delete the ACL, and then configure a new one.

### Procedure

1. In the navigation pane, expand the **Configuration > Security > Data Path** folders.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Click **Insert**.
5. In the **AcId** field, type an ACL ID from 1 to 2048, or accept the default value .
6. In **Type**, specify whether the ACL is VLAN or port-based, and whether it is ingress (in) or egress (out).

 **Note:**


IPv6 ingress QoS ACL/Filters and IPv6 Egress Security and QoS ACL/Filters are not supported.

7. In the **Name** field, specify a name for the ACL.
8. Perform one of the following:
  - a. If the ACL is VLAN-based, click the **VlanList** ellipsis, and then choose a VLAN list.
  - b. If the ACL is port-based, click the **PortList** ellipsis, and then choose a port list.

9. Select the desired ports, and then click **Ok**.
10. Configure the **DefaultAction**.
11. Configure the **ControlPktAction**.
12. Enable or disable the **State**, as required.
13. In the **PktType** field, select packet type appropriately to create either IPv4 or IPv6 ACLs.
14. Configure the remaining fields, as appropriate.
15. Click **Insert**.
16. To delete an ACL, select the ACL, and then click **Delete**.

## ACL field descriptions

Use the data in the following table to use the **ACL** tab.

Name	Description
<b>AcId</b>	Specifies a unique identifier for the ACL from 1–2048.
<b>Type</b>	Specifies whether the ACL is VLAN- or port-based. Valid options are <ul style="list-style-type: none"> <li>• inVlan</li> <li>• inPort</li> <li>• outPort</li> </ul> <p> <b>Important:</b> The inVlan ACLs drop packets if you add a VLAN after ACE creation.</p>
<b>Name</b>	Specifies a descriptive user-defined name for the ACL.
<b>VlanList</b>	For inVlan ACL types, specifies all VLANs to associate with the ACL.
<b>PortList</b>	For inPort and outPort ACL types, specifies the ports to associate with the ACL.
<b>DefaultAction</b>	Specifies the action taken when no ACEs in the ACL match. Valid options are deny and permit, with permit as the default. Deny means the system drops the packets; permit means the system forwards packets.
<b>ControlPktAction</b>	Specifies the action taken for control packets. Valid options are deny and permit.
<b>State</b>	Enables or disables all of the ACEs in the ACL. The default value is enable.
<b>PktType</b>	Indicates the packet type to which this ACL applies.
<b>MirrorMltd</b>	Configures mirroring to a destination MLT.
<b>MirrorDstPortList</b>	Configures mirroring to a destination port or ports.

# Chapter 11: Access control entry configuration using CLI

Use an access control entry (ACE) to provide an ordered list of traffic filtering rules.

---

## Configuring ACEs

Use an ACE to define packet attributes and the desired behavior for packets that carry the attribute or list of attributes.

### Before you begin

- The ACL exists. If you want to use IPv6 filters, you must specify the packet type as IPv6 at the ACL level to enable IPv6 filtering.

### About this task

The system reserves ACE IDs in the range of 1 to 1000 for security, and the range of 1001 to 2000 for QoS.

ACLs are by default created in enabled state while ACEs are by default created in disabled state. Use CLI commands to enable an ACE.

### Procedure

1. Enter Global Configuration mode:

```
enable  
configure terminal
```

2. Create and name an ACE:

```
filter acl ace <1-2048> <1-2000> [name WORD<0-32>]
```

The ACE ID determines ACE precedence (that is, the lower the ID, the higher the precedence).

#### **Note:**

This feature is partially supported on some hardware platforms. If you try to create an ACE ID between 1001 and 2000, the device displays the following error message:

**qos filters are not supported.**



3. Configure the mode as deny or permit:

```
filter acl ace action <1-2048> <1-2000> <deny|permit>
```

4. Configure ACE actions as required.

5. Ensure the configuration is correct:

```
show filter acl ace [<1-2048>] [<1-2000>]
```

6. Ensure the filter is enabled:

```
filter acl ace <1-2048> <1-2000> enable
```

7. Optionally, reset an ACE to default values (reset the ACE name to the default name and the administrative state to the default value of disable):

```
default filter acl ace <1-2048> <1-2000>
```


8. Optionally, delete an ACE ID:

```
no filter acl ace <1-2048> <1-2000>
```

## Variable definitions

Use the data in the following table to use the `filter acl ace` and the `filter acl ace action` commands.

**Table 30: Variable definitions**

Variable	Value
<1-2048>	Specifies the ACL ID.
<1-2000>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<deny permit>	Configures the action mode for security ACEs (1–1000).   <b>Note:</b> For each Security ACE (1-1000), you must define one or more actions as well as the associated action mode (permit or deny). Otherwise, the security ACE cannot be enabled. There is no default configuration for Security ACEs. With QoS ACEs (1001-2000), the action mode is not configurable. QoS ACEs are always set to action mode permit.
enable	Enables an ACE within an ACL.  After you enable an ACE, to make changes, first disable it.
name <i>WORD</i> <0-32>	Specifies an optional descriptive name for the ACE that uses 0–32 characters.

## Configuring ACE actions

Configure ACE actions to determine the process that occurs after a packet matches an ACE.

### Before you begin

- The ACE exists.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Configure ACE actions:

```
filter acl ace action <1-2048> <1-2000> <permit | deny>
```

3. **(Optional)** Configure ACE actions to count matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> count
```

4. **(Optional)** Configure the QoS level for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> internal-qos
<0-7>
```

5. **(Optional)** Enable mirroring on destination MLT for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> monitor-dst-
mlt <1-512>
```

6. **(Optional)** Enable mirroring on a port for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> monitor-dst-
ports {slot/port[/sub-port] [-slot/port[/sub-port]] [,...]}
```

7. **(Optional)** Enable mirroring on destination I-SID for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> monitor-
isid-offset <1-1000>
```

8. **(Optional)** Configure the next hop IPv4 or IPv6 address for redirect mode for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> redirect-
next-hop WORD<1-45> [count | unreachable | vrf {WORD <1-16>}]
```

### Important:

Ensure you configure the ACE match rules so that you only collect the desired traffic. For example, routed packets.

9. **(Optional)** Configure the next hop IPv4 or IPv6 address for redirect mode for matching packets for a VRF. If the next hop is unreachable, you can also configure ACE actions to permit/deny packet dropping within the VRF:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> redirect-
next-hop WORD<1-45> vrf WORD <1-16> unreachable <permit | deny>
```

10. **(Optional)** Configure the next hop IPv4 or IPv6 address for redirect mode for matching packets for a VRF. If the next hop is unreachable, you can also configure ACE actions to count matching packets, or to permit/deny packet dropping within the VRF:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> redirect-
next-hop WORD<1-45> vrf WORD <1-16> unreachable <permit | deny>
count
```

11. **(Optional)** Configure the QoS dot1 priority for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> remark-dot1p
<0-7>
```

12. **(Optional)** Configure the QoS phb and dscp for matching packets:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> remark-dscp
[phbcs0 | phbcs1 | phbaf11 | phbaf12 | phbaf13 | phbcs2 | phbaf21 |
phbaf22 | phbaf23 | phbcs3 | phbaf31 | phbaf32 | phbaf33 | phbcs4 |
phbaf41 | phbaf42 | phbaf43 | phbcs5 | phbef | phbcs6 | phbcs7]
```

13. **(Optional)** Configure the mode when next hop is unreachable:

```
filter acl ace action <1-2048> <1-2000> <permit | deny> unreachable
[permit | deny]
```

14. Ensure the configuration is correct:

```
show filter acl action [<1-2048>] [<1-2000>]
```

OR

```
show filter acl config
```

OR

```
show filter acl ace
```

## Example

```
Switch:1> enable
Switch:1# configure terminal
Switch:1(config)# show filter acl action
=====
Ace Action Table (Part IV)
=====
Acl   Ace   Monitor   Dscp   Ttl   Monitor   Isid   QoS   Remove-Tag
Id    Id    Dst-IP                               Isid   Offset
-----
10    100  0.0.0.0   ----   ----   16776009  10    1    TRUE

Switch:1> enable
Switch:1# configure terminal
Switch:1(config)# show filter acl config
=====
Filter ACL-ACE Configuration
=====
```

## Access control entry configuration using CLI

```
filter acl 10 type inPort name "ACL-10"
filter acl port 10 1/48
filter acl ace 10 100
filter acl ace action 10 100 deny
filter acl ace action 10 100 deny monitor-isid-offset 10 qos 3 remove-tag
filter acl ace ethernet 10 100 ether-type eq ip
filter acl ace ip 10 100 src-ip eq 40.1.1.10
filter acl ace 10 100 enable
```

```
Switch:1> enable
```

```
Switch:1# configure terminal
```

```
Switch:1(config)# show filter acl ace
```

```
=====
                        Ace Action Table (Part I)
=====
Acl  Ace  AceName          Admin  Oper   Mode   Mlt  Remark  Remark
Id   Id                               State  State                                Id  DSCP   Dot1p
-----
10   100  ACE-100           Enable Up      deny   0    disable disable
=====

                        Ace Action Table (Part II)
=====
Acl  Ace  Redirect vrf      Unreach Police  Internal
Id   Id  Next-Hop name     -able           Qos
-----
10   100  0.0.0.0 green             deny   0      0
=====

                        Ace Action Table (Part III)
=====
Acl  Ace  Ipfix   Count  Log   CopyTo  Monitor  Monitor  Monitor
Id   Id                               Pcap    Dst-Mlt  Dst-Vlan Dst-Port
-----
10   100  disable disable disable disable 0         0
=====

                        Ace Action Table (Part IV)
=====
Acl  Ace  Monitor          Dscp   Ttl   Monitor  Isid  QoS  Remove-Tag
Id   Id  Dst-Ip                               Isid  Offset
-----
10   100  0.0.0.0          ----   ----   16776009 10    3    TRUE
=====

Displayed 1 of 1 Entries
```

## Variable definitions

Use the data in the following table to use the **filter acl ace action** command.

Variable	Value
<1-2048>	Specifies the ACL ID.
<1-2000>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.

*Table continues...*

Variable	Value
	<p><b>* Note:</b></p> <p>The ACE IDs for QoS rules are not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>
count	Enables the ability to count matching packets. Use this parameter with either a security or QoS ACE. The default is disabled.
<deny permit>	<p>Configures the action mode for security ACEs.</p> <p><b>* Note:</b></p> <p>For each Security ACE (1-1000), you must define one or more actions as well as the associated action mode (permit or deny). Otherwise, the security ACE cannot be enabled. There is no default configuration for Security ACEs. With QoS ACEs (1001-2000), the action mode is not configurable. QoS ACEs are always set to action mode permit.</p>
monitor-isid-offset <1–1000>	<p>Specifies the offset ID which will be mapped to the actual monitor I-SID where packets are mirrored.</p> <p>Monitor I-SID = base monitor I-SID + offset ID.</p> <p>The base monitor I-SID is 16776000.</p> <p><b>* Note:</b></p> <p>This variable is not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>
remove-tag	<p>Removes the outer VLAN tag for matching packets.</p> <p><b>* Note:</b></p> <p>remove-tag is available only when matching packets are denied.</p> <p><b>* Note:</b></p> <p>This variable is not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>
qos <0–5>	<p>Defines the Quality of Service (QoS) profiles for the system.</p> <p>The monitoring I-SID can support six different QoS levels from 0 to 5. You can configure each QoS level individually.</p> <p>The default value is 1.</p> <p><b>* Note:</b></p> <p>This variable is not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>
internal-qos <0–7>	This variable is a QoS action. The ACE ID must be in the range of 1001–2000. The default value is 1.

*Table continues...*

Variable	Value
	<p><b>* Note:</b></p> <p>This variable is not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>
monitor-dst-ports {slot/port[/sub-port] [-slot/port[/sub-port]] [...]}	<p>Configures mirroring to a destination port or ports. This action is a security action. The ACE ID must be in the range of 1–1000.</p> <p>Identifies the slot and port in one of the following formats: a single slot and port (slot/port), a range of slots and ports (slot/port-slot/port), or a series of slots and ports (slot/port,slot/port,slot/port). If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.</p>
monitor-dst-mlt <1–512>	Configures mirroring to a destination MLT in the range of 1 to 512.
redirect-next-hop WORD <1–45>	<p>Specifies the nexthop IPv4 or IPv6 address for redirect node.</p> <p>This action is a security action. The ACE ID must be in the range of 1–1000.</p>
unreachable <permit deny>	<p>Denies or permits packet dropping when the next hop for the packet is unreachable.</p> <p>The default value is deny.</p> <p>This action is a security action. The ACE ID must be in the range of 1–1000.</p>
vrf WORD<1–16>	Specifies the direct next hop VRF name. The name must be in the range of 1 to 16 characters.
remark-dscp <phbcs0 phbcs1 phbaf11 phbaf12 phbaf13 phbcs2 phbaf21 phbaf22 phbaf23 phbcs3 phbaf31 phbaf32 phbaf33 phbcs4 phbaf41 phbaf42 phbaf43 phbcs5 phbcs6 phbef phbcs7>	<p>Specifies the new Per-Hop Behavior (PHB) for matching packets: phbcs0, phbcs1, phbaf11, phbaf12, phbaf13, phbcs2, phbaf21, phbaf22, phbaf23, phbcs3, phbaf31, phbaf32, phbaf33, phbcs4, phbaf41, phbaf42, phbaf43, phbcs5, phbef, phbcs6, phbcs7.</p> <p>This action is a QoS action. The ACE ID must be in the range of 1001–2000.</p> <p><b>* Note:</b></p> <p>This variable is not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>
remark-dot1p <0–7>	<p>Specifies the new 802.1 priority bit for matching packets: zero, one, two, three, four, five, six, or seven.</p> <p>This action is a QoS action. The ACE ID must be in the range of 1001–2000.</p> <p><b>* Note:</b></p> <p>This variable is not supported on all hardware platforms. For more information, see <i>Release Notes</i>.</p>

## Configuring ARP ACEs

Use ACE Address Resolution Protocol (ARP) entries to ensure the filter looks for ARP requests or responses.

You cannot configure ARP attributes for IPv6 filters.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. Enter Global Configuration mode:

```
enable
```

```
configure terminal
```

2. Configure an ACE for ARP packets:

```
filter acl ace arp <1-2048> <1-2000> operation eq <arprequest|
arpresponse>
```

3. Ensure the configuration is correct:

```
show filter acl arp [<1-2048>] [<1-2000>]
```

4. Optionally, delete the individual attributes from the ARP portion of the ACE:

```
no filter acl ace arp <1-2048> <1-2000> [operation]
```

5. Optionally, delete all the attributes from the ARP portion of the ACE:

```
default filter acl ace arp <1-2048> <1-2000>
```

## Variable definitions

Use the data in the following table to use the `filter acl ace arp` command.

**Table 31: Variable definitions**

Variable	Value
<1-2048>	Specifies the ACL ID.
<1-2000>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
operation eq <arprequest arpresponse>	Specifies the type of ARP operation to filter: arpRequest or arpResponse.

## Configuring an Ethernet ACE

Configure an Ethernet ACE to filter on Ethernet parameters.

You do not need to configure Ethertype for IPv6 filters. If you try to configure an Ethertype other than 0x86dd or IPv6 the device displays an error.

### Before you begin

- The ACL exists.
- The ACE exists.

### About this task

The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Configure an ACE for the destination or source MAC address attribute:

```
filter acl ace ethernet <1-2048> <1-2000> <dst-mac|src-mac> eq
WORD<1-1024>
```

**OR**

```
filter acl ace ethernet <1-2048> <1-2000> <dst-mac|src-mac> mask
WORD<1-1024> WORD<1-1024>
```

#### \* Note:

This is supported only for IPv4 filters.

3. Configure an ACE for an Ethernet type attribute:

```
filter acl ace ethernet <1-2048> <1-2000> ether-type eq WORD<1-200>
```

4. Configure an ACE for a port attribute:

```
filter acl ace ethernet <1-2048> <1-2000> port eq {slot/port[sub-
port]}
```

5. Configure an ACE for a VLAN attribute:

```
filter acl ace ethernet <1-2048> <1-2000> vlan-id eq <1-4059>
```

**OR**

```
filter acl ace ethernet <1-2048> <1-2000> vlan-id mask <1-4059>
<0-0xFFF>
```

6. Configure an ACE for a VLAN tagged priority attribute:



```
filter acl ace ethernet <1-2048> <1-2000> vlan-tag-prio eq <0-7>
```

OR

```
filter acl ace ethernet <1-2048> <1-2000> vlan-tag-prio mask <0-7>
<0-0x7>
```

7. Ensure the configuration is correct:

```
show filter acl ethernet [<1-2048>] [<1-2000>]
```

8. Optionally, delete the individual attributes from the Ethernet portion of the ACE:

```
no filter acl ace ethernet <1-2048> <1-2000>
```

9. Optionally, delete all the attributes from the Ethernet portion of the ACE:

```
default filter acl ace ethernet <1-2048> <1-2000>
```

## Variable definitions

Use the data in the following table to use the **filter acl ace ethernet** command.

Variable	Value
<0-7>	Specifies the priority bits (3-bit field) from the 802.1Q/p tag.
<0-0x7>	Specifies the mask value for VLAN tagged priority attribute.
<0-0xFFF>	Specifies the mask value for a VLAN attribute. For example: <pre>filter acl ace ethernet 10 10 vlan-id eq 10 filter acl ace ethernet 10 10 vlan-id mask 1025 0xF</pre>
<1-2000>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<1-2048>	Specifies the ACL ID.
<1-4059>	Specifies the VLAN ID in the range of 1 to 4059. By default, VLAN IDs 1 to 4059 are configurable and the system reserves VLAN IDs 4060 to 4094 for internal use. On switches that support the vrf-scaling and spbm-config-mode boot configuration flags, if you enable these flags, the system also reserves VLAN IDs 3500 to 3998. VLAN ID 1 is the default VLAN and you cannot create or delete VLAN ID 1.
{slot/port[/sub-port]}	Identifies a single slot and port. If your platform supports channelization and the port is channelized, you must also specify the sub-port in the format slot/port/sub-port.
WORD<1-200>	Specifies an ether-type name or number: <ul style="list-style-type: none"> <li>• 0x0–0xffff</li> </ul>

*Table continues...*

Variable	Value
	<ul style="list-style-type: none"> <li>ip, arp, ipx802dot3, ipx802dot2, ipxSnap, ipxEthernet2, appleTalk, decLat, decOther, sna802dot2, snaEthernet2, netBios, xns, vines, ipv6, rarp, or PPPoE</li> </ul>
<i>WORD</i> <1–1024>	<p>If the operator is mask, the <i>WORD</i>&lt;1–1024&gt; parameter is {" 1..48 ,  mac address mask 0x0..FFFFFFFF}}}</p> <p>If the operator is eq, the <i>WORD</i>&lt;1–1024&gt; parameter is the destination or source MAC address: AA:BB:CC:DD:EE:FF</p> <p>For example:</p> <pre>filter acl ace ethernet 10 10 dst-mac eq 0x01:00:5:00:00:01  filter acl ace ethernet 10 10 dst-mac mask 0x01:00:5:00:00:01 24  filter acl ace ethernet 10 10 src-mac mask 0x01:00:5:00:00:01 0xFFFFFFFF0000</pre>

## Configuring an IP ACE

Configure an IP ACE to filter on the source IP address, destination IP address, DiffServ Code Point (DSCP), protocol, IP options, and IP fragmentation parameters.

### Before you begin

- The ACL exists.
- The ACE exists.

### About this task

The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Configure an ACE for the DSCP attribute:

```
filter acl ace ip <1-2048> <1-2000> dscp eq {<0..63>|<0x00..0x3f>|
phbcs0|phbcs1|phbaf11|phbaf12|phbaf13|phbcs2|phbaf21|phbaf22|
phbaf23|phbcs3|phbaf31|phbaf32|phbaf33|phbcs4|phbaf41|phbaf42|
phbaf43|phbcs5|phbcs6|phbef|phbcs7}
```

OR

```
filter acl ace ip <1-2048> <1-2000> dscp mask {<0..63>|<0x00..0x3f>|
phbcs0|phbcs1|phbaf11|phbaf12|phbaf13|phbcs2|phbaf21|phbaf22|
phbaf23|phbcs3|phbaf31|phbaf32|phbaf33|phbcs4|phbaf41|phbaf42|
phbaf43|phbcs5|phbcs6|phbef|phbcs7} WORD<0x0-0x40>
```

3. Configure an ACE for the destination or source IP address attribute:

```
filter acl ace ip <1-2048> <1-2000> <dst-ip|src-ip> eq WORD<1-1024>
```

OR

```
filter acl ace ip <1-2048> <1-2000> <dst-ip|src-ip> mask WORD<1-
1024> {<0-32>|null|<A.B.C.D>}
```

4. Configure an ACE for the IP fragmentation attribute:

```
filter acl ace ip <1-2048> <1-2000> ip-frag-flag eq <noFragment|
anyFragment>
```

5. Configure an ACE for the IP options attribute:

```
filter acl ace ip <1-2048> <1-2000> ip-options any
```

6. Configure an ACE for the protocol type attribute:

```
filter acl ace ip <1-2048> <1-2000> ip-protocol-type eq WORD<1-256>
```

7. Ensure the configuration is correct:

```
show filter acl ip [<1-2048>] [<1-2000>]
```

8. Optionally, delete the individual attributes from the IP portion of the ACE:

```
no filter acl ace ip <1-2048> <1-2000> [dscp] [dstIp] [ipFragFlag]
[ipOptions] [ipProtoType] [srcIp]
```

9. Optionally, delete all the attributes from the IP (Layer 3) portion of the ACE:

```
default filter acl ace ip <1-2048> <1-2000>
```

### Example

```
Switch:1# filter acl ace ip 1 12 dst-ip eq 198.51.100.0
```

## Variable definitions

Use the data in the following table to use the **filter acl ace ip** command.

Variable	Value
<1-2000>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<1-2048>	Specifies the ACL ID.
{<0-32> null <A.B.C.D>}	Specifies the mask value for the destination or source IP address

*Table continues...*

Variable	Value
	<p>For example:</p> <pre>filter acl ace ip 10 10 dst-ip mask 198.51.100.0 25 filter acl ace ip 10 10 dst-ip mask 198.51.100.1 203.0.113.0 filter acl ace ip 10 10 src-ip mask 198.51.100.2 22 filter acl ace ip 10 10 src-ip mask 198.51.100.3 203.0.113.1</pre>
<noFragment anyFragment>	<p>Specifies a match option for IP fragments noFragment or anyFragment.</p>
{<0..63> <0x00..0x3f> phbcs0 phbcs1 phbaf11 phbaf12 phbaf13 phbcs2 phbaf21 phbaf22 phbaf23 phbcs3 phbaf31 phbaf32 phbaf33 phbcs4 phbaf41 phbaf42 phbaf43 phbcs5 phbcs6 phbef phbcs7}	<p>Specifies the DSCP value using one of the following formats:</p> <ul style="list-style-type: none"> <li>• Enter as an integer (0–63) or hex (0x00–0x3f), or as a string: <ul style="list-style-type: none"> <li>- phbcs0 — Enter as string “phbcs0”, integer 0 or hex 0x00</li> <li>- phbcs1 — Enter as string “phbcs1”, integer 8 or hex 0x08</li> <li>- phbaf11 — Enter as string “phbcs11” integer 10 or hex 0x0a</li> <li>- phbaf12 — Enter as string “phbcs12”, integer 12 or hex 0x0c</li> <li>- phbaf13 — Enter as string “phbcs13”, integer 14 or hex 0x0e</li> <li>- phbcs2 — Enter as string “phbcs2”, integer 16 or hex 0x10</li> <li>- phbaf21 — Enter as string “phbcs21”, integer 18 or hex 0x12</li> <li>- phbaf22 — Enter as string “phbcs22”, integer 20 or hex 0x14</li> <li>- phbaf23 — Enter as string “phbcs23”, integer 22 or hex 0x16</li> <li>- phbcs3 — Enter as string “phbcs3”, integer 24 or hex 0x18</li> <li>- phbaf31 — Enter as string “phbcs31”, integer 26 or hex 0x1a</li> <li>- phbaf32 — Enter as string “phbcs32”, integer 28 or hex 0x1c</li> <li>- phbaf33 — Enter as string “phbcs33”, integer 30 or hex 0x1e</li> <li>- phbcs4 — Enter as string “phbcs4”, integer 32 or hex 0x20</li> <li>- phbaf41 — Enter as string “phbcs41”, integer 34 or hex 0x22</li> <li>- phbaf42 — Enter as string “phbcs42”, integer 36 or hex 0x24</li> <li>- phbaf43 — Enter as string “phbcs43”, integer 38 or hex 0x26</li> <li>-  phbcs5 — Enter as string “phbcs5”, integer 40 or hex 0x28</li> <li>- phbcs6 — Enter as string “phbcs6”, integer 46 or hex 0x2e</li> <li>- phbef — Enter as string “phbef”, integer 48 or hex 0x30</li> <li>- phbcs7 — Enter as string “phbcs7”, integer 56 or hex 0x38</li> </ul> </li> </ul>
WORD<0x0-0x40>	<p>Specifies the mask value, for example,</p> <pre>filter acl ace ip 10 10 dscp mask 129 0x40</pre>

Table continues...

Variable	Value
<i>WORD</i> <1-256>	Specifies one or more IP protocol types: (1–256), or tcp, udp, ipsecesp, vrrp, snmp or undefined.
<i>WORD</i> <1–1024>	Specifies the destination or source IP address (a.b.c.d).

## Configuring an IPv6 ACE

Configure an IPv6 ACE to filter traffic based on Source IPv6 address, Destination IPv6 address, IPv6 next header and IPv6 traffic class.

Source IPv6 and destination IPv6 support equal (eq) and mask operators. Next header and traffic class attributes support the equal (eq) operator. The equal to rule operator looks for an exact match with the field defined. If the field matches exactly with the rule, the system will return a match (hit). ACL-based filters provide the mask operator to match on Layer 2, Layer 3, and Layer 4 packet fields. The mask operator is used to mask bits in packet fields during a search or to match on a partial value of a packet field.

### Before you begin

- The ACL exists. The ACL exists with the IPv6 packet type. You can only configure ACE IPv6 attributes to filter on an IPv6 packet.
- The ACE exists.

### About this task

The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.

### Procedure

1. Enter Global Configuration mode:

```
enable
configure terminal
```

2. Create and name an ACE:

```
filter acl ace <1-2048> <1-2000> [name Word<1-32>]
```

3. Configure an ACE for the destination IPv6 address attribute:

```
filter acl ace ipv6 <1-2048> <1-2000> dst-ipv6 eq WORD<0-255>
```

OR

```
filter acl ace ipv6 <1-2048> <1-2000> dst-ipv6 mask WORD<1-128>
WORD<0-255>
```

4. Configure an ACE for the source IP address attribute:

```
filter acl ace ipv6 <1-2048> <1-2000> src-ipv6 eq WORD<0-255>
```

OR

```
filter acl ace ipv6 src-ipv6 <1-2048> <1-2000> mask WORD<1-128>  
WORD<0-255>
```

5. Specify the next header of the IP header:

```
filter acl ace ipv6 <1-2048> <1-2000> nxt-hdr eq {fragment|hop-by-hop|  
icmpv6|ipsecah|ipsecesp|noHdr|routing|tcp|udp|undefined}
```

You must configure next header to configure the protocol attributes.

6. Specify the traffic class attribute of the IPv6 header:

```
filter acl ace ipv6 <1-2048> <1-2000> traffic-class eq WORD<0-255>
```

7. Ensure that your configuration is correct:

```
show filter acl ipv6 [<1-2048>] [<1-2000>]
```

8. (Optional) Delete the individual attributes from the IPv6 portion of the ACE:

```
no filter acl ace ipv6 <1-2048> <1-2000> [dst-ipv6 ] [nxt-hdr] [src-  
ipv6] [traffic-class]
```

### Example

```
Switch:1# filter acl ace ipv6 15 15 dst-ipv6 eq 30:0:0:0:0:0:0:ffff/64
```

---

## Configuring a protocol ACE

Configure a protocol ACE to filter on the source port, destination port, ICMP and ICMPv6 message type, or TCP flags.

### \* Note:

For IPv6 filters, you must configure next header to configure the protocol attributes.

### Before you begin

- The ACL exists.
- The ACE exists.

### About this task

The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.

### Procedure

1. Enter Global Configuration mode:

```
enable  
configure terminal
```

## 2. Configure an ACE for destination port attributes:

```
filter acl ace protocol <1-2048> <1-2000> dst-port eq WORD<1-60>
```

OR

```
filter acl ace protocol <1-2048> <1-2000> dst-port mask WORD<1-60>
WORD<1-256>
```

## 3. Configure an ACE for source port attributes:

```
filter acl ace protocol <1-2048> <1-2000> src-port eq WORD<1-65535>
```

OR

```
filter acl ace protocol <1-2048> <1-2000> src-port mask WORD<1-
65535> WORD<1-256>
```

## 4. Configure an ACE for ICMP message type attributes:

```
filter acl ace protocol <1-2048> <1-2000> icmp-msg-type eq WORD<1-
200>
```

The icmp-msg-type command options support lists.

## 5. Configure an ACE for ICMPv6 message type attributes:

```
filter acl ace protocol <1-2048> <1-2000> icmpv6-msg-type eq WORD<1-
200>
```

The icmpv6-msg-type command options support lists.

## 6. Configure an ACE for TCP flags attributes:

```
filter acl ace protocol <1-2048> <1-2000> tcp-flags eq WORD<1-50>
```

OR

```
filter acl ace protocol <1-2048> <1-2000> tcp-flags mask {0-0x3F|
0-0x3F}
```

The tcp-flags command options support lists.

## 7. Ensure the configuration is correct:

```
show filter acl protocol [<1-2048>] [<1-2000>]
```

## 8. (Optional) Delete the individual attributes from the protocol portion of the ACE:

```
no filter acl ace protocol <1-2048> <1-2000> [dst-port] [icmp-msg-
type] [icmpv6-msg-type] [routing-type] [src-port] [tcp-flags]
```

## 9. (Optional) Delete all the attributes from the protocol portion of the ACE:

```
default filter acl ace protocol <1-2048> <1-2000>
```

### Example

#### Specify ICMP packets:

```
Switch:1(config)#filter acl ace protocol 1 12 icmpv6-msg-type eq echoRequest
```

**TCP Flags Order in Packet:**

32 (decimal)	16 (decimal)	8 (decimal)	4 (decimal)	2 (decimal)	1 (decimal)
<b>Urgent</b>	<b>Ack</b>	<b>Push</b>	<b>Reset</b>	<b>Syn</b>	<b>Fin</b>

**Configure an ACE for TCP flags attributes: Example 1**

The mask is set for an 'ack' tcp flag bit regardless of whether any other tcp flag bits are also set:

```
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags mask ack ?
    <0-0x3F | 0-63> Mask value <Hex | Decimal>: This six bit mask is a reverse mask where
0:care
    about, 1:do not care about
```

```
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags mask ack 0x2f
Hex Value 20 10 8 4 2 1
TCP Flags _ack
Binary Value 1 0 1 1 1 1 or in hex = 0x2F
```

**Configure an ACE for TCP flags attributes: Example 2**

A packet will match this filter if the 3 tcpflag bits are set in the tcp header (and only those 3 bits).

```
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags eq ?
WORD<1-50> Tcp flags
{none | fin | syn | rst | push | ack | urg | undefined}
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags eq syn,push,urg
```

You can configure a functionally equivalent filter with the mask operator as follows:

```
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags mask syn,push,urg 0x0
```

**Configure an ACE for TCP flags attributes: Example 3**

The mask operator provides more flexibility. For example a packet will match the following filter if the 'syn,push,urg' tcpflag bits are set, regardless of whether any other tcpflag bits are also set:

```
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags mask syn,push,urg ?
    <0-0x3F | 0-63> Mask value <Hex | Decimal>: This six bit mask is a reverse mask where
0:care
    about, 1:do not care about
```

```
Switch:1(config)#filter acl ace protocol 1 1 tcp-flags mask syn,push,urg 0x15
```

---

## Variable definitions

Use the data in the following table to use the `filter acl ace protocol` command.

**Table 32: Variable definitions**

Variable	Value
{0-0x3F}	Specifies the mask value.
<1-2000>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<1-2048>	Specifies the ACL ID.

*Table continues...*



Variable	Value
<i>WORD</i> <1–50>	Specifies one or more TCP flags—none, fin (finish connection), syn (synchronize), rst (reset connection), push, ack (acknowledge), urg (urgent), and undefined.
<i>WORD</i> <1–60>	Specifies the destination port: (0–65535), or echo, ftpdata, ftpcontrol, ssh, telnet, dns, http, hdot323, bootpServer, bootpClient, tftp, rtp, rtcp, or undefined.
<i>WORD</i> <1–200>	Specifies the ICMP message type: Icmpmsg type (0–255), or echoreply, destunreach, sourcequench, redirect, echo-request, routeradv, routerselct, time-exceeded, param-problem, timestamp-request, timestamp-reply, addressmask-request, addressmask-reply, or traceroute.
<i>WORD</i> <1–200>	Specifies the ICMPv6 message type: Icmpmsg type (0-255), or destUnreach, pktTooBig, timeExceeded, paramProblem, echoRequest, echoReply, mcastListenReq, mcastListenRpt, mcastListenDone, routerSolicit, routerAdvert, neighborSolicit, neighborAdvert, redirectMsg, nodeInfoReq, nodeInfoRsp, or v2McastListenRpt.
<i>WORD</i> <1–256>	Specifies the mask parameter, {0-0xFFFF}.
<i>WORD</i> <0–65535>	Specifies the source port (0–65535).

---

## Viewing ACL and ACE configuration data

View your configuration to review the information and ensure it is correct.

### Procedure

1. Enter Privileged EXEC mode:  
`enable`
2. View ACL information:  
`show filter acl [<1-2048>]`
3. View IPv6 ACL information:  
`show filter acl ipv6 [<1-2048>] [<1-2000>]`
4. View the running configuration for an ACL and corresponding ACE:  
`show filter acl config [<1-2048>] [<1-2000>]`

---

## Variable definitions

Use the data in the following table to use the `show filter acl` and `show filter acl config` commands.

**Table 33: Variable definitions**

Variable	Value
<1-2000>	Specifies an ACE ID from 1–2000. ACE IDs in the range 1–1000 are security ACEs; ACE IDs in the range 1001–2000 are QoS ACEs.
<1-2048>	Specifies an ACL ID from 1–2048.

# Chapter 12: Access control entry configuration using EDM

Use an access control entry (ACE) to define a pattern (found in a packet) and the desired behavior for packets that carry the pattern.

It is recommended that you create access control lists (ACL) with a default action of permit, and with an ACE mode of deny. For deny or permit ACLs or ACEs, the default action and the mode must be opposite for the ACE (filter) to have meaning.

---

## Configuring an ACE

Configure an ACE to define filter actions, for example, re-marking the Differentiated Services Code Point (DSCP), or mirroring.

### Before you begin

- The ACL exists.

### About this task

The system reserves ACE IDs in the range of 1 to 1000 for security, and the range of 1001 to 2000 for QoS.

### Procedure

1. In the navigation pane, expand the **Configuration > Security > Data Path** folders.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the ACL to which to add an ACE.
5. Click **ACE**.
6. Click the **ACE Common** tab.
7. Click **Insert**.
8. Configure the ACE ID.
9. Name the ACE.
10. Choose the mode: **deny** (drop packets) or **permit** (forward packets).

11. Configure the ACE actions as required.
12. Click **Insert**.
13. Configure the ACE attributes as required.
14. To enable the ACE, in the **ACE Common** tab, configure **AdminState** to enable, and then click **Apply**.
15. To delete an ACE Common entry, select the entry, and then click **Delete**.

## ACE Common field descriptions

Use the data in the following table to use the **ACE Common** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Name</b>	Specifies a descriptive user-defined name for the ACE. The system automatically assigns a name if you do not type one.
<b>AdminState</b>	Indicates the status of the ACE as enabled or disabled. You can modify an ACE only if you disable it.
<b>OperState</b>	Indicates the current operational state of the ACE.
<b>Mode</b>	Indicates the operating mode for this ACE. Valid options are deny and permit, with deny as the default.
<b>RedirectNextHop</b>	Redirects matching IPv4/IPv6 traffic to IPv4/IPv6 nexthop.
<b>RedirectNextHopVrfname</b>	Specifies the direct next hop VRF name. The name must be in the range of 1 to 16 characters.
<b>RedirectUnreach</b>	Denies or permits packet dropping when the next hop for the packet is unreachable.  The default value is deny.  This action is a security action. The ACE ID must be in the range of 1–1000.
<b>InternalQos</b>	This variable is a QoS action. The ACE ID must be in the range of 1001–2000. The default value is 1.
<b>RemarkDscp</b>	Specifies whether the DSCP parameter marks nonstandard traffic classes and local-use Per-Hop Behavior. The default is disable. Use this option to create a QoS ACE.
<b>RemarkDot1Priority</b>	Specifies whether Dot1 Priority, as described by Layer 2 standards (802.1Q and 802.1p) is enabled. The default is disable. Use this option to create a QoS ACE.

## Configuring ACE actions

Configure ACE actions to determine the process that occurs after a packet matches (or does not match) an ACE. Use debug actions (flags) to use filters for troubleshooting and monitoring procedures.

### Before you begin

- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration** > **Security** > **Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select an **Acelid**.
7. Click **Action**.
8. Configure the actions as required, and then click **Apply**.

## Action field descriptions

Use the data in the following table to use the **Action** tab.

### \* Note:

The table lists the options for both Security ACEs and QoS ACEs. Dependent upon the ACE, different options appear on the EDM interface.

Name	Description
<b>Acld</b>	Specifies the ACL ID from 1–2048
<b>Acelid</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Mode</b>	Configures the action mode for security ACEs. The default value is deny.
<b>RemarkDscp</b>	Specifies the new Per-Hop Behavior (PHB) for matching packets: phbcs0, phbcs1, phbaf11, phbaf12, phbaf13, phbcs2, phbaf21, phbaf22, phbaf23, phbcs3, phbaf31, phbaf32, phbaf33, phbcs4, phbaf41, phbaf42, phbaf43, phbcs5, phbef, phbcs6, phbcs7.

*Table continues...*

Name	Description
	This action is a QoS action. The ACE ID must be in the range of 1001–2000.
<b>RemarkDot1Priority</b>	Specifies the new 802.1 priority bit for matching packets: zero, one, two, three, four, five, six, or seven.  This action is a QoS action. The ACE ID must be in the range of 1001–2000.
<b>InternalQoS</b>	This variable is a QoS action. The ACE ID must be in the range of 1001–2000. The default value is 1.
<b>RedirectNextHop</b>	Specifies the next-hop IPv4 address (a.b.c.d) or IPv6 address (aaaa:bbbb:cccc:dddd:eeee:fff:gggg:hhhh) for redirect mode.  Applies to ingress ACLs (routed and L2 packets).
<b>Count</b>	Enables the ability to count matching packets. Use this parameter with either a security or QoS ACE. The default is disabled.
<b>DstPortList</b>	Configures mirroring to a destination port or ports. This action is a security action. The ACE ID must be in the range of 1–1000.
<b>DstMltid</b>	Configures mirroring to a destination MLT. This action is a security action. The ACE ID range is 1-1000.
<b>MonitoringIsidOffset</b>	Configures the monitoring I-SID offset value. The offset ID is mapped to the actual monitor I-SID value to which the packets are mirrored.
<b>MirroringQoS</b>	Defines the Quality of Service (QoS) profiles for the mirrored packet into monitoring I-SID.

---

## Configuring ACE ARP entries

Use ACE Address Resolution Protocol (ARP) entries so that the filter looks for ARP request or response packets.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.

3. Click the **ACL** tab.
4. Select a parameter for the appropriate ACL.
5. Click **ACE**.
6. Select a parameter for the appropriate ACE.
7. Click **Arp**.
8. Click **Insert**.
9. Select ARP request or response.
10. Click **Insert**.

---

## ARP field descriptions

Use the data in the following table to use the **ARP** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID from 1–2048.
<b>AceId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Type</b>	Specifies the ACE ARP operation. The only option is operation.
<b>Oper</b>	Specifies the operator for the ACE ARP operation. The only option is eq (equal).
<b>Value</b>	Specifies the ARP packet type. Valid options are arpRequest and arpResponse.

---

## Viewing all ACE ARP entries for an ACL

View all of the ACE ARP entries associated with an ACL.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **Arp**.
6. To modify a parameter, double-click the parameter, select the option, and then click **Apply**.

---

## ARP field descriptions

Use the data in the following table to use the **ARP** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Type</b>	Specifies the ACE ARP operation. The only option is operation.
<b>Oper</b>	Specifies the operator for the ACE ARP operation. The only option is eq (equal).
<b>Value</b>	Specifies the ARP packet type. Valid options are arpRequest and arpResponse.

---

## Configuring an ACE Ethernet source address

Perform this procedure to filter on specific Ethernet source addresses.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Eth**.
8. Click the **Source Address** tab.
9. Click **Insert**.
10. Specify the ACE Ethernet operation.
11. In the **List** dialog box, specify the Ethernet source address.
12. Click **Insert**.



---

## Source Address field descriptions

Use the data in the following table to use the **Source Address** tab.

**Table 34: Variable definitions**

Variable	Value
<b>Acld</b>	Specifies the ACL ID, from 1–2048.
<b>Aceld</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>List</b>	Specifies the MAC address to match.
<b>OperMask</b>	Specifies the MAC Address mask value in hexadecimal format. The value for this variable is empty or 000000000000 if the <b>Oper</b> variable is eq.

---

## Configuring an ACE Ethernet destination address

Perform this procedure to filter on specific Ethernet destination addresses.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Eth**.
8. Click the **Destination Address** tab.
9. Click **Insert**.
10. Specify the ACE Ethernet operation.

11. In the **List** dialog box, specify the Ethernet source address.
12. Click **Insert**.

---

## Destination Address field descriptions

Use the data in the following table to use the **Destination Address** tab.

**Table 35: Variable definitions**

Variable	Value
<b>AcId</b>	Specifies the ACL ID.
<b>AcId</b>	Specifies the associated ACE index.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>List</b>	Specifies the MAC address to match.
<b>OperMask</b>	Specifies the MAC address mask value in hexadecimal format if the <b>Oper</b> variable is mask. The value of this variable is empty or 000000000000 if <b>Oper</b> is eq.

---

## Configuring an ACE LAN traffic type

Perform this procedure to filter for specific LAN traffic packets.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Eth**.
8. Click the **Ethernet Type** tab.
9. Click **Insert**.

10. Specify the operation type.
11. In the **TypeList** box, type the Ethernet types.
12. Click **Insert**.

---

## Ethernet Type field descriptions

Use the data in the following table to use the **Ethernet Type** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>TypeOper</b>	The eq parameter specifies an operator for a field match condition: equal to.
<b>TypeList</b>	Specifies the Ethernet type. Entries include: 0 to 0xffff or ip, arp, ipx802.3, ipx802.2, ipxSnap, ipxEthernet2, appleTalk, appleTalk-ARP, sna802.2, snaEthernet2, netBios, xns, vines, ipv6, rarp, PPPoE-discovery, and PPPoE-session.

---

## Configuring an ACE Ethernet VLAN tag priority

Perform this procedure to filter for specific VLAN tag priorities.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Eth**.
8. Click the **Vlan Tag Priority** tab.
9. Click **Insert**.

10. Specify the operation type.
11. In the **VlanTagPrio** box, select the priority bits.
12. Click **Insert**.

---

## VLAN Tag Priority field descriptions

Use the data in the following table to use the **Vlan Tag Priority** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>VlanTagPrio</b>	Specifies the priority bits (3-bit field) from the 802.1Q/p tag: <ul style="list-style-type: none"> <li>• zero</li> <li>• one</li> <li>• two</li> <li>• three</li> <li>• four</li> <li>• five</li> <li>• six</li> <li>• seven</li> </ul>
<b>OperMask</b>	Specifies the mask value in hexadecimal format if the <b>Oper</b> value is mask.

---

## Configuring an ACE Ethernet port

Use ACE Ethernet port entries so that the filter looks for traffic on specific ports. You can only insert an ACE Common Ethernet port for VLAN ACL types.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.

2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Eth**.
8. Click the **Port** tab.
9. Click **Insert**.
10. Specify the operation type.
11. Click the **Port** ellipses (...).
12. Choose the ports.
13. Click **OK**.
14. Click **Insert**.

---

## Port field descriptions

Use the data in the following table to use the **Port** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq parameter specifies an operator for a field match condition: equal to.
<b>Port</b>	Specifies the port or port list on which to perform a match.

---

## Configuring an ACE Ethernet VLAN ID

Use ACE Ethernet VLAN ID entries so that the filter looks for traffic on specific VLANs. You can insert an ACE Ethernet VLAN ID only for ACL VLAN types.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.

2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Eth**.
8. Click the **Vlan Id** tab.
9. Click **Insert**.
10. Specify the operation type.
11. Enter the VLAN ID or select from a list.
12. Click **Insert**.

---

## VLAN ID field descriptions

Use the data in the following table to use the **Vlan Id** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq parameter specifies an operator for a field match condition: equal to.
<b>VlanId</b>	Specifies the VLAN ID on which to perform a match.
<b>OperMask</b>	Specifies the mask value for a VLAN attribute.

---

## Viewing all ACE Ethernet entries for an ACL

View all of the ACE Ethernet entries associated with an ACL.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **Eth**.

## Ethernet field descriptions

Use the data in the following table to use the **Ethernet** tab.

Name	Description
<b>AcId</b>	Shows the ACL ID.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>SrcAddrList</b>	Shows the list of Ethernet source addresses to match.
<b>SrcAddrOper</b>	Shows the operators for the ACE Ethernet source MAC address.
<b>SrcAddrOperMask</b>	Shows the source MAC address mask value in hexadecimal format if the <b>SrcAddrOper</b> variable is mask. The value of this field is empty or 000000000000 if the <b>SrcAddrOper</b> field is eq.
<b>DstAddrList</b>	Shows the list of Ethernet destination addresses to match.
<b>DstAddrOper</b>	Shows the operators for the ACE Ethernet destination MAC address.
<b>DstAddrOperMask</b>	Shows the destination MAC address mask value in hexadecimal format if the <b>DstAddrOper</b> variable is mask. The value for this field is empty or 000000000000 if the <b>DstAddrOper</b> field is eq
<b>EtherTypeList</b>	Shows the EtherType value from the Ethernet header. For example, ARP uses 0x0806 and IP uses 0x0800.  Platform support determines the behavior for 802.1Q/p tagged packets. The EtherType for 802.1Q tagged frames is 0x8100.  The range is 0–65535 and supports lists and ranges of values. An invalid Ether-type of 65536 indicates that you do not want the parameter in the match criteria.
<b>EtherTypeOper</b>	Shows the Ethernet type operators.
<b>VlanTagPrio</b>	Shows the priority bits (3-bit field) from the 802.1Q/p tag.
<b>VlanTagPrioOper</b>	Shows the operators for the ACE Ethernet VLAN tag priority.
<b>VlanTagPrioOperMask</b>	Shows the VLAN tag priority mask value in hexadecimal format if the <b>VlanTagPrioOper</b> field is mask.
<b>Port</b>	Shows the port number or port list to match.
<b>PortOper</b>	Shows the operator for the ACE Ethernet port.
<b>VlanId</b>	Shows the VLAN ID to match.
<b>VlanIdOper</b>	Shows the operator for the ACE Ethernet VLAN ID.
<b>VlanIdOperMask</b>	Shows the VLAN ID mask value in hexadecimal format if the <b>VlanIdOper</b> field is mask.

---

## Configuring an ACE IP source address

Configure ACE IP source address entries to have the filter look for specific source IP addresses.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IP**.
8. Click the Source Address tab.
9. Click **Insert**.
10. Specify the operation type.
11. In the **IPAddr** box, enter the source IP address.
12. Click **Insert**.

---

## Source Address field descriptions

Use the data in the following table to use the **Source Address** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>IPAddr</b>	Specifies the source IP address.
<b>OperMask</b>	Specifies the mask value for the source IP address.



## Configuring an ACE IP destination address

Configure ACE IP destination address entries to have the filter look for specific destination IP addresses.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IP**.
8. Click the **Destination Address** tab.
9. Click **Insert**.
10. Specify the operation type.
11. In the **IPAddr** box, enter the destination IP address.
12. Click **Insert**.

## Destination Address field descriptions

Use the data in the following table to use the **Destination Address** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>IPAddr</b>	Specifies the destination IP address.
<b>OperMask</b>	Specifies the mask value for the destination IP address.

## Configuring an ACE IP DSCP

Configure ACE IP DSCP entries to have the filter look for packets with specific DSCP markings.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IP**.
8. Click the **DSCP** tab.
9. Click **Insert**.
10. Specify the operation type.
11. In the **List** box, enter the count for the DSCP values.
12. Click **Insert**.

## DSCP field descriptions

Use the data in the following table to use the **DSCP** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>List</b>	Specifies a count for the number of discrete ranges entered for the DSCP values. Entries include 0–256, disable, phbcs0, phbcs1, phbaf11, phbaf12, phbaf13, phbcs2, phbaf21, phbaf22, phbaf23, phbcs3, phbaf31, phbaf32, phbaf33, phbcs4, phbaf41, phbaf42, phbaf43, phbcs5, phbcs6, phbef, and phbcs7.
<b>OperMask</b>	Specifies the mask value.

## Configuring an ACE IP protocol

Configure ACE IP protocol entries to have the filter look for packets of specific protocols.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IP**.
8. Click the **Protocol** tab.
9. Click **Insert**.
10. Specify the operation type.
11. In the **List** box, enter the IP protocol type.
12. Click **Insert**.

## Protocol field descriptions

Use the data in the following table to use the **Protocol** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq parameter specifies an operator for a field match condition: equal to.
<b>List</b>	Specifies the IP protocol type. Entries include 0–256, undefined, tcp, udp, ipsecesp, vrrp, and undefined.

## Configuring ACE IP options

Configure ACE IP option entries to have the filter look for packets with an IP option specified.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IP**.
8. Click the **Options** tab.
9. Click **Insert**.
10. Specify the logical operator.  
**Any** is the only choice.
11. Click **Insert**.

## Options field descriptions

Use the data in the following table to use the **Options** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	Specifies the logical operator for the ACE IP options. Any is the only option.

## Configuring ACE IP fragmentation

Configure ACE IP fragmentation entries to have the filter look for packets with the fragmentation flag.

**Before you begin**

- The ACL exists.
- The ACE exists.

**Procedure**

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IP**.
8. Click the **Fragmentation** tab.
9. Click **Insert**.
10. Specify the operator for IP fragmentation.  
**Eq** is the only choice.
11. Specify the fragmentation bits to match from the IP header.
12. Click **Insert**.

---

**Fragmentation field descriptions**

Use the data in the following table to use the **Fragmentation** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Fragmentation</b>	Specifies the IP fragmentation bits to match from the IP header: <ul style="list-style-type: none"> <li>• noFragment</li> <li>• anyFragment</li> </ul> The default is noFragment.

## Viewing all ACE IP entries for an ACL

View all of the ACE IP entries associated with an ACL.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **IP**.

## IP field descriptions

Use the data in the following table to use the **IP** tab.

Name	Description
<b>AcId</b>	Shows the ACL IP ID.
<b>AcId</b>	Shows the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>SrcAddrOper</b>	Shows the operators for the ACE IP source address.
<b>SrcAddrIpAddr</b>	Shows the IP source address to match from the IP header.
<b>SrcAddrOperMaskRange</b>	Shows the IP mask value if <b>SrcAddrOper</b> is set to mask, or the highest IP address if <b>SrcAddrOper</b> is set to range.
<b>DstAddrOper</b>	Shows the operators for the ACE IP destination address.
<b>DstAddrIpAddr</b>	Shows the IP destination address to match from the IP header.
<b>DstAddrOperMaskRange</b>	Shows the IP mask value if <b>DstAddrIpAddr</b> is set to mask, or the highest IP address if <b>DstAddrIpAddr</b> is set to range.
<b>DscpList</b>	Shows how the 6-bit DSCP parameter from the TOS byte in the IPv4 header encodes PHB information following RFC 2474.
<b>DscpOper</b>	Shows the operators for the ACE IP DSCP.
<b>DscpOperMask</b>	Shows the mask value in hexadecimal format when the mask option is selected in <b>DscpOper</b> .
<b>ProtoList</b>	Shows the IP protocol type from the IP header to match. The range is 0–255.
<b>ProtoOper</b>	Shows the operators for the ACE IP protocols.
<b>Options</b>	Shows the IP options to match from the IP header.
<b>OptionsOper</b>	Shows the logical operator. Any is the only option.
<b>Fragmentation</b>	Shows the IP fragmentation bits to match from the IP header.
<b>FragOper</b>	Shows the operator for IP fragmentation.

## Configuring an ACE IPv6 source address

Configure ACE IPv6 source address entries to have the filter look for specific source IP addresses.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IPv6**.
8. Click the **Source Address** tab.
9. Click **Insert**.
10. In the **Oper** field, select the operation type.
11. In the **List** field, enter the source IP address.
12. In the **OperMask** field, enter the operation mask value.
13. Click **Insert**.

## Source Address field descriptions

Use the data in the following table to use the **Source Address** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>List</b>	Specifies the source IP address.
<b>OperMask</b>	Specifies the mask value for the source IP address.

---

## Configuring an ACE IPv6 destination address

Configure ACE IPv6 destination address entries to have the filter look for specific destination IP addresses.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IPv6**.
8. Click the **Destination Address** tab.
9. Click **Insert**.
10. In the **Oper** field, select the operation type.
11. In the **List** field, enter the destination IP address.
12. In the **OperMask** field, enter the operation mask value.
13. Click **Insert**.

---

## Destination Address field descriptions

Use the data in the following table to use the **Destination Address** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>List</b>	Specifies the destination IP address.
<b>OperMask</b>	Specifies the mask value for the destination IP address.



## Configuring an ACE IPv6 next header

Configure ACE IPv6 next header entries to have the filter look for specific next headers.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IPv6**.
8. Click the **Next Hdr** tab.
9. Click **Insert**.
10. In the **Oper** field, select the operation type.
11. In the **NextHdr** field, select the next header type.
12. Click **Insert**.

## Next Header field descriptions

Use the data in the following table to use the **Next Hdr** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq parameter specifies an operator for an “equal to” field match condition.
<b>NextHdr</b>	Specifies the next header of the IPv6 header. Specifies hop-by-hop, tcp, udp, routing, fragment, ipsecESP, ipsecAH, icmpv6, noNxtHdr, or undefined.

---

## Configuring an ACE IPv6 traffic class

Configure ACE IPv6 traffic class.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IPv6**.
8. Click the **Traffic Class** tab.
9. Click **Insert**.
10. In the **Oper** field, select the operation type.
11. In the **TrafficCls** field, enter the traffic class number.
12. Click **Insert**.

---

## Traffic Class field descriptions

Use the data in the following table to use the **Traffic Class** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq parameter specifies an operator for an “equal to” field match condition.
<b>TrafficCls</b>	Specifies the traffic class attribute of the IPv6 header. Traffic class identifies different classes or priorities of IPv6 packets. The range is 0–255.

## Viewing all ACE IPv6 entries for an ACL

View all of the ACE IPv6 entries associated with an ACL.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **IPv6**.
8. Click the **IPv6** tab.

## IPv6 field descriptions

Use the data in the following table to use the **IPv6** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AceId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>SrcAddrList</b>	Shows the source IP address.
<b>SrcAddrOper</b>	Shows the operators for the ACE IP source address.
<b>DstAddrList</b>	Shows the destination IP address.
<b>DstAddrOper</b>	Shows the operators for the ACE IP destination address.
<b>NxtHdrNxtHdr</b>	Shows the next header of the IPv6 header.
<b>NxtHdrOper</b>	Shows the operators for the next header.
<b>TrafficClsOper</b>	Shows the operators for the traffic class.
<b>TrafficCls</b>	Shows the traffic class attribute of the IPv6 header.
<b>SrcAddrMask</b>	Shows the mask value for the source IP address.
<b>DstAddrMask</b>	Shows the mask value for the destination IP address.

## Configuring an ACE source port

Configure ACE source port entries to have the filter look for packets with a specific source port.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Proto**.
8. Click the **Source Port** tab.
9. Click **Insert**.
10. Specify the operator for the source port.
11. Specify the port number or port list to match.
12. Click **Insert**.

## Source Port field descriptions

Use the data in the following table to use the **Source Port** tab.

Name	Description
<b>AcId</b>	Specifies the ACL ID, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Port</b>	Specifies the source port (1–65535).
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>OperMask</b>	Specifies the mask parameter, {0-0xFFFF}.

## Configuring an ACE destination port

Configure ACE destination port entries to have the filter look for packets with a specific destination port.

### Before you begin

- The ACE exists.
- The ACL exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Proto**.
8. Click the **Destination Port** tab.
9. Click **Insert**.
10. Specify the operator for the destination port.
11. Specify the port number or port list to match.
12. Click **Insert**.

## Destination Port field descriptions

Use the data in the following table to use the Destination Port tab.

Name	Description
<b>AcId</b>	Specifies the ACL index, from 1–2048.
<b>AcId</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>Port</b>	Specifies the port number. As noted at the bottom of the tab, potential entries include 0–65535, echo, ftpdata, ftpcontrol, ssh, telnet, dns, http, h.323, and undefined.
<b>OperMask</b>	Specifies the mask parameter, {0-0xFFFF}.

## Configuring an ACE ICMP message type

Configure ACE Internet Control Message Protocol (ICMP) message type entries to have the filter look for packets of a specific ICMP message type.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Proto**.
8. Click the **Icmp Msg Type** tab.
9. Click **Insert**.
10. Specify the operator for the ICMP message type.
11. In the **List** box, specify the ICMP messages to match.
12. Click **Insert**.

## Icmp Msg Type field descriptions

Use the data in the following table to use the **Icmp Msg Type** tab.

Name	Description
<b>Acld</b>	Specifies the ACL Id, from 1–2048.
<b>Aceld</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	Specifies the operator for the ACE protocol ICMP message type. Equal (eq) is the only option.
<b>List</b>	Specifies the ICMP message type (0–255), or echoreply, destunreach, sourcequench, redirect, echo-request, routeradv, routerselect, time-exceeded, param-problem, timestamp-request, timestamp-reply, addressmask-request, addressmask-reply, or traceroute.

## Configuring an ACE ICMPv6 message type

### About this task

Configure ACE Internet Control Message Protocol v6 (ICMPv6) message type entries to have the filter look for packets of a specific ICMPv6 message type.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation pane, expand the following folders: **Configuration > Security > Data path**
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Proto**.
8. Click the **Icmpv6 Msg Type** tab.
9. Click **Insert**.
10. Specify the operator for the ICMPv6 message type.
11. In the **List** field, specify the ICMPv6 messages to match.
12. In the **Count** field, specify 1 through 100.
13. Click **Insert**.

## Icmpv6 Msg Type field descriptions

Use the data in the following table to use the Icmp6 Msg Type tab.

Name	Description
Acld	Specifies the ACL ID, from 1–2048.
Aceld	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
Oper	Specifies the operator for the ACE protocol ICMPv6 message type. Equal (eq) is the only option.
List	Specifies the ICMPv6 message type (0–255), or echoreply, destunreach, sourcequench, redirect, echo-request, routeradv, routerselect, time-

*Table continues...*

Name	Description
	exceeded, param-problem, timestamp-request, timestamp-reply, addressmask-request, addressmask-reply, or traceroute.
Count	<p>Specifies 1–100.</p> <p>Enables the ability to count matching packets. Use this parameter with either a security or QoS ACE. The default is disabled.</p>

---

## Configuring an ACE TCP flag

Configure ACE TCP flag entries to have the filter look for packets with a specific TCP flag.

### Before you begin

- The ACL exists.
- The ACE exists.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **ACE**.
6. Select the appropriate ACE.
7. Click **Proto**.
8. Click the **TCP Flags** tab.
9. Click **Insert**.
10. Specify the operator for the TCP flags entry.
11. In the **List** box, specify the TCP flags to match.
12. Click **Insert**.

---

## TCP Flags field descriptions

Use the data in the following table to use the **TCP Flags** tab.

Name	Description
AclId	Specifies the ACL ID, from 1–2048.

*Table continues...*



Name	Description
<b>Aceld</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>Oper</b>	The eq and mask parameters specify an operator for a field match condition: equal to or mask. The mask operator is an implied eq on the mask bits.
<b>List</b>	Specifies one or more TCP flags—none, fin (finish connection), syn (synchronize), rst (reset connection), push, ack (acknowledge), urg (urgent), and undefined.
<b>OperMask</b>	Specifies the mask value.

---

## Viewing all ACE protocol entries for an ACL

View all of the ACE protocol entries associated with an ACL.

### Procedure

1. In the navigation tree, expand the following folders: **Configuration > Security > Data Path**.
2. Click **Advanced Filters (ACE/ACLs)**.
3. Click the **ACL** tab.
4. Select the appropriate ACL.
5. Click **Proto**.

---

## Protocol field descriptions

Use the data in the following table to use the **Protocol** tab.

Name	Description
<b>Acld</b>	Specifies the ACL ID, from 1–2048.
<b>Aceld</b>	Specifies the ACE ID. Use ACE IDs 1–1000 for security rules. Use ACE IDs 1001–2000 for QoS rules.
<b>SrcPort</b>	Specifies the port number or port list to match.
<b>SrcPortOper</b>	Specifies the operator for the ACE protocol source port.
<b>SrcPortOperMaskRange</b>	The value is displayed in hexadecimal format when <b>SrcPortOper</b> is set to mask. When <b>SrcPortOper</b> is set to range, this field is used as the high range value. In this case, the value is displayed in decimal format. When <b>SrcPortOper</b> is set to eq, this field is set to 0.
<b>DstPort</b>	Specifies port number or port list to match.
<b>DstPortOper</b>	Specifies the operator for the ACE protocol destination port.

*Table continues...*

Name	Description
<b>DstPortOperMaskRange</b>	The value is displayed in hexadecimal format when <b>DstPortOper</b> is set to mask. When <b>DstPortOper</b> is set to range, this field is used as the high range value. In this case, the value is displayed in decimal format. When <b>SrcPortOper</b> is set to eq, this field is set to 0.
<b>IcmpMsgTypeList</b>	Specifies one or a list of ICMP messages to match. The valid range is 0–255 (reserved).
<b>IcmpMsgTypeOper</b>	Specifies the operator for the ACE protocol ICMP message types.
<b>TcpFlagsList</b>	Specifies one or a list of TCP flags to match. The valid range is 0–63.
<b>TcpFlagsOper</b>	Specifies the operator for the ACE protocol TCP flags.
<b>TcpFlagsOperMask</b>	Displays the mask value in hexadecimal format when <b>TcpFlagsOper</b> is set to mask. When <b>TcpFlagsOper</b> is set to eq, this field displays 0x0.

# Chapter 13: Common procedures using CLI

The following section describes common procedures that you use while you configure and monitor the switch Quality of Service (QoS) and filter operations.

---

## Saving the configuration

Save the configuration to a file to retain the configuration settings.

### About this task

File Transfer Protocol (FTP) and Trivial File Transfer Protocol (TFTP) support both IPv4 and IPv6 addresses, with no difference in functionality or configuration.

#### Note:

If you use File Transfer Protocol (FTP) or Trivial File Transfer Protocol (TFTP), ensure that you enable the FTP or TFTP server.

### Procedure

1. Enter Privileged EXEC mode:

```
enable
```

2. Save the running configuration:

```
save config [backup WORD<1-99>] [file WORD<1-99>] [verbose]
```

### Example

```
Switch:1> enable
```

Save the file to the default location:

```
Switch:1# save config
```

---

## Variable definitions

Use the data in the following table to use the `save config` command.

**Table 36: Variable definitions**

Variable	Value
backup <i>WORD</i> <1–99>	Saves the specified file name and identifies the file as a backup file.  <i>WORD</i>  uses one of the following formats: <ul style="list-style-type: none"> <li>• a.b.c.d:&lt;file&gt;</li> <li>• /intflash/&lt;file&gt;</li> </ul> The file name, including the directory structure, can include up to 99 characters.
file <i>WORD</i> <1–99>	Specifies the file name in one of the following formats: <ul style="list-style-type: none"> <li>• a.b.c.d:&lt;file&gt;</li> <li>• /intflash/&lt;file&gt;</li> </ul> The file name, including the directory structure, can include up to 99 characters.
verbose	Saves the default and current configuration. If you omit this parameter, the command saves only parameters you change.

---

## Restarting the platform

Restart the switch to implement configuration changes or recover from a system failure.

### About this task

When you restart the system, you can specify the boot source (flash file or TFTP server) and file name. If you do not specify a device and file, the run-time CLI uses the software and configuration files on the primary boot device defined by the `boot config choice` command.

After the switch restarts normally, it sends a cold trap within 45 seconds after a restart.

### Procedure

1. Enter Privileged EXEC mode:

```
enable
```

2. Restart the switch:

```
boot [config WORD<1–99>] [-y]
```

**! Important:**

If you enter the `boot` command with no arguments, you cause the switch to start using the current boot choices defined by the `boot config choice` command.

---

## Variable definitions

Use the data in the following table to use the `boot` command.

**Table 37: Variable definitions**

Variable	Value
config <i>WORD</i> <1–99>	Specifies the software configuration device and file name in one of the following format: <ul style="list-style-type: none"> <li>• a.b.c.d:&lt;file&gt;</li> </ul> The file name, including the directory structure, can include up to 99 characters.
-y	Suppresses the confirmation message before the switch restarts. If you omit this parameter, you must confirm the action before the system restarts.

# Chapter 14: Common procedures using EDM

The following section describes common procedures that you use while you configure and monitor the switch Quality of Service (QoS) and filter operations using Enterprise Device Manager (EDM).

---

## Saving the configuration

### About this task

After you change the configuration, you must save the changes on the device. Save the configuration to a file to retain the configuration settings.

#### **Note:**

When you logout of the EDM interface, a dialog box automatically prompts if you want to save the configuration. If you want to save the configuration, click **OK**. If you want to close without saving the configuration, click **Cancel**. If you no longer see the prompt, clear your browser cache, restart your browser and reconnect.

### Procedure

1. In the Device Physical View tab, select the Device.
2. In the navigation pane, expand the **Configuration** > **Edit** folders.
3. Click **Chassis**.
4. Click the **System** tab.
5. **(Optional)** Specify a filename in **ConfigFileName**.  
If you do not specify a filename, the system saves the information to the default file.
6. In **ActionGroup1**, select **saveRuntimeConfig**.
7. Click **Apply**.

# Chapter 15: Advanced filter examples

This section provides a detailed advanced filter configuration example.

---

## ACE filters for secure networks

The following example shows filters for two Layer 2 switched hosts and two Layer 3 routed hosts for an IP Deskphone and computer VLAN network.

These filters apply after an analysis of the traffic types flowing on the network. The filters provide security by permitting legitimate traffic and denying (dropping) all other traffic. Filters redirect certain traffic to another IP address. The filters can also determine which traffic is permitted on which parts of the network.

The access control entries (ACE) named DENY ANY or DENY ANY ANY are the clean-up filters. These filters drop traffic that does not match another ACE.

The ACEs permit the following traffic (this is not an exhaustive list):

- Domain Name Service (DNS) traffic
- Internet Control Message Protocol (ICMP) traffic
- Virtual Router Redundancy Protocol (VRRP) traffic (in certain areas)
- BootStrap Protocol server and client traffic
- Dynamic Host Configuration Protocol (DHCP) traffic
- Network Basic Input/Output System (NetBIOS) traffic (in certain areas)
- Transport Control Protocol (TCP) traffic with the Established flag on
- traffic with specific IP addresses
- Microsoft Operations Manager 2005 agent (MOM 2005) traffic
- Hypertext Transfer Protocol (HTTP), HTTP proxy, and HTTP, Secure (HTTPS) traffic
- remote desktop traffic
- Internet Security Association and Key Management Protocol (ISAKMP) and Internet Key Exchange (IKE) traffic
- SQL database system traffic

Other ACEs are configured to deny (drop):

- VRRP traffic (in certain areas)

- NetBIOS traffic (UDP destination ports 137, 138)
- specific multicast traffic (UDP destination ports 61011, 64046)
- specific UDP traffic
- instant messaging traffic (UDP destination port 1900)

## Layer 2 host configuration

This section shows the filters configured for the first Layer 2 switched host.

```
#
# FILTER CONFIGURATION
#
filter acl 1 type outPort name "VRRP_Drop"
filter acl port 1 1/24-1/25,1/37
filter acl ace 1 1 name "VRRP"
filter acl ace ethernet 1 1 ether-type eq ip
filter acl ace ip 1 1 ip-protocol-type eq vrrp
filter acl ace 1 1 enable
filter acl ace 1 2 name "NetbIOS_Drop"
filter acl ace ethernet 1 2 ether-type eq netBios
filter acl ace ip 1 2 ip-protocol-type eq udp
filter acl ace protocol 1 2 dst-port eq 137
filter acl ace 1 2 enable
filter acl ace 1 3 name "NetbIOS2_Drop"
filter acl ace ip 1 3 ip-protocol-type eq udp
filter acl ace protocol 1 3 dst-port eq 138
filter acl ace 1 3 enable
filter acl ace 1 4 name "WL_Multicast1_Drop"
filter acl ace ip 1 4 ip-protocol-type eq udp
filter acl ace protocol 1 4 dst-port eq 61011
filter acl ace 1 4 enable
filter acl ace 1 5 name "WL_Multicast2_Drop"
filter acl ace ip 1 5 ip-protocol-type eq udp
filter acl ace protocol 1 5 dst-port eq 64046
filter acl ace 1 5 enable
filter acl ace 1 6 name "UDP_1100_Drop"
filter acl ace ethernet 1 6 ether-type eq ip
```



```
filter acl ace ip 1 6 dst-ip eq 100.20.100.255
filter acl ace ip 1 6 ip-protocol-type eq udp
filter acl ace protocol 1 6 dst-port eq 1100
filter acl ace 1 6 enable
filter acl ace 1 7 name "UDP_67_Drop"
filter acl ace ip 1 7 ip-protocol-type eq udp
filter acl ace protocol 1 7 dst-port eq 67
filter acl ace 1 7 enable
filter acl ace 1 8 name "Messenger"
filter acl ace ip 1 8 ip-protocol-type eq udp
filter acl ace protocol 1 8 dst-port eq 1900
filter acl ace 1 8 enable
filter acl 20 type inVlan name "Symantec-Drop"
filter acl vlan 20 2
filter acl ace 20 10 name "Othello-drop"
filter acl ace ethernet 20 10 ether-type eq ip
filter acl ace ip 20 10 src-ip eq 100.20.2.47
filter acl ace ip 20 10 ip-protocol-type eq tcp
filter acl ace protocol 20 10 src-port eq 80
filter acl ace 20 10 enable
filter acl ace 20 15 name "Macbeth-drop"
filter acl ace action 20 15 deny
filter acl ace ethernet 20 15 ether-type eq ip
filter acl ace ip 20 15 src-ip eq 100.20.2.29
filter acl ace ip 20 15 ip-protocol-type eq tcp
filter acl ace protocol 20 15 src-port eq 80
filter acl 902 type inVlan name "ITD_REMOTE_in"
filter acl vlan 902 902
no filter acl 902 enable
filter acl ace 902 5 name "ITD_TO_ITD"
filter acl ace action 902 5 permit
filter acl ace ethernet 902 5 ether-type eq ip
filter acl ace ip 902 5 dst-ip eq 100.20.103.65
```

## Advanced filter examples

```
filter acl ace 902 5 enable
filter acl ace 902 10 name "ICMP_PERMIT"
filter acl ace action 902 10 permit
filter acl ace ethernet 902 10 ether-type eq ip
filter acl ace ip 902 10 ip-protocol-type eq icmp
filter acl ace 902 10 enable
filter acl ace 902 20 name "IGMP_PERMIT"
filter acl ace action 902 20 permit
filter acl ace ethernet 902 20 ether-type eq ip
filter acl ace ip 902 20 ip-protocol-type eq 2
filter acl ace 902 20 enable
filter acl ace 902 30 name "VRRP_PERMIT"
filter acl ace action 902 30 permit
filter acl ace ethernet 902 30 ether-type eq ip
filter acl ace ip 902 30 ip-protocol-type eq vrrp
filter acl ace 902 30 enable
filter acl ace 902 35 name "BOOTPS"
filter acl ace action 902 35 permit
filter acl ace protocol 902 35 dst-port eq 67
filter acl ace 902 35 enable
filter acl ace 902 36 name "BOOTPC"
filter acl ace action 902 36 permit
filter acl ace protocol 902 36 dst-port eq 68
filter acl ace 902 36 enable
filter acl ace 902 40 name "DNS_PERMIT"
filter acl ace action 902 40 permit
filter acl ace ethernet 902 40 ether-type eq ip
filter acl ace ip 902 40 src-ip eq 100.20.103.65
filter acl ace protocol 902 40 dst-port eq dns
filter acl ace 902 40 enable
filter acl ace 902 43 name "Netbios_Erisim"
filter acl ace action 902 43 permit
filter acl ace ethernet 902 43 ether-type eq ip
```

```
filter acl ace ip 902 43 src-ip eq 100.20.103.65
filter acl ace protocol 902 43 dst-port eq 135
filter acl ace 902 43 enable
filter acl ace 902 45 name "ESTABLISHED"
filter acl ace action 902 45 permit
filter acl ace ethernet 902 45 ether-type eq ip
filter acl ace ip 902 45 src-ip eq 100.20.103.65
filter acl ace ip 902 45 ip-protocol-type eq tcp
filter acl ace protocol 902 45 dst-port eq 1023
filter acl ace protocol 902 45 tcp-flags eq rst
filter acl ace 902 45 enable
filter acl ace 902 46 name "ESTABLISHED2"
filter acl ace action 902 46 permit
filter acl ace ethernet 902 46 ether-type eq ip
filter acl ace ip 902 46 src-ip eq 100.20.103.65
filter acl ace ip 902 46 ip-protocol-type eq tcp
filter acl ace protocol 902 46 dst-port eq 1023
filter acl ace protocol 902 46 tcp-flags eq ack
filter acl ace 902 46 enable
filter acl ace 902 50 name "DC-EXCH-DNS"
filter acl ace action 902 50 permit
filter acl ace ethernet 902 50 ether-type eq ip
filter acl ace ip 902 50 src-ip eq 100.20.103.65
filter acl ace ip 902 50 dst-ip eq 100.20.104.0
filter acl ace 902 50 enable
filter acl ace 902 55 name "DC-EXCH-DNS_OPC"
filter acl ace action 902 55 permit
filter acl ace ethernet 902 55 ether-type eq ip
filter acl ace ip 902 55 src-ip eq 100.20.103.65
filter acl ace ip 902 55 dst-ip eq 100.6.105.0
filter acl ace 902 55 enable
filter acl ace 902 60 name "Filesharing_Erisim"
filter acl ace action 902 60 permit
```

## Advanced filter examples

```
filter acl ace ethernet 902 60 ether-type eq ip
filter acl ace ip 902 60 src-ip eq 100.20.103.65
filter acl ace ip 902 60 dst-ip eq 100.20.103.71
filter acl ace 902 60 enable
filter acl ace 902 65 name "Filesharing_Erisim_Ek"
filter acl ace action 902 65 permit
filter acl ace ethernet 902 65 ether-type eq ip
filter acl ace ip 902 65 src-ip eq 100.20.103.65
filter acl ace ip 902 65 dst-ip eq 10.10.230.6
filter acl ace 902 65 enable
filter acl ace 902 70 name "IBPSQL_Erisim"
filter acl ace action 902 70 permit
filter acl ace ethernet 902 70 ether-type eq ip
filter acl ace ip 902 70 src-ip eq 100.20.103.65
filter acl ace ip 902 70 dst-ip eq 100.20.100.176
filter acl ace ip 902 70 ip-protocol-type eq tcp
filter acl ace protocol 902 70 dst-port eq 4450
filter acl ace 902 70 enable
filter acl ace 902 75 name "CTI_Erisim"
filter acl ace action 902 75 permit
filter acl ace ethernet 902 75 ether-type eq ip
filter acl ace ip 902 75 src-ip eq 100.20.103.65
filter acl ace ip 902 75 dst-ip eq 100.6.100.161
filter acl ace ip 902 75 ip-protocol-type eq tcp
filter acl ace protocol 902 75 dst-port eq 1433
filter acl ace 902 75 enable
filter acl ace 902 80 name "PVA_ERISIM"
filter acl ace action 902 80 permit
filter acl ace ethernet 902 80 ether-type eq ip
filter acl ace ip 902 80 src-ip eq 100.20.103.65
filter acl ace ip 902 80 dst-ip eq 100.6.100.138
filter acl ace ip 902 80 ip-protocol-type eq tcp
filter acl ace protocol 902 80 dst-port eq 1521
```

```
filter acl ace 902 80 enable
filter acl ace 902 85 name "PWC_ERISIM"
filter acl ace action 902 85 permit
filter acl ace ethernet 902 85 ether-type eq ip
filter acl ace ip 902 85 src-ip eq 100.20.103.65
filter acl ace ip 902 85 dst-ip eq 100.6.100.113
filter acl ace ip 902 85 ip-protocol-type eq tcp
filter acl ace protocol 902 85 dst-port eq 1521
filter acl ace 902 85 enable
filter acl ace 902 90 name "OASIS_ERISIM"
filter acl ace action 902 90 permit
filter acl ace ethernet 902 90 ether-type eq ip
filter acl ace ip 902 90 src-ip eq 100.20.103.65
filter acl ace ip 902 90 dst-ip eq 100.6.100.112
filter acl ace ip 902 90 ip-protocol-type eq tcp
filter acl ace protocol 902 90 dst-port eq 1521
filter acl ace 902 90 enable
filter acl ace 902 95 name "AV-YAMA_YONETIM__9968"
filter acl ace action 902 95 permit
filter acl ace ethernet 902 95 ether-type eq ip
filter acl ace ip 902 95 src-ip eq 100.20.103.65
filter acl ace ip 902 95 ip-protocol-type eq tcp
filter acl ace protocol 902 95 dst-port eq 9968
filter acl ace 902 95 enable
filter acl ace 902 100 name "AV-YAMA_YONETIM_2967"
filter acl ace action 902 100 permit
filter acl ace ethernet 902 100 ether-type eq ip
filter acl ace ip 902 100 src-ip eq 100.20.103.65
filter acl ace ip 902 100 ip-protocol-type eq tcp
filter acl ace protocol 902 100 dst-port eq 2967
filter acl ace 902 100 enable
filter acl ace 902 105 name "AV-YAMA_YONETIM_UDP_2967"
filter acl ace action 902 105 permit
```

## Advanced filter examples

```
filter acl ace ip 902 105 src-ip eq 100.20.103.65
filter acl ace ip 902 105 ip-protocol-type eq udp
filter acl ace protocol 902 105 dst-port eq 2967
filter acl ace 902 105 enable
filter acl ace 902 108 name "AV-YAMA_YONETIM_SOURCE_9968"
filter acl ace action 902 108 permit
filter acl ace ethernet 902 108 ether-type eq ip
filter acl ace ip 902 108 src-ip eq 100.20.103.65
filter acl ace ip 902 108 ip-protocol-type eq udp
filter acl ace protocol 902 108 src-port eq 9968
filter acl ace 902 108 enable
filter acl ace 902 110 name "ALERT_MOM_SMS_ERISIM_TCP_1270"
filter acl ace action 902 110 permit
filter acl ace ethernet 902 110 ether-type eq ip
filter acl ace ip 902 110 src-ip eq 100.20.103.65
filter acl ace ip 902 110 dst-ip eq 100.6.140.10
filter acl ace ip 902 110 ip-protocol-type eq tcp
filter acl ace protocol 902 110 dst-port eq 1270
filter acl ace 902 110 enable
filter acl ace 902 120 name "ALERT_MOM_SMS_ERISIM_UDP_1270"
filter acl ace action 902 120 permit
filter acl ace ethernet 902 120 ether-type eq ip
filter acl ace ip 902 120 src-ip eq 100.20.103.65
filter acl ace ip 902 120 dst-ip eq 100.6.140.10
filter acl ace ip 902 120 ip-protocol-type eq udp
filter acl ace protocol 902 120 dst-port eq 1270
filter acl ace 902 120 enable
filter acl ace 902 130 name "ALERT_MOM_SMS_ERISIM_HTTP"
filter acl ace action 902 130 permit
filter acl ace ethernet 902 130 ether-type eq ip
filter acl ace ip 902 130 src-ip eq 100.20.103.65
filter acl ace ip 902 130 dst-ip eq 100.6.140.13
filter acl ace ip 902 130 ip-protocol-type eq tcp
```

```
filter acl ace protocol 902 130 dst-port eq 80
filter acl ace 902 130 enable
filter acl ace 902 135 name "ALERT_MOM_SMS_ERISIM_HTTP2"
filter acl ace action 902 135 permit
filter acl ace ethernet 902 135 ether-type eq ip
filter acl ace ip 902 135 src-ip eq 100.20.103.65
filter acl ace ip 902 135 dst-ip eq 100.6.106.92
filter acl ace ip 902 135 ip-protocol-type eq tcp
filter acl ace protocol 902 135 dst-port eq 80
filter acl ace 902 135 enable
filter acl ace 902 140 name "ALERT_MOM_SMS_ERISIM_1521"
filter acl ace action 902 140 permit
filter acl ace ethernet 902 140 ether-type eq ip
filter acl ace ip 902 140 src-ip eq 100.20.103.65
filter acl ace ip 902 140 dst-ip eq 100.6.100.126
filter acl ace ip 902 140 ip-protocol-type eq tcp
filter acl ace protocol 902 140 dst-port eq 1521
filter acl ace 902 140 enable
filter acl ace 902 150 name "ALERT_MOM_SMS_ERISIM_1521x"
filter acl ace action 902 150 permit
filter acl ace ethernet 902 150 ether-type eq ip
filter acl ace ip 902 150 src-ip eq 100.20.103.65
filter acl ace ip 902 150 dst-ip eq 100.20.100.47
filter acl ace ip 902 150 ip-protocol-type eq tcp
filter acl ace protocol 902 150 dst-port eq 1521
filter acl ace 902 150 enable
filter acl ace 902 155 name "FULL_ERISIM"
filter acl ace action 902 155 permit
filter acl ace ethernet 902 155 ether-type eq ip
filter acl ace ip 902 155 dst-ip eq 100.20.100.149
filter acl ace 902 155 enable
filter acl ace 902 160 name "LOGLAMAK_ICIN"
filter acl ace action 902 160 permit redirect-next-hop 100.20.150.34
```

## Advanced filter examples

```
filter acl ace ethernet 902 160 ether-type eq ip
filter acl ace ip 902 160 src-ip eq 0.0.0.0
filter acl ace 902 170 name "DENY_ANY_ANY"
filter acl ace action 902 170 deny
filter acl ace ethernet 902 170 ether-type eq ip
filter acl ace ip 902 170 src-ip eq 0.0.0.0
filter acl ace ip 902 170 dst-ip eq 0.0.0.0
filter acl ace 902 170 enable
```

The following section provides details about the filter configuration for the second switched Layer 2 host.

```
#
# FILTER CONFIGURATION
#
filter acl 1 type outPort name "VRRP Drop"
filter acl port 1 add 1/24-1/25,1/37
filter acl ace 1 1 name "VRRP"
filter acl ace action 1 1 deny
filter acl ace ethernet 1 1 ether-type eq ip
filter acl ace ip 1 1 ip-protocol-type eq vrrp
filter acl ace 1 1 enable
filter acl ace 1 2 name "NetbIOS_Drop"
filter acl ace action 1 2 deny
filter acl ace ethernet 1 2 ether-type eq ip
filter acl ace ip 1 2 ip-protocol-type eq udp
filter acl ace protocol 1 2 dst-port eq 137
filter acl ace 1 2 enable
filter acl ace 1 3 name "NetbIOS2_Drop"
filter acl ace action 1 3 deny
filter acl ace ethernet 1 3 ether-type eq ip
filter acl ace ip 1 3 ip-protocol-type eq udp
filter acl ace protocol 1 3 dst-port eq 138
filter acl ace 1 3 enable
filter acl ace 1 4 name "WL_Multicast1_Drop"
```



```
filter acl ace action 1 4 deny
filter acl ace ethernet 1 4 ether-type eq ip
filter acl ace ip 1 4 ip-protocol-type eq udp
filter acl ace protocol 1 4 dst-port eq 61011
filter acl ace 1 4 enable
filter acl ace 1 5 name "WL_Multicast2_Drop"
filter acl ace action 1 5 deny
filter acl ace ethernet 1 5 ether-type eq ip
filter acl ace ip 1 5 ip-protocol-type eq udp
filter acl ace protocol 1 5 dst-port eq 64046
filter acl ace 1 5 enable
filter acl 20 type inVlan name "Symantec-Drop"
filter acl vlan 20 2
filter acl ace 20 10 name "Othello-drop"
filter acl ace action 20 10 deny
filter acl ace ethernet 20 10 ether-type eq ip
filter acl ace ip 20 10 src-ip eq 100.20.2.47
filter acl ace ip 20 10 ip-protocol-type eq tcp
filter acl ace protocol 20 10 src-port eq 80
filter acl ace 20 10 enable
filter acl ace 20 15 name "Macbeth-drop"
filter acl ace 20 15 action deny
filter acl ace ethernet 20 15 ether-type eq ip
filter acl ace ip 20 15 src-ip eq 100.20.2.29
filter acl ace ip 20 15 ip-protocol-type eq tcp
filter acl ace protocol 20 15 src-port eq 80

filter acl 902 type inVlan name "ITD_REMOTE_in"
filter acl vlan 902 902
filter acl 902 disable
filter acl ace 902 5 name "ITD_TO_ITD"
filter acl ace action 902 5 permit
filter acl ace ethernet 902 5 ether-type eq ip
filter acl ace ip 902 5 dst-ip eq 100.20.103.65
```

## Advanced filter examples

```
filter acl ace 902 5 enable
filter acl ace 902 10 name "ICMP_PERMIT"
filter acl ace action 902 10 permit
filter acl ace ethernet 902 10 ether-type eq ip
filter acl ace ip 902 10 ip-protocol-type eq icmp
filter acl ace 902 10 enable
filter acl ace 902 20 name "IGMP_PERMIT"
filter acl ace action 902 20 permit
filter acl ace ethernet 902 20 ether-type eq ip
filter acl ace ip 902 20 ip-protocol-type eq 2
filter acl ace 902 20 enable
filter acl ace 902 30 name "VRRP_PERMIT"
filter acl ace action 902 30 permit
filter acl ace ethernet 902 30 ether-type eq ip
filter acl ace ip 902 30 ip-protocol-type eq vrrp
filter acl ace 902 30 enable
filter acl ace 902 35 name "BOOTPS"
filter acl ace action 902 35 permit
filter acl ace protocol 902 35 dst-port eq 67
filter acl ace 902 35 enable
filter acl ace 902 36 name "BOOTPC"
filter acl ace action 902 36 permit
filter acl ace protocol 902 36 dst-port eq 68
filter acl ace 902 36 enable
filter acl ace 902 40 name "DNS_PERMIT"
filter acl ace action 902 40 permit
filter acl ace ethernet 902 40 ether-type eq ip
filter acl ace ip 902 40 src-ip eq 100.20.103.65
filter acl ace protocol 902 40 dst-port eq dns
filter acl ace 902 40 enable
filter acl ace 902 43 name "Netbios_Erisim"
filter acl ace action 902 43 permit
filter acl ace ethernet 902 43 ether-type eq ip
```

```
filter acl ace ip 902 43 src-ip eq 100.20.103.65
filter acl ace protocol 902 43 dst-port eq 135
filter acl ace 902 43 enable
filter acl ace 902 45 name "ESTABLISHED ACK"
filter acl ace action 902 45 permit
filter acl ace ethernet 902 45 ether-type eq ip
filter acl ace ip 902 45 src-ip eq 100.20.103.65
filter acl ace ip 902 45 ip-protocol-type eq tcp
filter acl ace protocol 902 45 dst-port eq 1023
filter acl ace protocol 902 45 tcp-flags eq ack
filter acl ace 902 45 enable
filter acl ace 902 46 name "ESTABLISHED RST"
filter acl ace action 902 46 permit
filter acl ace ethernet 902 46 ether-type eq ip
filter acl ace protocol 902 46 tcp-flags eq rst
filter acl ace 902 46 enable
filter acl ace 902 50 name "DC-EXCH-DNS"
filter acl ace action 902 50 permit
filter acl ace ethernet 902 50 ether-type eq ip
filter acl ace ip 902 50 src-ip eq 100.20.103.65
filter acl ace ip 902 50 dst-ip eq 100.20.104.0
filter acl ace 902 50 enable
filter acl ace 902 55 name "DC-EXCH-DNS_OPC"
filter acl ace action 902 55 permit
filter acl ace ethernet 902 55 ether-type eq ip
filter acl ace ip 902 55 src-ip eq 100.20.103.65
filter acl ace ip 902 55 dst-ip eq 100.6.105.0
filter acl ace 902 55 enable
filter acl ace 902 60 name "Filesharing_Erisim"
filter acl ace action 902 60 permit
filter acl ace ethernet 902 60 ether-type eq ip
filter acl ace ip 902 60 src-ip eq 100.20.103.65
filter acl ace ip 902 60 dst-ip eq 100.20.103.71
```

## Advanced filter examples

```
filter acl ace 902 60 enable
filter acl ace 902 65 name "Filesharing_Erisim_Ek"
filter acl ace action 902 65 permit
filter acl ace ethernet 902 65 ether-type eq ip
filter acl ace ip 902 65 src-ip eq 100.20.103.65
filter acl ace ip 902 65 dst-ip eq 10.10.230.6
filter acl ace 902 65 enable
filter acl ace 902 70 name "IBPSQL_Erisim"
filter acl ace action 902 70 permit
filter acl ace ethernet 902 70 ether-type eq ip
filter acl ace ip 902 70 src-ip eq 100.20.103.65
filter acl ace ip 902 70 dst-ip eq 100.20.100.176
filter acl ace ip 902 70 ip-protocol-type eq tcp
filter acl ace protocol 902 70 dst-port eq 4450
filter acl ace 902 70 enable
filter acl ace 902 75 name "CTI_Erisim"
filter acl ace action 902 75 permit
filter acl ace ethernet 902 75 ether-type eq ip
filter acl ace ip 902 75 src-ip eq 100.20.103.65
filter acl ace ip 902 75 dst-ip eq 100.6.100.161
filter acl ace ip 902 75 ip-protocol-type eq tcp
filter acl ace protocol 902 75 dst-port eq 1433
filter acl ace 902 75 enable
filter acl ace 902 80 name "PVA_ERISIM"
filter acl ace action 902 80 permit
filter acl ace ethernet 902 80 ether-type eq ip
filter acl ace ip 902 80 src-ip eq 100.20.103.65
filter acl ace ip 902 80 ip eq 100.6.100.138
filter acl ace ip 902 80 ip-protocol-type eq tcp
filter acl ace protocol 902 80 dst-port eq 1521
filter acl ace 902 80 enable
filter acl ace 902 85 name "PWC_ERISIM"
filter acl ace action 902 85 permit
```

```
filter acl ace ethernet 902 85 ether-type eq ip
filter acl ace ip 902 85 src-ip eq 100.20.103.65
filter acl ace ip 902 85 dst-ip eq 100.6.100.113
filter acl ace ip 902 85 ip-protocol-type eq tcp
filter acl ace protocol 902 85 dst-port eq 1521
filter acl ace 902 85 enable
filter acl ace 902 90 name "OASIS_ERISIM"
filter acl ace action 902 90 permit
filter acl ace ethernet 902 90 ether-type eq ip
filter acl ace ip 902 90 src-ip eq 100.20.103.65
filter acl ace ip 902 90 dst-ip eq 100.6.100.112
filter acl ace ip 902 90 ip-protocol-type eq tcp
filter acl ace protocol 902 90 dst-port eq 1521
filter acl ace 902 90 enable
filter acl ace 902 95 name "AV-YAMA_YONETIM__9968"
filter acl ace action 902 95 permit
filter acl ace ethernet 902 95 ether-type eq ip
filter acl ace ip 902 95 src-ip eq 100.20.103.65
filter acl ace ip 902 95 ip-protocol-type eq tcp
filter acl ace protocol 902 95 dst-port eq 9968
filter acl ace 902 95 enable
filter acl ace 902 100 name "AV-YAMA_YONETIM_2967"
filter acl ace action 902 100 permit
filter acl ace ethernet 902 100 ether-type eq ip
filter acl ace ip 902 100 src-ip eq 100.20.103.65
filter acl ace ip 902 100 ip-protocol-type eq tcp
filter acl ace protocol 902 100 dst-port eq 2967
filter acl ace 902 100 enable
filter acl ace 902 105 name "AV-YAMA_YONETIM_UDP_2967"
filter acl ace action 902 105 permit
filter acl ace ethernet 902 105 ether-type eq ip
filter acl ace ip 902 105 src-ip eq 100.20.103.65
filter acl ace ip 902 105 ip-protocol-type eq udp
```

## Advanced filter examples

```
filter acl ace protocol 902 105 dst-port eq 2967
filter acl ace 902 105 enable
filter acl ace 902 108 name "AV-YAMA_YONETIM_SOURCE_9968"
filter acl ace action 902 108 permit
filter acl ace ethernet 902 108 ether-type eq ip
filter acl ace ip 902 108 src-ip eq 100.20.103.65
filter acl ace ip 902 108 ip-protocol-type eq udp
filter acl ace protocol 902 108 src-port eq 9968
filter acl ace 902 108 enable
filter acl ace 902 110 name "ALERT_MOM_SMS_ERISIM_TCP_1270"
filter acl ace action 902 110 permit
filter acl ace ethernet 902 110 ether-type eq ip
filter acl ace ip 902 110 src-ip eq 100.20.103.65
filter acl ace ip 902 110 dst-ip eq 100.6.140.10
filter acl ace ip 902 110 ip-protocol-type eq tcp
filter acl ace protocol 902 110 dst-port eq 1270
filter acl ace 902 110 enable
filter acl ace 902 120 name "ALERT_MOM_SMS_ERISIM_UDP_1270"
filter acl ace action 902 120 permit
filter acl ace ethernet 902 120 ether-type eq ip
filter acl ace ip 902 120 src-ip eq 100.20.103.65
filter acl ace ip 902 120 dst-ip eq 100.6.140.10
filter acl ace ip 902 120 ip-protocol-type eq udp
filter acl ace protocol 902 120 dst-port eq 1270
filter acl ace 902 120 enable
filter acl ace 902 130 name "ALERT_MOM_SMS_ERISIM_HTTP"
filter acl ace action 902 130 permit
filter acl ace ethernet 902 130 ether-type eq ip
filter acl ace ip 902 130 src-ip eq 100.20.103.65
filter acl ace ip 902 130 dst-ip eq 100.6.140.13
filter acl ace ip 902 130 ip-protocol-type eq tcp
filter acl ace protocol 902 130 dst-port eq 80
filter acl ace 902 130 enable
```

```
filter acl ace 902 135 name "ALERT_MOM_SMS_ERISIM_HTTP2"  
filter acl ace action 902 135 permit  
filter acl ace ethernet 902 135 ether-type eq ip  
filter acl ace ip 902 135 src-ip eq 100.20.103.65  
filter acl ace ip 902 135 dst-ip eq 100.6.106.92  
filter acl ace ip 902 135 ip-protocol-type eq tcp  
filter acl ace protocol 902 135 dst-port eq 80  
filter acl ace 902 135 enable  
filter acl ace 902 140 create name "ALERT_MOM_SMS_ERISIM_1521"  
filter acl ace action 902 140 permit  
filter acl ace ethernet 902 140 ether-type eq ip  
filter acl ace ip 902 140 src-ip eq 100.20.103.65  
filter acl ace ip 902 140 dst-ip eq 100.6.100.126  
filter acl ace ip 902 140 ip-protocol-type eq tcp  
filter acl ace protocol 902 140 dst-port eq 1521  
filter acl ace 902 140 enable  
filter acl ace 902 150 name "ALERT_MOM_SMS_ERISIM_1521x"  
filter acl ace action 902 150 permit  
filter acl ace ethernet 902 150 ether-type eq ip  
filter acl ace ip 902 150 src-ip eq 100.20.103.65  
filter acl ace ip 902 150 dst-ip eq 100.20.100.47  
filter acl ace ip 902 150 ip-protocol-type eq tcp  
filter acl ace protocol 902 150 dst-port eq 1521  
filter acl ace 902 150 enable  
filter acl ace 902 155 name "FULL_ERISIM"  
filter acl ace action 902 155 permit  
filter acl ace ethernet 902 155 ether-type eq ip  
filter acl ace ip 901 155 dst-ip eq 100.20.100.149  
filter acl ace 902 155 enable  
filter acl ace 902 160 name "LOGLAMAK_ICIN"  
filter acl ace action 902 160 permit redirect-next-hop 100.20.150.34  
filter acl ace ethernet 902 160 ether-type eq ip  
filter acl ace ip 902 160 src-ip ge 0.0.0.0
```

## Advanced filter examples

```
filter acl ace 902 170 name "DENY_ANY_ANY"  
filter acl ace action 902 170 deny  
filter acl ace ethernet 902 170 ether-type eq ip  
filter acl ace ip 902 170 src-ip eq 0.0.0.0  
filter acl ace ip 902 170 dst-ip eq 0.0.0.0  
filter acl ace 902 170 enable
```

### Layer 3 host configuration

The following section provides details about the filter configuration for the first core Layer 3 host.

```
#  
# FILTER CONFIGURATION  
#  
filter acl 1 type outPort name "VRRP_Drop_ACL"  
filter acl port 1 1/46  
filter acl ace 1 1 name "Vrrp"  
filter acl ace action 1 1 deny  
filter acl ace ethernet 1 1 ether-type eq ip  
filter acl ace ip 1 1 ip-protocol-type eq vrrp  
filter acl ace 1 1 enable  
filter acl 171 type inVlan name "TOPLANTI_VE_EGITIM_ACL"  
filter acl vlan 171 171  
filter acl 171 disable  
filter acl ace 171 10 name "ICMP_PERMIT"  
filter acl ace action 171 10 permit  
filter acl ace ethernet 171 10 ether-type eq ip  
filter acl ace ip 171 10 ip-protocol-type eq icmp  
filter acl ace 171 10 enable  
filter acl ace 171 20 name "IGMP_PERMIT"  
filter acl ace action 171 20 permit  
filter acl ace ethernet 171 20 ether-type eq ip  
filter acl ace ip 171 20 ip-protocol-type eq 2  
filter acl ace 171 20 enable  
filter acl ace 171 30 name "VRRP_PERMIT"  
filter acl ace action 171 30 permit
```



```
filter acl ace ethernet 171 30 ether-type eq ip
filter acl ace ip 171 30 ip-protocol-type eq vrrp
filter acl ace 171 30 enable
filter acl ace 171 40 name "DNS_PERMIT"
filter acl ace action 171 40 permit
filter acl ace ethernet 171 40 ether-type eq ip
filter acl ace ip 171 40 src-ip eq 100.20.171.0
filter acl ace ip 171 40 dst-ip eq 100.20.104.0
filter acl ace protocol 171 40 dst-port eq dns
filter acl ace 171 40 enable
filter acl ace 171 50 name "ESTABLISHED_RST"
filter acl ace action 171 50 permit
filter acl ace ethernet 171 50 ether-type eq ip
filter acl ace ip 171 50 src-ip eq 100.6.172.0
filter acl ace ip 171 50 ip-protocol-type eq tcp
filter acl ace protocol 171 50 dst-port eq 1023
filter acl ace protocol 171 50 tcp-flags eq rst
filter acl ace 171 50 enable
filter acl ace 171 51 name "ESTABLISHED_ACK"
filter acl ace action 171 51 permit
filter acl ace ethernet 171 51 ether-type eq ip
filter acl ace ip 171 51 src-ip eq 100.6.172.0
filter acl ace ip 171 51 ip-protocol-type eq tcp
filter acl ace protocol 171 51 dst-port eq 1023
filter acl ace protocol 171 51 tcp-flags eq ack
filter acl ace 171 51 enable
filter acl ace 171 60 name "DHCP_PERMIT"
filter acl ace action 171 60 permit
filter acl ace ethernet 171 60 ether-type eq ip
filter acl ace protocol 171 60 dst-port eq bootpServer
filter acl ace 171 60 enable
filter acl ace 171 80 name "DC_DNS_EXC_PERMIT"
filter acl ace action 171 80 permit
```

## Advanced filter examples

```
filter acl ace ethernet 171 80 ether-type eq ip
filter acl ace ip 171 80 src-ip eq 100.20.172.0
filter acl ace ip 181 70 dst-ip eq 100.20.104.0
filter acl ace 171 80 enable
filter acl ace 171 90 name "HTTP_PERMIT"
filter acl ace action 171 90 permit
filter acl ace ethernet 171 90 ether-type eq ip
filter acl ace ip 171 90 src-ip eq 100.20.172.0
filter acl ace protocol 171 90 dst-port eq 80
filter acl ace 171 90 enable
filter acl ace 171 100 name "HTTPS_PERMIT"
filter acl ace action 171 100 permit
filter acl ace ethernet 171 100 ether-type eq ip
filter acl ace ip 171 100 src-ip eq 100.20.172.0
filter acl ace protocol 171 100 dst-port eq 443
filter acl ace 171 100 enable
filter acl ace 171 110 name "PROXY_8080_PERMIT"
filter acl ace action 171 110 permit
filter acl ace ethernet 171 110 ether-type eq ip
filter acl ace ip 171 110 src-ip eq 100.20.172.0
filter acl ace ip 171 110 dst-ip eq 100.20.189.0
filter acl ace protocol 171 110 dst-port eq 8080
filter acl ace 171 110 enable
filter acl ace 171 120 name "CITRIX_Conn"
filter acl ace action 171 120 permit
filter acl ace ethernet 171 120 ether-type eq ip
filter acl ace protocol 171 120 dst-port eq 1494
filter acl ace protocol 171 120 dst-port eq 1604
filter acl ace 171 120 enable
filter acl ace 171 130 name "PWC_VPN_ERISIM"
filter acl ace action 171 130 permit
filter acl ace ethernet 171 130 ether-type eq ip
filter acl ace ip 171 130 src-ip eq 100.20.172.0
```

```
filter acl ace protocol 171 130 dst-port eq 11160
filter acl ace 171 130 enable
filter acl ace 171 150 name "Microsoft_FileSharing_PERMIT"
filter acl ace action 171 150 permit
filter acl ace protocol 171 150 dst-port eq 445
filter acl ace 171 150 enable

filter acl 172 type inVlan name "MISAFIR_ACL"
filter acl vlan 172 172
filter acl 172 disable
filter acl ace 172 5 name "Misafir_to_Misafir"
filter acl ace action 172 5 permit
filter acl ace ethernet 172 5 ether-type eq ip
filter acl ace ip 172 5 dst-ip eq 100.20.172.0
filter acl ace 172 5 enable
filter acl ace 172 10 name "ICMP_PERMIT"
filter acl ace action 172 10 permit
filter acl ace ethernet 172 10 ether-type eq ip
filter acl ace ip 172 10 ip-protocol-type eq icmp
filter acl ace 172 10 enable
filter acl ace 172 20 name "IGMP_PERMIT"
filter acl ace action 172 20 permit
filter acl ace ethernet 172 20 ether-type eq ip
filter acl ace ip 172 20 ip-protocol-type eq 2
filter acl ace 172 20 enable
filter acl ace 172 30 name "VRRP_PERMIT"
filter acl ace action 172 30 permit
filter acl ace ethernet 172 30 ether-type eq ip
filter acl ace ip 172 30 ip-protocol-type eq vrrp
filter acl ace 172 30 enable
filter acl ace 172 40 name "DNS_PERMIT"
filter acl ace action 172 40 permit
filter acl ace ethernet 172 40 ether-type eq ip
filter acl ace ip 172 40 src-ip eq 100.20.172.0
```

## Advanced filter examples

```
filter acl ace ip 172 40 dst-ip eq 100.20.104.0
filter acl ace protocol 172 40 dst-port eq dns
filter acl ace 172 40 enable
filter acl ace 172 50 name "ESTABLISHED RST"
filter acl ace action 172 50 permit
filter acl ace ethernet 172 50 ether-type eq ip
filter acl ace ip 172 50 src-ip eq 100.20.172.0
filter acl ace ip 172 50 ip-protocol-type eq tcp
filter acl ace protocol 172 50 dst-port eq 1023
filter acl ace protocol 172 50 tcp-flags eq rst
filter acl ace 172 50 enable
filter acl ace 172 51 name "ESTABLISHED ACK"
filter acl ace action 172 51 permit
filter acl ace ethernet 172 51 ether-type eq ip
filter acl ace ip 172 51 src-ip eq 100.20.172.0
filter acl ace ip 172 51 ip-protocol-type eq tcp
filter acl ace protocol 172 51 dst-port eq 1023
filter acl ace protocol 172 51 tcp-flags eq ack
filter acl ace 172 51 enable
filter acl ace 172 60 name "DHCP_PERMIT"
filter acl ace action 172 60 permit
filter acl ace protocol 172 60 dst-port eq bootpServer
filter acl ace 172 60 enable
filter acl ace 172 80 name "DC_DNS_EXC_PERMIT"
filter acl ace action 172 80 permit
filter acl ace ethernet 172 80 ether-type eq ip
filter acl ace ip 172 80 src-ip eq 100.20.172.0
filter acl ace ip 172 80 dst-ip eq 100.20.104.0
filter acl ace 172 80 enable
filter acl ace 172 90 name "HTTP_PERMIT"
filter acl ace action 172 90 permit
filter acl ace ethernet 172 90 ether-type eq ip
filter acl ace ip 172 90 src-ip eq 100.20.172.0
```

```
filter acl ace ip 172 90 ip-protocol-type eq tcp
filter acl ace protocol 172 90 dst-port eq 80
filter acl ace 172 90 enable
filter acl ace 172 100 name "HTTPS_PERMIT"
filter acl ace action 172 100 permit
filter acl ace ethernet 172 100 ether-type eq ip
filter acl ace ip 172 100 src-ip eq 100.20.172.0
filter acl ace ip 172 100 ip-protocol-type eq tcp
filter acl ace protocol 172 100 dst-port eq 443
filter acl ace 172 100 enable
filter acl ace 172 105 name "REMDESKTOP_PERMIT"
filter acl ace action 172 105 permit
filter acl ace ethernet 172 105 ether-type eq ip
filter acl ace ip 172 105 src-ip eq 100.20.172.0
filter acl ace ip 172 105 ip-protocol-type eq tcp
filter acl ace protocol 172 105 dst-port eq 3389
filter acl ace 172 105 enable
filter acl ace 172 106 name "NORKOM_PERMIT"
filter acl ace action 172 106 permit
filter acl ace ethernet 172 106 ether-type eq ip
filter acl ace ip 172 106 src-ip eq 100.20.172.0
filter acl ace ip 172 106 dst-ip eq 100.6.106.0
filter acl ace 172 106 enable
filter acl ace 172 107 name "SPECTRUM_PERMIT"
filter acl ace action 172 107 permit
filter acl ace ethernet 172 107 ether-type eq ip
filter acl ace ip 172 107 src-ip eq 100.20.172.0
filter acl ace ip 172 107 dst-ip eq 100.20.17.0
filter acl ace 172 107 enable
filter acl ace 172 110 name "PROXY_8080_PERMIT"
filter acl ace action 172 110 permit
filter acl ace ethernet 172 110 ether-type eq ip
filter acl ace ip 172 110 src-ip eq 100.20.172.0
```

## Advanced filter examples

```
filter acl ace ip 172 110 dst-ip eq 100.20.189.0
filter acl ace ip 172 110 ip-protocol-type eq tcp
filter acl ace protocol 172 110 dst-port eq 8080
filter acl ace 172 110 enable
filter acl ace 172 120 name "CITRIX_Conn-tcp"
filter acl ace action 172 120 permit
filter acl ace ethernet 172 120 ether-type eq ip
filter acl ace ip 172 120 ip-protocol-type eq tcp
filter acl ace protocol 172 120 dst-port eq 1494
filter acl ace 172 120 enable
filter acl ace 172 121 name "CITRIX_Conn-udp"
filter acl ace action 172 121 permit
filter acl ace ethernet 172 121 ether-type eq ip
filter acl ace ip 172 121 ip-protocol-type eq udp
filter acl ace protocol 172 121 dst-port eq 1604
filter acl ace 172 121 enable
filter acl ace 172 128 name "VOIP_VLAN_PERMIT"
filter acl ace action 172 128 permit
filter acl ace ethernet 172 128 ether-type eq ip
filter acl ace ip 172 128 dst-ip eq 10.201.0.0
filter acl ace 172 128 enable
filter acl ace 172 129 name "GANYMEDE-PERMIT"
filter acl ace action 172 129 permit
filter acl ace ethernet 172 130 ether-type eq ip
filter acl ace ip 172 129 src-ip eq 100.20.172.0
filter acl ace ip 172 129 dst-ip eq 100.6.100.225
filter acl ace 172 129 enable
filter acl ace 172 130 name "PWC_VPN_ERISIM"
filter acl ace action 172 130 permit
filter acl ace ethernet 172 51 ether-type eq ip
filter acl ace ip 172 130 src-ip eq 100.20.172.0
filter acl ace ip 172 130 ip-protocol-type eq tcp
filter acl ace protocol 172 130 tcp-dst-port eq 11160
```

```
filter acl ace 172 130 enable
filter acl ace 172 131 name "ISAKMP"
filter acl ace action 172 131 permit
filter acl ace ethernet 172 131 ether-type eq ip
filter acl ace ip 172 131 ip-protocol-type eq udp
filter acl ace protocol 172 131 dst-port eq 500
filter acl ace 172 131 enable
filter acl ace 172 132 name "ESP"
filter acl ace action 172 132 permit
filter acl ace ethernet 172 132 ether-type eq ip
filter acl ace ip 172 132 ip-protocol-type eq 50
filter acl ace 172 132 enable
filter acl ace 172 133 name "LOGLAMAK_ICIN"
filter acl ace action 172 133 permit redirect-next-hop 100.20.150.34
filter acl ace ip 172 133 src-ip eq 0.0.0.0
filter acl ace 172 140 name "DENY_ANY_ANY"
filter acl ace action 172 140 deny
filter acl ace ethernet 172 140 ether-type eq ip
filter acl ace ip 172 140 src-ip eq 0.0.0.0
filter acl ace ip 172 140 dst-ip eq 0.0.0.0
filter acl ace 172 140 enable
filter acl 802 type inVlan name "NICE-CLS_ACL-in"
filter acl vlan 802 802
filter acl 802 disable
filter acl ace 802 1 name "NICE_to_NICE"
filter acl ace action 802 1 permit
filter acl ace ethernet 802 1 ether-type eq ip
filter acl ace ip 802 1 dst-ip eq 100.20.174.32
filter acl ace 802 1 enable
filter acl ace 802 10 name "ICMP_PERMIT"
filter acl ace action 802 10 permit
filter acl ace ethernet 802 10 ether-type eq ip
filter acl ace ip 802 10 ip-protocol-type eq icmp
```

## Advanced filter examples

```
filter acl ace 802 10 enable
filter acl ace 802 20 name "IGMP_PERMIT"
filter acl ace action 802 20 permit
filter acl ace ethernet 802 20 ether-type eq ip
filter acl ace ip 802 20 ip-protocol-type eq 2
filter acl ace 802 20 enable
filter acl ace 802 30 name "VRRP_PERMIT"
filter acl ace action 802 30 permit
filter acl ace ethernet 802 30 ether-type eq ip
filter acl ace ip 802 30 ip-protocol-type eq vrrp
filter acl ace 802 30 enable
filter acl ace 802 40 name "DNS_PERMIT"
filter acl ace action 802 40 permit
filter acl ace ethernet 802 40 ether-type eq ip
filter acl ace ip 802 40 src-ip eq 100.20.174.32
filter acl ace ip 802 40 dst-ip eq 100.20.104.0
filter acl ace protocol 802 40 dst-port eq dns
filter acl ace 802 40 enable
filter acl ace 802 45 name "DC-EXCH-DNS"
filter acl ace action 802 45 permit
filter acl ace ethernet 802 45 ether-type eq ip
filter acl ace ip 802 45 dst-ip eq 100.20.104.0
filter acl ace 802 45 enable
filter acl ace 802 50 name "ESTABLISHED RST"
filter acl ace action 802 50 permit
filter acl ace ethernet 802 50 ether-type eq ip
filter acl ace ip 802 50 src-ip eq 100.20.174.32
filter acl ace ip 802 50 ip-protocol-type eq tcp
filter acl ace protocol 802 50 dst-port eq 1023
filter acl ace protocol 802 50 tcp-flags eq rst
filter acl ace 802 50 enable
filter acl ace 802 51 name "ESTABLISHED ACK"
filter acl ace action 802 51 permit
```



```
filter acl ace ethernet 802 51 ether-type eq ip
filter acl ace ip 802 51 src-ip eq 100.20.174.32
filter acl ace ip 802 51 ip-protocol-type eq tcp
filter acl ace protocol 802 51 dst-port eq 1023
filter acl ace protocol 802 51 tcp-flags eq ack
filter acl ace 802 51 enable
filter acl ace 802 52 name "UDP_Permit"
filter acl ace action 802 52 permit
filter acl ace ethernet 802 52 ether-type eq ip
filter acl ace ip 802 52 ip-protocol-type eq udp
filter acl ace 802 52 enable
filter acl ace 802 60 name "NICE_Logging"
filter acl ace action 802 60 permit
filter acl ace ethernet 802 60 ether-type eq ip
filter acl ace ip 802 60 src-ip eq 100.20.174.32
filter acl ace ip 802 60 ip-protocol-type eq tcp
filter acl ace protocol 802 60 dst-port eq 2011
filter acl ace 802 60 enable
filter acl ace 802 65 name "RTS_Conn"
filter acl ace action 802 65 permit
filter acl ace ethernet 802 65 ether-type eq ip
filter acl ace ip 802 65 dst-ip eq 100.20.152.20
filter acl ace 802 65 enable
filter acl ace 802 70 name "CTI_Conn"
filter acl ace action 802 70 permit
filter acl ace ethernet 802 70 ether-type eq ip
filter acl ace ip 802 70 src-ip eq 100.20.174.32
filter acl ace ip 802 70 ip-protocol-type eq tcp
filter acl ace protocol 802 70 dst-port eq 3750
filter acl ace 802 70 enable
filter acl ace 802 90 name "LOGLAMA"
filter acl ace action 802 90 permit redirect-next-hop 100.20.150.217
filter acl ace ethernet 802 90 ether-type eq ip
```

## Advanced filter examples

```
filter acl ace ip 802 90 src-ip eq 0.0.0.0
filter acl ace 802 100 name "DENY_ANY"
filter acl ace action 802 100 deny
filter acl ace ip 802 100 src-ip eq 0.0.0.0
filter acl ace ip 802 100 dst-ip eq 0.0.0.0
filter acl ace 802 100 enable

filter acl 804 type inVlan name "BASIM_LIMITED-in"
filter acl vlan 804 804
filter acl ace 804 5 name "Basim_to_Basim"
filter acl ace action 804 5 permit
filter acl ace ethernet 804 5 ether-type eq ip
filter acl ace ip 804 5 dst-ip eq 100.20.174.96
filter acl ace 804 5 enable
filter acl ace 804 10 name "ICMP_PERMIT"
filter acl ace action 804 10 permit
filter acl ace ethernet 804 10 ether-type eq ip
filter acl ace ip 804 10 ip-protocol-type eq icmp
filter acl ace 804 10 enable
filter acl ace 804 20 name "IGMP_PERMIT"
filter acl ace action 804 20 permit
filter acl ace ethernet 804 20 ether-type eq ip
filter acl ace ip 804 20 ip-protocol-type eq 2
filter acl ace 804 20 enable
filter acl ace 804 30 name "VRRP_PERMIT"
filter acl ace action 804 30 permit
filter acl ace ethernet 804 30 ether-type eq ip
filter acl ace ip 804 30 ip-protocol-type eq vrrp
filter acl ace 804 30 enable
filter acl ace 804 40 name "DNS_PERMIT"
filter acl ace action 804 40 permit
filter acl ace protocol 804 40 dst-port eq dns
filter acl ace 804 40 enable
filter acl ace 804 45 name "DC-EXCH-DNS"
```

```
filter acl ace action 804 45 permit
filter acl ace ethernet 804 45 ether-type eq ip
filter acl ace ip 804 45 dst-ip eq 100.20.104.0
filter acl ace 804 45 enable
filter acl ace 804 50 name "ESTABLISHED RST"
filter acl ace action 804 50 permit
filter acl ace ethernet 804 50 ether-type eq ip
filter acl ace ip 804 50 src-ip eq 100.20.174.97
filter acl ace ip 804 50 ip-protocol-type eq tcp
filter acl ace protocol 804 50 dst-port eq 1023
filter acl ace protocol 804 50 tcp-flags eq rst
filter acl ace 804 50 enable
filter acl ace 804 51 name "ESTABLISHED ACK"
filter acl ace action 804 51 permit
filter acl ace ethernet 804 51 ether-type eq ip
filter acl ace ip 804 51 src-ip eq 100.20.174.97
filter acl ace ip 804 51 ip-protocol-type eq tcp
filter acl ace protocol 804 51 dst-port eq 1023
filter acl ace protocol 804 51 tcp-flags eq ack
filter acl ace 804 51 enable
filter acl ace 804 60 name "E-BANK_ERISIM"
filter acl ace action 804 60 permit
filter acl ace ethernet 804 60 ether-type eq ip
filter acl ace ip 804 60 dst-ip eq 100.20.115.11
filter acl ace ip 804 60 ip-protocol-type eq tcp
filter acl ace protocol 804 60 dst-port eq 80
filter acl ace 804 60 enable
filter acl ace 804 70 name "E-BANK_ERISIM_HTTPS"
filter acl ace action 804 70 permit
filter acl ace ethernet 804 70 ether-type eq ip
filter acl ace ip 802 70 dst-ip eq 100.20.115.11
filter acl ace ip 804 70 ip-protocol-type eq tcp
filter acl ace protocol 804 70 dst-port eq 443
```

## Advanced filter examples

```
filter acl ace 804 70 enable
filter acl ace 804 80 name "FRED_Erisim"
filter acl ace action 804 80 permit
filter acl ace ethernet 804 80 ether-type eq ip
filter acl ace ip 804 80 dst-ip eq 100.20.100.145
filter acl ace 804 80 enable
filter acl ace 804 81 name "BARNEY_Erisim"
filter acl ace action 804 81 permit
filter acl ace ethernet 804 81 ether-type eq ip
filter acl ace ip 804 81 dst-ip eq 100.20.100.151
filter acl ace 804 81 enable
filter acl ace 804 90 name "BUFFY_ERISIM"
filter acl ace action 804 90 permit
filter acl ace ethernet 804 90 ether-type eq ip
filter acl ace ip 804 90 dst-ip eq 100.20.100.77
filter acl ace ip 804 90 ip-protocol-type eq tcp
filter acl ace protocol 804 90 dst-port eq 1433
filter acl ace 804 90 enable
filter acl ace 804 100 name "ROMTest_ERISIM"
filter acl ace action 804 100 permit
filter acl ace ethernet 804 100 ether-type eq ip
filter acl ace ip 804 100 dst-ip eq 100.20.24.77
filter acl ace ip 804 100 ip-protocol-type eq tcp
filter acl ace protocol 804 100 dst-port eq 1433
filter acl ace 804 100 enable
filter acl ace 804 101 name "Mrksql-t0_ERISIM"
filter acl ace action 804 101 permit
filter acl ace ethernet 804 101 ether-type eq ip
filter acl ace ip 804 101 dst-ip eq 100.20.20.77
filter acl ace ip 804 101 ip-protocol-type eq tcp
filter acl ace protocol 804 101 dst-port eq 1433
filter acl ace 804 101 enable
filter acl ace 804 110 name "ROSETTA_ERISIM"
```

```
filter acl ace action 804 110 permit
filter acl ace ethernet 804 110 ether-type eq ip
filter acl ace ip 804 110 dst-ip eq 172.17.1.100
filter acl ace 804 110 enable
filter acl ace 804 120 name "PLAST_ERISIM"
filter acl ace action 804 120 permit
filter acl ace ethernet 804 120 ether-type eq ip
filter acl ace ip 804 120 dst-ip eq 212.57.7.20
filter acl ace 804 120 enable
filter acl ace 804 130 name "AV-Yama_YONETIM_2967"
filter acl ace action 804 130 permit
filter acl ace ethernet 804 130 ether-type eq ip
filter acl ace ip 804 130 ip-protocol-type eq tcp
filter acl ace protocol 804 130 dst-port eq 2967
filter acl ace 804 130 enable
filter acl ace 804 140 name "AV-Yama_YONETIM_9968"
filter acl ace action 804 140 permit
filter acl ace ethernet 804 140 ether-type eq ip
filter acl ace ip 804 140 ip-protocol-type eq tcp
filter acl ace protocol 804 140 dst-port eq 9968
filter acl ace 804 140 enable
filter acl ace 804 150 name "AV-Yama_YONETIM_UDP_2967"
filter acl ace action 804 150 permit
filter acl ace ethernet 804 150 ether-type eq ip
filter acl ace ip 804 150 ip-protocol-type eq udp
filter acl ace protocol 804 150 dst-port eq 2967
filter acl ace 804 150 enable
filter acl ace 804 160 name "AV-Yama_YONETIM_UDP_9968"
filter acl ace action 804 160 permit
filter acl ace ip 804 160 ip-protocol-type eq udp
filter acl ace protocol 804 160 dst-port eq 9968
filter acl ace 804 160 enable
filter acl ace 804 170 name "AV-Yama_YONETIM_UDP_Source"
```

## Advanced filter examples

```
filter acl ace action 804 170 permit
filter acl ace ethernet 804 170 ether-type eq ip
filter acl ace ip 804 170 ip-protocol-type eq udp
filter acl ace protocol 804 170 src-port eq 9968
filter acl ace 804 170 enable
filter acl ace 804 210 name "PROXY_ERISIM_EK"
filter acl ace action 804 210 permit
filter acl ace ethernet 804 210 ether-type eq ip
filter acl ace ip 804 210 dst-ip eq 100.20.189.0
filter acl ace ip 804 210 ip-protocol-type eq tcp
filter acl ace protocol 804 210 dst-port eq 8080
filter acl ace 804 210 enable
filter acl ace 804 220 name "LOGLAMA"
filter acl ace action 804 220 permit redirect-next-hop 100.20.150.217
filter acl ace ethernet 804 220 ether-type eq ip
filter acl ace ip 804 220 src-ip eq 0.0.0.0
filter acl ace 804 230 name "DENY_ANY"
filter acl ace action 804 230 deny
filter acl ace ip 804 230 src-ip eq 0.0.0.0
filter acl ace ip 804 230 dst-ip eq 0.0.0.0
filter acl ace 804 230 enable

filter acl 805 type inVlan name "SBS-Remote"
filter acl vlan 805 805
filter acl ace 805 5 name "SBS-to-SBS"
filter acl ace action 805 5 permit
filter acl ace ethernet 805 5 ether-type eq ip
filter acl ace ip 805 5 dst-ip eq 100.20.174.128
filter acl ace 805 5 enable
filter acl ace 805 10 name "ICMP_PERMIT"
filter acl ace action 805 10 permit
filter acl ace ethernet 805 10 ether-type eq ip
filter acl ace ip 805 10 ip-protocol-type eq icmp
filter acl ace 805 10 enable
```

```
filter acl ace 805 20 name "IGMP_PERMIT"
filter acl ace action 805 20 permit
filter acl ace ethernet 805 20 ether-type eq ip
filter acl ace ip 805 20 ip-protocol-type eq 2
filter acl ace 805 20 enable
filter acl ace 805 30 name "VRRP_PERMIT"
filter acl ace action 805 30 permit
filter acl ace ethernet 805 30 ether-type eq ip
filter acl ace ip 805 30 ip-protocol-type eq vrrp
filter acl ace 805 30 enable
filter acl ace 805 40 name "DNS_PERMIT"
filter acl ace action 805 40 permit
filter acl ace protocol 805 40 dst-port eq 53
filter acl ace 805 40 enable
filter acl ace 805 50 name "ESTABLISHED_RST"
filter acl ace action 805 50 permit
filter acl ace ethernet 805 50 ether-type eq ip
filter acl ace ip 805 50 src-ip eq 100.20.174.128
filter acl ace ip 805 50 ip-protocol-type eq tcp
filter acl ace protocol 805 50 dst-port eq 1023
filter acl ace protocol 805 50 tcp-flags eq rst
filter acl ace 805 50 enable
filter acl ace 805 51 name "ESTABLISHED_ACK"
filter acl ace action 805 51 permit
filter acl ace ethernet 805 51 ether-type eq ip
filter acl ace ip 805 51 src-ip eq 100.20.174.128
filter acl ace ip 805 51 ip-protocol-type eq tcp
filter acl ace protocol 805 51 dst-port eq 1023
filter acl ace protocol 805 51 tcp-flags eq ack
filter acl ace 805 51 enable
filter acl ace 805 80 name "DC_DNS_EXCH_PERMIT"
filter acl ace action 805 80 permit
filter acl ace ethernet 805 80 ether-type eq ip
```

## Advanced filter examples

```
filter acl ace ip 805 80 dst-ip eq 100.20.104.0
filter acl ace 805 80 enable
filter acl ace 805 90 name "HTTP_PERMIT"
filter acl ace action 805 90 permit
filter acl ace ethernet 805 90 ether-type eq ip
filter acl ace ip 805 90 ip-protocol-type eq tcp
filter acl ace protocol 805 90 dst-port eq 80
filter acl ace 805 90 enable
filter acl ace 805 100 name "HTTPS_PERMIT"
filter acl ace action 805 100 permit
filter acl ace ethernet 805 100 ether-type eq ip
filter acl ace ip 805 100 ip-protocol-type eq tcp
filter acl ace protocol 805 100 dst-port eq 443
filter acl ace 805 100 enable
filter acl ace 805 105 name "REMDESKTOP_PERMIT"
filter acl ace action 805 105 permit
filter acl ace ethernet 805 105 ether-type eq ip
filter acl ace ip 805 105 ip-protocol-type eq tcp
filter acl ace protocol 805 105 dst-port eq 3389
filter acl ace 805 105 enable
filter acl ace 805 110 name "PROXY_8080_PERMIT"
filter acl ace action 805 110 permit
filter acl ace ethernet 805 110 ether-type eq ip
filter acl ace ip 805 110 dst-ip eq 100.20.189.0
filter acl ace ip 805 110 ip-protocol-type eq tcp
filter acl ace protocol 805 110 dst-port eq 8080
filter acl ace 805 110 enable
filter acl ace 805 120 name "DAMEWARE_PERMIT"
filter acl ace action 805 120 permit
filter acl ace ethernet 805 120 ether-type eq ip
filter acl ace ip 805 120 src-ip eq 100.20.174.128
filter acl ace protocol 805 120 dst-port eq 445,6129
filter acl ace 805 120 enable
```



```
filter acl ace 805 140 name "DENY_ANY_ANY"
filter acl ace action 805 140 deny
filter acl ace ethernet 805 140 ether-type eq ip
filter acl ace ip 805 140 src-ip eq 0.0.0.0
filter acl ace ip 805 140 dst-ip eq 0.0.0.0
filter acl ace 805 140 enable

filter acl 1000 type inPort name "CS1K-RemDesk"
filter acl port 1000 1/33
filter acl ace 1000 10 name "ICMP"
filter acl ace action 1000 10 permit
filter acl ace ethernet 1000 10 ether-type eq ip
filter acl ace ip 1000 10 ip-protocol-type eq icmp
filter acl ace 1000 10 enable
filter acl ace 1000 15 name "ESTABLISHED_PERMIT_RST"
filter acl ace action 1000 15 permit
filter acl ace ethernet 1000 15 ether-type eq ip
filter acl ace protocol 1000 15 dst-port eq 1023
filter acl ace protocol 1000 15 tcp-flags eq rst,ack
filter acl ace 1000 15 enable
filter acl ace 1000 16 name "ESTABLISHED_PERMIT_ACK"
filter acl ace action 1000 16 permit
filter acl ace ethernet 1000 16 ether-type eq ip
filter acl ace protocol 1000 16 dst-port eq 1023
filter acl ace protocol 1000 16 tcp-flags eq ack
filter acl ace 1000 16 enable
filter acl ace 1000 20 name "LOGLAMAK_ICIN"
filter acl ace action 1000 20 permit redirect-next-hop 10.201.12.8
filter acl ace ethernet 1000 20 ether-type eq ip
filter acl ace ip 1000 20 src-ip eq 0.0.0.0
filter acl ace 1000 30 name "DENY-ANY_ANY"
filter acl ace action 1000 30 deny
filter acl ace ethernet 1000 30 ether-type eq ip
filter acl ace ip 1000 30 src-ip eq 0.0.0.0
```

## Advanced filter examples

```
filter acl ace 1000 30 enable

filter acl vlan 1802 802
filter acl 1802 disable
filter acl ace 1802 10 name "ICMP_PERMIT"
filter acl ace action 1802 10 permit
filter acl ace ethernet 1802 10 ether-type eq ip
filter acl ace ip 1802 10 ip-protocol-type eq icmp
filter acl ace 1802 10 enable
filter acl ace 1802 20 name "IGMP_PERMIT"
filter acl ace action 1802 20 permit
filter acl ace ethernet 1802 20 ether-type eq ip
filter acl ace ip 1802 20 ip-protocol-type eq 2
filter acl ace 1802 20 enable
filter acl ace 1802 30 name "VRRP_PERMIT"
filter acl ace action 1802 30 permit
filter acl ace ethernet 1802 30 ether-type eq ip
filter acl ace ip 1802 30 ip-protocol-type eq vrrp
filter acl ace 1802 30 enable
filter acl ace 1802 51 name "UDP_Permit"
filter acl ace action 1802 51 permit
filter acl ace ethernet 1802 51 ether-type eq ip
filter acl ace ip 1802 51 ip-protocol-type eq udp
filter acl ace 1802 51 enable
filter acl ace 1802 60 name "NICE_Logging"
filter acl ace action 1802 60 permit
filter acl ace ethernet 1802 60 ether-type eq ip
filter acl ace ip 1802 60 src-ip eq 100.20.174.32
filter acl ace protocol 1802 60 dst-port eq 2011
filter acl ace 1802 60 enable
filter acl ace 1802 65 name "RTS_Conn"
filter acl ace action 1802 65 permit
filter acl ace 1802 100 name "DENY_ANY"
filter acl ace action 1802 100 deny
```

```
filter acl ace ethernet 1802 100 ether-type eq ip
filter acl ace ip 1802 100 src-ip eq 0.0.0.0
filter acl ace ip 1802 100 dst-ip eq 0.0.0.0
filter acl ace 1802 100 enable

filter acl vlan 1804 804
filter acl ace 1804 5 name "BASIM_to_BASIM"
filter acl ace action 1804 5 permit
filter acl ace ethernet 1804 5 ether-type eq ip
filter acl ace ip 1804 5 src-ip eq 100.20.174.96
filter acl ace 1804 5 enable
filter acl ace 1804 10 name "ICMP_PERMIT"
filter acl ace action 1804 10 permit
filter acl ace ethernet 1804 10 ether-type eq ip
filter acl ace ip 1804 10 ip-protocol-type eq icmp
filter acl ace 1804 10 enable
filter acl ace 1804 20 name "IGMP_PERMIT"
filter acl ace action 1804 20 permit
filter acl ace ethernet 1804 20 ether-type eq ip
filter acl ace ip 1804 20 ip-protocol-type eq 2
filter acl ace 1804 20 enable
filter acl ace 1804 30 name "VRRP_PERMIT"
filter acl ace action 1804 30 permit
filter acl ace ethernet 1804 30 ether-type eq ip
filter acl ace ip 1804 30 ip-protocol-type eq vrrp
filter acl ace 1804 30 enable
filter acl ace 1804 40 name "DNS_PERMIT"
filter acl ace action 1804 40 permit
filter acl ace protocol 1804 40 src-port eq 53
filter acl ace 1804 40 enable
filter acl ace 1804 45 name "DC-EXCH-DNS"
filter acl ace action 1804 45 permit
filter acl ace ethernet 1804 45 ether-type eq ip
filter acl ace ip 1804 45 src-ip eq 100.20.104.0
```

## Advanced filter examples

```
filter acl ace 1804 45 enable
filter acl ace 1804 50 name "ESTABLISHED_RST"
filter acl ace action 1804 50 permit
filter acl ace ethernet 1804 50 ether-type eq ip
filter acl ace ip 1804 50 dst-ip eq 100.20.174.97
filter acl ace ip 1804 50 ip-protocol-type eq tcp
filter acl ace protocol 1804 50 tcp-dst-port eq 1023
filter acl ace protocol 1804 50 tcp-flags eq rst
filter acl ace 1804 50 enable
filter acl ace 1804 51 name "ESTABLISHED_ACK"
filter acl ace action 1804 51 permit
filter acl ace ethernet 1804 51 ether-type eq ip
filter acl ace ip 1804 51 dst-ip eq 100.20.174.97
filter acl ace ip 1804 51 ip-protocol-type eq tcp
filter acl ace protocol 1804 51 tcp-dst-port eq 1023
filter acl ace protocol 1804 51 tcp-flags eq ack
filter acl ace 1804 51 enable
filter acl ace 1804 80 name "PWC_ERISIM"
filter acl ace action 1804 80 permit
filter acl ace ethernet 1804 80 ether-type eq ip
filter acl ace ip 1804 80 src-ip eq 100.20.100.145
filter acl ace 1804 80 enable
filter acl ace 1804 110 name "ROSETTA_ERISIM"
filter acl ace action 1804 110 permit
filter acl ace ethernet 1804 110 ether-type eq ip
filter acl ace ip 1804 110 src-ip eq 172.17.1.100
filter acl ace 1804 110 enable
filter acl ace 1804 120 name "PLAST_ERISIM"
filter acl ace action 1804 120 permit
filter acl ace ethernet 1804 120 ether-type eq ip
filter acl ace ip 1804 120 src-ip eq 212.57.7.20
filter acl ace 1804 120 enable
filter acl ace 1804 130 name "AV-Yama_YONETIM_9968"
```

```
filter acl ace action 1804 130 permit
filter acl ace ethernet 1804 130 ether-type eq ip
filter acl ace ip 1804 130 ip-protocol-type eq tcp
filter acl ace protocol 1804 130 dst-port eq 9968
filter acl ace 1804 130 enable
filter acl ace 1804 140 name "AV-Yama_YONETIM_2967"
filter acl ace action 1804 140 permit
filter acl ace ethernet 1804 140 ether-type eq ip
filter acl ace ip 1804 140 ip-protocol-type eq tcp
filter acl ace protocol 1804 140 dst-port eq 2967
filter acl ace 1804 140 enable
filter acl ace 1804 150 name "AV-Yama_YONETIM_UDP_9968"
filter acl ace action 1804 150 permit
filter acl ace ethernet 1804 150 ether-type eq ip
filter acl ace ip 1840 150 ip-protocol-type eq udp
filter acl ace protocol 1804 150 dst-port eq 9968
filter acl ace 1804 150 enable
filter acl ace 1804 160 name "AV-Yama_YONETIM_UDP_2967"
filter acl ace action 1804 160 permit
filter acl ace ethernet 1804 160 ether-type eq ip
filter acl acl ip 1804 160 ip-protocol-type eq udp
filter acl ace protocol 1804 160 dst-port eq 2967
filter acl ace 1804 160 enable
filter acl ace 1804 180 name "SUNUCU_YONETIM"
filter acl ace action 1804 180 permit
filter acl ace ethernet 1804 180 ether-type eq ip
filter acl ace ip 1804 180 src-ip eq 100.20.150.80
filter acl ace ip 1804 180 ip-protocol-type eq tcp
filter acl ace protocol 1804 180 dst-port eq 3389
filter acl ace 1804 180 enable
filter acl ace 1804 200 name "OTOMIZE_DEBIT_CARD_OPS"
filter acl ace action 1804 200 permit
filter acl ace ethernet 1804 200 ether-type eq ip
```

## Advanced filter examples

```
filter acl ace ip 1804 200 src-ip eq 100.20.114.0
filter acl ace ip 1804 200 ip-protocol-type eq tcp
filter acl ace protocol 1804 200 dst-port eq 445
filter acl ace 1804 200 enable
filter acl ace 1804 210 name "OTOMIZE_DEBIT_CARD_OPS"
filter acl ace action 1804 210 permit
filter acl ace ethernet 1804 210 ether-type eq ip
filter acl ace ip 1804 210 src-ip eq 100.20.24.0
filter acl ace ip 1804 210 ip-protocol-type eq tcp
filter acl ace protocol 1804 210 dst-port eq 445
filter acl ace 1804 210 enable
filter acl ace 1804 220 name "LOGLAMA"
filter acl ace action 1804 220 permit
filter acl ace ethernet 1804 220 ether-type eq ip
filter acl ace ip 1804 220 src-ip eq 0.0.0.0
filter acl ace 1804 220 enable
filter acl ace 1804 230 name "DENY_ANY"
filter acl ace action 1804 230 deny
filter acl ace ethernet 1804 230 ether-type eq ip
filter acl ace ip 1804 230 src-ip eq 0.0.0.0
filter acl ace ip 1804 230 dst-ip eq 0.0.0.0
filter acl ace 1804 230 enable
```

The following section provides details about the filter configuration for the second core Layer 3 host

```
#
# FILTER CONFIGURATION
#
filter acl port 1 1/46
filter acl ace 1 1 name "Vrrp"
filter acl ace action 1 1 deny
filter acl ace ethernet 1 1 ether-type eq ip
filter acl ace ip 1 1 ip-protocol-type eq vrrp
filter acl ace 1 1 enable

filter acl 171 type inVlan name "TOPLANTI_VE_EGITIM_ACL"
```

```
filter acl vlan 171 171
filter acl 171 disable
filter acl ace 171 10 name "ICMP_PERMIT"
filter acl ace action 171 10 permit
filter acl ace ethernet 171 10 ether-type eq ip
filter acl ace ip 171 10 ip-protocol-type eq icmp
filter acl ace 171 10 enable
filter acl ace 171 20 name "IGMP_PERMIT"
filter acl ace action 171 20 permit
filter acl ace ethernet 171 20 ether-type eq ip
filter acl ace ip 171 20 ip-protocol-type eq 2
filter acl ace 171 20 enable
filter acl ace 171 30 name "VRRP_PERMIT"
filter acl ace action 171 30 permit
filter acl ace ethernet 171 30 ether-type eq ip
filter acl ace ip 171 30 ip-protocol-type eq vrrp
filter acl ace 171 30 enable
filter acl ace 171 40 name "DNS_PERMIT"
filter acl ace action 171 40 permit
filter acl ace ethernet 171 40 ether-type eq ip
filter acl ace ip 171 40 src-ip eq 100.20.171.0
filter acl ace ip 171 40 dst-ip eq 100.20.104.0
filter acl ace protocol 171 40 dst-port eq dns
filter acl ace 171 40 enable
filter acl ace 171 50 name "ESTABLISHED RST"
filter acl ace action 171 50 permit
filter acl ace ethernet 171 50 ether-type eq ip
filter acl ace ip 171 50 src-ip eq 100.6.172.0
filter acl ace ip 171 50 ip-protocol-type eq tcp
filter acl ace protocol 171 50 dst-port eq 1023
filter acl ace protocol 171 50 flags eq rst
filter acl ace 171 50 enable
filter acl ace 171 51 name "ESTABLISHED ACK"
```

## Advanced filter examples

```
filter acl ace action 171 51 permit
filter acl ace ethernet 171 51 ether-type eq ip
filter acl ace ip 171 51 src-ip eq 100.6.172.0
filter acl ace ip 171 51 ip-protocol-type eq tcp
filter acl ace protocol 171 51 dst-port eq 1023
filter acl ace protocol 171 51 flags eq ack
filter acl ace 171 51 enable
filter acl ace 171 60 name "DHCP_PERMIT"
filter acl ace action 171 60 permit
filter acl ace protocol 171 60 dst-port eq bootpServer
filter acl ace 171 60 enable
filter acl ace 171 80 name "DC_DNS_EXC_PERMIT"
filter acl ace action 171 80 permit
filter acl ace ethernet 171 80 ether-type eq ip
filter acl ace ip 171 80 src-ip eq 100.20.172.0
filter acl ace ip 171 80 dst-ip eq 100.20.104.0
filter acl ace 171 80 enable
filter acl ace 171 90 name "HTTP_PERMIT"
filter acl ace action 171 90 permit
filter acl ace ethernet 171 90 ether-type eq ip
filter acl ace ip 171 90 src-ip eq 100.20.172.0
filter acl ace protocol 171 90 dst-port eq 80
filter acl ace 171 90 enable
filter acl ace 171 100 name "HTTPS_PERMIT"
filter acl ace action 171 100 permit
filter acl ace ethernet 171 100 ether-type eq ip
filter acl ace ip 171 100 src-ip eq 100.20.172.0
filter acl ace protocol 171 100 dst-port eq 443
filter acl ace 171 100 enable
filter acl ace 171 110 name "PROXY_8080_PERMIT"
filter acl ace action 171 110 permit
filter acl ace ethernet 171 110 ether-type eq ip
filter acl ace ip 171 110 src-ip eq 100.20.172.0
```



```
filter acl ace ip 171 110 dst-ip eq 100.20.189.0
filter acl ace protocol 171 110 dst-port eq 8080
filter acl ace 171 110 enable
filter acl ace 171 120 name "CITRIX_Conn"
filter acl ace action 171 120 permit
filter acl ace ethernet 171 120 ether-type eq ip
filter acl ace protocol 171 120 dst-port eq 1494
filter acl ace protocol 171 120 dst-port eq 1604
filter acl ace 171 120 enable
filter acl ace 171 130 name "PWC_VPN_ERISIM"
filter acl ace action 171 130 permit
filter acl ace ethernet 171 130 ether-type eq ip
filter acl ace ip 171 130 src-ip eq 100.20.172.0
filter acl ace protocol 171 130 dst-port eq 11160
filter acl ace 171 130 enable
filter acl ace 171 140 name "Microsoft_FileSharing_PERMIT"
filter acl ace action 171 140 permit
filter acl ace protocol 171 140 dst-port eq 135-139
filter acl ace 171 140 enable
filter acl ace 171 150 create name "Microsoft_FileSharing_PERMIT"
filter acl ace action 171 150 permit
filter acl ace protocol 171 150 dst-port eq 445
filter acl ace 171 150 enable

filter acl 172 type inVlan name "MISAFIR_ACL"
filter acl vlan 172 172
filter acl 172 disable
filter acl ace 172 5 name "Misafir_to_Misafir"
filter acl ace action 172 5 permit
filter acl ace ethernet 172 5 ether-type eq ip
filter acl ace ip 172 5 dst-ip eq 100.20.172.0
filter acl ace 172 5 enable
filter acl ace 172 10 name "ICMP_PERMIT"
filter acl ace action 172 10 permit
```

## Advanced filter examples

```
filter acl ace ethernet 172 10 ether-type eq ip
filter acl ace ip 172 10 ip-protocol-type eq icmp
filter acl ace 172 10 enable
filter acl ace 172 20 name "IGMP_PERMIT"
filter acl ace action 172 20 permit
filter acl ace ethernet 172 20 ether-type eq ip
filter acl ace ip 172 20 ip-protocol-type eq 2
filter acl ace 172 20 enable
filter acl ace 172 30 name "VRRP_PERMIT"
filter acl ace action 172 30 permit
filter acl ace ethernet 172 30 ether-type eq ip
filter acl ace ip 172 30 ip-protocol-type eq vrrp
filter acl ace 172 30 enable
filter acl ace 172 40 name "DNS_PERMIT"
filter acl ace action 172 40 permit
filter acl ace ethernet 172 40 ether-type eq ip
filter acl ace ip 172 40 src-ip eq 100.20.172.0
filter acl ace ip 172 40 dst-ip eq 100.20.104.0
filter acl ace protocol 172 40 dst-port eq dns
filter acl ace 172 40 enable
filter acl ace 172 50 name "ESTABLISHED RST"
filter acl ace action 172 50 permit
filter acl ace ethernet 172 50 ether-type eq ip
filter acl ace ip 172 50 src-ip eq 100.20.172.0
filter acl ace ip 172 50 ip-protocol-type eq tcp
filter acl ace protocol 172 50 dst-port eq 1023
filter acl ace protocol 172 50 tcp-flags eq ack
filter acl ace 172 50 enable
filter acl ace 172 51 name "ESTABLISHED ACK"
filter acl ace action 172 51 permit
filter acl ace ethernet 172 51 ether-type eq ip
filter acl ace ip 172 51 src-ip eq 100.20.172.0
filter acl ace ip 172 51 ip-protocol-type eq tcp
```

```
filter acl ace protocol 172 51 dst-port eq 1023
filter acl ace protocol 172 51 tcp-flags eq ack
filter acl ace 172 51 enable
filter acl ace 172 60 name "DHCP_PERMIT"
filter acl ace action 172 60 permit
filter acl ace protocol 172 60 dst-port eq bootpServer
filter acl ace 172 60 enable
filter acl ace 172 80 name "DC_DNS_EXC_PERMIT"
filter acl ace action 172 80 permit
filter acl ace ethernet 172 80 ether-type eq ip
filter acl ace ip 172 80 src-ip eq 100.20.172.0
filter acl ace ip 172 80 dst-ip eq 100.20.104.0
filter acl ace 172 80 enable
filter acl ace 172 90 name "HTTP_PERMIT"
filter acl ace action 172 90 permit
filter acl ace ethernet 172 90 ether-type eq ip
filter acl ace ip 172 90 src-ip eq 100.20.172.0
filter acl ace ip 172 90 ip-protocol-type eq tcp
filter acl ace protocol 172 90 dst-port eq 80
filter acl ace 172 100 name "HTTPS_PERMIT"
filter acl ace action 172 100 permit
filter acl ace ethernet 172 100 ether-type eq ip
filter acl ace ip 172 100 src-ip eq 100.20.172.0
filter acl ace ip 172 100 ip-protocol-type eq tcp
filter acl ace protocol 172 100 dst-port eq 443
filter acl ace 172 100 enable
filter acl ace 172 105 name "REMDESKTOP_PERMIT"
filter acl ace action 172 105 permit
filter acl ace ethernet 172 105 ether-type eq ip
filter acl ace ip 172 105 src-ip eq 100.20.172.0
filter acl ace ip 172 105 ip-protocol-type eq tcp
filter acl ace protocol 172 105 dst-port eq 3389
filter acl ace 172 105 enable
```

## Advanced filter examples

```
filter acl ace 172 106 name "NORKOM_PERMIT"
filter acl ace action 172 106 permit
filter acl ace ethernet 172 106 ether-type eq ip
filter acl ace ip 172 106 src-ip eq 100.20.172.0
filter acl ace ip 172 106 dst-ip eq 100.6.106.0
filter acl ace 172 106 enable
filter acl ace 172 107 name "SPECTRUM_PERMIT"
filter acl ace action 172 107 permit
filter acl ace ethernet 172 107 ether-type eq ip
filter acl ace ip 172 107 src-ip eq 100.20.172.0
filter acl ace ip 172 107 dst-ip eq 100.20.17.0
filter acl ace 172 107 enable
filter acl ace 172 110 name "PROXY_8080_PERMIT"
filter acl ace action 172 110 permit
filter acl ace ethernet 172 110 ether-type eq ip
filter acl ace ip 172 110 src-ip eq 100.20.172.0
filter acl ace ip 172 110 dst-ip eq 100.20.189.0
filter acl ace ip 172 110 ip-protocol-type eq tcp
filter acl ace protocol 172 110 dst-port eq 8080
filter acl ace 172 110 enable
filter acl ace 172 120 name "CITRIX_Conn-tcp"
filter acl ace action 172 120 permit
filter acl ace ethernet 172 120 ether-type eq ip
filter acl ace ip 172 120 ip-protocol-type eq tcp
filter acl ace protocol 172 120 dst-port eq 1494
filter acl ace 172 120 enable
filter acl ace 172 121 name "CITRIX_Conn-udp"
filter acl ace action 172 121 permit
filter acl ace ethernet 172 121 ether-type eq ip
filter acl ace ip 172 121 ip-protocol-type eq udp
filter acl ace protocol 172 121 dst-port eq 1604
filter acl ace 172 121 enable
filter acl ace 172 128 name "VOIP_VLAN_PERMIT"
```

```
filter acl ace action 172 128 permit
filter acl ace ethernet 172 128 ether-type eq ip
filter acl ace ip 172 128 src-ip eq 100.20.172.0
filter acl ace ip 172 128 dst-ip eq 10.201.0.0
filter acl ace 172 128 enable
filter acl ace 172 129 name "GANYMEDE_PERMIT"
filter acl ace action 172 129 permit
filter acl ace ethernet 172 129 ether-type eq ip
filter acl ace ip 172 129 src-ip eq 100.20.172.0
filter acl ace ip 172 129 dst-ip eq 100.6.100.225
filter acl ace 172 129 enable
filter acl ace 172 130 name "PWC_VPN_ERISIM"
filter acl ace action 172 130 permit
filter acl ace ethernet 172 130 ether-type eq ip
filter acl ace ip 172 130 src-ip eq 100.20.172.0
filter acl ace ip 172 130 ip-protocol-type eq tcp
filter acl ace protocol 172 130 dst-port eq 11160
filter acl ace 172 130 enable
filter acl ace 172 131 name "ISAKMP"
filter acl ace action 172 131 permit
filter acl ace ethernet 172 131 ether-type eq ip
filter acl ace ip 172 131 ip-protocol-type eq udp
filter acl ace protocol 172 131 dst-port eq 500
filter acl ace 172 131 enable
filter acl ace 172 132 name "ESP"
filter acl ace action 172 132 permit
filter acl ace ethernet 172 132 ether-type eq ip
filter acl ace ip 172 132 ip-protocol-type eq 50
filter acl ace 172 132 enable
filter acl ace 172 133 name "LOGLAMAK_ICIN"
filter acl ace action 172 133 permit redirect-next-hop 100.20.150.34
filter acl ace ethernet 172 133 ether-type eq ip
filter acl ace ip 172 133 src-ip eq 100.20.172.72
```

## Advanced filter examples

```
filter acl ace 172 140 name "DENY_ANY_ANY"
filter acl ace action 172 140 deny
filter acl ace ethernet 172 140 ether-type eq ip
filter acl ace ip 172 140 src-ip eq 0.0.0.0
filter acl ace ip 172 140 dst-ip eq 0.0.0.0
filter acl ace 172 140 enable

filter acl 802 type inVlan name "NICE-CLS_ACL-in"
filter acl vlan 802 802
filter acl 802 disable
filter acl ace 802 1 name "NICE_to_NICE"
filter acl ace action 802 1 permit
filter acl ace ethernet 802 1 ether-type eq ip
filter acl ace ip 802 1 dst-ip eq 100.20.174.32
filter acl ace 802 1 enable
filter acl ace 802 10 name "ICMP_PERMIT"
filter acl ace action 802 10 permit
filter acl ace ethernet 802 10 ether-type eq ip
filter acl ace ip 802 10 ip-protocol-type eq icmp
filter acl ace 802 10 enable
filter acl ace 802 20 name "IGMP_PERMIT"
filter acl ace action 802 20 permit
filter acl ace ethernet 802 20 ether-type eq ip
filter acl ace ip 802 20 ip-protocol-type eq 2
filter acl ace 802 20 enable
filter acl ace 802 30 name "VRRP_PERMIT"
filter acl ace action 802 30 permit
filter acl ace ethernet 802 30 ether-type eq ip
filter acl ace ip 802 30 ip-protocol-type eq vrrp
filter acl ace 802 30 enable
filter acl ace 802 40 name "DNS_PERMIT"
filter acl ace action 802 40 permit
filter acl ace ethernet 802 40 ether-type eq ip
filter acl ace ip 802 40 src-ip eq 100.20.174.32
```

```
filter acl ace ip 802 40 dst-ip eq 100.20.104.0
filter acl ace protocol 802 40 dst-port eq dns
filter acl ace 802 40 enable
filter acl ace 802 45 name "DC-EXCH-DNS"
filter acl ace action 802 45 permit
filter acl ace ethernet 802 45 ether-type eq ip
filter acl ace ip 802 45 dst-ip eq 100.20.104.0
filter acl ace 802 45 enable
filter acl ace 802 50 name "ESTABLISHED RST"
filter acl ace action 802 50 permit
filter acl ace ethernet 802 50 ether-type eq ip
filter acl ace ip 802 50 src-ip eq 100.20.174.32
filter acl ace ip 802 50 ip-protocol-type eq tcp
filter acl ace protocol 802 50 dst-port eq 1023
filter acl ace protocol 802 50 tcp-flags eq rst
filter acl ace 802 50 enable
filter acl ace 802 51 name "ESTABLISHED ACK"
filter acl ace action 802 51 permit
filter acl ace ethernet 802 51 ether-type eq ip
filter acl ace ip 802 51 src-ip eq 100.20.174.32
filter acl ace ip 802 51 ip-protocol-type eq tcp
filter acl ace protocol 802 51 dst-port eq 1023
filter acl ace protocol 802 51 tcp-flags eq ack
filter acl ace 802 51 enable
filter acl ace 802 52 ame "UDP_Permit"
filter acl ace 802 52 action permit
filter acl ace ethernet 802 52 ether-type eq ip
filter acl ace ip 802 52 ip-protocol-type eq udp
filter acl ace 802 52 enable
filter acl ace 802 60 name "NICE_Logging"
filter acl ace action 802 60 permit
filter acl ace ethernet 802 60 ether-type eq ip
filter acl ace ip 802 60 src-ip eq 100.20.174.32
```

## Advanced filter examples

```
filter acl ace ip 802 60 ip-protocol-type eq tcp
filter acl ace protocol 802 60 dst-port eq 2011
filter acl ace 802 60 enable
filter acl ace 802 65 name "RTS_Conn"
filter acl ace action 802 65 permit
filter acl ace ethernet 802 65 ether-type eq ip
filter acl ace ip 802 65 dst-ip eq 100.20.152.20
filter acl ace 802 65 enable
filter acl ace 802 70 name "CTI_Conn"
filter acl ace action 802 70 permit
filter acl ace ethernet 802 70 ether-type eq ip
filter acl ace ip 802 70 src-ip eq 100.20.174.32
filter acl ace ip 802 70 ip-protocol-type eq tcp
filter acl ace protocol 802 70 dst-port eq 3750
filter acl ace 802 70 enable
filter acl ace 802 90 name "LOGLAMA"
filter acl ace action 802 90 permit redirect-next-hop 100.20.150.217
filter acl ace ethernet 802 90 ether-type eq ip
filter acl ace ip 802 90 src-ip eq 0.0.0.0
filter acl ace 802 100 name "DENY_ANY"
filter acl ace action 802 100 deny
filter acl ace ethernet 802 100 ether-type eq ip
filter acl ace ip 802 100 src-ip eq 0.0.0.0
filter acl ace ip 802 100 dst-ip eq 0.0.0.0
filter acl ace 802 100 enable

filter acl 804 type inVlan name "BASIM_LIMITED-in"
filter acl vlan 804 804
filter acl ace 804 5 name "Basim_to_Basim"
filter acl ace action 804 5 permit
filter acl ace ethernet 804 5 ether-type eq ip
filter acl ace ip 804 5 dst-ip eq 100.20.174.96
filter acl ace 804 5 enable
filter acl ace 804 10 name "ICMP_PERMIT"
```



```
filter acl ace action 804 10 permit
filter acl ace ethernet 804 10 ether-type eq ip
filter acl ace ip 804 10 ip-protocol-type eq icmp
filter acl ace 804 10 enable
filter acl ace 804 20 name "IGMP_PERMIT"
filter acl ace action 804 20 permit
filter acl ace ethernet 804 20 ether-type eq ip
filter acl ace ip 804 20 ip-protocol-type eq 2
filter acl ace 804 20 enable
filter acl ace 804 30 name "VRRP_PERMIT"
filter acl ace action 804 30 permit
filter acl ace ethernet 804 30 ether-type eq ip
filter acl ace ip 804 30 ip-protocol-type eq vrrp
filter acl ace 804 30 enable
filter acl ace 804 40 name "DNS_PERMIT"
filter acl ace action 804 40 permit
filter acl ace protocol 804 40 dst-port eq dns
filter acl ace 804 40 enable
filter acl ace 804 45 name "DC-EXCH-DNS"
filter acl ace action 804 45 permit
filter acl ace ethernet 804 45 ether-type eq ip
filter acl ace ip 804 45 dst-ip eq 100.20.104.0
filter acl ace 804 45 enable
filter acl ace 804 50 name "ESTABLISHED RST"
filter acl ace action 804 50 permit
filter acl ace ethernet 804 50 ether-type eq ip
filter acl ace ip 804 50 src-ip eq 100.20.174.97
filter acl ace ip 804 50 ip-protocol-type eq tcp
filter acl ace protocol 804 50 dst-port eq 1023
filter acl ace protocol 804 50 tcp-flags eq rst
filter acl ace 804 50 enable
filter acl ace 804 51 name "ESTABLISHED ACK"
filter acl ace action 804 51 permit
```

## Advanced filter examples

```
filter acl ace ethernet 804 51 ether-type eq ip
filter acl ace ip 804 51 src-ip eq 100.20.174.97
filter acl ace ip 804 51 ip-protocol-type eq tcp
filter acl ace protocol 804 51 dst-port eq 1023
filter acl ace protocol 804 51 tcp-flags eq ack
filter acl ace 804 51 enable
filter acl ace 804 60 name "E-BANK_ERISIM"
filter acl ace action 804 60 permit
filter acl ace ethernet 804 60 ether-type eq ip
filter acl ace ip 804 60 dst-ip eq 100.20.115.11
filter acl ace ip 804 60 ip-protocol-type eq tcp
filter acl ace protocol 804 60 tcp-dst-port eq 80
filter acl ace 804 60 enable
filter acl ace 804 70 name "E-BANK_ERISIM_HTTPS"
filter acl ace action 804 70 permit
filter acl ace ethernet 804 70 ether-type eq ip
filter acl ace ip 804 70 dst-ip eq 100.20.115.11
filter acl ace ip 804 70 ip-protocol-type eq tcp
filter acl ace protocol 804 70 dst-port eq 443
filter acl ace 804 70 enable
filter acl ace 804 80 name "FRED_Erisim"
filter acl ace action 804 80 permit
filter acl ace ethernet 804 80 ether-type eq ip
filter acl ace ip 804 80 dst-ip eq 100.20.100.145
filter acl ace 804 80 enable
filter acl ace 804 81 name "BARNEY_Erisim"
filter acl ace action 804 81 permit
filter acl ace ethernet 804 81 ether-type eq ip
filter acl ace ip 804 81 dst-ip eq 100.20.100.151
filter acl ace 804 81 enable
filter acl ace 804 90 name "BUFFY_ERISIM"
filter acl ace action 804 90 permit
filter acl ace ethernet 804 90 ether-type eq ip
```

```
filter acl ace ip 804 90 dst-ip eq 100.20.100.77
filter acl ace ip 804 90 ip-protocol-type eq tcp
filter acl ace protocol 804 90 dst-port eq 1433
filter acl ace 804 90 enable
filter acl ace create 804 100 name "ROMTest_ERISIM"
filter acl ace action 804 100 permit
filter acl ace ethernet 804 100 ether-type eq ip
filter acl ace ip 804 100 dst-ip eq 100.20.24.77
filter acl ace ip 804 100 ip-protocol-type eq tcp
filter acl ace protocol 804 100 dst-port eq 1433
filter acl ace 804 100 enable
filter acl ace 804 101 name "Mrksql-t0_ERISIM"
filter acl ace action 804 101 permit
filter acl ace ethernet 804 101 ether-type eq ip
filter acl ace ip 804 101 dst-ip eq 100.20.20.77
filter acl ace ip 804 101 ip-protocol-type eq tcp
filter acl ace protocol 804 101 dst-port eq 1433
filter acl ace 804 101 enable
filter acl ace 804 110 name "ROSETTA_ERISIM"
filter acl ace action 804 110 permit
filter acl ace ethernet 804 110 ether-type eq ip
filter acl ace ip 804 110 dst-ip eq 172.17.1.100
filter acl ace 804 110 enable
filter acl ace 804 120 name "PLAST_ERISIM"
filter acl ace action 804 120 permit
filter acl ace ethernet 804 120 ether-type eq ip
filter acl ace ip 804 120 dst-ip eq 212.57.7.20
filter acl ace 804 120 enable
filter acl ace 804 130 name "AV-Yama_YONETIM_2967"
filter acl ace action 804 130 permit
filter acl ace ethernet 804 130 ether-type eq ip
filter acl ace ip 804 130 ip-protocol-type eq tcp
filter acl ace protocol 804 130 dst-port eq 2967
```

## Advanced filter examples

```
filter acl ace 804 130 enable
filter acl ace 804 140 name "AV-Yama_YONETIM_9968"
filter acl ace action 804 140 permit
filter acl ace ethernet 804 140 ether-type eq ip
filter acl ace ip 804 140 ip-protocol-type eq tcp
filter acl ace protocol 804 140 dst-port eq 9968
filter acl ace 804 140 enable
filter acl ace 804 150 name "AV-Yama_YONETIM_UDP_2967"
filter acl ace action 804 150 permit
filter acl ace ethernet 804 150 ether-type eq ip
filter acl ace ip 804 150 ip-protocol-type eq udp
filter acl ace protocol 804 150 dst-port eq 2967
filter acl ace 804 150 enable
filter acl ace 804 160 name "AV-Yama_YONETIM_UDP_9968"
filter acl ace action 804 160 permit
filter acl ace ethernet 804 160 ether-type eq ip
filter acl ace ip 804 160 ip-protocol-type eq udp
filter acl ace protocol 804 160 dst-port eq 9968
filter acl ace 804 160 enable
filter acl ace 804 170 name "AV-Yama_YONETIM_UDP_Source"
filter acl ace action 804 170 permit
filter acl ace ethernet 804 170 ether-type eq ip
filter acl ace ip 804 170 ip-protocol-type eq udp
filter acl ace protocol 804 170 src-port eq 9968
filter acl ace 804 170 enable
filter acl ace 804 210 name "PROXY_ERISIM_EK"
filter acl ace action 804 210 permit
filter acl ace ethernet 804 210 ether-type eq ip
filter acl ace ip 804 210 dst-ip eq 100.20.189.0
filter acl ace ip 804 210 ip-protocol-type eq tcp
filter acl ace protocol 804 210 dst-port eq 8080
filter acl ace 804 210 enable
filter acl ace 804 220 name "LOGLAMA"
```

```
filter acl ace action 804 220 permit redirect-next-hop 100.20.150.217
filter acl ace ethernet 804 220 ether-type eq ip
filter acl ace ip 804 220 src-ip eq 0.0.0.0
filter acl ace 804 230 name "DENY_ANY"
filter acl ace action 804 230 deny
filter acl ace ethernet 804 230 ether-type eq ip
filter acl ace ip 804 230 src-ip eq 0.0.0.0
filter acl ace ip 804 230 dst-ip eq 0.0.0.0
filter acl ace 804 230 enable

filter acl 805 type inVlan name "SBS_Remote"
filter acl vlan 805 805
filter acl ace 805 5 name "SBS-to-SBS"
filter acl ace action 805 5 permit
filter acl ace ethernet 804 5 ether-type eq ip
filter acl ace ip 805 5 dst-ip eq 100.20.174.128
filter acl ace 805 5 enable
filter acl ace 805 10 name "ICMP_PERMIT"
filter acl ace action 805 10 permit
filter acl ace ethernet 805 10 ether-type eq ip
filter acl ace ip 805 10 ip-protocol-type eq icmp
filter acl ace 805 10 enable
filter acl ace 805 20 name "IGMP_PERMIT"
filter acl ace action 805 20 permit
filter acl ace ethernet 805 20 ether-type eq ip
filter acl ace ip 805 20 ip-protocol-type eq 2
filter acl ace 805 20 enable
filter acl ace 805 30 name "VRRP_PERMIT"
filter acl ace action 805 30 permit
filter acl ace ethernet 805 30 ether-type eq ip
filter acl ace ip 805 30 ip-protocol-type eq vrrp
filter acl ace 805 30 enable
filter acl ace 805 40 name "DNS_PERMIT"
filter acl ace action 805 40 permit
```

## Advanced filter examples

```
filter acl ace protocol 805 40 dst-port eq 53
filter acl ace 805 40 enable
filter acl ace 805 50 name "ESTABLISHED RST"
filter acl ace action 805 50 permit
filter acl ace ethernet 805 50 ether-type eq ip
filter acl ace ip 805 50 src-ip eq 100.20.174.128
filter acl ace ip 805 50 ip-protocol-type eq tcp
filter acl ace protocol 805 50 dst-port eq 1023
filter acl ace protocol 805 50 tcp-flags eq rst
filter acl ace 805 50 enable
filter acl ace 805 51 name "ESTABLISHED ACK"
filter acl ace action 805 51 permit
filter acl ace ethernet 805 51 ether-type eq ip
filter acl ace ip 805 51 src-ip eq 100.20.174.128
filter acl ace ip 805 51 ip-protocol-type eq tcp
filter acl ace protocol 805 51 dst-port eq 1023
filter acl ace protocol 805 51 tcp-flags eq ack
filter acl ace 805 51 enable
filter acl ace 805 80 name "DC_DNS_EXCH_PERMIT"
filter acl ace action 805 80 permit
filter acl ace ethernet 805 80 ether-type eq ip
filter acl ace ip 805 80 dst-ip eq 100.20.104.0
filter acl ace 805 80 enable
filter acl ace 805 90 name "HTTP_PERMIT"
filter acl ace action 805 90 permit
filter acl ace ethernet 805 90 ether-type eq ip
filter acl ace ip 805 90 ip-protocol-type eq tcp
filter acl ace protocol 805 90 dst-port eq 80
filter acl ace 805 90 enable
filter acl ace 805 100 name "HTTPS_PERMIT"
filter acl ace action 805 100 permit
filter acl ace ethernet 805 100 ether-type eq ip
filter acl ace ip 805 100 ip-protocol-type eq tcp
```

```
filter acl ace protocol 805 100 dst-port eq 443
filter acl ace 805 100 enable
filter acl ace 805 105 name "REMDESKTOP_PERMIT"
filter acl ace action 805 105 permit
filter acl ace ethernet 805 105 ether-type eq ip
filter acl ace ip 805 105 ip-protocol-type eq tcp
filter acl ace protocol 805 105 dst-port eq 3389
filter acl ace 805 105 enable
filter acl ace 805 110 name "PROXY_8080_PERMIT"
filter acl ace action 805 110 permit
filter acl ace ethernet 805 110 ether-type eq ip
filter acl ace ip 805 110 dst-ip eq 100.20.189.0
filter acl ace ip 805 110 ip-protocol-type eq tcp
filter acl ace protocol 805 110 dst-port eq 8080
filter acl ace 805 110 enable
filter acl ace 805 120 name "DAMEWARE_PERMIT"
filter acl ace action 805 120 permit
filter acl ace ethernet 805 120 ether-type eq ip
filter acl ace ip 805 120 src-ip eq 100.20.174.128
filter acl ace protocol 805 120 dst-port eq 445,6129
filter acl ace 805 120 enable
filter acl ace 805 140 name "DENY_ANY_ANY"
filter acl ace action 805 140 deny
filter acl ace ethernet 805 140 ether-type eq ip
filter acl ace ip 805 140 src-ip eq 0.0.0.0
filter acl ace ip 805 140 dst-ip eq 0.0.0.0
filter acl ace 805 140 enable

filter acl vlan 1802 802
filter acl 1802 disable
filter acl ace 1802 10 name "ICMP_PERMIT"
filter acl ace action 1802 10 permit
filter acl ace ethernet 1802 10 ether-type eq ip
filter acl ace ip 1802 10 ip-protocol-type eq icmp
```

## Advanced filter examples

```
filter acl ace 1802 10 enable
filter acl ace 1802 20 name "IGMP_PERMIT"
filter acl ace action 1802 20 permit
filter acl ace ethernet 1802 20 ether-type eq ip
filter acl ace ip 1802 20 ip-protocol-type eq 2
filter acl ace 1802 20 enable
filter acl ace 1802 30 name "VRRP_PERMIT"
filter acl ace action 1802 30 permit
filter acl ace ethernet 1802 30 ether-type eq ip
filter acl ace ip 1802 30 ip-protocol-type eq vrrp
filter acl ace 1802 30 enable
filter acl ace 1802 51 name "UDP_Permit"
filter acl ace action 1802 51 permit
filter acl ace ethernet 1802 51 ether-type eq ip
filter acl ace ip 1802 51 ip-protocol-type eq udp
filter acl ace 1802 51 enable
filter acl ace 1802 60 name "NICE_Logging"
filter acl ace action 1802 60 permit
filter acl ace ethernet 1802 60 ether-type eq ip
filter acl ace ip 1802 60 src-ip eq 100.20.174.32
filter acl ace protocol 1802 60 dst-port eq 2011
filter acl ace 1802 60 enable
filter acl ace 1802 100 name "DENY_ANY"
filter acl ace action 1802 100 deny
filter acl ace ip 1802 100 src-ip eq 0.0.0.0
filter acl ace ip 1802 100 dst-ip eq 0.0.0.0
filter acl ace 1802 100 enable
filter acl vlan 1804 804
filter acl ace 1804 5 name "BASIM-to-BASIM"
filter acl ace action 1804 5 permit
filter acl ace ethernet 1804 10 ether-type eq ip
filter acl ace ip 1804 5 src-ip eq 100.20.174.96
filter acl ace ip 1804 5 dst-ip eq 100.20.174.96
```



```
filter acl ace 1804 5 enable
filter acl ace 1804 10 name "ICMP_PERMIT"
filter acl ace action 1804 10 permit
filter acl ace ethernet 1804 10 ether-type eq ip
filter acl ace ip 1804 10 ip-protocol-type eq icmp
filter acl ace 1804 10 enable
filter acl ace 1804 20 create name "IGMP_PERMIT"
filter acl ace action 1804 20 permit
filter acl ace ethernet 1804 20 ether-type eq ip
filter acl ace ip 1804 20 ip-protocol-type eq 2
filter acl ace 1804 20 enable
filter acl ace 1804 30 name "VRRP_PERMIT"
filter acl ace action 1804 30 permit
filter acl ace ethernet 1804 30 ether-type eq ip
filter acl ace ip 1804 30 ip-protocol-type eq vrrp
filter acl ace 1804 30 enable
filter acl ace 1804 40 create name "DNS_PERMIT"
filter acl ace action 1804 40 permit
filter acl ace protocol 1804 40 src-port eq 53
filter acl ace 1804 40 enable
filter acl ace 1804 45 name "DC-EXCH-DNS"
filter acl ace action 1804 45 permit
filter acl ace ethernet 1804 45 ether-type eq ip
filter acl ace ip 1804 45 src-ip eq 100.20.104.0
filter acl ace 1804 45 enable
filter acl ace 1804 50 name "ESTABLISHED RST"
filter acl ace action 1804 50 permit
filter acl ace ethernet 1804 50 ether-type eq ip
filter acl ace ip 1804 50 dst-ip eq 100.20.174.97
filter acl ace ip 1804 50 ip-protocol-type eq tcp
filter acl ace protocol 1804 50 dst-port eq 1023
filter acl ace protocol 1804 50 tcp-flags eq rst
filter acl ace 1804 50 enable
```

## Advanced filter examples

```
filter acl ace 1804 51 name "ESTABLISHED ACK"
filter acl ace action 1804 51 permit
filter acl ace ethernet 1804 51 ether-type eq ip
filter acl ace ip 1804 51 dst-ip eq 100.20.174.97
filter acl ace ip 1804 51 ip-protocol-type eq tcp
filter acl ace protocol 1804 51 dst-port eq 1023
filter acl ace protocol 1804 51 tcp-flags eq ack
filter acl ace 1804 51 enable
filter acl ace 1804 80 name "PWC_ERISIM"
filter acl ace action 1804 80 permit
filter acl ace ethernet 1804 80 ether-type eq ip
filter acl ace ip 1804 80 src-ip eq 100.20.100.145
filter acl ace 1804 80 enable
filter acl ace 1804 110 name "ROSETTA_ERISIM"
filter acl ace action 1804 110 permit
filter acl ace ethernet 1804 110 ether-type eq ip
filter acl ace ip 1804 110 src-ip eq 172.17.1.100
filter acl ace 1804 110 enable
filter acl ace 1804 120 name "PLAST_ERISIM"
filter acl ace action 1804 120 permit
filter acl ace ethernet 1804 120 ether-type eq ip
filter acl ace ip 1804 120 src-ip eq 212.57.7.20
filter acl ace 1804 120 enable
filter acl ace 1804 130 name "AV-Yama_YONETIM_9968"
filter acl ace action 1804 130 permit
filter acl ace ethernet 1804 130 ether-type eq ip
filter acl ace ip 1804 130 ip-protocol-type eq tcp
filter acl ace protocol 1804 130 dst-port eq 9968
filter acl ace 1804 130 enable
filter acl ace 1804 140 name "AV-Yama_YONETIM_2967"
filter acl ace action 1804 140 permit
filter acl ace ethernet 1804 140 ether-type eq ip
filter acl ace ip 1804 140 ip-protocol-type eq tcp
```

```
filter acl ace protocol 1804 140 dst-port eq 2967
filter acl ace 1804 140 enable
filter acl ace 1804 150 name "AV-Yama_YONETIM_UDP_9968"
filter acl ace action 1804 150 permit
filter acl ace ethernet 1804 150 ether-type eq ip
filter acl ace ip 1804 50 ip-protocol-type eq udp
filter acl ace protocol 1804 50 dst-port eq 9968
filter acl ace 1804 40 enable
filter acl ace 1804 160 name "AV-Yama_YONETIM_UDP_2967"
filter acl ace action 1804 160 permit
filter acl ace ethernet 1804 160 ether-type eq ip
filter acl ace ip 1804 160 ip-protocol-type eq udp
filter acl ace protocol 1804 160 dst-port eq 2967
filter acl ace 1804 160 enable
filter acl ace 1804 180 create name "SUNUCU_YONETIM"
filter acl ace action 1804 180 permit
filter acl ace ethernet 1804 180 ether-type eq ip
filter acl ace ip 1804 180 src-ip eq 100.20.150.80
filter acl ace ip 1804 180 ip-protocol-type eq tcp
filter acl ace protocol 1804 180 dst-port eq 3389
filter acl ace 1804 180 enable
filter acl ace 1804 200 name "OTOMIZE_DEBIT_CARD_OPS"
filter acl ace action 1804 200 permit
filter acl ace ethernet 1804 200 ether-type eq ip
filter acl ace ip 1804 200 src-ip eq 100.20.114.0
filter acl ace ip 1804 200 ip-protocol-type eq tcp
filter acl ace protocol 1804 200 dst-port eq 445
filter acl ace 1804 200 enable
filter acl ace 1804 210 name "OTOMIZE_DEBIT_CARD_OPS"
filter acl ace action 1804 210 permit
filter acl ace ethernet 1804 210 ether-type eq ip
filter acl ace ip 1804 210 src-ip eq 100.20.24.0
filter acl ace ip 1804 210 ip-protocol-type eq tcp
```

## Advanced filter examples

```
filter acl ace protocol 1804 210 dst-port eq 445
filter acl ace 1804 210 enable
filter acl ace 1804 230 name "DENY_ANY"
filter acl ace action 1804 230 deny
filter acl ace ethernet 1804 230 ether-type eq ip
filter acl ace ip 1804 230 src-ip eq 0.0.0.0
filter acl ace ip 1804 230 dst-ip eq 0.0.0.0
filter acl ace 1804 230 enable
```

# Glossary

<b>Address Resolution Protocol (ARP)</b>	Maps an IP address to a physical machine address, for example, maps an IP address to an Ethernet media access control (MAC) address.
<b>aggregate</b>	A prefix length that is formed by combining several specific prefixes. The resulting prefix is used to combine blocks of address space into a single routing announcement.
<b>Autonomous System (AS)</b>	A set of routers under a single technical administration, using a single IGP and common metrics to route packets within the Autonomous System, and using an EGP to route packets to other Autonomous Systems.
<b>Autonomous System Number (ASN)</b>	A two-byte number that is used to identify a specific AS.
<b>Bootstrap Protocol (BootP)</b>	A User Datagram Protocol (UDP)/Internet Protocol (IP)-based protocol that a booting host uses to configure itself dynamically and without user supervision.
<b>bootstrap router (BSR)</b>	A dynamically elected Protocol Independent Multicast (PIM) router that collects information about potential Rendezvous Point routers and distributes the information to all PIM routers in the domain.
<b>Bridge Protocol Data Unit (BPDU)</b>	A data frame used to exchange information among the bridges in local or wide area networks for network topology maintenance.
<b>candidate bootstrap router (C-BSR)</b>	Provides backup protection in case the primary rendezvous point (RP) or bootstrap router (BSR) fails. Protocol Independent Multicast (PIM) uses the BSR and C-BSR.
<b>Circuitless IP (CLIP)</b>	A CLIP is often called a loopback and is a virtual interface that does not map to any physical interface.
<b>classless interdomain routing (CIDR)</b>	The protocol defined in RFCs 1517 and 1518 for using subnetwork masks, other than the defaults for IP address classes.
<b>Dynamic Random Access Memory (DRAM)</b>	A read-write random-access memory, in which the digital information is represented by charges stored on the capacitors and must be repeatedly replenished to retain the information.

<b>Enterprise Device Manager (EDM)</b>	A web-based embedded management system to support single-element management. EDM provides complete configuration management functionality for the supported devices and is supplied to the customer as embedded software in the device.
<b>equal cost multipath (ECMP)</b>	Distributes routing traffic among multiple equal-cost routes.
<b>Global routing engine (GRE)</b>	The base router or routing instance 0 in the Virtual Routing and Forwarding (VRF).
<b>Institute of Electrical and Electronics Engineers (IEEE)</b>	An international professional society that issues standards and is a member of the American National Standards Institute, the International Standards Institute, and the International Standards Organization.
<b>Interior Gateway Protocol (IGP)</b>	Distributes routing information between routers that belong to a single Autonomous System (AS).
<b>Internet Assigned Numbers Authority (IANA)</b>	The central registry for various assigned numbers, for example, Internet protocol parameters (such as port, protocol, and enterprise numbers), options, codes, and types.
<b>Internet Control Message Protocol (ICMP)</b>	A collection of error conditions and control messages exchanged by IP modules in both hosts and gateways.
<b>Internet Protocol version 4 (IPv4)</b>	The protocol used to format packets for the Internet and many enterprise networks. IPv4 provides packet routing and reassembly.
<b>Layer 1</b>	Layer 1 is the Physical Layer of the Open System Interconnection (OSI) model. Layer 1 interacts with the MAC sublayer of Layer 2, and performs character encoding, transmission, reception, and character decoding.
<b>Layer 2</b>	Layer 2 is the Data Link Layer of the OSI model. Examples of Layer 2 protocols are Ethernet and Frame Relay.
<b>Layer 3</b>	Layer 3 is the Network Layer of the OSI model. An example of a Layer 3 protocol is Internet Protocol (IP).
<b>Layer 3 Virtual Services Network</b>	The Layer 3 Virtual Services Network (L3 VSN) feature provides IP connectivity over SPBM for VRFs. Backbone Edge Bridges (BEBs) handle Layer 3 virtualized. At the BEBs through local provisioning, you map the end-user IP enabled VLAN or VLANs to a Virtualized Routing and Forwarding (VRF) instance. Then you map the VRF to a Service Instance Identifier (I-SID). VRFs that have the same I-SID configured can participate in the same Layer 3 Virtual Service Network (VSN).

<b>link-state advertisement (LSA)</b>	Packets that contain state information about directly connected links (interfaces) and adjacencies. Each Open Shortest Path First (OSPF) router generates the packets.
<b>management information base (MIB)</b>	The MIB defines system operations and parameters used for the Simple Network Management Protocol (SNMP).
<b>mask</b>	A bit string that the device uses along with an IP address to indicate the number of leading bits in the address that correspond with the network part.
<b>maximum transmission unit (MTU)</b>	The largest number of bytes in a packet—the maximum transmission unit of the port.
<b>media</b>	A substance that transmits data between ports; usually fiber optic cables or category 5 unshielded twisted pair (UTP) copper wires.
<b>Media Access Control (MAC)</b>	Arbitrates access to and from a shared medium.
<b>MultiLink Trunking (MLT)</b>	A method of link aggregation that uses multiple Ethernet trunks aggregated to provide a single logical trunk. A multilink trunk provides the combined bandwidth of multiple links and the physical layer protection against the failure of a single link.
<b>multiplexing</b>	Carriage of multiple channels over a single transmission medium; a process where a dedicated circuit is shared by multiple users. Typically, data streams intersperse on a bit or byte basis (time division), or separate by different carrier frequencies (frequency division).
<b>Network Basic Input/Output System (NetBIOS)</b>	An application programming interface (API) that augments the DOS BIOS by adding special functions for Local Area Networks (LAN).
<b>next hop</b>	The next hop to which a packet can be sent to advance the packet to the destination.
<b>operation, administration, and maintenance (OA&amp;M)</b>	All the tasks necessary for providing, maintaining, or modifying switching system services.
<b>Packet Capture Tool (PCAP)</b>	A data packet capture tool that captures ingress and egress (on Ethernet modules only) packets on selected ports. You can analyze captured packets for troubleshooting purposes.
<b>port</b>	A physical interface that transmits and receives data.

<b>prefix</b>	A group of contiguous bits, from 0 to 32 bits in length, that defines a set of addresses.
<b>Protocol Data Units (PDUs)</b>	A unit of data that is specified in a protocol of a specific layer and that consists of protocol-control information of the specific layer and possibly user data of that layer.
<b>Protocol Independent Multicast, Sparse Mode (PIM-SM)</b>	PIM-SM is a multicast routing protocol for IP networks. PIM-SM provides multicast routing for multicast groups that can span wide-area and inter-domain networks, where receivers are not densely populated. PIM-SM sends multicast traffic only to those routers that belong to a specific multicast group and that choose to receive the traffic. PIM-SM adds a Rendezvous Point router to avoid multicast-data flooding. Use PIM-SM when receivers for multicast data are sparsely distributed throughout the network.
<b>remote monitoring (RMON)</b>	A remote monitoring standard for Simple Network Management Protocol (SNMP)-based management information bases (MIB). The Internetwork Engineering Task Force (IETF) proposed the RMON standard to provide guidelines for remote monitoring of individual LAN segments.
<b>Reverse Address Resolution Protocol (RARP)</b>	A protocol that maintains a database of mappings between physical hardware addresses and IP addresses.
<b>reverse path checking (RPC)</b>	Prevents packet forwarding for incoming IP packets with incorrect or forged (spoofed) IP addresses.
<b>route flapping</b>	An instability that is associated with a prefix, where the associated prefix routes can exhibit frequent changes in availability over a period of time.
<b>route table manager (RTM)</b>	Determines the best route to a destination based on reachability, route preference, and cost.
<b>Routed Split MultiLink Trunking (RSMLT)</b>	Provides full router redundancy and rapid failover in routed core SMLT networks and as RSMLT-edge in routed SMLT edge applications; eliminating routing protocol timer dependencies when network failures occur.
<b>Routing Information Protocol (RIP)</b>	A distance vector protocol in the IP suite, used by IP network-layer protocol, that enables routers in the same AS to exchange routing information by means of periodic updates. You often use RIP as a very simple interior gateway protocol (IGP) within small networks.
<b>routing policy</b>	A form of routing that is influenced by factors other than the default algorithmically best route, such as the shortest or quickest path.
<b>Service Instance Identifier (I-SID)</b>	The SPBM B-MAC header includes a Service Instance Identifier (I-SID) with a length of 24 bits. SPBM uses this I-SID to identify and transmit any



virtualized traffic in an encapsulated SPBM frame. SPBM uses I-SIDs to virtualize VLANs (Layer 2 Virtual Services Network [VSN]) or VRFs (Layer 3 Virtual Services Network [VSN]) across the MAC-in-MAC backbone. With Layer 2 VSNs, you associate the I-SID with a customer VLAN, which is then virtualized across the backbone. With Layer 3 VSNs, you associate the I-SID with a customer VRF, which is also virtualized across the backbone.

**Shortest Path Bridging (SPB)**

Shortest Path Bridging is a control Link State Protocol that provides a loop-free Ethernet topology. There are two versions of Shortest Path Bridge: Shortest Path Bridging VLAN and Shortest Path Bridging MAC. Shortest Path Bridging VLAN uses the Q-in-Q frame format and encapsulates the source bridge ID into the VLAN header. Shortest Path Bridging MAC uses the 802.1 ah MAC-in-MAC frame format and encapsulates the source bridge identifier into the B-MAC header.

**Shortest Path Bridging MAC (SPBM)**

Shortest Path Bridging MAC (SPBM) uses the Intermediate-System-to-Intermediate-System (IS-IS) link-state routing protocol to provide a loop-free Ethernet topology that creates a shortest-path topology from every node to every other node in the network based on node MAC addresses. SPBM uses the 802.1ah MAC-in-MAC frame format and encapsulates the source bridge identifier into the B-MAC header. SPBM eliminates the need for multiple overlay protocols in the core of the network by reducing the core to a single Ethernet-based link-state protocol, which can provide virtualization services, both layer 2 and layer 3, using a pure Ethernet technology base.

**Simple Network Management Protocol (SNMP)**

SNMP administratively monitors network performance through agents and management stations.

**SMLT aggregation switch**

One of two IST peer switches that form a split link aggregation group. It connects to multiple wiring closet switches, edge switches, or customer premise equipment (CPE) devices.

**spanning tree**

A simple, fully-connected active topology formed from the arbitrary physical topology of connected bridged Local Area Network components by relaying frames through selected bridge ports. The protocol parameters and states that are used and exchanged to facilitate the calculation of the active topology and to control the bridge relay function.

**Spanning Tree Group (STG)**

A collection of ports in one spanning-tree instance.

**time-to-live (TTL)**

The field in a packet used to determine the valid duration for the packet. The TTL determines the packet lifetime. The system discards a packet with a TTL of zero.

<b>Trivial File Transfer Protocol (TFTP)</b>	A protocol that governs transferring files between nodes without protection against packet loss.
<b>trunk</b>	A logical group of ports that behaves like a single large port.
<b>Universal/Local (U/L)</b>	Determines global and local link addresses; used with the Extended Unique Identifier (EUI).
<b>User Datagram Protocol (UDP)</b>	In TCP/IP, a packet-level protocol built directly on the Internet Protocol layer. TCP/IP host systems use UDP for application-to-application programs.
<b>variable-length subnet masking (VLSM)</b>	Allocating IP addressing resources to subnets according to their individual need rather than some general network-wide rule.
<b>virtual router</b>	An abstract object managed by the Virtual Router Redundancy Protocol (VRRP) that acts as a default router for hosts on a shared LAN.
<b>virtual router forwarding (VRF)</b>	Provides traffic isolation between customers operating over the same node. Each virtual router emulates the behavior of a dedicated hardware router by providing separate routing functionality, and the network treats each VRF as a separate physical router.
<b>Virtual Router Redundancy Protocol (VRRP)</b>	A protocol used in static routing configurations, typically at the edge of the network. This protocol operates on multiple routers on an IP subnet and elects a primary gateway router. When the primary router fails, a backup router is quickly available to take its place.
<b>Voice over IP (VOIP)</b>	The technology that delivers voice information in digital form in discrete packets using the Internet Protocol (IP) rather than the traditional circuit-committed protocols of the public switched telephone network (PSTN).