



ExtremeCloud IQ Controller v10.20.01.0029 Release Notes

Enhancements, Changes, Supported Devices, and Known Issues

9041228-00
September 11, 2026

ABSTRACT

This release notes document for ExtremeCloud™ IQ Controller version 10.20.01.0029 outlines technical enhancements, supported hardware, installation guidance, and known limitations for IT professionals managing unified access networks. This release introduces Extreme Wi-Fi 7 access point model AP3020W (with an internal Omni directional antenna). The AP3020W supports 6 GHz Standard Power (AFC) and is designed for deployment in high-density, high-throughput indoor environments, such as schools, warehouses, healthcare facilities, and stadiums.. Other enhancements include: Smart RF Auto Sensor, which automatically assigns sensor APs at a Site while targeting a ratio of one sensor AP to three WLAN service APs; improved troubleshooting capabilities with greater visibility of client-associated VLAN IDs; Layer 2 MAC-based Access Control Lists, enabling administrators to define allow/deny rules using full MAC addresses or OUI-based wildcard masks; two new restricted AP5060 SKUs (AP5060U-WW-LPI and AP5060D-WW-LPI) supporting 6 GHz Low Power Indoor (LPI) operation for large venue deployments; support for deploying ExtremeCloud IQ Controller as a virtual appliance on Nutanix AHV, including high-availability configurations; a new AP5020 power profile providing 1 Gbps uplink performance when powered via 802.3at (PoE+); support for the AP5022FX 6 GHz LPI-only internal antenna with AFC handling; and a new option to display controller system time using UTC or GMT, with log timestamps reflecting the configured time zone.

INTRODUCTION

The ExtremeCloud IQ Controller is a next generation orchestration application offering all the mobility services required for modern unified access deployments. The ExtremeCloud IQ Controller includes comprehensive critical network services for wireless and wired connectivity, wireless device secure onboarding, distributed and centralized data paths, role-based access control through the Application Layer (Layer 7), integrated location services, and IoT device onboarding through a single platform. Built on field-proven architectures with the latest technology, the embedded operating system supports containerization of applications, enabling future expansion of value-added applications for the unified access edge.

- The CE1000 is an application on the Universal Compute Platform 1130C, replacing the E1120 appliance with similar functionality and limits. It supports up to 250 APs/Defenders and 2,000 users standalone, or 500 APs and 4,000 users in a high-availability setup.
- The CE2000 is an application on the Universal Compute Platform 2130C, replacing the E2120 and E2122 appliances with similar functionality and limits. It supports up to 2,000 APs/Defenders and 16,000 users standalone, or 4,000 APs and 32,000 users in a high-availability setup.
- The CE3000 is an application on the Universal Compute Platform 3150C, replacing the E3120 and E3125 appliances with similar functionality and limits. It supports up to 10,000 APs/Defenders and 50,000 users standalone, or 20,000 APs and 100,000 users in a high-availability setup.
- The E1120 is an appliance that meets the needs of entry to mid-level deployments, and is scalable to 250 APs/Defenders, 100 switches, and 4,000 mobility sessions in high-availability mode.
- The E2122 is an appliance that meets the needs of medium-sized, high-density and mission-critical deployments. It supports up to 4,000 APs/Defenders, 800 switches, and 32,000 mobility sessions in high-availability mode. Optionally, a redundant power supply can be ordered separately.
- The E3120 is an appliance that meets the needs of high-density and mission-critical deployments. It supports up to 20,000 APs/Defenders, 2,000 switches, and 100,000 mobility sessions in high-availability mode. Optionally, a redundant power supply can be ordered separately.
- The E3125 is an appliance that meets the needs of high-density and mission-critical deployments. It supports up to 20,000 APs/Defenders, 2,000 switches, and 100,000 mobility sessions in high-availability mode. Optionally, a redundant power supply can be ordered separately.
- The VE6120 is an elastic virtual appliance that supports up to 1,000 APs/Defenders, up to 400 switches and 16,000 mobility sessions in high-availability mode, depending on the hosting hardware.
- The VE6120, VE6120H, and VE6120K offer elastic capacities to cover the full range of offerings as VMWare/MS Hyper-V/Linux KVM, ranging from VE6120/VE6120H/VE6120K-Small to VE6120/VE6120H/VE6120K-Large.
- The VE6125/VE6125K XL are virtual appliances that support up to 4,000 APs/Defenders, up to 400 switches, and 32,000 mobility sessions in high-availability mode, depending on the hosting hardware.

The ExtremeCloud IQ Controller can expand its capacity to meet any growing business needs. The hardware and virtual packages are available for purchase. The customer purchases adoption capacity as a Right-To-Use Subscription model, supporting flexible quantities (per managed device) and term (multiple-year extended term) options.

Enhancements in 10.20.01.0029	ID
ExtremeCloud IQ Controller can now be deployed as a virtual appliance on Nutanix AHV (Acropolis Hypervisor). The Nutanix deployment option is supported, including high-availability (HA) configurations.	XCC-5316
ExtremeCloud IQ Controller 10.20.01 adds general availability (GA) support for the AP3020W, a Wi-Fi 7 (802.11be) wallplate access point. The AP3020W is a dual-radio 2x2 AP (2.4 GHz and 5/6 GHz) with integrated Ethernet ports for in-room wired devices, designed for hospitality, dormitory, and multi-dwelling deployments.	XCC-6759
Users now have the option to set the controller System Time to display time referencing the UTC (Coordinated Universal Time) or GMT (Greenwich Mean Time) time zone. Also, users now have an option (Display Times Using System Time Zone) to view Logs entries with time stamps based on the current time zone setting (the local web UI does not convert timestamps to local time). Note: In this release, if a user enables the "Display Times Using System Time Zone" option, it will not persist when using a browser's incognito mode or if an organization has browser policy where the browser storage is automatically cleaned when the browser window closes.	XCC-8325
AP4060X now supports the AIO-TQ06120-N external antenna.	XCC-7945
AP4020X now supports these external antennas: AIO-DD05120-RPSMA, AIO-DD75060-RPSMA, WS-AI-DQ05120 (30702), ML-2452-SEC6M4-036, and AI-TQ06120.	XCC-7944
AP4020FX now supports the AI-TH08055, AI-TH06120, and AIO-TH14035 antennas.	XCC-7921
New AP3020W-EG variant adds Wi-Fi 7 regulatory support for Egypt.	XCC-7910
AP5022FX now supports 6 GHz with the AI-TQ08055 antenna, and adds support for these external antennas: AIO-HE17020 and AI-TQ06120.	XCC-7879
Adds a new AP5020 power profile that supports a 1 Gbps uplink when powered via 802.3at (PoE+), providing more flexible power and performance options where 802.3bt power is not available.	XCC-7847
AP5022FX Radio 3 (6 GHz) provides an internal antenna to support Low Power Indoor (LPI) only, including corresponding AFC handling.	XCC-7816
Introducing Smart RF Auto Sensor, which automatically optimizes dedicated sensor radio assignments based on AP density, targeting one active sensor for every three data APs. This reduces sensor overhead in dense deployments while maintaining full-band coverage. Applies to APs with a dedicated sensor radio (AP410i/c, AP4020, AP4060, AP5022, AP5060).	XCC-7540
Adds Layer 2 MAC-based Access Control Lists applied after client association. Administrators can define allow/deny rules using full MAC addresses or OUI-based wildcard masks (e.g., MAC F4:EA:B5:00:00:00 with mask FF:FF:FF:00:00:00 matches all clients with that OUI).	XCC-7348

Enhancements in 10.20.01.0029	ID
Adds two new restricted AP5060 SKUs - AP5060U-WW-LPI and AP5060D-WW-LPI - enabling 6 GHz Low Power Indoor (LPI) operation with 1200 MHz power tables. These SKUs are US-only and restricted to on-premises controller deployments in large venues.	XCC-7096

Changes in 10.20.01.0029	ID
Fixed an issue where changing the display language on the captive portal failed to load the selected localized page on iOS devices.	CFD-13155
Resolved an issue where ACL rules with specified destination ports could unintentionally block return traffic (e.g., DNS responses), ensuring expected bidirectional communication without requiring additional reverse rules.	CFD-14952
Resolved an issue where RADIUS Health diagnostic tools in XIQ-C displayed inaccurate excessive failure and delay percentages.	CFD-15078
Clarified and corrected channel utilization metrics (including ChannelUtilization and ChannelOccupancy) returned via XIQ-C management APIs.	CFD-15965
Improved robustness in 802.11mc (Fine Timing Measurement) handling to increase stability and reliability.	CFD-16713
Added the AI-TH06120 (120° flat panel) antenna as a selectable configuration option in the GUI for AP4020FX.	CFD-16942
Improved system security by resolving multiple medium-severity vulnerabilities identified through security assessments.	CFD-17233
Fixed an issue where AP power change informational messages were improperly forwarded to syslog servers when the logging level was set to Critical.	CFD-17322
Corrected the extraction of username from certificates to correct display	CFD-17325
Resolved an issue that could cause port utilization graphs to display inaccurate percentage values, enabling customers to more reliably monitor network performance and capacity.	CFD-17357
Fixed an issue in the internal NAC Pre-Registration Portal that prevented customers from importing users through CSV files. Customers can now download the CSV template, upload user details, and have the imported accounts added successfully to the portal and local password repository.	CFD-17358
Updated internal component in the admin web portal to address potential security vulnerabilities (CVE-2014-6071).	CFD-17663
Corrected AP radio statistics reporting when wired port MTU set to 1380.	CFD-17753
Resolved an issue where SSIDs containing a hash (#) character prevented APs from correctly inserting OWE transition mode Information Elements into open beacon and probe responses.	CFD-17803
Fixed an issue in XIQ-C Controller GUI where event information for clients, Smart-RF, and APs failed to display.	CFD-18030

Extreme Networks recommends that you thoroughly review this document prior to installing or upgrading this product.

For the latest firmware versions, visit the download site at:
www.extremenetworks.com/support/

FIRMWARE SPECIFICATION

Status	Version No.	Type	Release Date
Current Version	V.10.20.01.0029	Feature Release	September 11, 2026

SUPPORTED CONTROLLER APPLICATIONS AND APPLIANCES, ACCESS POINTS, AND SWITCHES

Product Name	Image
Applications	
ExtremeCloud IQ Controller CE1000 application for Universal Compute Platform 1130C	XIQC-10.20.01.0029-1.dke
ExtremeCloud IQ Controller CE2000 application for Universal Compute Platform 2130C	XIQC-10.20.01.0029-1.gse
ExtremeCloud IQ Controller CE3000 application for Universal Compute Platform 3150C	XIQC-10.20.01.0029-1.ble
Appliances	
ExtremeCloud IQ Controller VE6120 VMware Min Supported ESXi version 5.1 or later, (tested 8.0)	XIQC-10.20.01.0029-1.dle
ExtremeCloud IQ Controller VE6120H (Windows server 2016 or later)	XIQC-10.20.01.0029-1.spe
ExtremeCloud IQ Controller VE6120K Linux KVM	XIQC-10.20.01.0029-1.dve
ExtremeCloud IQ Controller VE6125 Min Supported ESXi version 5.5 or later, (tested 7.0)	XIQC-10.20.01.0029-1.rse
ExtremeCloud IQ Controller VE6125K Linux KVM	XIQC-10.20.01.0029-1.mfe
ExtremeCloud IQ Controller E1120	XIQC-10.20.01.0029-1.sme
ExtremeCloud IQ Controller E2122	XIQC-10.20.01.0029-1.wze
ExtremeCloud IQ Controller E3120	XIQC-10.20.01.0029-1.ose
ExtremeCloud IQ Controller E3125	XIQC-10.20.01.0029-1.dze
Access Points	
AP3000-WW	AP3xxx-LEAN-10.20.1.0-025R.img
AP3000X-WW	AP3xxx-LEAN-10.20.1.0-025R.img
AP3020W-WW	AP40xx-10.20.1.0-025R.img
AP302W-CAN AP302W-FCC	AP302W-LEAN-10.20.1.0-025R.img

Product Name	Image
AP302W-IL AP302W-WR	
AP305C-1-CAN AP305C-1-FCC AP305C-1-IL AP305C-1-WR AP305C-CAN AP305C-FCC AP305C-IL AP305C-WR AP305CX-CAN AP305CX-FCC AP305CX-IL AP305CX-WR	AP3xxC-LEAN-10.20.1.0-025R.img
AP310e-1-WR AP310e-CAN AP310e-FCC AP310e-IL AP310e-WR AP310i-1-WR AP310i-CAN AP310i-FCC AP310i-IL AP310i-WR	AP3xx-LEAN-10.20.1.0-025R.img
AP360e-CAN AP360e-FCC AP360e-IL AP360e-WR AP360i-CAN AP360i-FCC AP360i-IL AP360i-WR	AP3xx-LEAN-10.20.1.0-025R.img
AP3912i-FCC AP3912i-ROW	AP391x-10.51.28.0001.img
AP3915e-FCC AP3915e-ROW AP3915i-FCC AP3915i-ROW	AP391x-10.51.28.0001.img
AP3916ic-FCC AP3916ic-ROW	AP391x-10.51.28.0001.img
AP3916-camera	AP3916IC-V1-0-14-1.dlf
AP3917e-FCC AP3917e-ROW AP3917i-FCC AP3917i-ROW AP3917k-FCC AP3917k-ROW	AP391x-10.51.28.0001.img
AP3935e-FCC AP3935e-ROW	AP3935-10.51.28.0001.img

Product Name	Image
AP3935i-FCC AP3935i-IL AP3935i-ROW	
AP3965e-FCC AP3965e-ROW AP3965i-FCC AP3965i-ROW	AP3935-10.51.28.0001.img
AP4000-1-WW AP4000-WW	AP4000x-LEAN-10.20.1.0-025R.img
AP4000U-WW	AP4000x-LEAN-10.20.1.0-025R.img
AP4020-WW	AP40xx-10.20.1.0-025R.img
AP4020FX-WW	AP40xx-10.20.1.0-025R.img
AP4020X-WW	AP40xx-10.20.1.0-025R.img
AP4060-WW	AP40xx-10.20.1.0-025R.img
AP4060X-WW	AP40xx-10.20.1.0-025R.img
AP410C-1-CAN AP410C-1-FCC AP410C-1-IL AP410C-1-WR AP410C-CAN AP410C-FCC AP410C-IL AP410C-WR	AP4xxC-LEAN-10.20.1.0-025R.img
AP410e-CAN AP410e-FCC AP410e-IL AP410e-WR AP410i-1-FCC AP410i-1-WR AP410i-CAN AP410i-FCC AP410i-IL AP410i-WR	AP4xx-LEAN-10.20.1.0-025R.img
AP460C-CAN AP460C-FCC AP460C-IL AP460C-WR AP460S12C-CAN AP460S12C-FCC AP460S12C-IL AP460S12C-WR AP460S6C-CAN AP460S6C-FCC AP460S6C-IL AP460S6C-WR	AP4xxC-LEAN-10.20.1.0-025R.img
AP460e-CAN AP460e-FCC	AP4xx-LEAN-10.20.1.0-025R.img

Product Name	Image
AP460e-IL AP460e-WR AP460i-CAN AP460i-FCC AP460i-IL AP460i-WR	
AP5010-WW	AP5xxx-LEAN-10.20.1.0-025R.img
AP5010U-WW	AP5xxx-LEAN-10.20.1.0-025R.img
AP5020-WW	AP5020-10.20.1.0-025R.img
AP5022-WW AP5022S6D-WW	AP5020-10.20.1.0-025R.img
AP5022FX-WW	AP5020-10.20.1.0-025R.img
AP5050D-WW	AP5xxx-LEAN-10.20.1.0-025R.img
AP5050U-WW	AP5xxx-LEAN-10.20.1.0-025R.img
AP505i-FCC AP505i-WR	AP5xx-LEAN-10.20.1.0-025R.img
AP5060D-WW AP5060U-WW	AP5020-10.20.1.0-025R.img
AP5060D-WW-LPI AP5060U-WW-LPI	AP5020-10.20.1.0-025R.img
AP510e-FCC AP510e-WR AP510i-1-FCC AP510i-1-WR AP510i-FCC AP510i-WR	AP5xx-LEAN-10.20.1.0-025R.img
AP560h-FCC AP560h-WR AP560i-FCC AP560i-WR	AP5xx-LEAN-10.20.1.0-025R.img
SA201	AP391x-10.51.28.0001.img
APVMAPI-FCC APVMAPI-ROW	APVMAP-10.51.28.0001.img
APVMAP10i-FCC APVMAP10i-WR	APVMAP10-10.20.1.0-025R.img
Switches	
210-12p-10GE2 210-24p-10GE2 210-48p-10GE2 210-12p-10GE2 POE 210-24p-10GE2 POE 210-48p-10GE2 POE	210-series_V1.02.05.0013.stk fp-connector-3.3.0.4.pyz (cloud connector)
220-12p-10GE2 220-24p-10GE2	220-series_V1.02.05.0013.stk fp-connector-3.3.0.4.pyz (cloud connector)

Product Name	Image
220-48p-10GE2 220-12p-10GE2 POE 220-24p-10GE2 POE 220-48p-10GE2 POE	
X435-24P/T-4S	summitlite_arm-30.7.1.1.xos summitlite_arm-30.5.0.259-cloud_connector-3.4.2.6.xmod
X440G2-12t-10G4 X440G2-24t-10G4 X440G2-48t-10G4 X440G2-12t-10G4 POE X440G2-24t-10G4 POE X440G2-48t-10G4 POE	summitX-30.2.1.8-patch2-5.xos summitX-30.2.1.8-cloud_connector-3.4.1.8.xmod (cloud connector)
X465_24W X465_48T X465_48P X465_48W X465_24MU X465_24MU_24W	onie-30.2.1.8-patch2-5-vpex_controlling_bridge.lst onie-30.2.1.8-cloud_connector-3.4.1.20.xmod
X620-16x	summitX-30.2.1.8-patch2-5.xos summitX-30.2.1.8-cloud_connector-3.4.1.8.xmod (cloud connector)

NETWORK MANAGEMENT SOFTWARE SUPPORT

Network Management	Version
ExtremeControl™	22.3 or higher
ExtremeAnalytics™	22.3 or higher
ExtremeCloud™ A3	4.0
ExtremeCloud™ IQ-Site Engine	22.3 or higher

Air Defense	Version
ExtremeAirDefense™	10.6.2

ExtremeGuest	Version
ExtremeGuest™	6.0.1.0-001

Note:

Platform and Access Point Configuration functions are not supported by ExtremeManagement™. ExtremeCloud™ IQ Site Engine v21.9 or greater is required.

Extreme Platform ONE – ExtremeCloud IQ Pilot Twin License Provides Backwards Compatibility

Some versions of ExtremeCloud IQ Site Engine and ExtremeCloud IQ Controller do not support Extreme Platform ONE licenses. To provide you with the necessary time to upgrade to later versions, every Extreme Platform ONE Standard subscription includes an ExtremeCloud IQ Pilot Twin license with the same start date, end date, and licensed quantity.

- The Extreme Portal shows both Extreme Platform ONE Standard and ExtremeCloud IQ Pilot Twin licenses.
- ExtremeCloud IQ (Classic) and ExtremeCloud IQ (New) do not show ExtremeCloud IQ Pilot Twin licenses.
- Extreme Platform ONE (that is, Extreme Platform ONE Networking or Extreme Platform ONE Security) does not show ExtremeCloud IQ Pilot Twin licenses.
- ExtremeCloud IQ Site Engine version 25.2 and earlier supports ExtremeCloud IQ Pilot and ExtremeCloud IQ Pilot Twin licenses.
- ExtremeCloud IQ Site Engine version 25.5 and later supports ExtremeCloud IQ Pilot licenses and Extreme Platform ONE subscriptions.
- ExtremeCloud IQ Controller versions support ExtremeCloud IQ Pilot and ExtremeCloud IQ Pilot Twin licenses.

Note:

If you purchased Extreme Platform ONE subscriptions and are running management application versions that are incompatible with Extreme Platform ONE subscriptions, you can use the provided ExtremeCloud.

INSTALLATION INFORMATION

Application and Appliance Installations	
CE1000, CE2000, CE3000	ExtremeCloud IQ Controller CE1000, CE2000, CE3000 Installation Guide
E1120	ExtremeCloud IQ Controller E1120 Installation Guide
E2122	ExtremeCloud IQ Controller E2122 Installation Guide
E3120	ExtremeCloud IQ Controller E3120 Installation Guide
E3125	ExtremeCloud IQ Controller E3125 Installation Guide
VE6120/VE6125	ExtremeCloud IQ Controller VE6120/VE6125 Installation Guide
VE6120H	ExtremeCloud IQ Controller VE6120H Installation Guide
VE6120K/VE6125K	ExtremeCloud IQ Controller VE6120K/VE6125K Installation Guide

Known Restrictions and Limitations

Known Restriction or Limitation	ID
When an AP radio is administratively turned off, the device may be incorrectly displayed as a Sensor on the floor map for the corresponding band, instead of being displayed as an AP.	XCC-8072
In some cases after upgrading to 10.18.01, APs may not receive updated Spectrum (SP) settings, which can result in APs operating at reduced LPI power or disabling 6 GHz radios on outdoor models, even though the GUI shows normal Spectrum refresh activity. The issue has been identified and will be fixed in a future release.	XCC-7772
In certain corner situation enabling MLO may result in reduced uplink throughput. This is end client driver dependent.	WOS-7879
AP3900 series requires a minimum firmware revision of 10.41.01 (or later) for onboarding into ExtremeCloud IQ Controller. Customers migrating from ExtremeWireless installations or onboarding new AP3900 inventory to ExtremeCloud IQ Controller must ensure APs are running at least the minimum revision prior to onboarding. Depending on the age of the inventory, this may require a manual upgrade of the unit firmware outside of the management framework.	XCC-3178
AP4020/X/FX and AP4060/X Radio 4 sensor functionality is restricted to basic WIPS and Reporting.	WOS-7913
The AP4020 Radio 4 sensor may fail to detect its own 2.4 GHz and 5 GHz BSS while detecting other BSS. This behavior is under investigation, and no workaround is currently available.	WOS-7802
Fourth radio detection and sensing capabilities are limited to legacy rates.	WOS-7792
AP4020X/FX radios using Operational Mode 2 (2.4/5H/5L GHz) do not support transmit power for 160 MHz channels, unlike other AP models. Note that 5 GHz Low has only one 160 MHz channel; therefore, it is advised that 160 MHz channel not be used in enterprise deployments.	WOS-7664
11mc not recommended for 2.4GHz band; 11mc works better with wider channels.	Info

SUPPORTED WEB BROWSERS

For ExtremeCloud IQ Controller management GUI, the following Web browsers were tested for interoperability:

Browsers	Version	OS
Chrome	117.0.5938.152	Windows 10 Windows 11
Microsoft Edge	117.0.2045.60	Windows 10 Windows 11
Firefox	118.0.01	Windows 10 Windows 11

Note: Microsoft IE browser is not supported for UI management.

For Wireless Clients (Captive Portal, AAA), recommended browsers are:

Browsers	Version	OS
Chrome	117.0.5938.152	Windows 10 Windows 11
Microsoft Edge	117.0.2045.60	Windows 10
Firefox	118.0.01	Windows 10 Windows 11
Safari	15.4 (17613.1.17.1.13)	iOS 16.7.1

PORT LIST

The following list of ports may need to remain open so that the Appliances and APs will function properly on a network that includes protection equipment like a firewall.

ExtremeCloud IQ Controller TCP/UDP Port Assignment Reference

Comp. Source	Comp. Dest	Protocol (TCP/UDP)	Src Port	Dest Port	Service	Remark	Open Firewall Req'd
Ports for AP/Appliance Communication							
Appliance	Access Point	UDP	Any	13910	WASSP	Management and Data Tunnel between AP and Appliance	Yes
Access Point	Appliance	UDP	Any	13910	WASSP	Management and Data Tunnel between AP and Appliance	Yes

Comp. Source	Comp. Dest	Protocol (TCP/UDP)	Src Port	Dest Port	Service	Remark	Open Firewall Req'd
Appliance	Access Point	UDP	4500	Any	Secured WASSP	Management Tunnel between AP and Appliance	Optional
Access Point	Appliance	UDP	Any	4500	Secured WASSP	Management Tunnel between AP and Appliance	Optional
Access Point	Appliance	UDP	Any	13907	WASSP	AP Registration to Appliance	Yes
Access Point	Appliance	UDP	Any	67	DHCP Server	If Appliance is DHCP Server for AP	Optional
Access Point	Appliance	UDP	Any	68	DHCP Server	If Appliance is DHCP Server for AP	Optional
Access Point	Appliance	UDP	Any	427	SLP	AP Registration to Appliance	Optional
Appliance	Access Point	TCP/UDP	Any	69	TFTP	AP image transfer	Yes
Access Point	Appliance	TCP/UDP	Any	69	TFTP	AP image transfer	Yes
Appliance	Access Point	TCP/UDP	Any	22	SCP	AP traces	Yes
Any	Access Point	TCP	Any	2002, 2003	RCAPD	AP Real Capture (if enabled)	Optional
Any	Access Point	TCP/UDP	Any	22	SSH	Remote AP login (if enabled)	Optional
Any	Access Point	TCP/UDP	Any	445	Microsoft CIFS	LDAP support	Optional
Any	Access Point	TCP/UDP	Any	137, 138, 139	NetBIOS	LDAP support	Optional
Ports for Appliance Management							
Any	Appliance	TCP/UDP	Any	22	SSH	Appliance CLI access	Yes
Any	Appliance	TCP/UDP	Any	5825	HTTPS	Appliance GUI access	Yes
Any	Appliance	TCP/UDP	Any	161	SNMP	Appliance SNMP access	Yes
Any	Appliance	TCP/UDP	Any	162	SNMP Trap	Appliance SNMP access	Yes

Comp. Source	Comp. Dest	Protocol (TCP/UDP)	Src Port	Dest Port	Service	Remark	Open Firewall Req'd
Any	Appliance	TCP	Any	80	HTTP	Appliance SNMP access ICP Self Registration	Yes
Any	Appliance	TCP	Any	443	HTTPS	ICP Self Registration	Yes
Any	Appliance	UDP	500	500	IKE	IKE phase 1	Yes
Any	Appliance	TCP/UDP	Any	69	TFTP	TFTP support	Yes
Any	Appliance	UDP	Any	4500	IPSec	IPSec NAT traversal	Yes
Any	Appliance	UDP	Any	13907	Discovery	Used by Discovery	Yes
Any	Appliance	UDP	Any	13910	WASSP	Used by L3 WASSP	Yes
Ports for Inter Controller Mobility¹ and Availability							
Appliance	Appliance	UDP	Any	13911	WASSP	Mobility and Availability Tunnel	Yes
Appliance	Appliance	TCP	Any	427	SLP	SLP Directory	Yes
Appliance	Appliance	TCP	Any	20506	Langley	Remote Langley Secure	Yes
Appliance	Appliance	TCP	Any	60606	Mobility	VN MGR	Yes
Appliance	Appliance	TCP	Any	123	NTP	Availability time sync	Yes
Appliance	DHCP Server	UDP	Any	67	SLP	Asking DHCP Server for SLP DA	Yes
DHCP Server	Appliance	UDP	Any	68	SLP	RespoECA from DHCP Server for SLP DA request	Yes
Appliance	Appliance	TCP	Any	6380	REDIS	High Availability (HA) Pair Configuration Synchronization	Yes
Core Back-End Communication							
Appliance	DNS Server	UDP	Any	53	DNS	If using DNS	Optional
Appliance	Syslog Server	UDP	Any	514	Syslog	If Appliance logs to external syslog server	Optional

¹For extension of ExtremeWireless deployment via Inter Controller Mobility.

Comp. Source	Comp. Dest	Protocol (TCP/UDP)	Src Port	Dest Port	Service	Remark	Open Firewall Req'd
Appliance	RADIUS Server	UDP	Any	1812	RADIUS Authentication and Authorization	If using RADIUS AAA	Optional
Appliance	RADIUS Server	UDP	Any	1813	RADIUS Accounting	If enabled RADIUS accounting	Optional
Appliance	RADIUS server	UDP	Any	1814	RADIUS Authentication and Authorization	If using RADIUS AAA	Optional
Appliance	RADIUS server	UDP	Any	1815	RADIUS Accounting	If enabled RADIUS Accounting	Optional
Dynamic Auth. Server (NAC)	Appliance	UDP	Any	3799	DAS	Request from DAS client to disconnect a specific client	Optional
Appliance	AeroScout Server	UDP	1144	12092	Location Based Service Proxy	Aeroscout Location-Based Service	Optional
AeroScout Server	Appliance	UDP	12092	1144	Location Based Service Proxy	Aeroscout Location-Based Service	Optional
Appliance	Extreme Cloud IQ	TCP	Any	443	NSight	Statistics Report into ExtremeCloud IQ	Yes

IETF STANDARDS MIB SUPPORT

RFC No.	Title	Groups Supported
Draft version of 802.11	IEEE802dot11-MIB	
1213	RFC1213-MIB	Most of the objects supported
1573	IF-MIB	ifTable and interface scalar supported
1907	SNMPv2-MIB	System scalars supported
1493	BRIDGE-MIB	EWC supports relevant subset of the MIB
2674	P-BRIDGE-MIB	EWC supports relevant subset of the MIB
2674	Q-BRIDGE-MIB	EWC supports relevant subset of the MIB

EXTREME NETWORKS PRIVATE ENTERPRISE MIB SUPPORT

Extreme Networks Private Enterprise MIBs are available in ASN.1 format from the Extreme Networks website at: <https://extreme-networks.my.site.com/ExtrSupportHome>.

Standard MIBs

Title	Description
IEEE802dot11-MIB	Standard MIB for wireless devices
RFC1213-MIB.my	Standard MIB for system information
IF-MIB	Interface MIB
SNMPv2-MIB	Standard MIB for system information
BRIDGE-MIB	VLAN configuration information that pertains to EWC
P-BRIDGE-MIB	VLAN configuration information that pertains to EWC
Q-BRIDGE-MIB	VLAN configuration information that pertains to EWC

Siemens Proprietary MIB

Title	Description
HIPATH-WIRELESS-HWC-MIB.my	Configuration and statistics related to EWC and associated objects
HIPATH-WIRELESS-PRODUCTS-MIB.my	Defines product classes
HIPATH-WIRELESS-DOT11-EXTNS-MIB.my	Extension to IEEE802dot11-MIB that complements standard MIB
HIPATH-WIRELESS-SMI.my	Root for Chantry/Siemens MIB

802.11AC AND 802.11N CLIENTS

Please refer to the latest release notes for ExtremeWireless™ 10.41.09 or later and/or ExtremeWireless WiNG 5.9.02 or later for the list of compatibility test devices.

RADIUS SERVERS AND SUPPLICANTS**RADIUS Servers Used During Testing**

Vendor	Model OS	Version
FreeRADIUS	1.1.6	FreeRADIUS
FreeRADIUS IAS	1.0.1	FreeRADIUS
	5.2.3790.3959	Microsoft Server 2003 IAS

Vendor	Model OS	Version
SBR50	6.1.6	SBR Enterprise edition
NPS	6.0.6002.18005	Microsoft Server 2008 NPS

802.1x Supplicants Supported

Vendor	Model OS	Version
Juniper Networks® / Funk	Odyssey client	Version 5.10.14353.0
		Version 5.00.12709.0
		Version 4.60.49335.0
Microsoft®	Wireless Zero Configuration	Version Windows XP-4K-891859-Beta1
	Wireless Network Connection Configuration	Version Microsoft Window Server 2003, Enterprise Edition R2 SP2
	Wi-Fi Protected Access 2 (WPA2)/Wireless Provisioning Services Information Element (WPS IE) update for Windows XP with Service Pack 2	Version WindowsXP-KB893357-v2-x86-ENU.exe
Intel®	Intel PRO Set/Wireless	Version 13.0.0.x (with Windows® Intel® driver version 13.0.0.x)
Microsoft® Wireless Zero	Windows 7, 8, 8.1 Pro, 10 Pro Windows Phone 8.1, Windows Mobile 10	Provided with Windows®

Appliance LAN Switch Verification

Vendor	Model OS	Version	Role
Extreme	X-460-G2	12.5.4.5	XIQC connection
Extreme	X440G2-48p-10G4	21.1.1.4	XIQC connectivity
Extreme	Summit 300-48	7.6e1.4	XIQC connection
Extreme	VSP-4850GTS-PWR	(6.0.1.1_B003) (PRIVATE) HW Base: ERS 4850	XIQC connection
Extreme	K6	08.63.02.0004	XIQC connection
Extreme	K6	08.42.03.0006	XIQC connection
Extreme	X440G2-48p-10GE4	21.1.5.2	XIQC connection
Extreme	X440-G2-12p	21.1.1.4	XIQC connection
Extreme	X460-48p	12.5.4.5	XIQC connection

Vendor	Model OS	Version	Role
Cisco	Catalyst 3550	12.1(19)EA1c	XIQC connection

CERTIFICATION AUTHORITY

Server Vendor	Model OS	Version
Microsoft CA	Windows Server 2003 Enterprise Edition	5.2.3790.1830
Microsoft CA	Windows Server 2008 Enterprise Edition	6.0
OpenSSL	Linux	1.1.1g

RADIUS ATTRIBUTES SUPPORT

RADIUS Authentication and Authorization Attributes

Attribute	RFC Source
Called-Station-Id	RFC 2865, RFC 3580
Calling-Station-Id	RFC 2865, RFC 3580
Class	RFC 2865
EAP-Message	RFC 3579
Event-Timestamp	RFC 2869
Filter-Id	RFC 2865, RFC 3580
Framed-IPv6-Pool	RFC 3162
Framed-MTU	RFC 2865, RFC 3580
Framed-Pool	RFC 2869
Idle-Timeout	RFC 2865, RFC 3580
Message-Authenticator	RFC 3579
NAS-Identifier	RFC 2865, RFC 3580
NAS-IP-Address	RFC 2865, RFC 3580
NAS-IPv6-Address	RFC 3162
NAS-Port	RFC 2865, RFC 3580
NAS-Port-Id	RFC 2865, RFC 3580
NAS-Port-Type	RFC 2865, RFC 3580
Password-Retry	RFC 2869
Service-Type	RFC 2865, RFC 3580
Session-Timeout	RFC 2865
State	RFC 2865

Attribute	RFC Source
Termination-Action	RFC 2865, RFC 3580
Tunnel Attributes	RFC 2867, RFC 2868, RFC 3580
User-Name	RFC 2865, RFC 3580
Vendor-Specific	RFC 2865

RADIUS Accounting Attributes

Attribute	RFC Source
Acct-Authentic	RFC 2866
Acct-Delay-Time	RFC 2866
Acct-Input-Octets	RFC 2866
Acct-Input-Packets	RFC 2866
Acct-Interim-Interval	RFC 2869
Acct-Output-Octets	RFC 2866
Acct-Output-Packets	RFC 2866
Acct-Session-Id	RFC 2866
Acct-Session-Time	RFC 2866
Acct-Status-Type	RFC 2866
Acct-Terminate-Cause	RFC 2866

GLOBAL SUPPORT

By Phone: +1 800-998-2408 (toll-free in U.S. and Canada)

For the toll-free support number in your country:
<https://www.extremenetworks.com/support/contact>

By Email: support@extremenetworks.com

By Web: <https://extreme-networks.my.site.com/ExtrSupportHome>

For information regarding the latest software release, recent release note revisions and documentation, or if you require additional assistance, please visit the Extreme Networks Support website.

LEGAL

Legal Notice

Extreme Networks, Inc. reserves the right to make changes in specifications and other information contained in this document and its website without prior notice. The reader should in all cases consult representatives of Extreme Networks to determine whether any such changes have been made.

The hardware, firmware, software, or any specifications described or referred to in this document are subject to change without notice.

Trademarks

Extreme Networks and the Extreme Networks logo are trademarks or registered trademarks of Extreme Networks, Inc. in the United States and/or other countries. All other names (including any product names) mentioned in this document are the property of their respective owners and may be trademarks or registered trademarks of their respective companies/owners.

For additional information on Extreme Networks trademarks, please see:
[Trademarks | Extreme Networks](#)

© EXTREME NETWORKS. 2026. ALL RIGHTS RESERVED.