

ExtremeLocation Essentials Setup Guide

ExtremeCloud IQ Essentials Documentation

Published: May 2021

Extreme Networks, Inc. Phone / +1 408.579.2800 Toll-free / +1 888.257.3000 www.extremenetworks.com

© 2021 Extreme Networks, Inc. All rights reserved.

Extreme Networks and the Extreme Networks logo are trademarks or registered trademarks of Extreme Networks, Inc. in the United States and/or other countries. All other names are the property of their respective owners. All other registered trademarks, trademarks, and service marks are property of their respective owners. For additional information on Extreme Networks trademarks, see www.extremenetworks.com/company/legal/trademarks

Contents

Introduction to ExtremeLocation Essentials	2
Setup Procedure 1: Create a Location	3
Setup Procedure 2: Create a Network Policy	5

Introduction to ExtremeLocation Essentials

ExtremeLocation Essentials is a scalable, cloud-based location and analytics solutions from Extreme Networks. With real-time location and analytics, you can engage with your customers providing personalized experience for guests and visitors. ExtremeLocation Essentials can also be used to monitor your workflows and assets to improve your overall operation and efficiency.

ExtremeLocation Essentials provides enterprises powerful location services which can scale to thousands of branch sites and 100,000 access points. Use ExtremeLocation Essentials to access unlimited customizable dashboards for data analysis and site monitoring, drill down to floor level at a site to monitor assets, visitors and staff, and create and view reports to help you proactively plan or troubleshoot issues.

ExtremeLocation Essentials offers a range of accurate and granular location accuracy to address your deployment scenarios and includes:

- Real-time and historical location analysis
- New and repeat visitor tracking
- Engagement time monitoring
- Site- or zone-specific intelligence
- Assets and employee tracking

ExtremeLocation Essentials supports multi-site, multi-AP deployments that provide support to thousands of sites and one hundred thousand access points. Hosted on the cloud, it provides a resilient, always-available service to meet your location and analytics needs.

With ExtremeLocation Essentials, you can react quickly to a visitor or customer to your site or venue. Use this feature to provide a customized welcome message to customers upon arrival. Enhance the quality of engagement with visitors by promoting coupons, offers, advertisements, and other real-time notifications to visitors' devices.

Upload a floor map of an area of interest and create zones on the floor map that meet your requirements. A zone is an area covered by an AP or a sensor. You can also detect devices, visitors, and staff within a zone. You can locate and track assets, view which zones are popular or unpopular, and track (live and historical) time spent by users or staff members in a zone.

Use ExtremeLocation Essentials to auto classify devices based on user-defined rules. Separating devices enhances accurate visitor analysis. It also improves asset tracking and monitoring of staff activity.

ExtremeLocation Essentials displays crowding events in real-time. A crowding event occurs when the ratio of the number of visitors to the number of staff in a category or a zone exceeds the minimum threshold value © 2021 Extreme Networks, Inc. All rights reserved.

ExtremeLocation Essentials Setup Guide

configured for that category or configured globally. Real-time crowding events can either be configured globally or by category, and real-time event notification and analytics can be generated. Active events for a category are viewed in the floor plan by zone so that you can identify which categories need immediate staff attention.

ExtremeLocation Essentials supports export of the dashboard as reports. Reports can be exported as PDF files. ExtremeLocation Essentials's report scheduling interface enables you to create periodic reports that are emailed automatically. Schedules can be set daily, weekly, or monthly.

Use ExtremeLocation Essentials to track your assets throughout your site. An asset is a physical device or item that you want to track. With ExtremeLocation Essentials, you can track such critical assets within your sites using BLE beacons or by using the device's inbuilt Wi-Fi radio. The Asset Tracking and Management feature enables you to locate a tracked asset within your site. ExtremeLocation Essentials Asset Tracking also can raise alarms if your tracked asset moves out of its designated area or enters an area where it is prohibited to enter. It can also raise an alarm if the asset that you track is not seen within your site for a configured period of time.

Setup Procedure 1: Create a Location

To set up ExtremeLocation Essentials, begin by creating a location. Follow these steps:



2. In ExtremeCloud IQ, select ML Insights > Add network plan > Create Location, Building and Floor.



3. In Global view, create a location by selecting Add icon > Location. Fill in the mandatory fields (Name and Address, highlighted below) and select Save.

← -	d G	va2.extremecloudiq.e		228026/overview							07	☆ <mark>O</mark> ≯	3 :
III Ap	ps M G	āmail 関 pgAdmin 4 🌖	Course: CWS-100 e	It takes 30 days to f.	C http://52.6	56.198.69: E ExtremeLoc	ation 🗲 TestLink	E XCA 🔤 ADP	Python	🖸 g7envi 🏼 😰 E	dube Interactive : 🚺	Udemy Courses	35
-	Extre	emeCloud IQ Pil	ot	_					<u>م</u> (•	e xigproductiong xigproductiong	apps+va2 QA apps+va2@g	E
6	AN		Q	IMPORT		LOCATION BUILDI	NG FLOOR						
\$⇒	60 PL	Global View	ik er e	Мар	-				*			8	
*>	ORK 3	□ 🖓 Chennai_1			dd Location								
di >	NETW	🕀 📕 Chenna_1			ame *				Greenland				
	HTS - I	☐ ♥ Delhi_1		Ac	idress						Finland		
6	INSIGHTS	⊞ 🖩 Delh_1		Russia Cit	ty		State AK	*	1	iceland No	Sweden		R
ж	¥	□ ♥ Mumbai_1		200		Is it an outdoor location	1? OFF	1		United Kingdom	Poland ermany Ukraine		4
0		⊞ 🖩 Mumba_1		Mon	sociated With	Extreme Networks 1		, 		Gi France Spain		Kazakhstan	
6		□ Va2_location	12 + mx	A	sociated with	Extreme Networks_1			North Atlantic Ocean	Algeria	frag in	Afghanist Pakistan	
0		田 圓 va2_building	12 +	ndia			CAN	ICEL SAVE		Mali	Saudi Arabia Niger Sudan	The	
		+ Add		Indones	ia Papus New Guinea			Vecez Colombia	Brazi	Section.	gerra Ethiopia DRC Kenya Tanzenia		

4. Create a building by selecting selecting Add icon > Building. Fill in the mandatory fields (Name and Address, highlighted below) and select Save.

Ŷ D	XLOC-419]	× 🕱 [XLOC-419] ×	ExtremeClou ×	🛱 [DOP-2999]	🗙 🛛 🎽 Search - Ext	🗙 🛛 🜌 Notification 🗙 🗍	🕱 [DOP-3001] × 🗲	ExtremeClou 🗙 📔 🥌 C	iomplete - 🛛 🗙 📔 🗖	How to - Lo: × +	- 0	×
← ·	→ C	va2.extremecloudiq.com	m/#/plan/63351197	1228026/overviev	v					04	☆ O ★	: 3
III Ap	ops MG	mail 🛐 pgAdmin 4 🐠 C	ourse: CWS-100 e	E It takes 30 days	to f C http://52	.66.198.69: ExtremeLocat	ion 🔚 TestLink 🔳 X	CA 🚾 ADP 🕐 Pyth	non 🔚 g7envi	P Edube Interactive :	🚺 Udemy Courses	39
-	Extre	emeCloud IQ Pilo	t					م	() A	e xiqproduction xiqproduction	qapps+va2 QA qapps+va2@g	E
۵	AN	Search Maps	٩	IMPORT		LOCATION BUILDING	FLOOR				0	
\$ >	560 PL	Global View		Мар		\rightarrow		<u>^</u>			20	
*>	/ORK 3	Chennai_1			Add Building			- 11				
di >	NETW	⊞ 🛱 Chenna_1		+	Name *			Gr	cerviand			
٠	- SHTS	Delhi_1		The second	Address				Iceland	Finland		
۵	. INSIGHTS	田園 Delh_1		Russia	City		State AK +			Sweden	Ph	
ж	Я	☐ ♥ Mumbai_1		Caller of	Associated With	Extreme Networks_1	•		Unit Kangi	ed form Poland Germany Ukraine	Kazakhstan	Ľ
0		⊞ 🕅 Mumba_1		Mon					orth	France Italy Turkey		
6		■ Va2_location		1 march			CANCEL	SAVE Att		Algeria Libya Egypt Saudi Ara	Pakistan	
•		⊞ 📕 va2_building		India				Venezuela	-	Aall Niger Chad Sudan Nigerla Ethiopia	tinda	
		+ Add						Colombia		DRC Kenya		

5. Create a floor by selecting selecting Add icon > Floor. Specify a map size, for example 71 x 50 meters (highlighted below). Then scroll down to reveal the rest of the dialog.

X	XLOC-419]	× 🛱 [XLOC-419] ×	E ExtremeClou ×	🕻 [DOP-2999] 🗙 🛛 🗙 Sea	rch - Exti 🗙 🛛 📈 Notific	tation: 🗙 🛛 😤 [DOP-3001] :	K	x 🔷 Complete - 🛛 x	How to - Lor × +	- o ×
÷	→ C	va2.extremecloudiq.cor	m/#/plan/63351197122	28026/overview					o \$	o 🛪 😨 :
III A	pps M G	imail 🛐 pgAdmin 4 🔌 Ci	ourse: CWS-100 e 🔳	It takes 30 days to f	nttp://52.66.198.69: E	ExtremeLocation E TestLink	E XCA 🔤 AD	P 🕐 Python 토 g7envi	Edube Interactive : 4 Uder	my Courses »
-	Extre	emeCloud IQ Pilo	t	_				۹ 🛈 🌲	B e xiqproductionqapps- xiqproductionqapps-	+va2 QA +va2@g E
٠	PLAN	Search Maps	٩	ІМРС	LOCATION	BUILDING FLOOR				10
\$>	360 PI	Global View		Mai Add Floor				•		0
*>	ETWORK 3	E 🛛 Chennai_1			General		_			
di >	NETW	🕀 🖪 Chenna_1		+ Name*	Floor-2			Greenland		
	I-STH	Delhi_1		Associated Wi	th Select One		•	1 and	Finland	
â	INSIGHTS	🕀 📕 Delh_1		Ruse Environment	Auto Estimate		*	Iceland	Sweden	
ж	ML	G V Mumbai_1		Floor Attenua	ion 15	dB		K	Inited Ingdom Poland Germany Ukraine	
•		🕀 🗒 Mumba_1		AP Installation	3.6576	meters	*		Germany Okraine Kazak France Kazak Spain Italy Turkey	Ahstan
6		□ Va2_location	12 + m 13	Height				Atlantic Ocean	Iraq Iran	anist.
		🕀 📕 va2_building	10 + ··· Ind	Map Size *	71 X	50 meters	-		Mali Niger Sudan Chad	Ţ
		+ Add							Nigeria Ethiopia DRC Kenya	
					1		CANCEL SAV		Tanzania Angola Namibia	
				ian san Austra	-		Chile		Botswana	
0					New Se	ocean	A	rgentina	douts Africa	

6. Attach the floor plan, either by uploading a new floor plan or choosing a floor plan that is already in the library. When you have attached the floor plan, select **Save**.

III App	ps M G	āmail 🛂 pgAdmin 4 🐠 Ci	ourse: CW5-100 e 📘 1	takes 30 days to f 📴 htt	:p://52.66.198.69: Extrem	neLocation 💽 TestLink 💽 XCA 🤷 /	ADP 🛛 Python 🔚 g7envi 🕻	Edube Interactive : 🚺 Udemy Courses 🛛 »
-	Extre	emeCloud IQ Pilo	t				۹ 🛈 🏚	8 xiqproductionqapps+va2 QA xiqproductionqapps+va2@g
6	NA		Q	мрс	LOCATION BUILD	ING FLOOR		13
\$ >	360 PL	Global View	HAR	Associated With	Select One	-	•	10 ^{10,0} 10
*>	ORK 3	☐ ♥ Chennai_1		Environment	Auto Estimate	•		
ılı >	NETWO	🕀 🖁 Chenna_1	Z +	Floor Attenuatio	on 15	dB	Greenland	
	1	Delbi_1		AP Installation	3.6576	meters *	and the second	Finland
8	INSIGHTS			Russ			loeland	Sweden Ra
ж	ML	□ ♥ Mumbai_1		Map Size *	71 X 50	meters *	Units	Poland
0		⊞ Mumba_1		Background Im	age for floor plan		Spo	Germony Ukraine Kazakhstan France m Italy
0		□ ♥ va2_location	II +	Buckground in		Choose from Libra *	North Atlantic Dcean	Turkey Iraq Iran Afghanist Igeria Ukya Egypt Pakistan
•			[2] + ••• India			Choose from Library	1	all Niger Sudan
		+ Add				Upload New		Nigeria Ethiopia
						CANCEL	Bolma	Tanzania Angola

Setup Procedure 2: Create a Network Policy

Finish the setup by creating a Network Policy. Follow these steps:

ExtremeLocation Essentials Setup Guide

I. In Extreme cloud IQ, select Manage Devices > Create Network Policy.						
E EstemaClad Q x +					- 1	0
← → C 🔒 va.extremedoudiq.com/#/config					\$	Θ
🟥 Apps 🗞 Index of /Atalybuild 🧧 CLOUD-ExtremeClow 🧟 Sign in (Jenking) 😵 System Dashboard 🦉 G7-ExtremeClowal D2 🦉 G882-ExtremeClowal D2 🖉 G882-ExtremeClowal D2						
ExtremeCloud IQ Pilot	Q	0	≜ ∎	e qa qa QA-test		E
CONFIGURE Network Policies > New Poli						
Network Policies Policy Details Wireless Networks Device templates Router settings Additional settings Delicy Details						
Applications						
di > Common Objects New Policy						
Users What type of policy are you creating?						
C Whreess Switches Routing						
Please name your policy						
						1
Policy Name * Network Policy Name						
Description						
Enable Presence Analytics () OTT						

1. In ExtremeCloud IQ, select Manage Devices > Create Network Policy.

2. Update the corresponding device template as follows.

Note: This configuration is for tri-radio APs. Dual-radio APs automatically start sending as soon as presence is enabled.

- Enable wifiO and WifiI as Client access mode.
- Enable Wifi2.
- Save the device template.

	ExtremeCloud [®] IQ	Pilot
۵	IES	ExtremeCloud IQ ETH CONSOLE WIFIO WIFI
۵	POLICIES	
*>	NETWORK	
di >		Wireless Interfaces ▼ Control actions from the Access Point's WI-FI ports
	URE -	Control actions from the Access Point's wri-ri ports Note: Please ensure the radio profile setting conforms to the regulatory channel and transmit power.
ê	CONFIGURE	
ж	ŏ	WIFIO WIFII WIFI2
0		Radio Status ON
6		Operating Mode SENSOR
•		AirDefense Configuration
		Primary Server 10.1.1.1 Port 443
		Example: 10.1.1.0 Secondary Server Port
		Example: 10.1.0

3. In Additional Settings, enable iBeacon Services.

Network Policies > Policy-1 > iBeac	on Service			
Network Policies Policy-1 > iBeact Policy DETAILS WIRELE MANAGEMENT SERVER	SS NETWORKS DEVICE TEMPLAT	ES ROUTER SETTINGS	ADDITIONAL SETTINGS	DEPLOY POLICY
MANAGEMENT SERVER	iBeacon Service	s		
DNC Comment				
NTP Server				
NTP Server SNMP Server	Service Name *	Policy-1		
Syslog Server	Description	Policy-1		
POLICY SETTINGS				
ACSP Logging	IBeacon UUID			
Bonjour Gateway Settings		UUID format: 32 hexidecimal (base 16) o displayed in five groups separated by hy		
Device Credentials		form 8-4-4-4-12 for a total of 36 charact alphanumeric and four hyphens). For ex 123e4567-e89b-12d3-a456-4266554400	ample:	
Device Data Collection And				
Monitoring	Enable IBeacon Monitor	ring		
Device Time Zone				
HIVE				
iBeacon Service				
Management & Native VLAN				
Presence Analytics				
NETWORK SERVICES				

4. In Additional Settings, enable Presence Analytics.

POLICY DETAILS WIRE	ELESS NETWORKS DEVICE TEMPLATES	ROUTER SETTINGS	ADDITIONAL SETTINGS	DEPLOY POLIC
MANAGEMENT SERVER	Presence Analytics			
DNS Server	Enable Presence Analytics			
NTP Server	Name *	Policy-1		
SNMP Server Syslog Server	Description			
POLICY SETTINGS	Trap Interval	60		
ACSP Logging		15 - 600 seconds		
Bonjour Gateway Settings	Aging Time	60 15 - 600 seconds		
Device Credentials	Aggregate Time	60		
Device Data Collection And Monitoring		15 - 600 seconds		
Device Time Zone				
HIVE				
iBeacon Service				
Management & Native VLAN				

5. In ExtremeCloud IQ, select Manage Devices and onboard AP460C/AP410C.

Extremet	Cloud IQ	× +														-
· > C	a va.extremeci	loudiq.com/#/devices														☆
Apps 📀	Index of /images	Index of /dailybuild	E CLOUD-Extrem	neClo 🧕 Sig	n in [Jenkins] 💡	System Dashboard	💷 🖪 G7-ExtremeCloud IQ 🔳 G8R2-Extrem	eClou 🖪 G2R1-Extreme	Clou							
Ext	tremeCloud	Q Pilot										Q	0	A	e qa qa QA-test	
	Evaluate & Buy															
	New European Ge	neral Data Protection I	Regulations (GDPF	R) are here! Plea	se review our Clo	ud Terms of Serv	ice. Learn more about GDPR and related featu	ires in ExtremeCloud IQ he	re.							
Manag	ige															
	CONNECTIO		C.	TOTAL APPS	2		CLIENTS 1	USERS 0			ALARMS 0	3 0		2 Rogi	SECURITY Je APs O Rogue C	lients
T	3 Online / 0	Offline	C] TOTAL APPS	2		CLIENTS 1	USERS 0			ALARMS 0		1 3 0 Sele			
T	3 Online / 0	Offline	5	3 TOTAL APPS	2		CLIENTS 1	USERS 0	Addr or Seria	III Q	ALARMS 0 :				ect: All Pages, M	None
T	3 Online / 0	 Offline II 	 POLICY 	UPTIME	2 MGT IP ADDRESS	CLIENTS MAC				OS VERSION	utilities	Showing 3 of		ected Sel	ect: All Pages, M	None
T	3 Online / 0 Default View + 1	W B HOST NAME			MGT IP			Enter Hostname, MAC / SERIAL #	MODEL	OS VERSION	utilities	Showing 3 of ACTIONS WIFIO	UPDA	ected Sel	ect: All Pages, M EES III (AGENT NTP STATI	None
> •	3 Online / 0 Default View + 1 STATUS	HOST NAME	 POLICY 	UPTIME	MGT IP ADDRESS	1 BCF	LOCATION	Enter Hostname, MAC J SERIAL # lagar >> J 246020011700	MODEL 21 AP460C	os version	UTILITIES UPDATED 2020-10-01	Showing 3 of ACTIONS WIFIO CHANNEL	UPDA WIFII CHANN	ected Sel	ect: All Pages, P EES III (AGENT NTP STATI	None
T	3 Online / 0 Default Vien + 1 STATUS	W HOST NAME AH-2a9500 AH-2a990	POLICY 460C-NP	UPTIME Od 3h îm	MGT IP ADDRESS 160.36.30.48	1 BCF 0 BCF	Location 3102A950 QA-test >> Kamataka >> JayaN	Enter Hostname, MAC / SERIAL # lagar >> J 246020011700 mbal >> n 246020011700	MODEL 21 AP460C 4 AP460C	os version 10.2.2.0 (10. 10.2.2.0 (10.	UPDATED 2020-10-01 02:52:27 2020-10-01 03:44:55	Showing 3 of ACTIONS WIFIO CHANNEL 11	UPDA WIFI1 CHANN 161	ected Sel TE DEVIC EL IQ. N/	ect: All Pages, ? ect: All Pages, ? RES IIII ; AGENT NTP STATI 'A Enabled 'A Enabled	None

6. When the device is reported online, assign the location you created earlier . Then assign the newly-created network policy.

			remeciou	idiq.com/#/devices																	Q 1
Apps	Index	of /ima	ges 📀	Index of /dailybuild	E CLOUD-I	ktremeClo 1	Sign in [Jenkins]	Sy Sy	stem Dashboard	i 🔄 G7-ExtremeCloud IQ 🔳 G8R2-	ExtremeClou	G2R1-	ExtremeClou								
Ex	tremeCl	loud I	Q Pilot															Q	•	. 0 3	a qa QA-test
SE			CONNECT	O Offline		[] TOT	AL APPS 2			CLIENTS 1		USERS	0		ALARP	501310			3 Rog	SECURITY un APs 0 Rog	ue Citents
DEVIC	Ŧ	De	fault View														She	owing 3 of 3	0 Selected	Select: All Pa	ages, Non
÷		+	1 /												Server Q	UTILITIES	AC	TIONS	UPDATE DE	VICES	щG
			STATUS	HOST NAME	· POLICY	UPTIME	MGT IP ADDRESS	CLIENTS	MAC	LOCATION	SERIAL #	MODEL	OS VERSION	UPDATED	WIFID CHANNEL	WIFII CHANNEL	IGAGENT	NTP STATE	WIFID POWER	WIFII POWER	MGT VLAN
MANA						Od 3h 50m	100.16.10.48	1	BCF3102A9500	QA-test >> Kamataka >> JayaNagar >> Jaya	2460200170028	AMGOC	10.2.2.0 (10	2020-10-01 02:52:27	11	161	N/A	Enabled	20	20	1
MANA			- 5	AH-2a9500	460C-NP	od an som	HERE HERE THE THE														
MANA			• 5	AH-2a9500 AH-2a99c0	460C-NP	Od an som	192368 20.21		BCF3102A99C	QA-test >> Maharashtra >> mumbai >> mum	246020011/004/	AP460C	10.2.2.0 (10	2020-10-01 0.5:44:55	п	157	N/A	Enabled	20	20	1

Extre	emeCloud K													
	c (aca.extremeclou	diq.com/#/devic										ŕ	r 😸 Incognito
imail	F9 pgA	Admin 4 🏼 🐗 Course	e: CWS-100 e	It takes 30 days to	f 🕒 http://5	2.66.198.69:	ExtremeLoc	ation 🧧 TestLink	👅 XCA 💆	ADP 🕜 Python	g7envi 🛛 Edube Inte	eractive :	🚺 Udemy Cou	ses
	Extren	neCloud [®] IQ	Pilot								Q ()		e xiqprodu xiqprodu	ctioncan QA ctionqCanada
		ONNECTION STATU Online / 0 Offline	JS	C TOTAL APPS	0	CLIENT	s o		USERS 0		ALARMS 0 0 0			CURITY 0 Rogue Clients
	Ŧ	Default View									Showing 1 of 1	0 Select	ed Select: All	Pages, None
>		+ ± /	Î					Hostname, MAC Add	ir or Serial #	QUTILITIES	ACTIONS	UPDAT	E DEVICES	 G
		STATUS	HOST NAME	- POLICY	UPTIME	MGT IP ADDRESS	CLIENTS	MAC	OCATION S	ERIAL # MOD	EL NTP STATE	OS VERS	ION IQAGENT	UPDATED
		📄 📥 💼 ಖ	AH-7062c0	aca_policy	0d 2h 28m	30.1.1.148	0	BCF3107062C	Extreme Ne C	0410200608274 AP4	IOC Enabled	10.2.3.0		2020-12-07 17:10:14
		4												۲

If necessary, upgrade the device's HOS version to 10.2r3 or later: Select **Update Device**, and then select **Upgrade IQ Engine and Extreme Network Switch images > Select Upgrade to the latest version**

Extren	neCloud	IQ Pilot		۹ 🛈 🌲	e xiqproduc xiqproduc	tioncan QA tionqCanada
CES		ECTION STATUS	Device Update	×		URITY 0 Rogue Clients
DEVICES	T D	efault View	1 device will be updated Device List may need to be reloaded/refreshed to see some changes due to the update.	_ f1 1 Sel	lected Select: All I	ages, None
AGE -	+	· · / ·	Update Network Policy and Configuration	UPD	ATE DEVICES	 C
MAN	C	STATUS H	Upgrade IQ Engine and Extreme Network Switch Images	P STATE	OS VERSION IQ.	GENT UPDA
	4	3 - 8 2° A	Upgrade to the latest version (10.2r3) Upgrade to the specific version	abled	10.2.3.0 (10 N/	4 202C 17:10:
			Upgrade even if the versions are the same			
			Enable Distributed Image Upgrade Only applicable to APs			
			Activation Time for Extreme Networks Devices Running Images			
			Activate at next reboot (requires rebooting manually) SAVE AS DEFAULTS CLOSE PERFORM U	IPDATE		

8. Perform a complete CONFIG PUSH on the onboarded AP460C/AP410C after the very first onboarding and assignment of network policy.

ExtremeC	loud	IQ Pilot	IN STATUS		D 10	TAL APPS 2	Device Update	×	ALARP	501010		Q	G 🖡	SECURIT	qa qa Q:A-test Y gue Clients
ae - DEVIC		Default View	سرر				1 device will be updated	Less	be Summer, Q.	uternes		Showing 3 ct 1	(1 Selected) UPDATE DE		ages, Nore
TANA		STATUS	HOST NAME	· POLICY	UPTIME	HOT IP ADORE	Update Network Policy and Configuration		WIFTO CHANNEL	WIFTS	IDAGENT	NTPSTATE	WIFID	WIFE	MGT
			AH-249500	460C Not	Oct (Ris Solim	80.1630.48	O Detta Configuration Update	225220	н	364	14/A	+ motived :	20	20.	
			AH-2a99c0	4600-641	Od 2h 58m	192,68,20,28	O Complete Configuration Update	12.44%	5 H		N/A	Enabled	20	20	
		- 5	AH-Sec680	HOC	0:t2h.36m	992368-2015	Updaté device arm all consignations, build to send directa to Extensico.con la contiguration Updaté device mantelig IOS er GE Firmware) Upgrade IG Engine and Externe Network Sentch mages		0	149	N/A	Enabled	20	15	
							Activation Time for Estreme Networks Devices Running Images Activate at next reboot (requires rebooting manually)	_							

9. Launch the ExtremeLocation Essentials app by selecting the Location icon in the left panel and then <u>se</u>lecting **Subscribe**.

Extre	emeCloud IQ Pilot	4.0
os ¢> ★> du>	ExtremeLocation Essentials	Want to know more about ExtremeLocation Essentials?
■ ズ ② ◎		Subscription
	Cloud-managed Location services & Analytics Indoor location service for Wi-Fi and BLE devices Presence, Zone tracking, Asset tracking	Subscribe to explore Location Services Included with Pilot subscription - no additional cost SUBSCRIBE
	Extreme.Location Essentials brings out the true value of location-based services by delivering powerful analytics and trends to provide business insights Subscribe for free with your ExtremeCloud IQ Pilot license	 ExtremeLocation Essentials Supported Devices AP410C, AP460C

The ExtremeLocation Essentials Summary page loads and begins displaying analytics.



10. To view additional details, select More Insights. ExtremeCloud IQ Pilot Q () A O xiqextremeqapps+Shrisha-g_ | E -• Extreme Location Essentials lew As on 25 Nov 2020 02:10:50 PM 0 hts by Locatio Most Visited Site Loc_3_Building 12-9-6-3-۰ Visit D TOTAL : 5 Visit Typ Inside Visitor

Use the additional options for configuration, dashboards and monitoring.



End of document