

# ExtremeSwitching CES and ExtremeRouting CER 2000 Series Technical Specifications

Copyright © 2018 Extreme Networks, Inc. All Rights Reserved.

## Legal Notice

Extreme Networks, Inc. reserves the right to make changes in specifications and other information contained in this document and its website without prior notice. The reader should in all cases consult representatives of Extreme Networks to determine whether any such changes have been made.

The hardware, firmware, software or any specifications described or referred to in this document are subject to change without notice.

## Trademarks

Extreme Networks and the Extreme Networks logo are trademarks or registered trademarks of Extreme Networks, Inc. in the United States and/or other countries.

All other names (including any product names) mentioned in this document are the property of their respective owners and may be trademarks or registered trademarks of their respective companies/owners.

For additional information on Extreme Networks trademarks, please see: [www.extremenetworks.com/company/legal/trademarks](http://www.extremenetworks.com/company/legal/trademarks)

## Software Licensing

Some software files have been licensed under certain open source or third-party licenses. End-user license agreements and open source declarations can be found at: [www.extremenetworks.com/support/policies/software-licensing](http://www.extremenetworks.com/support/policies/software-licensing)

## Support

For product support, phone the Global Technical Assistance Center (GTAC) at 1-800-998-2408 (toll-free in U.S. and Canada) or +1-408-579-2826. For the support phone number in other countries, visit: <http://www.extremenetworks.com/support/contact/>

For product documentation online, visit: <https://www.extremenetworks.com/documentation/>

# Contents

---

<b>ExtremeSwitching CES and ExtremeRouting CER 2000 Series Technical Specifications.....</b>	<b>5</b>
System specifications.....	5
Ethernet.....	5
LEDs.....	5
Other.....	6
Weight and physical dimensions.....	6
Environmental requirements.....	7
Power supply specifications (per PSU).....	7
Power consumption (idle configuration).....	7
Power consumption (typical configuration).....	8
Power consumption (maximum configuration).....	9
Data port specifications (Ethernet).....	10
Serial port specifications (DB9).....	10
Serial port specifications (pinout RJ-45).....	11
Serial port specifications (protocol).....	11
Memory specifications.....	11
Regulatory compliance (EMC).....	11
Regulatory compliance (safety).....	12
Regulatory compliance (environmental).....	12



# ExtremeSwitching CES and ExtremeRouting CER 2000 Series Technical Specifications

This document highlights the features and specifications for CES/CER 2000 Series devices.

## NOTE

Beginning with NetIron OS 6.3.00a and later, the ExtremeSwitching CES 2000 Series devices are not supported. Refer to the [End of Sale and End of Support](#) page for additional information.

## System specifications

System component	Description
Enclosure	1U
Power inlet	C14
Power supplies	One internal AC or DC power supply, 1+1 redundancy
Fans	6
Cooling	Six 4-speed fans; front-to-back airflow

## Ethernet

System component	Description
SFP GbE ports	24 SFP, 4 Combo, 2 XFP 24 SFP, 4 Combo, 4 SFP+ 48 SFP, 2 XFP
Ethernet management port	10/100/1000 MbE RJ-45

## LEDs

System component	Description
<b>10/100/1000 Port LEDs</b>	
Lnk/Act	Indicates whether a link is up or down and the port is transmitting and receiving traffic
<b>10-Gbps Port LEDs on devices with two or four 10-Gbps ports</b>	
Lnk/Act (2 LEDs)	Indicates whether the fiber port is connected and the traffic is being transmitted and received on the fiber port
<b>Power and fan status LEDs</b>	
Fan	Indicates the status of the fan tray
AC PS1	Indicates whether power supply 1 is installed and operating normally

System component	Description
AC PS2	Indicates whether power supply 2 is installed and operating normally
DC	Indicates whether the power supply has DC power

## Other

System component	Description
Serial cable	EIA or TIA DB9 serial cable
RJ-45 connector	10/100/1000 copper

## Weight and physical dimensions

Model	Height	Width	Depth	Weight
CES 2000 Series 2024C-4X	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.4 kg 20.7 lb
CES 2000 Series 2024C-4X with 4x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.5 kg 21 lb
CES 2000 Series 2024C	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7 kg 15.5 lb
CES 2000 Series 2024C with 2x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7.9 kg 17.5 lb
CES 2000 Series 2024F-4X	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.5 kg 21 lb
CES 2000 Series 2024F-4X with 4x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.7 kg 21.4 lb
CES 2000 Series 2024F	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7 kg 15.5 lb
CES 2000 Series 2024F with 2x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7.9 kg 17.5 lb
CER 2000 Series 2024C-4X-RT	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	9.5 kg 21 lb
CER 2000 Series 2024C-4X-RT with 4x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.5 kg 21 lb
CER 2000 Series 2024C	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	7 kg 15.5 lb
CER 2000 Series 2024C with 2x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7.9 kg 17.5 lb
CER 2000 Series 2024F-4X-RT	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.4 kg 20.8 lb

Model	Height	Width	Depth	Weight
CER 2000 Series 2024F-4X-RT with 4x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	43.9 cm 17.3 inches	9.9 kg 21.8 lb
CER 2000 Series 2024F	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7 kg 15.5 lb
CER 2000 Series 2024F with 2x10G uplink installed	4.4 cm 1.7 inches	44.3 cm 17.4 inches	44.8 cm 17.6 inches	7.9 kg 17.5 lb

## Environmental requirements

Condition	Operational	Non-operational
Ambient temperature	0°C to 40°C (32°F to 104°F)	-25°C to 70°C (-13°F to 158°F)
Relative humidity (non-condensing)	5% to 95% at 40°C (104°F)	95% maximum
Altitude (above sea level)	3000 m (10,000 feet)	4500 m (15,000 feet)
Shock	N/A	N/A
Vibration	N/A	N/A
Airflow	267 lfm	N/A
Operating noise	< 60 dB	N/A

## Power supply specifications (per PSU)

Power supply model	Maximum output power rating (DC)	Input voltage	Input line frequency	Maximum input current	Input line protection	Maximum inrush current
RPS9	504 W	100 - 240 VAC (nominal) 85 - 264 VAC (range)	50/60 Hz (nominal) 47 - 63 Hz (range)	6 A	Line Fused	30 A peak @ 25°C
RPS9DC	504 W	48 VDC (nominal) 40 - 60 VDC (range)	N/A	15 A	-Ve Fused	25 A peak @ 25°C

## Power consumption (idle configuration)

Idle: No optics or connections to ports installed and system booted up. Fans at nominal speed.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
BR-CES-2024C-4X with 4x10G Uplink AC & DC	1.64 A 184 W 628.79 BTU/hr	0.86 A 182 W 619.30 BTU/hr	2.96 A 158 W 540.63 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
BR-CES-2024C-4X AC & DC	1.64 A 184 W 628.79 BTU/hr	0.86 A 182 W 619.30 BTU/hr	2.96 A 158 W 540.63 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024F-4X with 4x10G Uplink AC & DC	1.87 A 205 W 699.51 BTU/hr	0.98 A 189 W 643.19 BTU/hr	2.98 A 162 W 553.74 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024F-4X AC & DC	1.87 A 205 W 699.51 BTU/hr	0.98 A 189 W 643.19 BTU/hr	2.98 A 162 W 553.74 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024C-4X-RT with 4x10G uplink AC & DC	1.88 A 205 W 699.48 BTU/hr	0.96 A 201 W 684.53 BTU/hr	3.20 A 171 W 583.23 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024C-4X-RT AC & DC	1.88 A 205 W 699.48 BTU/hr	0.96 A 201 W 684.53 BTU/hr	3.20 A 171 W 583.23 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024F-4X-RT with 4x10G uplink AC & DC	1.82 A 197 W 672.79 BTU/hr	0.94 A 195 W 666.34 BTU/hr	3.34 A 184 W 629.10 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024F-4X-RT AC & DC	1.82 A 197 W 672.79 BTU/hr	0.94 A 195 W 666.34 BTU/hr	3.34 A 184 W 629.10 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.

## Power consumption (typical configuration)

Typical: Fully configure all ports and 25% traffic on all ports. Random packet size, random payload, and room temperature. Fans at nominal speed.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
BR-CES-2024C-4X with 4x10G Uplink AC & DC	2.19 A 241 W 823.44 BTU/hr	1.11 A 237 W 808.73 BTU/hr	3.82 A 200 W 681.87 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024C-4X AC & DC	1.80 A 203 W 692.04 BTU/hr	0.93 A 199 W 677.33 BTU/hr	3.02 A 161 W 550.46 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024F-4X with 4x10G Uplink AC & DC	2.39 A 255 W 871.53 BTU/hr	1.23 A 251 W 857.95 BTU/hr	3.80 A 209 W 711.35 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024F-4X AC & DC	2.00 A	1.04 A	3.00 A	1	Input current only 1 PSU installed. Watts

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
	217 W 740.13 BTU/hr	213 W 726.54 BTU/hr	167 W 579.95 BTU/hr		and BTU/hr with 2 PSUs.
BR-CER-2024C-4X-RT with 4x10G Uplink AC & DC	2.34 A 246 W 840.14 BTU/hr	1.20 A 243 W 829.58 BTU/hr	3.96 A 210 W 714.63 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024C-4X-RT AC & DC	1.94 A 208 W 708.69 BTU/hr	1.01 A 205 W 698.18 BTU/hr	3.16 A 171 W 583.23 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024F-4X-RT with 4x10G uplink AC & DC	2.83 A 297 W 1014.30 BTU/hr	1.44 A 293 W 997.81 BTU/hr	4.16 A 217 W 740.84 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024F-4X-RT AC & DC	2.42 A 259 W 882.90 BTU/hr	1.25 A 254 W 866.41 BTU/hr	3.36 A 179 W 609.44 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.

## Power consumption (maximum configuration)

Maximum: Fully configure all ports with connection and traffic at maximum throughput. Fans at high speed.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
BR-CES-2024C-4X with 4x10G Uplink AC & DC	2.41 A 256 W 874.91 BTU/hr	1.24 A 253 W 862.96 BTU/hr	4.14 A 217 W 739.96 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024C-4X AC & DC	1.95 A 212 W 724.73 BTU/hr	1.01 A 209 W 712.79 BTU/hr	3.22 A 173 W 589.78 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024F-4X with 4x10G Uplink AC & DC	2.54 A 268 W 914.91 BTU/hr	1.32 A 264 W 900.47 BTU/hr	4.06 A 222 W 756.34 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CES-2024F-4X AC & DC	2.09 A 224 W 764.78 BTU/hr	1.08 A 220 W 750.30 BTU/hr	3.14 A 178 W 606.16 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024C-4X-RT with 4x10G Uplink AC & DC	2.51 A 266 W 906.68 BTU/hr	1.31 A 261 W 890.37 BTU/hr	4.22 A 225 W 766.95 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024C-4X-RT AC & DC	2.06 A 222 W 756.51 BTU/hr	1.07 A 217 W 740.20 BTU/hr	3.92 A 183 W 622.55 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
BR-CER-2024F-4X-RT with 4x10G uplink AC & DC	3.03 A 315 W 1075.87 BTU/hr	1.53 A 298 W 1017.54 BTU/hr	4.56 A 239 W 815.32 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.
BR-CER-2024F-4X-RT AC & DC	2.54 A 271 W 672.79 BTU/hr	0.94 A 254 W 666.34 BTU/hr	3.64 A 195 W 665.14 BTU/hr	1	Input current only 1 PSU installed. Watts and BTU/hr with 2 PSUs.

## Data port specifications (Ethernet)

Model	Port type	Number of ports	Description
CES 2000 Series 2024C-4X	10 GbE	4	Supports four 10-GbE SFP+ uplink ports
CES 2000 Series 2024C	10 GbE	2	Supports an optional field-ungradable two 10-GbE uplink ports
CES 2000 Series 2024F-4X	10 GbE	4	Supports four 10-GbE SFP+ uplink ports
CES 2000 Series 2024F	10 GbE	2	Supports an optional field-ungradable two 10-GbE uplink ports
CER 2000 Series 2024C-4X-RT	10 GbE	4	Supports four 10-GbE SFP+ uplink ports
CER 2000 Series 2024C	10 GbE	2	Supports an optional field-upgradable two 10-GbE uplink ports
CER 2000 Series 2024F-4X-RT	10 GbE	4	Supports four 10-GbE SFP+ uplink ports
CER 2000 Series 2024F	10 GbE	2	Supports an optional field-upgradable two 10-GbE uplink ports

## Serial port specifications (DB9)

Pin	Signal	Description
1	Reserved	Reserved
2	TXD (output)	Transmit data
3	RXD (input)	Receive data
4	Reserved	Reserved
5	GND	Logic ground
6	Reserved	Reserved
7	Reserved	Reserved
8	Reserved	Reserved
9	Reserved	Reserved

## Serial port specifications (pinout RJ-45)

Pin	Signal	Description
1	TD+	Transmit data
2	TD-	Transmit data
3	RD+	Receive data
4	Not used (10BaseT) CMT (100BaseTX)	Not used
5	Not used (10BaseT) CMT (100BaseTX)	Not used
6	RD-	Receive data
7	Not used (10BaseT) CMT (100BaseTX)	Not used
8	Not used (10BaseT) CMT (100BaseTX)	Not used

## Serial port specifications (protocol)

Parameter	Value
Baud	9600
Data bits	8
Parity	None
Stop bits	1
Flow control	None

## Memory specifications

Memory	Type	Size
Main memory	DRAM	1 GB
Compact Flash	Internal compact flash	64 MB

## Regulatory compliance (EMC)

- FCC Part 15, Subpart B (Class A)
- EN 55022 (CE mark) (Class A)
- EN 55024 (CE mark) (Immunity) for Information Technology Equipment
- ICES-003 (Canada) (Class A)
- AS/NZ 55022 (Australia) (Class A)
- VCCI (Japan) (Class A)

- EN 61000-3-2
- EN 61000-3-3
- EN 61000-6-1

## Regulatory compliance (safety)

- CAN/CSA-C22.2 No. 60950-1-07/UL60950-1 - Safety of Information Technology Equipment
- EN 60825-1 Safety of Laser Products - Part 1: Equipment Classification, Requirements and User's Guide
- EN 60825-2 Safety of Laser Products - Part 2: Safety of Optical Fibre Communications Systems
- EN 60950-1, IEC 60950-1 Safety of Information Technology Equipment

## Regulatory compliance (environmental)

- 2011/65/EU – Restriction of the use of certain hazardous substance in electrical and electronic equipment (EU RoHS)
- 2012/19/EU – Waste electrical and electronic equipment (EU WEEE)
- 94/62/EC – packaging and packaging waste (EU)
- 2006/66/EC – batteries and accumulators and waste batteries and accumulators (EU battery directive)
- 1907/2006 of the European Parliament and of the Council of 18 December 2006 concerning the Registration, Evaluation, Authorisation and Restriction of Chemicals (EU REACH)
- Section 1502 of the Dodd-Frank Wall Street Reform and Consumer Protection Act of 2010 – U.S. Conflict Minerals
- 30/2011/TT-BCT – Vietnam circular
- SJ/T 11363-2006 Requirements for Concentration Limits for Certain Hazardous Substances in EIPs (China)
- SJ/T 11364-2006 Marking for the Control of Pollution Caused by EIPs (China)