



ExtremeCloud™ IQ Site Engine v25.08.12 Release Notes:

Features, Enhancements, and Issues

10/2025
25.08.12
PN: 9039402-02 Rev AA
Subject to Change Without Notice



Abstract

The release notes for ExtremeCloud IQ Site Engine version 25.08.12 provide a comprehensive overview of features, enhancements, and resolved issues pertinent to the deployment and management of the software platform. The document details critical upgrade paths and considerations, including a mandatory data migration procedure for versions earlier than 24.7 and requirements for internet connectivity during OS upgrades. It highlights the system requirements for server and client hardware, emphasizing optimal CPU and memory configurations to support various deployment scales, including ExtremeControl and ExtremeAnalytics features. Addressed vulnerabilities cover a wide range of CVEs, ensuring the system's robustness against potential exploits. Users are advised on specific configuration settings for various devices, including Fabric Engine and ERS devices, to maintain compatibility and performance standards.

Legal Notices

Extreme Networks, Inc., on behalf of or through its wholly-owned subsidiary, Enterasys Networks, Inc., reserves the right to make changes in specifications and other information contained in this document and its website without prior notice. The reader should in all cases consult representatives of Extreme Networks to determine whether any such changes have been made.

The hardware, firmware, software or any specifications described or referred to in this document are subject to change without notice.

Trademarks

Extreme Networks and the Extreme Networks logo are trademarks or registered trademarks of Extreme Networks, Inc. in the United States and/or other countries.

All other names (including any product names) mentioned in this document are the property of their respective owners and may be trademarks or registered trademarks of their respective companies/owners.

For additional information on Extreme Networks trademarks, please see:

www.extremenetworks.com/company/legal/trademarks/

Contact

If you require assistance, contact Extreme Networks using one of the following methods.

- [Global Technical Assistance Center \(GTAC\) for Immediate Support](#)
 - **Phone:** 1-800-998-2408 (toll-free in U.S. and Canada) or 1-603-952-5000. For the Extreme Networks support phone number in your country, visit: www.extremenetworks.com/support/contact
 - **Email:** support@extremenetworks.com. To expedite your message, enter the product name or model number in the subject line.
- [GTAC Knowledge](#) — Get on-demand and tested resolutions from the GTAC Knowledgebase, or create a help case if you need more guidance.
- [The Hub](#) — A forum for Extreme customers to connect with one another, get questions answered, share ideas and feedback, and get problems solved. This community is monitored by Extreme Networks employees, but is not intended to replace specific guidance from GTAC.
- [Support Portal](#) — Manage cases, downloads, service contracts, product licensing, and training and certifications.



Extreme Networks® Software License Agreement

This Extreme Networks Software License Agreement is an agreement ("Agreement") between You, the end user, and Extreme Networks, Inc. ("Extreme"), on behalf of itself and its Affiliates (as hereinafter defined and including its wholly owned subsidiary, Enterasys Networks, Inc. as well as its other subsidiaries). This Agreement sets forth Your rights and obligations with respect to the Licensed Software and Licensed Materials. BY INSTALLING THE LICENSE KEY FOR THE SOFTWARE ("License Key"), COPYING, OR OTHERWISE USING THE LICENSED SOFTWARE, YOU ARE AGREEING TO BE BOUND BY THE TERMS OF THIS AGREEMENT, WHICH INCLUDES THE LICENSE AND THE LIMITATION OF WARRANTY AND DISCLAIMER OF LIABILITY. IF YOU DO NOT AGREE TO THE TERMS OF THIS AGREEMENT, RETURN THE LICENSE KEY TO EXTREME OR YOUR DEALER, IF ANY, OR DO NOT USE THE LICENSED SOFTWARE AND CONTACT EXTREME OR YOUR DEALER WITHIN TEN (10) DAYS FOLLOWING THE DATE OF RECEIPT FOR A REFUND. IF YOU HAVE ANY QUESTIONS ABOUT THIS AGREEMENT, CONTACT EXTREME, Attn: LegalTeam@extremenetworks.com.

1. **DEFINITIONS.** "Affiliates" means any person, partnership, corporation, limited liability company, or other form of enterprise that directly or indirectly through one or more intermediaries, controls, or is controlled by, or is under common control with the party specified. "Server Application" shall refer to the License Key for software installed on one or more of Your servers. "Client Application" shall refer to the application to access the Server Application. "Licensed Materials" shall collectively refer to the licensed software (including the Server Application and Client Application), Firmware, media embodying the software, and the documentation. "Concurrent User" shall refer to any of Your individual employees who You provide access to the Server Application at any one time. "Firmware" refers to any software program or code imbedded in chips or other media. "Licensed Software" refers to the Software and Firmware collectively.
2. **TERM.** This Agreement is effective from the date on which You install the License Key, use the Licensed Software, or a Concurrent User accesses the Server Application. You may terminate the Agreement at any time by destroying the Licensed Materials, together with all copies, modifications and merged portions in any form. The Agreement and Your license to use the Licensed Materials will also terminate if You fail to comply with any term of condition herein.
3. **GRANT OF SOFTWARE LICENSE.** Extreme will grant You a non-transferable, non-exclusive license to use the machine-readable form of the Licensed Software and the accompanying documentation if You agree to the terms and conditions of this Agreement. You may install and use the Licensed Software as permitted by the license type purchased as described below in License Types. The license type purchased is specified on the invoice issued to You by Extreme or Your dealer, if any. YOU MAY NOT USE, COPY, OR MODIFY THE LICENSED MATERIALS, IN WHOLE OR IN PART, EXCEPT AS EXPRESSLY PROVIDED IN THIS AGREEMENT.

4. LICENSE TYPES.

- *Single User, Single Computer.* Under the terms of the Single User, Single Computer license, the license granted to You by Extreme when You install the License Key authorizes You to use the Licensed Software on any one, single computer only, or any replacement for that computer, for internal use only. A separate license, under a separate Software License Agreement, is required for any other computer on which You or another individual or employee intend to use the Licensed Software. A separate license under a separate Software License Agreement is also required if You wish to use a Client license (as described below).
- *Client.* Under the terms of the Client license, the license granted to You by Extreme will authorize You to install the License Key for the Licensed Software on your server and allow the specific number of Concurrent Users shown on the relevant invoice issued to You for each Concurrent User that You order from Extreme or Your dealer, if any, to access the Server Application. A separate license is required for each additional Concurrent User.

5. AUDIT RIGHTS. You agree that Extreme may audit Your use of the Licensed Materials for compliance with these terms and Your License Type at any time, upon reasonable notice. In the event that such audit reveals any use of the Licensed Materials by You other than in full compliance with the license granted and the terms of this Agreement, You shall reimburse Extreme for all reasonable expenses related to such audit in addition to any other liabilities You may incur as a result of such non-compliance, including but not limited to additional fees for Concurrent Users over and above those specifically granted to You. From time to time, the Licensed Software will upload information about the Licensed Software and the associated devices to Extreme. This is to verify the Licensed Software is being used with a valid license. By using the Licensed Software, you consent to the transmission of this information. Under no circumstances, however, would Extreme employ any such measure to interfere with your normal and permitted operation of the Products, even in the event of a contractual dispute.

6. RESTRICTION AGAINST COPYING OR MODIFYING LICENSED MATERIALS. Except as expressly permitted in this Agreement, You may not copy or otherwise reproduce the Licensed Materials. In no event does the limited copying or reproduction permitted under this Agreement include the right to decompile, disassemble, electronically transfer, or reverse engineer the Licensed Software, or to translate the Licensed Software into another computer language.

The media embodying the Licensed Software may be copied by You, in whole or in part, into printed or machine readable form, in sufficient numbers only for backup or archival purposes, or to replace a worn or defective copy. However, You agree not to have more than two (2) copies of the Licensed Software in whole or in part, including the original media, in your possession for said purposes without Extreme's prior written consent, and in no event shall You operate more copies of the Licensed Software than the specific licenses granted to You. You may not copy or reproduce the documentation. You agree to maintain appropriate records of the location of the original media and all copies of the Licensed Software, in whole or in part, made by You. You may modify the machine-readable form of the Licensed Software for (1) your own internal use or (2) to merge the Licensed Software into other program material to form a modular work for your own use, provided that such work remains modular, but on termination of this Agreement, You are required to completely remove the Licensed Software from any such modular work. Any portion of the Licensed Software included in any such modular work shall be used only on a single computer for internal purposes and shall remain subject to all the terms and conditions of this Agreement. You agree to include any copyright or other proprietary notice set forth on the label of the media embodying the Licensed Software on any copy of the Licensed Software in any form, in whole or in part, or on any modification of the Licensed Software or any such modular work containing the Licensed Software or any part thereof.

7. TITLE AND PROPRIETARY RIGHTS

- a. The Licensed Materials are copyrighted works and are the sole and exclusive property of Extreme, any company or a division thereof which Extreme controls or is controlled by, or which may result from the merger or consolidation with Extreme (its "Affiliates"), and/or their suppliers. This Agreement conveys a limited right to operate the Licensed Materials and shall not be construed to convey title to the Licensed Materials to You. There are no implied rights. You shall not sell, lease, transfer, sublicense, dispose of, or otherwise make available the Licensed Materials or any portion thereof, to any other party.
- b. You further acknowledge that in the event of a breach of this Agreement, Extreme shall suffer severe and irreparable damages for which monetary compensation alone will be inadequate. You therefore agree that in the event of a breach of this Agreement, Extreme shall be entitled to monetary damages and its reasonable attorney's fees and costs in enforcing this Agreement, as well as injunctive relief to restrain such breach, in addition to any other remedies available to Extreme.

8. PROTECTION AND SECURITY. In the performance of this Agreement or in contemplation thereof, You and your employees and agents may have access to private or confidential information owned or controlled by Extreme relating to the Licensed Materials supplied hereunder including, but not limited to, product specifications and schematics, and such information may contain proprietary details and disclosures. All information and data so acquired by You or your employees or agents under this Agreement or in contemplation hereof shall be and shall remain Extreme's exclusive property, and You shall use your best efforts (which in any event shall not be less than the efforts You take to ensure the confidentiality of your own proprietary and other confidential information) to keep, and have your employees and agents keep, any and all such information and data confidential, and shall not copy, publish, or disclose it to others, without Extreme's prior written approval, and shall return such information and data to Extreme at its request. Nothing herein shall limit your use or dissemination of information not actually derived from Extreme or of information which has been or subsequently is made public by Extreme, or a third party having authority to do so.

You agree not to deliver or otherwise make available the Licensed Materials or any part thereof, including without limitation the object or source code (if provided) of the Licensed Software, to any party other than Extreme or its employees, except for purposes specifically related to your use of the Licensed Software on a single computer as expressly provided in this Agreement, without the prior written consent of Extreme. You agree to use your best efforts and take all reasonable steps to safeguard the Licensed Materials to ensure that no unauthorized personnel shall have access thereto and that no unauthorized copy, publication, disclosure, or distribution, in whole or in part, in any form shall be made, and You agree to notify Extreme of any unauthorized use thereof. You acknowledge that the Licensed Materials contain valuable confidential information and trade secrets, and that unauthorized use, copying and/or disclosure thereof are harmful to Extreme or its Affiliates and/or its/their software suppliers.

9. MAINTENANCE AND UPDATES. Updates and certain maintenance and support services, if any, shall be provided to You pursuant to the terms of an Extreme Service and Maintenance Agreement, if Extreme and You enter into such an agreement. Except as specifically set forth in such agreement, Extreme shall not be under any obligation to provide Software Updates, modifications, or enhancements, or Software maintenance and support services to You.
10. DEFAULT AND TERMINATION. In the event that You shall fail to keep, observe, or perform any obligation under this Agreement, including a failure to pay any sums due to Extreme, or in the event that you become insolvent or seek protection, voluntarily or involuntarily, under any bankruptcy law, Extreme may, in addition to any other remedies it may have under law, terminate the License and any other agreements between Extreme and You.

- a. Immediately after any termination of the Agreement or if You have for any reason discontinued use of Software, You shall return to Extreme the original and any copies of the Licensed Materials and remove the Licensed Software from any modular works made pursuant to Section 3, and certify in writing that through your best efforts and to the best of your knowledge the original and all copies of the terminated or discontinued Licensed Materials have been returned to Extreme.
 - b. Sections 1, 7, 8, 10, 11, 12, 13, 14 and 15 shall survive termination of this Agreement for any reason.
11. EXPORT REQUIREMENTS. You are advised that the Software is of United States origin and subject to United States Export Administration Regulations; diversion contrary to United States law and regulation is prohibited. You agree not to directly or indirectly export, import or transmit the Software to any country, end user or for any Use that is prohibited by applicable United States regulation or statute (including but not limited to those countries embargoed from time to time by the United States government); or contrary to the laws or regulations of any other governmental entity that has jurisdiction over such export, import, transmission or Use.
12. UNITED STATES GOVERNMENT RESTRICTED RIGHTS. The Licensed Materials (i) were developed solely at private expense; (ii) contain "restricted computer software" submitted with restricted rights in accordance with section 52.227-19 (a) through (d) of the Commercial Computer Software-Restricted Rights Clause and its successors, and (iii) in all respects is proprietary data belonging to Extreme and/or its suppliers. For Department of Defense units, the Licensed Materials are considered commercial computer software in accordance with DFARS section 227.7202-3 and its successors, and use, duplication, or disclosure by the U.S. Government is subject to restrictions set forth herein.
13. LIMITED WARRANTY AND LIMITATION OF LIABILITY. The only warranty that Extreme makes to You in connection with this license of the Licensed Materials is that if the media on which the Licensed Software is recorded is defective, it will be replaced without charge, if Extreme in good faith determines that the media and proof of payment of the license fee are returned to Extreme or the dealer from whom it was obtained within ninety (90) days of the date of payment of the license fee.
 NEITHER EXTREME NOR ITS AFFILIATES MAKE ANY OTHER WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, WITH RESPECT TO THE LICENSED MATERIALS, WHICH ARE LICENSED "AS IS". THE LIMITED WARRANTY AND REMEDY PROVIDED ABOVE ARE EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES, INCLUDING IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE EXPRESSLY DISCLAIMED, AND STATEMENTS OR REPRESENTATIONS MADE BY ANY OTHER PERSON OR FIRM ARE VOID. ONLY TO THE EXTENT SUCH EXCLUSION OF ANY IMPLIED WARRANTY IS NOT PERMITTED BY LAW, THE DURATION OF SUCH IMPLIED WARRANTY IS LIMITED TO THE DURATION OF THE LIMITED WARRANTY SET FORTH ABOVE. YOU ASSUME ALL RISK AS TO THE QUALITY, FUNCTION AND PERFORMANCE OF THE LICENSED MATERIALS. IN NO EVENT WILL EXTREME OR ANY OTHER PARTY WHO HAS BEEN INVOLVED IN THE CREATION, PRODUCTION OR DELIVERY OF THE LICENSED MATERIALS BE LIABLE FOR SPECIAL, DIRECT, INDIRECT, RELIANCE, INCIDENTAL OR CONSEQUENTIAL DAMAGES, INCLUDING LOSS OF DATA OR PROFITS OR FOR INABILITY TO USE THE LICENSED MATERIALS, TO ANY PARTY EVEN IF EXTREME OR SUCH OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN NO EVENT SHALL EXTREME OR SUCH OTHER PARTY'S LIABILITY FOR ANY DAMAGES OR LOSS TO YOU OR ANY OTHER PARTY EXCEED THE LICENSE FEE YOU PAID FOR THE LICENSED MATERIALS. Some states do not allow limitations on how long an implied warranty lasts and some states do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation and exclusion may not apply to You. This limited warranty gives You specific legal rights, and You may also have other rights which vary from state to state.

14. JURISDICTION. The rights and obligations of the parties to this Agreement shall be governed and construed in accordance with the laws and in the State and Federal courts of the State of California, without regard to its rules with respect to choice of law. You waive any objections to the personal jurisdiction and venue of such courts. None of the 1980 United Nations Convention on the Limitation Period in the International Sale of Goods, and the Uniform Computer Information Transactions Act shall apply to this Agreement.

15. GENERAL.

- a. This Agreement is the entire agreement between Extreme and You regarding the Licensed Materials, and all prior agreements, representations, statements, and undertakings, oral or written, are hereby expressly superseded and canceled.
- b. This Agreement may not be changed or amended except in writing signed by both parties hereto.
- c. You represent that You have full right and/or authorization to enter into this Agreement.
- d. This Agreement shall not be assignable by You without the express written consent of Extreme. The rights of Extreme and Your obligations under this Agreement shall inure to the benefit of Extreme's assignees, licensors, and licensees.
- e. Section headings are for convenience only and shall not be considered in the interpretation of this Agreement.
- f. The provisions of the Agreement are severable and if any one or more of the provisions hereof are judicially determined to be illegal or otherwise unenforceable, in whole or in part, the remaining provisions of this Agreement shall nevertheless be binding on and enforceable by and between the parties hereto.
- g. Extreme's waiver of any right shall not constitute waiver of that right in future. This Agreement constitutes the entire understanding between the parties with respect to the subject matter hereof, and all prior agreements, representations, statements and undertakings, oral or written, are hereby expressly superseded and canceled. No purchase order shall supersede this Agreement.
- h. Should You have any questions regarding this Agreement, You may contact Extreme at the address set forth below. Any notice or other communication to be sent to Extreme must be mailed by certified mail to the following address:

Extreme Networks, Inc.
145 Rio Robles
San Jose, CA 95134 United States
ATTN: General Counsel

Table of Contents

ExtremeCloud™ IQ Site Engine v25.08.12 Release Notes:	1
Features, Enhancements, and Issues	1
Abstract	2
Extreme Networks® Software License Agreement	4
Table of Contents	9
25.08.12 Release Notes	12
Licensing Changes	12
Version 25.02.10	13
Version 23.02.10	13
Version 21.09.10	13
Version 21.04.10	13
End of Software Maintenance	13
Onboarding ExtremeCloud IQ Site Engine to ExtremeCloud IQ in Connected Deployment Mode	14
Enhancements	14
Customer Found Defects and Known Issues	14
Customer Found Defects Addressed 25.08.12	14
Customer Found Defects Addressed 25.08.11	15
Customer Found Defects Addressed 25.08.10	16
Known Issues Addressed in 25.08.12	18
Known Issues Addressed in 25.08.11	18
Known Issues Addressed in 25.08.10	19
Addressed Vulnerabilities	19
25.08.12 ExtremeAnalytics, and Application Analytics Traffic Sensor images:	19
25.08.12 ExtremeControl images:	19
25.08.12 ExtremeCloud IQ Site Engine images:	19
25.08.11 ExtremeAnalytics, and Application Analytics Traffic Sensor images:	19
25.08.11 ExtremeControl images:	20
25.08.11 ExtremeCloud IQ Site Engine images:	20
25.08.10 ExtremeAnalytics, and Application Analytics Traffic Sensor images:	20

25.08.10 ExtremeControl images:	21
25.08.10 ExtremeCloud IQ Site Engine images:	22
Installation, Upgrade, and Configuration Changes	22
Installation Information	22
Upgrading Without an Internet Connection	23
Custom FlexViews	23
Custom MIBs and Images	23
Important Upgrade Information	23
Important Upgrade Considerations	25
License Renewal	26
Free Space Consideration	26
Site Discover Consideration	26
ExtremeAnalytics Upgrade Information	26
ExtremeControl Version 8.0 and later	27
Other Upgrade Information	27
Upgrading ExtremeControl Engine to Version 25.08.12	27
General Upgrade Information	27
LDAPS servers with FQDN	28
Upgrading to Policy Manager 25.08.12	28
Fabric Configuration Information	28
Certificate	28
Authentication Key	28
Service Configuration Change	29
CLIP Addresses	29
Upgrading VSP-8600	29
Removing Fabric Connect Configuration	29
Password Configuration	29
VRF Configuration	29
Device Configuration Information	30
VDX Device Configuration	30
Fabric Engine Device Configuration	30

ERS Device Configuration	30
SLX Device Configuration	31
ExtremeXOS Device Configuration	31
Firmware Upgrade Configuration Information	31
Wireless Manager Upgrade Information	32
Server and Client System Requirements	32
Operating System Requirements	32
ExtremeCloud IQ Site Engine Server Requirements	32
ExtremeCloud IQ Site Engine Client Requirements	33
ExtremeCloud IQ Site Engine Server and Client Hardware Requirements	33
ExtremeCloud IQ Site Engine Server Requirements	33
ExtremeCloud IQ Site Engine Client Requirements	34
Virtual Engine Requirements	34
ExtremeCloud IQ Site Engine Virtual Engine Requirements	34
ExtremeControl Virtual Engine Requirements	35
ExtremeAnalytics Virtual Engine Requirements	36
Fabric Manager Requirements	36
ExtremeControl Captive Portal Supported End-System Browsers	36
ExtremeControl Engine Version Requirements	37
ExtremeControl VPN Integration Requirements	37
ExtremeControl SMS Gateway Requirements	38
ExtremeControl SMS Text Messaging Requirements	38
ExtremeAnalytics Requirements	38

25.08.12 Release Notes

ExtremeCloud IQ Site Engine includes all the features and functionality of Extreme Management Center as well as issues that have been resolved and configuration changes for this release.

If you are an existing Extreme Management Center customer, contact your representative to have your Extreme Management Center license migrated to an ExtremeCloud IQ Site Engine license. The ExtremeCloud IQ Site Engine license also includes licensing for ExtremeAnalytics.

IMPORTANT:

- For upgrade and installation requirements, as well as configuration considerations, see [ExtremeCloud IQ Site Engine Configuration and Requirements](#).
- ExtremeCloud IQ Site Engine version 25.08.12 consumes licenses from Extreme Platform ONE or ExtremeCloud IQ in a connected deployment mode or from a license file in air gap deployment mode. ExtremeCloud IQ Site Engine is a subscription-based -only licensing model. Existing NMS licenses do not provide access to ExtremeCloud IQ Site Engine. You can view the status of your license by accessing [Administration > Licenses](#) after the installation is complete.
- ExtremeCloud IQ Site Engine is not compatible with an ExtremeCloud IQ Connect level account. You must use a commercial or trial subscription.
- ExtremeCloud IQ Site Engine is not compatible with ExtremeCloud IQ HIQ. You must use a standard VIQ or MSP account.
- For the information shared between ExtremeCloud IQ Site Engine and ExtremeCloud IQ , see [ExtremeCloud IQ Connection](#).

For information regarding the features supported by specific devices, see the [Firmware Support Matrix](#). Version 25.08.12 of ExtremeCloud IQ Site Engine supports the devices listed in the matrix.

Devices that do not have serial numbers or MAC addresses in Extreme Management Center must be rediscovered after you upgrade to ExtremeCloud IQ Site Engine before they can be onboarded to ExtremeCloud IQ.

Connected mode only - If your number of devices exceeds your licenses available, ExtremeCloud IQ Site Engine transitions to a license violation state and your access to ExtremeCloud IQ Site Engine is locked. To resolve the license shortage you need to access the Extreme Networks portal or ExtremeCloud IQ to evaluate the quantities of available Pilot and Navigator licenses versus the number of licenses required by ExtremeCloud IQ Site Engine.

Licensing Changes

The following sections describe licensing changes in ExtremeCloud IQ Site Engine software releases.

Version 25.02.10

Starting in ExtremeCloud IQ Site Engine version 25.02.10 the new Extreme Platform ONE subscriptions are recognized if ExtremeCloud IQ Site Engine is onboarded to ExtremeCloud IQ or Extreme Platform ONE.

Version 23.02.10

Starting in ExtremeCloud IQ Site Engine version 23.02.10 each stack member consumes a license in connected mode. In connected mode, ExtremeCloud IQ Site Engine now reports stack members to ExtremeCloud IQ. If you use stacks in connected mode, ensure that enough ExtremeCloud IQ Pilot licenses are in the license pool before upgrading to ExtremeCloud IQ Site Engine 23.02.10 or later.

Version 21.09.10

For users upgrading from Extreme Management Center to ExtremeCloud IQ Site Engine, note that the XIQ-NAC subscription must be used instead of IA-ES- license. For new users that complete an initial install of ExtremeCloud IQ Site Engine, ExtremeControl licensing does not include end-system capabilities.

Version 21.04.10

Starting in ExtremeCloud IQ Site Engine version 21.04.10, your ExtremeAnalytics license is included as part of your ExtremeCloud IQ Pilot license. Separate licenses are no longer required.

End of Software Maintenance

In ExtremeCloud IQ Site Engine version 24.10.12 and after, the following components and features are deprecated and removed:

- Microsoft Azure Connect module (for multi-cloud integration)
- Ekahau map import

In ExtremeCloud IQ Site Engine version 24.07.10 and after, the following components and features are deprecated and removed:

- ExtremeCompliance, also known as Information Governance Engine
- Public Cloud Dashboard

The following components and features reached end-of-software-maintenance on 30th September 2023:

- Guest and IoT Manager - last version is 23.07.11.6 (not compatible with ExtremeCloud IQ Site Engine version 24.07.10 and after)

- Fabric Manager - last version is 22.09.13.5
- Posture Assessment (both the agent-based and agent-less)

The mobile application "ExtremeManagement ZTP+" was removed from the Google Play store in August 2024.

Onboarding ExtremeCloud IQ Site Engine to ExtremeCloud IQ in Connected Deployment Mode

After installing or upgrading to ExtremeCloud IQ Site Engine, you need to [onboard](#) ExtremeCloud IQ Site Engine to ExtremeCloud IQ. When the onboarding is complete, you can then access ExtremeCloud IQ Site Engine.

Entering your ExtremeCloud IQ name and password are required during the first-time login to ExtremeCloud IQ Site Engine.

NOTE:

If Extreme Management Center is onboarded to ExtremeCloud IQ, when you upgrade to ExtremeCloud IQ Site Engine, you need to remove Extreme Management Center from ExtremeCloud IQ before onboarding ExtremeCloud IQ Site Engine.

Enhancements

The following enhancements were made to ExtremeCloud IQ Site Engine in this release. For additional information about each of the enhancements listed in the release notes, see [ExtremeCloud IQ Site Engine Documentation](#).

Customer Found Defects and Known Issues

Customer Found Defects Addressed 25.08.12

ExtremeControl CFDs Addressed	ID
Addressed an issue where MAC password and MAC sigbits were not configured or applied to the device from policy MAC settings.	03134863 CFD-14469
Addressed an issue with RADIUS attributes not shown after upgrade to 25.08.10 or 25.08.11. Now the system ensures that when Site Engine receives updated RADIUS attributes from NAC, the cache updates that controls the RADIUS attributes pull down.	03182092 CFD-15237
Addressed an issue where if one VOSS switch failed the CLI authentication during switch configuration, it caused other VOSS switches in the same enforcement to appear to fail CLI authentication even with valid credentials.	03165893 CFD-15299

ExtremeManagement CFDs Addressed	ID
Addressed an issue with CLI tasks being restricted to 5 concurrent connections. Now CLI Tasks can run on up to 50 devices in parallel.	03158282 CFD-15134

ExtremeManagement CFDs Addressed	ID
Addressed an issue with a non-partitioned nsalarmhistory table in the database after migration.	03101688 CFD-13972
Addressed an issue with switch archives group membership by device type resets when a device is deleted.	03141027 CFD-14605
Addressed an issue with custom monthly reports missing the first month data.	03087389 CFD-15033
Addressed an issue with enablePw being sent as **** instead of the correct value. Now the TCL and Python scripts send the enable password instead of *****.	03143911 CFD-15354

Customer Found Defects Addressed 25.08.11

ExtremeControl CFDs Addressed	ID
Addressed an issue where Access Control was assigning an end-system group while registering a device (with sponsor group).	03157727 CFD-14890
Addressed an issue of a PSQLErrorException ERROR when enabling captive portal with a customer database that had the nac_rule data in an abnormal state.	03094240 CFD-14780
Addressed an issue with IP address / Gateway IP address on Control interface being mis-calculated for host address use.	03147952 CFD-14704
Addressed an issue where Message-Authenticator setting was not persisted during switch configuration save.	03161312 03166136 03166738 CFD-14977
Addressed an issue with the delete button in Control Switches tab not working and always grayed out.	03161312 03166738 03166136 CFD-14976

ExtremeManagement CFDs Addressed	ID
Addressed an issue with vulnerable openssh packages. Upgraded openssh in local installer to version 1:8.9p1-3ubuntu0.13 to address cve-2025-32728.	03128335 CFD-14773
Addressed an issue with VPEX modules (V300 and V400) not being counted in the license calculation.	03161191 CFD-14963
Addressed an issue where an SNMP Contact Lost event was not triggering the Device Down alarm.	03147808 03146871 03145229 CFD-14741
Addressed an issue causing a server.log exception when the value for the IPADDRESS column of INVSCHEDULEENTRIES table is larger than 80 characters.	03141442 CFD-14580
Addressed an issue causing a server.log exception when the values for the chassis ID are very long and exceeded 32 characters. "Error writing out ExtDevice Info Entry to InvDatabase".	03158641 CFD-14879

ExtremeManagement CFDs Addressed	ID
Addressed an issue with NBI API returning incomplete data when run inside workflows. The following NBI calls documentation has been adjusted: CosDataInput.fromDatabase PolicyDomainListDataInput.fromDatabase NetworkRescDataInput.fromDatabase PviIslandDataInput.fromDatabase PviNsiDataInput.fromDatabase PviVlanDataInput.fromDatabase RoleDataInput.fromDatabase RuleDataInput.fromDatabase RuleListDataInput.fromDatabase ServiceDataInput.fromDatabase VlanDataInput.fromDatabase	03128394 CFD-14435
Addressed an issue with ZTP+ process repeating daily and causing firmware downgrade and already discovered devices to appear in Discovered tab. Now the Switch Engine stacks will be matching on base MAC as well as serial number and IP during Extreme Platform ONE licensing checking.	03084380 CFD-14193
Addressed an issue with a failure to Edit/Copy Scheduled Tasks if the task creator is in the DOMAIN\USER format.	03147642 CFD-14808
Addressed an issue with Switch Engine and Fabric Engine channelized ports not importing correctly for the device configure mode VLAN details.	03157405 CFD-15036
Addressed an issue with EXOS firmware upgrades failing with a CLI error when running shell scripts and then using the scp2 command.	03149747 03150559 03153969 03155320 03157709 03163677 CFD-15093
Addressed an issue with ExtremeCloud IQ Site Engine large Hyper-V virtual appliance default only allocating 16 CPU cores. The large Hyper-V virtual appliance default is now configured with 24 CPU cores.	03167093 CFD-15045

Customer Found Defects Addressed 25.08.10

ExtremeAnalytics CFDs Addressed	ID
Addressed an issue with the search in "Analytics > Reports > Most Use Application for User Name" being case sensitive and difficult to obtain valid search results.	03085838 CFD-13872
ExtremeControl CFDs Addressed	ID
Addressed an issue of failing captive portal authentication with a password longer than 16 characters.	03060132 03083352 CFD-13462
Addressed an issue with moving a MAC OUI entry from one end-system group to another.	03082002 CFD-13617

ExtremeControl CFDs Addressed	ID
Addressed an issue with Entra memberOf group limit of 100 items. ExtremeControl now retrieves the memberOf groups up to 999 items.	03082001 CFD-13638
Addressed an issue with disconnected end-systems onboarding to ExtremeCloud IQ.	03033066 CFD-13803
Addressed an issue with the FreeRADIUS daemon process crashing due to unavailable proxy servers.	03088115 CFD-13895
Addressed an issue with a null pointer exception causing abnormal behavior sending NAC notification when the NBI API was used to perform Add/Remove options to end-system groups.	03063045 CFD-13914
Addressed an issue with an ExtremeCloud IQ Site Engine restart could cause thousands of NAC reauthentications for end-systems that were queued to authenticate while system was down.	03091771 CFD-13958
Addressed an issue with permissions of group read/write access not allowing move of end-users.	03101659 CFD-14049
Addressed an issue with end-system group names that contains an en dash character not being found when importing from CSV.	03104024 CFD-14082
Addressed an issue with the warning message text shown when changing the Web Server HTTP / HTTPS port. The warning text now includes a statement that a separate enforce in ExtremeControl is required before restarting the ExtremeCloud IQ Site Engine.	03102916 CFD-14214
Addressed an issue with ExtremeControl not resolving to the most recent IP address when multiple IP addresses are found in the MIB.	03128385 CFD-14625
Addressed an issue with slow performance to show an Access Control configuration rules table when there are multiple configurations.	03133119 CFD-14446
Addressed an issue with an error "Could Not Load Report" when configuring multiple switches.	03147900 CFD-14726

ExtremeManagement CFDs Addressed	ID
Addressed an issue with Site Engine crashing silently and restarting. This issue was fixed in the 25.05.12 July 2025 release.	03014106 CFD-14310
Addressed an issue with Site Engine crashing silently and restarting. This issue was fixed in the 25.05.12 July 2025 release.	03110132 CFD-14244
Addressed an issue with CLI command password prompt handling failure. Updated password prompt detection for Fabric Engine and Switch Engine when part of a CLI command.	03082775 CFD-13736
Addressed an issue with nsalarms / nsalarmhistory information column not converting to text schema if you performed a .bin based upgrade and migrated your data before version 25.02.10.	03011688 CFD-13769
Addressed an issue with alarm table hidden columns being reset by a browser refresh.	03088755 CFD-13785
Addressed an issue there the Fabric Connect field "ISIS Source Address" was not enforced to the system under specific conditions.	03081441 CFD-14012
Addressed an issue with Port Name Cache not updating with a device interface name change.	03096752 CFD-14013
Addressed an issue with saveonconfigexit for nsscript and nsscripttasks being type char instead of boolean.	03109207 CFD-14081

ExtremeManagement CFDs Addressed	ID
Addressed an issue with the VLAN tab not displaying in maps after adding a third party device that uses the DOT1Q VLAN table.	03068346 CFD-14087
Addressed an issue with alarm TEST email triggered from within an alarm using generic unknown trigger subject and body. Now the alarm TEST email contains the deviceIp (if provided), alarmName, and alarmSeverity.	03109346 CFD-14098
Addressed an issue with ExtremeCloud IQ Site Engine managed ISW switches not onboarding to ExtremeCloud IQ due to "Invalid SN or MAC".	03061288 CFD-14264
Addressed an issue with onboarding a 4220 48P unable to perform an automatic upgrade of Switch Engine. The NOS Persona Change was showing as Fabric Engine which is incorrect and unsupported on that device.	03125058 CFD-14375
Addressed an issue with a NullPointerException when checking if the network RADIUS server is the same as the primary engine with load balancing enabled for an engine group.	03126337 CFD-14545
Addressed an issue with the Compare Configuration option being allowed when restricted. The Compare/View archive is now disabled if the user is associated with an Authorized Group without appropriate access.	03146985 CFD-14729
Addressed an issue with rediscover not updating the device sysLocation.	03147366 CFD-14738
Addressed an issue with the Custom Monthly Average Report not showing every month's data. Now the code is modified to always retrieve and display the data for the first month of monthly data.	03087389 CFD-13995
Addressed an issue with a non-partitioned nsalarmhistory table in the database after migration.	03101688 CFD-13972
Addressed an issue with custom monthly reports missing the first month data.	03087389 CFD-13995
Addressed an issue with missing map images after a database restore in versions 24.07.10. to 25.05.12. The map images are now stored the database backup of version 25.08.10 and later. You must generate a new backup with 25.08.10 and later to retain map images after a database restore.	03123138 CFD-14285
Addressed an issue when deleting an in use SMTP email list could trigger an exception error in server.log	03132293 CFD-14424
Addressed an issue with a database error due to incorrect syntax for DELETE FROM WORKFLOW_ACT_HIST,WORKFLOW_HIST USING WORKFLOW_HIST INNER JOIN WORKFLOW_ACT_HIST.	03141048 CFD-14568

Known Issues Addressed in 25.08.12

ExtremeCloud IQ Site Engine Issues Addressed

The vulnerable packages libsoup2.4-1 and libsoup2.4-common are no longer needed and have been removed from all appliances.

Known Issues Addressed in 25.08.11

ExtremeCloud IQ Site Engine Issues Addressed

Addressed an issue when the stack device could be onboarded to multiple ExtremeCloud IQ Site Engines (in connected mode), and all would own the configuration.

ExtremeManagement Issues Addressed

Addressed an issue with an error "Could not load report" when an Admin tries to generate CSR from Administration > Certificates.

Known Issues Addressed in 25.08.10

ExtremeManagement Issues Addressed

Addressed an issue with the top of the device grid showing empty after navigating from a device grid with many devices to a grid with a few devices.

Addressed Vulnerabilities

This section presents the vulnerabilities reported by vulnerability scanners in previous versions. The following components received updates in 25.08 regardless of whether the vulnerability could have been exploited or not. If you need more information on vulnerability testing, see [Security and Vulnerability Testing](#).

25.08.12 ExtremeAnalytics, and Application Analytics Traffic Sensor images:

CVE-2025-58364, CVE-2025-58060, CVE-2025-9714, CVE-2025-8058, CVE-2025-6297, CVE-2025-48989

25.08.12 ExtremeControl images:

CVE-2025-58364, CVE-2025-58060, CVE-2025-9714, CVE-2025-8058, CVE-2025-6297, CVE-2025-48989, CVE-2024-27282, CVE-2024-27280, CVE-2025-24294, CVE-2024-35176, CVE-2025-24294, CVE-2023-28755, CVE-2025-8713, CVE-2025-8715, CVE-2025-8714

25.08.12 ExtremeCloud IQ Site Engine images:

CVE-2025-58364, CVE-2025-58060, CVE-2025-9714, CVE-2025-8058, CVE-2025-6297, CVE-2025-2312

25.08.11 ExtremeAnalytics, and Application Analytics Traffic Sensor images:

CVE-2023-4039, CVE-2024-27407, CVE-2024-57996, CVE-2025-1215, CVE-2025-24014, CVE-2025-26603, CVE-2025-37752, CVE-2025-38003, CVE-2025-38004, CVE-2025-38031, CVE-2025-38034, CVE-2025-38035, CVE-2025-38037, CVE-2025-38043, CVE-2025-38044, CVE-2025-38048, CVE-2025-38051, CVE-2025-38052, CVE-2025-38058, CVE-2025-38061, CVE-2025-38065, CVE-2025-38066, CVE-2025-38068, CVE-2025-38072, CVE-2025-38075, CVE-2025-38077, CVE-2025-38078, CVE-2025-38079, CVE-2025-38350, CVE-2025-40909, CVE-2025-4373, CVE-2025-4598, CVE-2025-49794, CVE-2025-49796, CVE-2025-50077, CVE-2025-50078, CVE-2025-50079, CVE-2025-50080, CVE-2025-50081, CVE-2025-50082, CVE-2025-50083, CVE-2025-50084, CVE-2025-50085, CVE-2025-50086, CVE-2025-50087, CVE-2025-50091, CVE-2025-50092, CVE-2025-50093, CVE-2025-50094, CVE-2025-50096, CVE-2025-50097, CVE-2025-50098, CVE-2025-50099, CVE-2025-50100, CVE-2025-50101, CVE-2025-50102, CVE-2025-50104, CVE-2025-53023, CVE-2025-54389, CVE-2025-54409, CVE-

2025-6021, CVE-2025-6069, CVE-2025-6170, CVE-2025-8067, CVE-2025-8176, CVE-2025-8177, CVE-2025-8194, CVE-2025-8534, CVE-2025-8851

25.08.11 ExtremeControl images:

CVE-2023-4039, CVE-2024-27407, CVE-2024-57996, CVE-2025-1215, CVE-2025-24014, CVE-2025-26603, CVE-2025-37752, CVE-2025-38003, CVE-2025-38004, CVE-2025-38031, CVE-2025-38034, CVE-2025-38035, CVE-2025-38037, CVE-2025-38043, CVE-2025-38044, CVE-2025-38048, CVE-2025-38051, CVE-2025-38052, CVE-2025-38058, CVE-2025-38061, CVE-2025-38065, CVE-2025-38066, CVE-2025-38068, CVE-2025-38072, CVE-2025-38075, CVE-2025-38077, CVE-2025-38078, CVE-2025-38079, CVE-2025-38350, CVE-2025-40909, CVE-2025-4373, CVE-2025-4598, CVE-2025-49794, CVE-2025-49796, CVE-2025-50077, CVE-2025-50078, CVE-2025-50079, CVE-2025-50080, CVE-2025-50081, CVE-2025-50082, CVE-2025-50083, CVE-2025-50084, CVE-2025-50085, CVE-2025-50086, CVE-2025-50087, CVE-2025-50091, CVE-2025-50092, CVE-2025-50093, CVE-2025-50094, CVE-2025-50096, CVE-2025-50097, CVE-2025-50098, CVE-2025-50099, CVE-2025-50100, CVE-2025-50101, CVE-2025-50102, CVE-2025-50104, CVE-2025-53023, CVE-2025-54389, CVE-2025-54409, CVE-2025-6021, CVE-2025-6069, CVE-2025-6170, CVE-2025-8067, CVE-2025-8176, CVE-2025-8177, CVE-2025-8194, CVE-2025-8534, CVE-2025-8851, CVE-2025-6442

25.08.11 ExtremeCloud IQ Site Engine images:

CVE-2023-4039, CVE-2024-27407, CVE-2024-57996, CVE-2025-1215, CVE-2025-24014, CVE-2025-26603, CVE-2025-37752, CVE-2025-38003, CVE-2025-38004, CVE-2025-38031, CVE-2025-38034, CVE-2025-38035, CVE-2025-38037, CVE-2025-38043, CVE-2025-38044, CVE-2025-38048, CVE-2025-38051, CVE-2025-38052, CVE-2025-38058, CVE-2025-38061, CVE-2025-38065, CVE-2025-38066, CVE-2025-38068, CVE-2025-38072, CVE-2025-38075, CVE-2025-38077, CVE-2025-38078, CVE-2025-38079, CVE-2025-38350, CVE-2025-40909, CVE-2025-4373, CVE-2025-4598, CVE-2025-49794, CVE-2025-49796, CVE-2025-50077, CVE-2025-50078, CVE-2025-50079, CVE-2025-50080, CVE-2025-50081, CVE-2025-50082, CVE-2025-50083, CVE-2025-50084, CVE-2025-50085, CVE-2025-50086, CVE-2025-50087, CVE-2025-50091, CVE-2025-50092, CVE-2025-50093, CVE-2025-50094, CVE-2025-50096, CVE-2025-50097, CVE-2025-50098, CVE-2025-50099, CVE-2025-50100, CVE-2025-50101, CVE-2025-50102, CVE-2025-50104, CVE-2025-53023, CVE-2025-54389, CVE-2025-54409, CVE-2025-6021, CVE-2025-6069, CVE-2025-6170, CVE-2025-8067, CVE-2025-8176, CVE-2025-8177, CVE-2025-8194, CVE-2025-8534, CVE-2025-8851

25.08.10 ExtremeAnalytics, and Application Analytics Traffic Sensor images:

CVE-2025-30749, CVE-2025-50106, CVE-2025-30761, CVE-2025-30754, CVE-2025-38009, CVE-2025-37989, CVE-2025-37768, CVE-2025-37940, CVE-2025-37840, CVE-2025-37867, CVE-2025-37739, CVE-2025-37911, CVE-2025-37766, CVE-2024-36908, CVE-2025-23144, CVE-2025-37830, CVE-2025-37913, CVE-2024-46742, CVE-2025-37844, CVE-2025-37850, CVE-2025-37964, CVE-2025-38024, CVE-2024-27402, CVE-2025-37892, CVE-2025-37994, CVE-2025-37810, CVE-2025-37857, CVE-2024-35943, CVE-2025-37742, CVE-2025-37811, CVE-2025-37967, CVE-2024-38540, CVE-2025-23146, CVE-2025-37780, CVE-2025-37823, CVE-2025-23145, CVE-2025-37909, CVE-2025-37794, CVE-2024-26686, CVE-2024-35866, CVE-2025-37914, CVE-2025-37819, CVE-2025-23142, CVE-2022-49168, CVE-2022-48893, CVE-2025-37969, CVE-2024-49989, CVE-2025-37738, CVE-2024-35867, CVE-2022-21546, CVE-2025-37836, CVE-2025-37949, CVE-2025-22062, CVE-2025-37787, CVE-2024-53128, CVE-

CVE-2025-37991, CVE-2024-26739, CVE-2025-37858, CVE-2022-49535, CVE-2025-37803, CVE-2023-52572, CVE-2025-37773, CVE-2025-37789, CVE-2025-37905, CVE-2025-23147, CVE-2025-23150, CVE-2025-23157, CVE-2025-37841, CVE-2025-37875, CVE-2025-37756, CVE-2024-50258, CVE-2025-23159, CVE-2025-37796, CVE-2025-37998, CVE-2024-54458, CVE-2025-23140, CVE-2025-37982, CVE-2024-38541, CVE-2025-38023, CVE-2025-23151, CVE-2025-37881, CVE-2025-37985, CVE-2025-23161, CVE-2025-37781, CVE-2025-37995, CVE-2025-37838, CVE-2023-52757, CVE-2024-53203, CVE-2025-37859, CVE-2025-21839, CVE-2025-37740, CVE-2025-37992, CVE-2024-49960, CVE-2025-37912, CVE-2025-37765, CVE-2025-37862, CVE-2022-49063, CVE-2025-21853, CVE-2024-46816, CVE-2024-50125, CVE-2025-37771, CVE-2025-37790, CVE-2025-37983, CVE-2025-37805, CVE-2025-23156, CVE-2025-37970, CVE-2025-37829, CVE-2025-38005, CVE-2025-37812, CVE-2025-37770, CVE-2025-37839, CVE-2025-37797, CVE-2025-37792, CVE-2025-37923, CVE-2025-37927, CVE-2025-37788, CVE-2025-37817, CVE-2024-50280, CVE-2025-37767, CVE-2025-22027, CVE-2025-37749, CVE-2025-37808, CVE-2025-23158, CVE-2025-37758, CVE-2025-37824, CVE-2025-37930, CVE-2024-46751, CVE-2025-37883, CVE-2024-35790, CVE-2024-56751, CVE-2025-32463, CVE-2025-32462, CVE-2025-46835, CVE-2025-48386, CVE-2025-48385, CVE-2025-27614, CVE-2025-27613, CVE-2025-48384, CVE-2025-6965, CVE-2025-50182, CVE-2025-50181, CVE-2023-40403, CVE-2025-5351, CVE-2025-5372, CVE-2025-4877, CVE-2025-5318, CVE-2025-5987, CVE-2025-4878, CVE-2025-5449, CVE-2025-32990, CVE-2025-6395, CVE-2025-32988, CVE-2025-32989, CVE-2025-48964, CVE-2025-47268, CVE-2025-49125, CVE-2025-49124, CVE-2025-52520, CVE-2025-53506, CVE-2025-48988, CVE-2025-48976

25.08.10 ExtremeControl images:

CVE-2025-30749, CVE-2025-50106, CVE-2025-30761, CVE-2025-30754, CVE-2025-38009, CVE-2025-37989, CVE-2025-37768, CVE-2025-37940, CVE-2025-37840, CVE-2025-37867, CVE-2025-37739, CVE-2025-37911, CVE-2025-37766, CVE-2024-36908, CVE-2025-23144, CVE-2025-37830, CVE-2025-37913, CVE-2024-46742, CVE-2025-37844, CVE-2025-37850, CVE-2025-37964, CVE-2025-38024, CVE-2024-27402, CVE-2025-37892, CVE-2025-37994, CVE-2025-37810, CVE-2025-37857, CVE-2024-35943, CVE-2025-37742, CVE-2025-37811, CVE-2025-37967, CVE-2024-38540, CVE-2025-23146, CVE-2025-37780, CVE-2025-37823, CVE-2025-23145, CVE-2025-37909, CVE-2025-37794, CVE-2024-26686, CVE-2024-35866, CVE-2025-37914, CVE-2025-37819, CVE-2025-23142, CVE-2022-49168, CVE-2022-48893, CVE-2025-37969, CVE-2024-49989, CVE-2025-37738, CVE-2024-35867, CVE-2022-21546, CVE-2025-37836, CVE-2025-37949, CVE-2025-22062, CVE-2025-37787, CVE-2024-53128, CVE-2025-37991, CVE-2024-26739, CVE-2025-37858, CVE-2022-49535, CVE-2025-37803, CVE-2023-52572, CVE-2025-37773, CVE-2025-37789, CVE-2025-37905, CVE-2025-23147, CVE-2025-23150, CVE-2025-23157, CVE-2025-37841, CVE-2025-37875, CVE-2025-37756, CVE-2024-50258, CVE-2025-23159, CVE-2025-37796, CVE-2025-37998, CVE-2024-54458, CVE-2025-23140, CVE-2025-37982, CVE-2024-38541, CVE-2025-38023, CVE-2025-23151, CVE-2025-37881, CVE-2025-37985, CVE-2025-23161, CVE-2025-37781, CVE-2025-37995, CVE-2025-37838, CVE-2023-52757, CVE-2024-53203, CVE-2025-37859, CVE-2025-21839, CVE-2025-37740, CVE-2025-37992, CVE-2024-49960, CVE-2025-37912, CVE-2025-37765, CVE-2025-37862, CVE-2022-49063, CVE-2025-21853, CVE-2024-46816, CVE-2024-50125, CVE-2025-37771, CVE-2025-37790, CVE-2025-37983, CVE-2025-37805, CVE-2025-23156, CVE-2025-37970, CVE-2025-37829, CVE-2025-38005, CVE-2025-37812, CVE-2025-37770, CVE-2025-37839, CVE-2025-37797, CVE-2025-37792, CVE-2025-37923, CVE-2025-37927, CVE-2025-37788, CVE-2025-37817, CVE-2024-50280, CVE-2025-37767, CVE-2025-22027, CVE-2025-37749, CVE-2025-37808, CVE-2025-23158, CVE-2025-37758, CVE-2025-37824, CVE-

CVE-2025-37930, CVE-2024-46751, CVE-2025-37883, CVE-2024-35790, CVE-2024-56751, CVE-2025-32463, CVE-2025-32462, CVE-2025-46835, CVE-2025-48386, CVE-2025-48385, CVE-2025-27614, CVE-2025-27613, CVE-2025-48384, CVE-2025-6965, CVE-2025-50182, CVE-2025-50181, CVE-2023-40403, CVE-2025-5351, CVE-2025-5372, CVE-2025-4877, CVE-2025-5318, CVE-2025-5987, CVE-2025-4878, CVE-2025-5449, CVE-2025-32990, CVE-2025-6395, CVE-2025-32988, CVE-2025-32989, CVE-2025-48964, CVE-2025-47268, CVE-2025-1735, CVE-2025-6491, CVE-2025-1220, CVE-2025-49125, CVE-2025-49124, CVE-2025-52520, CVE-2025-53506, CVE-2025-48988, CVE-2025-48976

25.08.10 ExtremeCloud IQ Site Engine images:

CVE-2025-30749, CVE-2025-50106, CVE-2025-30761, CVE-2025-30754, CVE-2025-38009, CVE-2025-37989, CVE-2025-37768, CVE-2025-37940, CVE-2025-37840, CVE-2025-37867, CVE-2025-37739, CVE-2025-37911, CVE-2025-37766, CVE-2024-36908, CVE-2025-23144, CVE-2025-37830, CVE-2025-37913, CVE-2024-46742, CVE-2025-37844, CVE-2025-37850, CVE-2025-37964, CVE-2025-38024, CVE-2024-27402, CVE-2025-37892, CVE-2025-37994, CVE-2025-37810, CVE-2025-37857, CVE-2024-35943, CVE-2025-37742, CVE-2025-37811, CVE-2025-37967, CVE-2024-38540, CVE-2025-23146, CVE-2025-37780, CVE-2025-37823, CVE-2025-23145, CVE-2025-37909, CVE-2025-37794, CVE-2024-26686, CVE-2024-35866, CVE-2025-37914, CVE-2025-37819, CVE-2025-23142, CVE-2022-49168, CVE-2022-48893, CVE-2025-37969, CVE-2024-49989, CVE-2025-37738, CVE-2024-35867, CVE-2022-21546, CVE-2025-37836, CVE-2025-37949, CVE-2025-22062, CVE-2025-37787, CVE-2024-53128, CVE-2025-37991, CVE-2024-26739, CVE-2025-37858, CVE-2022-49535, CVE-2025-37803, CVE-2023-52572, CVE-2025-37773, CVE-2025-37789, CVE-2025-37905, CVE-2025-23147, CVE-2025-23150, CVE-2025-23157, CVE-2025-37841, CVE-2025-37875, CVE-2025-37756, CVE-2024-50258, CVE-2025-23159, CVE-2025-37796, CVE-2025-37998, CVE-2024-54458, CVE-2025-23140, CVE-2025-37982, CVE-2024-38541, CVE-2025-38023, CVE-2025-23151, CVE-2025-37881, CVE-2025-37985, CVE-2025-23161, CVE-2025-37781, CVE-2025-37995, CVE-2025-37838, CVE-2023-52757, CVE-2024-53203, CVE-2025-37859, CVE-2025-21839, CVE-2025-37740, CVE-2025-37992, CVE-2024-49960, CVE-2025-37912, CVE-2025-37765, CVE-2025-37862, CVE-2022-49063, CVE-2025-21853, CVE-2024-46816, CVE-2024-50125, CVE-2025-37771, CVE-2025-37790, CVE-2025-37983, CVE-2025-37805, CVE-2025-23156, CVE-2025-37970, CVE-2025-37829, CVE-2025-38005, CVE-2025-37812, CVE-2025-37770, CVE-2025-37839, CVE-2025-37797, CVE-2025-37792, CVE-2025-37923, CVE-2025-37927, CVE-2025-37788, CVE-2025-37817, CVE-2024-50280, CVE-2025-37767, CVE-2025-22027, CVE-2025-37749, CVE-2025-37808, CVE-2025-23158, CVE-2025-37758, CVE-2025-37824, CVE-2025-37930, CVE-2024-46751, CVE-2025-37883, CVE-2024-35790, CVE-2024-56751, CVE-2025-32463, CVE-2025-32462, CVE-2025-46835, CVE-2025-48386, CVE-2025-48385, CVE-2025-27614, CVE-2025-27613, CVE-2025-48384, CVE-2025-6965, CVE-2025-50182, CVE-2025-50181, CVE-2023-40403, CVE-2025-5351, CVE-2025-5372, CVE-2025-4877, CVE-2025-5318, CVE-2025-5987, CVE-2025-4878, CVE-2025-5449, CVE-2025-32990, CVE-2025-6395, CVE-2025-32988, CVE-2025-32989, CVE-2025-48964, CVE-2025-47268

Installation, Upgrade, and Configuration Changes

Installation Information

For license requirements for ExtremeCloud IQ Site Engine and devices, see [Licensing](#).

For complete installation instructions, see [ExtremeCloud IQ Site Engine Suite Installation](#).

Upgrading Without an Internet Connection

If your Linux system requires an operating system upgrade, you are prompted to upgrade using either an internet connection or locally (without an internet connection) if no additional Ubuntu packages need to be installed.

!!! ATTENTION !!!

We can attempt to upgrade the OS without using the internet if there were no extra Ubuntu packages installed. If there were extraneous packages installed, the upgrade will fail with this method.

Do you want to attempt a local in-place upgrade of the OS and reboot when complete? (Y/n)

Custom FlexViews

When reinstalling ExtremeCloud IQ Site Engine Console, the installation program saves copies of any FlexViews you created or modified in the `<install_directory>\.installer\backup\current\appdata\System\FlexViews` folder.

If you are deploying FlexViews via the ExtremeCloud IQ Site Engine server, save them in the `appdata\VendorProfiles\Stage\MyVendorProfile\FlexViews\My FlexViews` folder.

Custom MIBs and Images

If you are deploying MIBs via the ExtremeCloud IQ Site Engine server, they are saved in the `appdata\VendorProfiles\Stage\MyVendorProfile\MIBs\` folder.

If you are deploying device images (pictures) via the ExtremeCloud IQ Site Engine server, they are saved in the `appdata\VendorProfiles\Stage\MyVendorProfile\Images\` folder.

Important Upgrade Information

A special [Data Migration Procedure](#) is required to upgrade ExtremeCloud IQ Site Engine from versions older than 24.07. The minimum version to upgrade Analytics Engines and Access Control Engines is 24.02.13.

ExtremeCloud IQ Site Engine Version 25.08.12 contains an OS upgrade. Internet connectivity is required to download custom packages.

NOTE:

The installer prompts "Do you want to use the Internet to perform the OS upgrade?". The offline upgrade path is supported when no custom packages are installed (answer N). The online upgrade is required when custom packages are manually installed (answer Y). An online upgrade is recommended when an online upgrade was used previously, however there is a risk of session timeout due to 15 minutes of screen inactivity.

To upgrade Access Control Engines and Application Analytics Engines you can use the directive `--keepalive` to decrease the chance of a session expiry timeout from 15 minutes of no screen activity.

From Version (currently running)	To Version (next step in upgrade path)
ExtremeCloud IQ Site Engine 24.07.x, 24.10.x, 25.02.x, 25.05.x	ExtremeCloud IQ Site Engine 25.08
ExtremeCloud IQ Site Engine 24.02.x	Fresh installation of ExtremeCloud IQ Site Engine 25.08 and follow the Data Migration Procedure
Application Analytics Engine, Access Control Engine 24.02.15	Application Analytics Engine, Access Control Engine 25.08
ExtremeCloud IQ Site Engine 23.04.12, 23.07.x, 23.11.x, 24.02.x	ExtremeCloud IQ Site Engine 24.02.15
ExtremeCloud IQ Site Engine 21.x, 22.x, 23.2.x, 23.04.10, 23.04.11	ExtremeCloud IQ Site Engine 23.04.12
Extreme Management Center version 8.5.7	ExtremeCloud IQ Site Engine 24.02.15
Extreme Management Center version 8.2.x to 8.5.6	Extreme Management Center 8.5.7
Extreme Management Center version 8.0.x to 8.1.x	Extreme Management Center 8.3.3.11

From Version (currently running)	To Version (next step in upgrade path)
NetSight version 7.1.4.1	Extreme Management Center 8.3.3.11
NetSight version 7.x	NetSight 7.1.4.1
NetSight version 6.3.0.186	NetSight 7.1.4.1
NetSight version 6.x	NetSight 6.3.0.186

IMPORTANT:

A backup (**Administration** > [Backup/Restore](#)) of the database must be performed prior to the upgrade and saved to a safe location.

If you use LDAPS with a Fully Qualified Domain Name (FQDN) in the URL to authorize a user to the OneView, then ExtremeCloud IQ Site Engine presents the Server Certificate (located in Administration > Certificates > Server Certificate Information) to the LDAPS server. If the LDAPS server presents a certificate that does not match the LDAPS URL, then the certificate is rejected with the error "Certificate Unknown".

The best practice is to use a trusted certificate if the LDAPS URL is defined with FQDN, otherwise the LDAPS server might not accept the LDAPS connection. The alternative option is to use an IP address in the LDAPS URL instead of FQDN.

Important Upgrade Considerations

- If your network is using ExtremeAnalytics or ExtremeControl engines, or another add-on feature, you must first perform the ExtremeCloud IQ Site Engine upgrade to version 25.08.12 and then upgrade the feature.
- To upgrade Traffic Sensor from version 21.x, a fresh installation is recommended. If the fresh installation cannot be used, then please check [Knowledge Base](#) for a special procedure.
- If the online upgrade fails due to an Internet connectivity issue, fix the connectivity issue and rerun the upgrade.

IMPORTANT:

When performing an upgrade, be sure to back up the database prior to performing the upgrade, and save it to a safe location. Use the **Administration** > [Backup/Restore](#) tab to perform the backup.

- When upgrading the ExtremeCloud IQ Site Engine server, ExtremeAnalyticsengine, or ExtremeControlengine to version 25.08.12, ensure the DNS server IP address is correctly configured.
- When upgrading to ExtremeCloud IQ Site Engine version 25.08.12, if you adjusted the ExtremeCloud IQ Site Engine memory settings and want them to be saved on upgrade, a flag (`-DcustomMemory`) needs to be added to the `/usr/local/Extreme_Networks/NetSight/services/nsserver.cfg` file.

For example:

```
-Xms12g -Xmx24g -XX:HeapDumpPath=../..nsdump.hprof -  
XX:+HeapDumpOnOutOfMemoryError -XX:MetaspaceSize=128m -DcustomMemory
```

License Renewal

Upgrading to ExtremeCloud IQ Site Engine version 25.08.12 requires you to transition from perpetual to subscription-based license model. Existing NMS licenses do not provide access to ExtremeCloud IQ Site Engine. If your perpetual licenses were not transitioned to subscription-based licenses, contact your Extreme Networks Representative for assistance.

Free Space Consideration

When upgrading to ExtremeCloud IQ Site Engine version 25.08.12, a minimum of 15 GB of free disk space is required on the ExtremeCloud IQ Site Engine server

To increase the amount of free disk space on the ExtremeCloud IQ Site Engine server, perform the following:

- Decrease the number of ExtremeCloud IQ Site Engine backups (by default, saved in the `/usr/local/Extreme_Networks/NetSight/backup` directory).
- Decrease the Data Persistence settings (**Administration > Options > Access Control > Data Persistence**).
- Remove unnecessary archives (**Network > Archives**).
- Delete the files in the `<installation directory>/NetSight/.installer` directory.

Site Discover Consideration

Discovering devices via the **Site** tab using a **Range**, **Subnet**, or **Seed** discover might not successfully add all expected devices. To correct the issue, increase the **Length of SNMP Timeout** value on the **Administration > Options > Site** tab in the Discover First SNMP Request section.

ExtremeAnalytics Upgrade Information

Enabling or disabling the disk flow export feature might cause enforce operations to time out. Enforcing again resolves the issue.

When you delete an ExtremeXOS/Switch Engine device that is configured as a flow source via the Flow Sources table of the **Analytics > Configuration > Engines > Configuration** tab from the Devices list on the **Network > Devices** tab, an error message is generated in the `server.log`. The message does not warn you that the device is in use as a flow source. Adding the device back in the Devices list on the **Network > Devices** tab or removing the device from the Flow Source table fixes the issue.

The Flow Sources table on the **Analytics > Configuration > engine > Configuration** tab may take a few minutes to load.

ExtremeControl Version 8.0 and later

Beginning in version 8.0, ExtremeControl may fail to join Active Directory when accessing as a **Standard Domain User with Descendant Computer Objects ("Reset password" permissions only)** group member.

To allow this functionality, add the following permissions:

- Reset Password
- Validated write to DNS host name
- Validated write to service principal
- Read and write account restrictions
- Read and write DNS host name attributes
- Write servicePrincipalName

Other Upgrade Information

Immediately after you install version 25.08.12 on the ExtremeControlengine, the date and time does not properly synchronize and the following error message displays:

```
WARNING: Unable to synchronize to a NTP server. The time might not be
correctly set on this device.
```

Ignore the error message and the date and time automatically synchronize after a short delay.

Additionally, the following message might display during the ExtremeControl upgrade to version 25.08.12:

No domain specified

To stop domain-specific winbindd process, run `/etc/init.d/winbindd stop {example-domain.com}`

Upgrading ExtremeControl Engine to Version 25.08.12

General Upgrade Information

The EAP-TLS Certificates with SHA1 are considered weak and are not accepted anymore. The radius server fails to start with the SHA1 certificate. You can use a more secure certificate, such as SHA256.

You are not required to upgrade your ExtremeControl engine version to 25.08.12 when upgrading to ExtremeCloud IQ Site Engine version 25.08.12. However, both ExtremeCloud IQ Site Engine and ExtremeControl engine must be at version 25.08.12 in order to take advantage of the new ExtremeControl version 25.08.12 features. ExtremeCloud IQ Site Engine version 25.08.12 supports managing ExtremeControl engine versions 23.x and up to 25.08.12.

In addition, if your ExtremeControl solution utilizes a Nessus assessment server, you should also upgrade your assessment agent adapter to version 25.08.12 if you upgrade to ExtremeControl version 25.08.12.

You can download the latest ExtremeControl engine version at the [Extreme Portal](#).

LDAPS servers with FQDN

If the LDAPS server URL uses a Fully Qualified Domain Name (FQDN), then the LDAPS client of Access Control Engine presents the internal Communication Certificate to the LDAPS server. If the LDAPS server URL uses a FQDN then the LDAPS client of ExtremeCloud IQ Site Engine presents the Server Certificate (located in Administration > Certificates > Server Certificate Information) to the LDAPS server. If the LDAPS server presents a certificate that does not match the LDAPS URL, then the certificate is rejected with the error "Certificate Unknown"

The best practice is to use trusted certificates if the LDAPS URL is defined with FQDN, otherwise the LDAPS server might not accept the LDAPS connection. If the LDAPS server URL uses an IP address then the LDAPS client (of both Access Control Engine and ExtremeCloud IQ Site Engine) does not present the Certificate to the LDAPS server.

Upgrading to Policy Manager 25.08.12

- Policy Manager 25.08.12 only supports ExtremeWireless Controller version 8.01.03 and higher. If you upgrade to ExtremeCloud IQ Site Engine 25.08.12 prior to upgrading your controllers, then Policy Manager does not allow you to open a domain where the controllers already exist or add them to a domain. A dialog is displayed indicating your controllers do not meet minimum version requirements and that they must be upgraded before they can be in a domain.
- Following an upgrade to Wireless Controller version 8.31 and higher, a Policy Manager enforce fails if it includes changes to the default access control or any rules that are set to contain. To allow Policy Manager to modify the default access control or set rules to contain, you must disable the **"Allow" action in policy rules contains to the VLAN assigned by the role** checkbox accessed from the Wireless Controller's web interface on the Roles > **Policy Rules** tab. This will allow the enforce operation to succeed.

Fabric Configuration Information

Certificate

Fabric Manager might be unavailable via ExtremeCloud IQ Site Engine after upgrading if the certificate is missing in ExtremeCloud IQ Site Engine Trust store.

To ensure Fabric Manager is available, enter the Fabric Manager certificate in the ExtremeCloud IQ Site Engine Trust store using **Generate Certificate** option. See [Add Fabric Manager Certificate](#) for the certificate procedure.

Authentication Key

When you provision authentication keys for Fabric Attach, the key cannot be read back for security reasons. When the key is read from the device, it always shows "*****". For this reason, it

might seem that there is a configuration mismatch when one does not exist.

Service Configuration Change

If you change a configured service via the **Configure Device** window that references one of the following, and then enforce those changes to the device, the configuration on the device might change unexpectedly:

- MLT
- SMLT
- Port-specific settings to a port belonging to an MLT or SMLT

To prevent this merge, change rows in the **Enforce Preview** window where MLT or SMLT are in use from **Current** to **Desired**.

To correct the issue after enforcement, modify the service on the device via the CLI.

CLIP Addresses

Using the CLIP Addresses table in the Configure Device window, you can enter addresses in both IPv4 and IPv6 formats. However, ExtremeCloud IQ Site Engine version 25.08.12 only supports applying a single address (either IPv4 or IPv6) to a Loopback Interface.

Upgrading VSP-8600

When upgrading from Extreme Management Center version 8.2 to version 8.3, manually reload previously discovered VSP-8600 devices to gain access to Fabric Connect features.

Removing Fabric Connect Configuration

Removing a device's Fabric Connect configuration by setting the **Topology Definition** to **<None>** may fail if the device has Logical Interfaces assigned to ISIS.

Password Configuration

Fabric Manager fails to onboard in ExtremeCloud IQ Site Engine if the root password includes an ampersand (&) character. Additionally, if the Administration > Inventory Manager > SCP tab contains a password that includes an ampersand (&) in ExtremeCloud IQ Site Engine, the Fabric Manager firmware does not download successfully.

Ensure you use a password without an ampersand (&) character.

VRF Configuration

Fabric Engine SNMP performance is adversely affected as the number of VRF configurations increases. This issue can be resolved by upgrading to Fabric Engine release 8.1.1 or later or VSP-8600 series version 6.3.3 or later.

Device Configuration Information

VDX Device Configuration

To properly discover interfaces and links for VDX devices in ExtremeCloud IQ Site Engine, enable `three-tuple-if` on the device.

To enable `three-tuple-if` on the device in ExtremeCloud IQ Site Engine:

NOTE:

1. Access the **Network > Devices** tab.
2. Right-click on the device in the Devices table.
3. Select **Tasks > Config > VDX Config Basic Support**.

Additionally, for ExtremeCloud IQ Site Engine to display VCS fabric, the NOS version must be 7.2.0a or later.

Rediscover VDX devices after upgrading to ExtremeCloud IQ Site Engine.

Fabric Engine Device Configuration

Topology links from Fabric Engine devices to other Fabric Engine or ERS devices might not display in a topology map (or might display inconsistently). To ensure topology map links display correctly, verify that the Fabric Engine device is configured to publish its management IP address in the autotopology (SONMP) data.

Ensure that the output of `show sys setting` command shows:

```
autotopology : on
ForceTopologyIpFlag : true
clipId-topology-ip : 0
```

If the output values displayed are different, configure the Fabric Engine device to publish management IP address in SONMP data by executing the following CLI commands:

```
(config)# autotopology
(config)# sys force-topology-ip-flag enable
(config)# default sys clipId-topology-ip
```

The **Status** of LAG links in maps will start working after the next polling following an upgrade to ExtremeCloud IQ Site Engine. You can initiate the polling of a device by performing a refresh/rediscovery of the device.

ERS Device Configuration

ERS devices might automatically change VLAN configurations you define in ExtremeCloud IQ Site Engine. To disable this, change the `vlan configcontrol` setting for ERS devices you add to ExtremeCloud IQ Site Engine by entering the following in the device command line:

```
CLI commands
enable
```

```
config term
vlan configcontrol flexible
```

Additionally, configure all VLANs on the port for an ERS device with the same tag status (tagged or untagged). If enforcing to an ERS device on which a port has at least one VLAN as tagged, ExtremeCloud IQ Site Engine adds all untagged VLANs to the tagged VLAN list and clears the untagged VLAN list.

Creating an archive for ERS devices using the **Network > Archives** tab does not complete successfully if Menu mode (cmd-interface menu) is used instead of CLI mode (cmd-interface cli). See [How To Set Default Management Interface To Either Menu or CLI Mode](#) to create the archive.

SLX Device Configuration

When creating a ZTP+ Configuration for an SLX 9240 on which firmware version 18s.01.01 or 18s.01.02 is installed, the ZTP+ process fails if the **Administration Profile** value uses SSH or Telnet CLI credentials. ExtremeCloud IQ Site Engine indicates that the SSH or CLI profile is not supported by the device.

To create a ZTP+ configuration for an SLX 9240:

1. Create a new Device Profile with the **CLI Credential** set to **< No Access >**.

NOTE: The SLX ZTP+ Connector does NOT support configuring CLI credentials on the device.

2. Create the ZTP+ Configuration and select the new **Device Profile** you created in Step 1 as the **Administration Profile**.
3. After the ZTP+ process successfully completes and the device is added to ExtremeCloud IQ Site Engine, select a **Device Profile** that uses the correct CLI credentials for the SLX device in the **Administration Profile**.

ExtremeXOS Device Configuration

ExtremeXOS/Switch Engine devices on which firmware version 30.3.1.6 is installed do not download and install new firmware versions successfully via the ZTP+ process. To correct the issue, access the **Network > Firmware** tab in ExtremeCloud IQ Site Engine, select the ExtremeXOS device you are updating via ZTP+, and change the **Version** field in the Details right-panel from **builds/xos_30.3/30.3.1.6** to **30.3.1.6**.

Firmware Upgrade Configuration Information

ExtremeCloud IQ Site Engine supports firmware downloads and uploads to devices using TFTP, FTP, SCP, and SFTP. However, before firmware images can be downloaded or uploaded from the server, ExtremeCloud IQ Site Engine needs the root path or directory for each of the protocols. The following default root paths for each protocol are configurable from the **Administration > Options > Inventory Manager** tab:

Protocol Root Path:

- TFTP: /tftpboot/firmware/images/
- FTP: /tftpboot/firmware/images/
- SCP: /root/firmware/images/
- SFTP: /root/firmware/images/

To upload firmware images that are 2 GB or less to the server, use the ExtremeCloud IQ Site Engine **Network > Firmware** tab. For files larger than 2 GB, use a third-party client (such as SCP, WinSCP, or FTP).

For example, to use SCP to upload a firmware image to the SCP root path on the server, enter the following:

- `scp <LOCAL_FIRMWARE_PATH> root@<ExtremeCloud IQ Site Engine_SERVER_IP>:/root/firmware/images`
- Where:
 - `<ExtremeCloud IQ Site Engine_SERVER_IP>`= IP Address to ExtremeCloud IQ Site Engine Server
 - `<LOCAL_FIRMWARE_PATH>`= fully qualified path to a firmware image on the client machine

Wireless Manager Upgrade Information

A High Availability pair cannot be added as a flow source if the WLAN(s) selected are not in common with both wireless controllers.

Server and Client System Requirements

IMPORTANT:

Wireless event collection is disabled by default in version 25.08.12 due to the increase in disk space usage required. To enable event collection, select **Enable Event Collection** **Event Analyze**. Then select **Administration > Options > [Event Analyzer](#)**.

Internet Explorer is not supported in ExtremeCloud IQ Site Engine version 25.08.12.

Operating System Requirements

ExtremeCloud IQ Site Engine Server Requirements

Manufacturer	Operating System
Linux	Red Hat Enterprise Linux 9.4
VMware® (ExtremeCloud IQ Site Engine Virtual Engine)	VMware ESXi™ 6.0 server VMware ESXi™ 6.5 server VMware ESXi™ 6.7 server VMware ESXi™ 7.0 server VMware ESXi™ 8.0 server vSphere (client only)™
Microsoft® Hyper-V (ExtremeCloud IQ Site Engine Virtual Engine)	Windows® Server 2019 Windows® Server 2022

Manufacturer	Operating System
Nutanix (ExtremeCloud IQ Site Engine Virtual Engine)	AHV: 20230302.101026 AOS: 6.8.1 Prism Central: 2024.2
Extreme Networks	Universal Compute Platform 2130C version 5.09.01

These are the operating system requirements for the ExtremeCloud IQ Site Engine server.

ExtremeCloud IQ Site Engine Client Requirements

These are the operating system requirements for remote ExtremeCloud IQ Site Engine client machines.

Manufacturer	Operating System
Windows (qualified on the English version of the operating systems)	Windows® 10 and 11
Linux	Red Hat Enterprise Linux 9.4
Mac OS X*	Monterey, Sonoma

ExtremeCloud IQ Site Engine Server and Client Hardware Requirements

These are the hardware requirements for the ExtremeCloud IQ Site Engine server and ExtremeCloud IQ Site Engine client machines.

NOTES: ExtremeControl and ExtremeAnalytics are not supported on Small ExtremeCloud IQ Site Engine servers.

ExtremeCloud IQ Site Engine Server Requirements

	Small	Medium	Enterprise	Large Enterprise
Total CPUs	1	2	2	2
Total CPU Cores	8	16	24	24
Memory	16 GB	32 GB	64 GB	64 GB
Disk Size	240 GB	480 GB	960 GB	1.92 TB
IOPS	200	200	10,000	10,000
Recommended scale based on server configuration:				
Maximum APs	250	2,500	25,000	25,000
Maximum Wireless MUs	2,500	25,000	100,000	100,000
Maximum Managed Devices	100	1,000	10,000 air gap 8,000 connected	10,000 air gap 8,000 connected
Maximum Concurrent Management Sessions	5	15	50	50
ExtremeControl End-Systems	N/A	50,000	200,000	200,000
Statistics Retention (Days)	90	180	180	360

	Small	Medium	Enterprise	Large Enterprise
ExtremeAnalytics	No	Yes	Yes	Yes
MU Events	No	Yes	Yes	Yes

IMPORTANT: For optimal performance the CPU and Memory needs to reserved in the ESX Client and the virtual machine needs to be deployed using Thick Disk provisioning.

ExtremeCloud IQ Site Engine Client Requirements

Requirements	
CPU Speed	Dual Core Processor
Memory	8 GB
Disk Size	300 MB (User's home directory requires 50 MB for file storage)
Java Runtime Environment (JRE) (Oracle Java only)	Version 8 (for FlexView Editor / MIB Tools)
Browser ¹ (Enable JavaScript and Cookies)	Microsoft Edge Mozilla Firefox Google Chrome

¹Browsers set to a zoom ratio of less than 100% might not display ExtremeCloud IQ Site Engine properly (for example, missing borders around windows). Setting your browser to a zoom ratio of 100% corrects this issue.

Virtual Engine Requirements

The ExtremeCloud IQ Site Engine, ExtremeControl, and ExtremeAnalytics virtual engines must be deployed on a VMware, Hyper-V server, Nutanix, or Extreme Networks Universal Compute Platform.

- ExtremeCloud IQ Site Engine and virtual engines are packaged in the .OVA file format for VMware deployment.
- ExtremeCloud IQ Site Engine and virtual engines are packaged in the .ZIP file format for Hyper-V deployment.
- ExtremeCloud IQ Site Engine and virtual engines are packaged in the .OVA file format for deployment to the Nutanix through Prism Central.
- ExtremeCloud IQ Site Engine and virtual engines are packaged in the .TAR file format for deployment to the Universal Compute Platform.

IMPORTANT:

For ESX and Hyper-V servers configured with AMD processors, the ExtremeExtremeAnalytics virtual engine requires AMD processors with at least Bulldozer based Opterons.

ExtremeCloud IQ Site Engine Virtual Engine Requirements

Specifications	Small	Medium	Enterprise	UCP 2130C
Total CPU Cores	8	16	24	N/A
Memory	16 GB	32 GB	64 GB	N/A
Disk Size	240 GB	480 GB	960 GB	N/A

Specifications	Small	Medium	Enterprise	UCP 2130C
IOPS	200	200	10,000	N/A
Recommended scale based on server configuration:				
Maximum APs	250	2,500	25,000	25,000
Maximum Wireless MUs	2,500	25,000	100,000	100,000
Maximum Managed Devices	100	1,000	10,000 air gap 8,000 connected	10,000 air gap 8,000 connected
Maximum Concurrent Management Sessions	5	15	50	50
ExtremeControl End-Systems	N/A	50,000	200,000	200,000
Statistics Retention (Days)	90	180	180	180
ExtremeAnalytics	No	Yes	Yes	Yes
MU Events	No	Yes	Yes	Yes

IMPORTANT:

For optimal performance the CPU and Memory needs to reserved in the ESX Client and the virtual machine needs to be deployed using Thick Disk provisioning.

ExtremeControl Virtual Engine Requirements

Specifications	Small	Medium	Enterprise	Large Enterprise	UCP 2130C
Total CPU Cores	8	16	16	20	N/A
Memory	12 GB	16 GB	32 GB	48 GB	N/A
Disk Size	40 GB	120 GB	120 GB	120 GB	N/A
IOPS	200	200	200	200	N/A

Recommended scale based on server configuration:

ExtremeControl End-Systems	3,000	6,000	9,000/12,000 ¹	12,000/24,000 ²	12,000/24,000 ²
Authentication	Yes	Yes	Yes	Yes	Yes
Captive Portal	No	Yes	Yes/No ¹	Yes/No ²	Yes/No ²
Assessment	No	Yes	No	No	No

¹ The Enterprise ExtremeControlengine configuration supports two different scale options:

- Up to 9,000 end-systems if your network uses Captive Portal functionality.
- Up to 12,000 end-systems if your network does not use Captive Portal functionality.

² The Large Enterprise ExtremeControlengine configuration supports two different scale options:

- Up to 12,000 end-systems if your network uses Captive Portal functionality.
- Up to 24,000 end-systems if your network does not use Captive Portal functionality.

IMPORTANT:

For optimal performance the CPU and Memory needs to reserved in the ESX Client and the virtual machine needs to be deployed using Thick Disk provisioning.

ExtremeAnalytics Virtual Engine Requirements

Specifications	Small	Medium	Enterprise	UCP 2130C
Total CPU Cores	8	16	16	N/A
Memory	12 GB	32 GB	64 GB	N/A
Disk Size	40 GB	480 GB	960 GB	N/A
IOPS	200	10,000	10,000	N/A

Recommended scale based on server configuration:				
Flows Per Minute	250,000	500,000	750,000	750,000
End-Systems	10,000	20,000	30,000	30,000
Raw Flow Retention (Days)	3.5	3.5	7	7

IMPORTANT:

The ESXi free license supports a maximum of 8 CPU cores, and the medium and enterprise ExtremeAnalytics virtual engine installations require 16 CPU cores. Sixteen CPU cores are only available by purchasing a permanent license. To use the ExtremeAnalytics virtual engine with an ESXi free license, adjust the number of CPU cores to 8.

To reduce the possibility of impaired functionality, ensure at least 4 GB of swap space is available for flow storage on the ExtremeAnalytics virtual engine. To verify the amount of available RAM on your Linux system, use the `free` command

Fabric Manager Requirements

Specifications	Requirements
Total CPU Cores	4
Memory	9 GB
Memory allocated to Java:	
-Xms	4 GB
-Xmx	6 GB
Disk Size	60 GB

ExtremeControl Captive Portal Supported End-System Browsers

The following table outlines the supported desktop and mobile end-system browsers connecting to the network through the Mobile Captive Portal of Extreme Networks ExtremeControl.

Medium	Browser
Desktop	Microsoft Edge
	Microsoft Internet Explorer
	Mozilla Firefox
	Google Chrome

Medium	Browser
Mobile	Internet Explorer Mobile Microsoft Edge Microsoft Windows 10 Touch Screen Native (Surface Tablet) iOS Native Android Chrome Android Native Dolphin Opera

NOTES: A native browser indicates the default, system-installed browser. Although this might be Chrome (Android), this also includes the default, system-controlled browser used for a device's Captive Network Detection for a device. Typically, this is a non-configurable option for Wi-Fi Captive Network Detection, but default Android, Microsoft and iOS devices are tested for compatibility with the Mobile Captive Portal.

A mobile device can access the standard (non-mobile) version of the Captive Portal using any desktop-supported browsers available on a mobile device.

For other browsers, the Mobile Captive Portal requires the browser on the mobile device to be compatible with Webkit or Sencha Touch.

To confirm compatibility with Webkit or Sencha Touch, open `http://<ExtremeControlEngine IP>/mobile_screen_preview` using your mobile web browser.

- If the browser is compatible, the page displays properly.
- If the browser is not compatible with the Mobile Captive Portal, the following error displays:



ExtremeControl Engine Version Requirements

For complete information on ExtremeControl engine version requirements, see [Important Upgrade Information](#).

ExtremeControl VPN Integration Requirements

VPN concentrators are supported for use in ExtremeControl VPN deployment scenarios.

- Supported Functionality: Authentication and Authorization (policy enforcement)
 - Cisco ASA
 - Enterasys XSR
- Supported Functionality: Authentication
 - Juniper SA (requires an S-Series Stand Alone (SSA) system in order to provide access control)

NOTE: For all ExtremeControl VPN Deployment scenarios, an S-Series Stand Alone (SSA) system is required to change authorization levels beyond the initial authorization, such as when using assessment.

ExtremeControl SMS Gateway Requirements

The following SMS Gateways have been tested for interoperability with ExtremeControl:

- Clickatell
- Mobile Pronto

ExtremeControl SMS Text Messaging Requirements

The following mobile service providers are supported by default for SMS text messaging in an ExtremeControl deployment. Additional service providers can be added:

AT&T	Sprint PCS
Alltel	SunCom
Bell Mobility (Canada)	T-Mobile
Cingular	US Cellular
Metro PCS	Verizon
Rogers (Canada)	Virgin Mobile (US and Canada)

ExtremeAnalytics Requirements

To use an ExtremeSwitching X440-G2 switch as an Application Telemetry source for ExtremeAnalytics, install firmware version 22.4.1.4-patch2-5 or higher.